

COMPAQ



PC CARD

SOLUTION

PREMIER PC CARD CONFIGURATIONS

TABLE OF CONTENTS

| | |
|------------------------------------------------|------------|
| MODEMS | 3 |
| Compaq SpeedPaq 192 Cellular PC Card Fax Modem | 4-15 |
| Compaq 288 PC Card Fax Modem | 4-15 |
| Megahertz 28.8/14.4 Data Fax Modem | 4-15 |
| | |
| NETWORK CARDS | 16 |
| Compaq Ethernet LAN Card | 17-34 |
| 3Com EtherLink III | 35-55 |
| IBM Ethernet Credit Card Adapter II | 56-67 |
| Madge Token Ring Smart 16/4 RingNode | 68-79 |
| Xircom Ethernet Adapter IIPS | 80-97 |
| Xircom CreditCard Token Ring IIPS | 98-113 |
| | |
| ATA CARDS | 114 |
| SanDisk 10MB FlashDisk | 115-126 |
| Calluna Technology 170MB Hard Drive | 116-126 |
| | |
| AUDIO CARDS | 127 |
| New Media .WAVjammer | 128-139 |
| | |
| COMBINATION CARDS | 140 |
| New Media Toast 'n Jam (SCSI and Audio) | 141-152 |
| Xircom CreditCard Ethernet +19.2/14.4 Modem II | 153-170 |
| | |
| EMULATION CARDS | 171 |
| DCI 5250 PC Card | 172-183 |
| | |
| MEMORY CARDS | 184 |
| Intel Series 2 20MB Flash Memory Card | 185-196 |
| | |
| SCSI | 197 |
| Adaptec Slim SCSI | 198-209 |
| New Media Bus Toaster | 210-221 |

Disclaimer: Compaq Computer Corporation provides the information in this report "AS IS" without warranty of any kind either express or implied, including, but not limited to, the implied warranties of merchantability or fitness for a particular purpose. The information in this report is updated on a quarterly basis, and is subject to change without notice. Compaq Computer Corporation shall not be liable for claims made by the Vendors or for technical or editorial errors or omissions contained herein, nor for incidental or consequential damages resulting from the performance or use of the information in this report. Compaq Computer Corporation does not grant any warranty of any kind, including warranties of functionality or performance, for Vendor PC Cards.

MODEMS

PLATFORM: *COMPAQ AERO 4/33C*

ROM: *07/19/95*

PC CARDS:

COMPAQ SPEEDPAQ 192, PN: 187100-001

COMPAQ SPEEDPAQ 288, PN: 189650-001

MEGAHERTZ 28.8/14.4 DATA FAX, PN: XJ2288/ CC3288

OPERATING SYSTEM: *WINDOWS 3.1/DOS 6.2*

CARD AND SOCKET SERVICES: *1.25*

CONFIG.SYS

```
SHELL=C:\DOS\COMMAND.COM /P /E:1536
STACKS=9,256
DEVICE=C:\DOS\HIMEM.SYS
DEVICE=C:\DOS\EMM386.EXE NOEMS X=D000-DFFF
DOS=UMB
REM *** Begin PCMCIA Drivers
REM Warning: Do not move, reorder, or delete any of these lines.
REM
DEVICE=C:\CPQDOS\PCMSMIX.EXE
DEVICEHIGH=C:\CPQDOS\SSVLSI.EXE
DEVICEHIGH=C:\CPQDOS\CS.EXE
DEVICE=C:\CPQDOS\CSALLOC.EXE
DEVICEHIGH=C:\CPQDOS\ATADRV.EXE /D:1
DEVICEHIGH=C:\CPQDOS\CARDID.EXE C:\CPQDOS\CARDID.INI
DEVICEHIGH=C:\CPQDOS\MEMDRV.EXE
;DEVICEHIGH=C:\CPQDOS\DBLFLASH.EXE
;DEVICEHIGH=C:\CPQDOS\MS-FLASH.SYS
REM *** End PCMCIA Drivers
DOS=HIGH
BUFFERS=20
FILES=35
DEVICEHIGH=C:\CPQDOS\POWER.EXE
```

AUTOEXEC.BAT

```
@loadhigh C:\DOS\SHARE.EXE /I:500 /f:5100
SET PATH=C:\CPQDOS;C:\;C:\DOS;C:\WINDOWS; C:\WINDOWS\CPQWIN
SET LMOUSE=C:\MOUSE
SET PROMPT=SP$G
SET TEMP=C:\WINDOWS\TEMP
C:\CPQDOS\HIBRN8.EXE
C:\DOS\SMARTDRV.EXE
LH C:\MOUSE\MOUSE SWAP
C:\CPQDOS\MODE.COM CO80
C:\WINDOWS\WIN
```

CARDID.INI

```
[Common]
;
; Common Information section created by Config
;
ComPort1=3F8
ComIRQ1=4
ComPort2=2F8
ComIRQ2=3
ComPort3=3E8
ComIRQ3=4
ComPort4=2E8
ComIRQ4=3
ComBySocket=Yes
ComBDAAbsolute=No
FirstModem=2
SecondModem=2
ThirdModem=3
```

CARDID.INI-continued

FourthModem=4
Audio=Yes
RingIndicate=No
Lan1Port=300
Lan1IRQ=5
Lan1MemoryBase1=D8
Lan1MemoryBase2=DC
Lan2Port=310
Lan2IRQ=10
Lan2MemoryBase1=D8
Lan2MemoryBase2=DC
ATATryPrimary=No
ATATrySecondary=Yes
ATATryLinear=Yes
FastTokenRing=Yes
DetectNonCompliant=No
ContinueOnConfigFailure=No
BeepInDOS=Yes
BeepInWindows=Yes
GrabInitFile=Yes
InitBufferSize=512

[Libraries]

;
; The Libraries section contains references to any card libraries the user
; wishes to include. Libraries are searched in the specified order. Path
; names are relative to the directory containing CARDID.INI.
;
CardLib=cardid.clb

Configuration Notes:

In Windows 3.1 and DOS the modem will automatically be configured for Com 2. The drivers for all the above modems are also included in Windows 95, and upon insertion it will be configured for Com 2.

PLATFORM: *COMPAQ CONCERTO*

ROM: *11/17/93*

PC CARDS:

COMPAQ SPEEDPAQ 192, PN: 187100-001

COMPAQ SPEEDPAQ 288, PN: 189650-001

MEGAHERTZ 28.8/14.4 DATA FAX, PN: XJ2288/CC3288

OPERATING SYSTEM: *WINDOWS 3.1/DOS 6.2*

CARD AND SOCKET SERVICES: *1.25*

CONFIG.SYS

```
SHELL=C:\DOS\COMMAND.COM /P /E:1536
STACKS=9,256
DEVICE=C:\DOS\HIMEM.SYS
DEVICE=C:\DOS\EMM386.EXE NOEMS X=D000-DFFF
DOS=UMB
REM *** Begin PCMCIA Drivers
REM Warning: Do not move, reorder, or delete any of these lines.
REM
DEVICEHIGH=C:\CPQDOS\SSCIRRUS.EXE
DEVICEHIGH=C:\CPQDOS\CS.EXE
DEVICE=C:\CPQDOS\CSALLOC.EXE
DEVICEHIGH=C:\CPQDOS\ATADRV.EXE
DEVICEHIGH=C:\CPQDOS\CARDID.EXE C:\CPQDOS\CARDID.INI
DEVICEHIGH=C:\CPQDOS\MEMDRV.EXE
;DEVICEHIGH=C:\CPQDOS\DBLFLASH.EXE
;DEVICEHIGH=C:\CPQDOS\MS-FLASH.SYS
REM *** End PCMCIA Drivers
DOS=HIGH
BUFFERS=20
FILES=35
DEVICEHIGH=C:\CPQDOS\POWER.EXE
```

AUTOEXEC.BAT

```
SET PATH=C:\CPQDOS;C:\;C:\DOS;C:\WINDOWS;;C:\WINDOWS\CPQWIN
SET LMOUSE=C:\MOUSE
SET PROMPT=$PSG
SET TEMP=C:\WINDOWS\TEMP
C:\CPQDOS\HIBRN8.EXE
C:\DOS\SMARTDRV.EXE
LH C:\MOUSE\MOUSE
C:\CPQDOS\MODE.COM CO80
C:\WINDOWS\WIN
```

CARDID.INI

```
[Common]
;
; Common Information section created by Config
;
ComPort1=3F8
ComIRQ1=4
ComPort2=2F8
ComIRQ2=3
ComPort3=3E8
ComIRQ3=4
ComPort4=2E8
ComIRQ4=3
ComBySocket=Yes
ComBDAAbsolute=No
FirstModem=2
SecondModem=2
ThirdModem=3
FourthModem=4
Audio=Yes
RingIndicate=No
```

CARDID.INI-continued

Lan1Port=300
Lan1IRQ=5
Lan1MemoryBase1=D8
Lan1MemoryBase2=DC
Lan2Port=310
Lan2IRQ=10
Lan2MemoryBase1=D8
Lan2MemoryBase2=DC
ATATryPrimary=No
ATATrySecondary=Yes
ATATryLinear=Yes
FastTokenRing=Yes
DetectNonCompliant=No
ContinueOnConfigFailure=No
BeepInDOS=Yes
BeepInWindows=Yes
GrabInitFile=Yes
InitBufferSize=512

[Libraries]

;
; The Libraries section contains references to any card libraries the user
; wishes to include. Libraries are searched in the specified order. Path
; names are relative to the directory containing CARDID.INI.
;
CardLib=cardid.clb

Configuration Notes:

In Windows 3.1 and DOS the modem will automatically be configured for Com 2. The drivers for all the above modems are also included in Windows 95, and upon insertion it will be configured for Com 2.

PLATFORM: *COMPAQ CONTURA 400CX*

ROM: *04/10/95*

PC CARDS:

COMPAQ SPEEDPAQ 192, PN: 187100-001

COMPAQ SPEEDPAQ 288, PN: 189650-001

MEGAHERTZ 28.8/14.4 DATA FAX, PN: XJ2288/CC3288

OPERATING SYSTEM: *WINDOWS 3.1/DOS 6.2*

CARD AND SOCKET SERVICES: *3.12*

CONFIG.SYS

```
SHELL=C:\DOS\COMMAND.COM /P /E:1536
STACKS=9,256
DEVICE=C:\DOS\HIMEM.SYS
DEVICE=C:\DOS\EMM386.EXE NOEMS I=B000-B7FF X=D000-D4FF
DEVICEHIGH=C:\WINDOWS\CPQWIN\CPQCM.SYS
DOS=HIGH,UMB
REM *** Begin PCMCIA Drivers
REM Warning: Do not move, reorder, or delete any of these lines.
REM
;DEVICE=C:\CPQDOS\PCMSMIX.EXE
DEVICEHIGH=C:\CPQDOS\SSVLSI.EXE
DEVICEHIGH=C:\CPQDOS\CS.EXE
DEVICE=C:\CPQDOS\CSALLOC.EXE
;DEVICEHIGH=C:\CPQDOS\ATADRV.EXE
;DEVICEHIGH=C:\CPQDOS\MTAA.EXE
;DEVICEHIGH=C:\CPQDOS\MTAB.EXE
;DEVICEHIGH=C:\CPQDOS\MTI1.EXE
;DEVICEHIGH=C:\CPQDOS\MTI2P.EXE
;DEVICEHIGH=C:\CPQDOS\MTSRAM.EXE
;DEVICEHIGH=C:\CPQDOS\MTDDR.V.EXE
;DEVICEHIGH=C:\CPQDOS\DBLFLASH.EXE
;DEVICEHIGH=C:\CPQDOS\MS-FLASH.SYS
DEVICEHIGH=C:\CPQDOS\CARDID.EXE
REM *** End PCMCIA Drivers
BUFFERS=20
FILES=35
DEVICEHIGH=C:\CPQDOS\EPPBIOS.SYS
DEVICEHIGH=C:\CPQDOS\POWER.EXE
```

AUTOEXEC.BAT

```
@loadhigh C:\DOS\SHARE.EXE /l:500 /f:5100
@ECHO OFF
SET PATH=C:\CPQDOS;C:\;C:\DOS;C:\WINDOWS;;C:\WINDOWS\CPQWIN
SET LMOUSE=C:\MOUSE
LH C:\MOUSE\MOUSE
SET PROMPT=$PSG
SET TEMP=C:\WINDOWS\TEMP
C:\CPQDOS\HIBRN8.EXE
LH C:\DOS\SMARTDRV.EXE
C:\WINDOWS\WIN
```

CARDID.INI

```
[Common]
;
; Common Information section created by Config
;
ComPort1=3F8
ComIRQ1=4
ComPort2=2F8
ComIRQ2=3
ComPort3=3e8
ComIRQ3=4
ComPort4=2E8
ComIRQ4=3
```

CARDID.INI -continued

ComBySocket=Yes
ComBDAAbsolute=No
FirstModem=2
SecondModem=2
ThirdModem=3
FourthModem=4
Audio=Yes
RingIndicate=No
Lan1Port=300
Lan1IRQ=5
Lan1MemoryBase1=c0
Lan1MemoryBase2=0
Lan2Port=310
Lan2IRQ=9
Lan2MemoryBase1=
Lan2MemoryBase2=
ATATryPrimary=No
ATATrySecondary=Yes
ATATryLinear=Yes
FastTokenRing=No
DetectNonCompliant=No
ContinueOnConfigFailure=No
BeepInDOS=Yes
BeepInWindows=Yes
GrabInitFile=Yes
InitBufferSize=512
UseEMS=No

[Libraries]

;
; The Libraries section contains references to any card libraries the user
; wishes to include. Libraries are searched in the specified order. Path
; names are relative to the directory containing CARDID.INI.

;
CardLib=canonfd.clb
CardLib=xirdual.clb
CardLib=xircom.clb
CardLib=tdkklan2.clb
CardLib=sundisk5.clb
CardLib=intellan.clb
CardLib=dlink.clb
CardLib=linksys.clb
CardLib=linksys2.clb
CardLib=socketea.clb
CardLib=ibmlan.clb
CardLib=ibmtok.clb
CardLib=ibm3270.clb
CardLib=proxim.clb
CardLib=cbdas.clb
CardLib=genmodem.clb
CardLib=genata.clb
CardLib=wd.clb

Configuration Notes:

In Windows 3.1 and DOS the modem will automatically be configured for Com 2. The drivers for all the above modems are also included in Windows 95, and upon insertion it will be configured for Com 2.

PLATFORM: COMPAQ CONTURA 420C

ROM: 08/20/95

PC CARDS:

COMPAQ SPEEDPAQ 192, PN: 187100-001

COMPAQ SPEEDPAQ 288, PN: 189650-001

MEGAHERTZ 28.8/14.4 DATA FAX, PN: XJ2288/CC3288

OPERATING SYSTEM: WINDOWS 3.1/DOS 6.2

CARD AND SOCKET SERVICES: 3.12

CONFIG.SYS

```
switches=/F
SHELL=C:\DOS\COMMAND.COM /P /E:1536
STACKS=9,256
DEVICE=C:\DOS\HIMEM.SYS
DEVICE=C:\DOS\EMM386.EXE NOEMS I=B000-B7FF X=D000-D4FF
DEVICEHIGH=C:\WINDOWS\CPQWIN\CPQCM.SYS
DOS=HIGH,UMB
REM *** Begin PCMCIA Drivers
REM Warning: Do not move, reorder, or delete any of these lines.
REM
;DEVICE=C:\CPQDOS\PCMSMIX.EXE
DEVICEHIGH=C:\CPQDOS\SSVLSI.EXE
DEVICEHIGH=C:\CPQDOS\CS.EXE
DEVICE=C:\CPQDOS\CSALLOC.EXE
;DEVICEHIGH=C:\CPQDOS\ATADRV.EXE
;DEVICEHIGH=C:\CPQDOS\MTAA.EXE
;DEVICEHIGH=C:\CPQDOS\MTAB.EXE
;DEVICEHIGH=C:\CPQDOS\MTI1.EXE
;DEVICEHIGH=C:\CPQDOS\MTI2P.EXE
;DEVICEHIGH=C:\CPQDOS\MTSRAM.EXE
;DEVICEHIGH=C:\CPQDOS\MTDDRV.EXE
;DEVICEHIGH=C:\CPQDOS\DBLFLASH.EXE
;DEVICEHIGH=C:\CPQDOS\MS-FLASH.SYS
DEVICEHIGH=C:\CPQDOS\CARDID.EXE
REM *** End PCMCIA Drivers
BUFFERS=20
FILES=35
DEVICEHIGH=C:\CPQDOS\EPPBIOS.SYS
```

AUTOEXEC.BAT

```
@ECHO OFF
SET PATH=C:\CPQDOS;C:\;C:\DOS;C:\WINDOWS; C:\WINDOWS\CPQWIN
SET LMOUSE=C:\MOUSE
LH C:\MOUSE\MOUSE
SET PROMPT=$PSG
SET TEMP=C:\WINDOWS\TEMP
C:\CPQDOS\HIBRN8.EXE
C:\DOS\SMARTDRV.EXE 2048 512
C:\WINDOWS\WIN
```

CARDID.INI

```
[Common]
;
; Common Information section created by Config
;
ComPort1=3F8
ComIRQ1=4
ComPort2=2F8
ComIRQ2=3
ComPort3=3e8
ComIRQ3=4
ComPort4=2E8
ComIRQ4=3
ComBySocket=Yes
```

CARDID.INI -continued

ComBDAAbsolute=No
FirstModem=2
SecondModem=2
ThirdModem=3
FourthModem=4
Audio=Yes
RingIndicate=No
Lan1Port=300
Lan1IRQ=5
Lan1MemoryBase1=
Lan1MemoryBase2=
Lan2Port=310
Lan2IRQ=9
Lan2MemoryBase1=
Lan2MemoryBase2=
ATATryPrimary=No
ATATrySecondary=Yes
ATATryLinear=Yes
FastTokenRing=Yes
DetectNonCompliant=No
ContinueOnConfigFailure=No
BeepInDOS=Yes
BeepInWindows=Yes
GrabInitFile=Yes
InitBufferSize=512
UseEMS=No

[Libraries]

;
; The Libraries section contains references to any card libraries the user
; wishes to include. Libraries are searched in the specified order. Path
; names are relative to the directory containing CARDID.INI.

;
CardLib=canonfd.clb
CardLib=xirdual.clb
CardLib=xircom.clb
CardLib=tdkklan2.clb
CardLib=sundisk5.clb
CardLib=intellan.clb
CardLib=dlink.clb
CardLib=linksys.clb
CardLib=linksys2.clb
CardLib=socketea.clb
CardLib=ibmlan.clb
CardLib=ibmtok.clb
CardLib=ibm3270.clb
CardLib=proxim.clb
CardLib=cbdass.clb
CardLib=genmodem.clb
CardLib=genata.clb
CardLib=wd.clb

Configuration Notes:

In Windows 3.1 and DOS the modem will automatically be configured for Com 2. The drivers for all the above modems are also included in Windows 95, and upon insertion it will be configured for Com 2.

PLATFORM: *COMPAQ ELITE 450CX*

ROM: *07/19/95*

PC CARDS:

COMPAQ SPEEDPAQ 192, PN: 187100-001

COMPAQ 288, PN: 189650-001

MEGAHERTZ 28.8/14.4 DATA FAX, PN: XJ2288/CC3288

OPERATING SYSTEM: *WINDOWS 3.1/DOS 6.2*

CARD AND SOCKET SERVICES: *3.12*

CONFIG.SYS

```
switches=/F
SHELL=C:\DOS\COMMAND.COM /P /E:1536
STACKS=9,256
DEVICE=C:\DOS\HIMEM.SYS /TESTMEM:OFF
DEVICE=C:\DOS\EMM386.EXE NOEMS I=B000-B7FF X=D000-D4FF
DEVICEHIGH=C:\WINDOWS\CPQWIN\CPQCM.SYS
DOS=HIGH,UMB
REM *** Begin PCMCIA Drivers
REM Warning: Do not move, reorder, or delete any of these lines.
REM
;DEVICE=C:\CPQDOS\PCMSMIX.EXE
DEVICEHIGH=C:\CPQDOS\SSVLSI.EXE
DEVICEHIGH=C:\CPQDOS\CS.EXE
DEVICE=C:\CPQDOS\CSALLOC.EXE
;DEVICEHIGH=C:\CPQDOS\ATADRV.EXE
;DEVICEHIGH=C:\CPQDOS\MTAA.EXE
;DEVICEHIGH=C:\CPQDOS\MTAB.EXE
;DEVICEHIGH=C:\CPQDOS\MTI1.EXE
;DEVICEHIGH=C:\CPQDOS\MTI2P.EXE
;DEVICEHIGH=C:\CPQDOS\MTSRAM.EXE
;DEVICEHIGH=C:\CPQDOS\MTDDRV.EXE
;DEVICEHIGH=C:\CPQDOS\DBLFLASH.EXE
;DEVICEHIGH=C:\CPQDOS\MS-FLASH.SYS
DEVICEHIGH=C:\CPQDOS\CARDID.EXE
REM *** End PCMCIA Drivers
BUFFERS=20
FILES=35
LASTDRIVE = Z
DEVICEHIGH=C:\CPQDOS\POWER.EXE
```

AUTOEXEC.BAT

```
@ECHO OFF
SET PATH=C:\CPQDOS;C:\;C:\DOS;C:\WINDOWS;;C:\WINDOWS\CPQWIN
SET LMOUSE=C:\MOUSE
LH C:\MOUSE\MOUSE
SET PROMPT=$t $PSG
SET TEMP=C:\WINDOWS\TEMP
C:\CPQDOS\HIBRN8.EXE
LH C:\DOS\SMARTDRV.EXE /f 2048 1024
SET NWLANGUAGE=ENGLISH
C:\WINDOWS\WIN
```

CARDID.INI

```
[Common]
;
; Common Information section created by Config
;
ComPort1=3F8
ComIRQ1=4
ComPort2=2F8
ComIRQ2=3
ComPort3=3e8
ComIRQ3=4
ComPort4=2E8
CARDID.INI-continued
```

ComIRQ4=3
ComBySocket=Yes
ComBDAAbsolute=No
FirstModem=2
SecondModem=2
ThirdModem=3
FourthModem=4
Audio=Yes
RingIndicate=No
Lan1Port=300
Lan1IRQ=5
Lan1MemoryBase1=
Lan1MemoryBase2=
Lan2Port=310
Lan2IRQ=9
Lan2MemoryBase1=
Lan2MemoryBase2=
ATATryPrimary=No
ATATrySecondary=Yes
ATATryLinear=Yes
FastTokenRing=Yes
DetectNonCompliant=No
ContinueOnConfigFailure=No
BeepInDOS=Yes
BeepInWindows=Yes
GrabInitFile=Yes
InitBufferSize=512
UseEMS=No

[Libraries]

;
; The Libraries section contains references to any card libraries the user
; wishes to include. Libraries are searched in the specified order. Path
; names are relative to the directory containing CARDID.INI.

;
CardLib=canonfd.clb
CardLib=xirdual.clb
CardLib=xircom.clb
CardLib=tdkklan2.clb
CardLib=sundisk5.clb
CardLib=intellan.clb
CardLib=dlink.clb
CardLib=linksys.clb
CardLib=linksys2.clb
CardLib=socketea.clb
CardLib=ibmlan.clb
CardLib=ibmtok.clb
CardLib=ibm3270.clb
CardLib=proxim.clb
CardLib=cbdass.clb
CardLib=genmodem.clb
CardLib=genata.clb
CardLib=wd.clb

Configuration Notes:

In Windows 3.1 and DOS the modem will automatically be configured for Com 2. The drivers for all the above modems are also included in Windows 95, and upon insertion it will be configured for Com 2.

PLATFORM: COMPAQ LTE 5000

ROM: 09/19/95

PC CARDS:

COMPAQ SPEEDPAQ 192, PN: 187100-001

COMPAQ 288, PN: 189650-001

MEGAHERTZ 28.8/14.4 DATA FAX, PN: XJ2288/CC3288

OPERATING SYSTEM: WINDOWS 3.1/DOS 6.2

CARD AND SOCKET SERVICES: 3.14

CONFIG.SYS

```
DEVICE=C:\CPQDOS\MACHCHK.SYS 02A8 02B0 02BA 02CA
DEVICE=C:\DOS\HIMEM.SYS
DEVICE=C:\DOS\EMM386.exe NOEMS I=B000-B7FF X=C800-CBFF X=D100-D5FF X=E800-EFFF
COUNTRY=001,437,C:\DOS\COUNTRY.SYS
SHELL=C:\DOS\COMMAND.COM /P /E:1536
DOS=HIGH,UMB
FILES=35
BUFFERS=20,0
STACKS=9,256
DEVICEHIGH=C:\AUDIO_CD\TEAC_CDI.SYS /D:TEAC-CDI
LASTDRIVE=M
REM PC Card: Begin PC Card (PCMCIA) Drivers
REM **Warning: Do not move, reorder, or delete any of these lines. **
DEVICEHIGH=C:\CARDWIZ\SSCIRUS2.EXE
DEVICEHIGH=C:\CARDWIZ\CS.EXE /POLL:1
DEVICEHIGH=C:\CARDWIZ\CSALLOC.EXE
DEVICEHIGH=C:\CARDWIZ\CARDID.EXE
REM PC Card: End PC Card(PCMCIA) Drives
```

AUTOEXEC.BAT

```
@ECHO OFF
C:\WINDOWS\VGAUTIL\winmode.exe t640=60 t800=60 t1024=87 t1280=87
SET NWLANGUAGE=ENGLISH
PATH C:\WINDOWS;C:\CPQDOS;C:\DOS;C:\AUDIO_CD;C:\CARDWIZ
PROMPT $p$g
SET DIRCMD=/ogn
SET TEMP=C:\WINDOWS\TEMP
SET BLASTER=A220 D1 15
SET LMOUSE=C:\MOUSE
SET MOUSE=C:\MOUSE
C:\MOUSE\MOUSE.EXE MEMU
C:\DOS\MSCDEX.EXE /D:TEAC-CDI /M:15
IF ERRORLEVEL 1 GOTO NO_CDROM
C:\AUDIO_CD\ESSVOL /V:15 /C:15
:NO_CDROM
LH C:\DOS\SMARTDRV.EXE
C:\CPQDOS\0VMAKFIL
IF NOT EXIST C:\CPQDOS\SAVEDONE.CPQ CALL SAVEALL /A
WIN
```

CARDID.INI

```
[Common]
; Common Information section created by Config
ComPort1=3F8
ComIRQ1=4
ComPort2=2F8
ComIRQ2=9
ComPort3=3E8
ComIRQ3=4
ComPort4=2E8
ComIRQ4=3
ComBySocket=No
ComBDAAbsolute=Yes
ComRollOverOn=No
CARDID.INI-continued
```

FirstModem=4
SecondModem=2
ThirdModem=2
FourthModem=1
Audio=Yes
RingIndicate=No
Suspend_Power=No
Lan1Port=300
Lan1IRQ=5
Lan1MemoryBase1=D4
Lan1MemoryBase2=D6
Lan2Port=310
Lan2IRQ=10
Lan2MemoryBase1=D8
Lan2MemoryBase2=DC
ATATryPrimary=Yes
ATATrySecondary=Yes
ATATryLinear=Yes
FastTokenRing=No
DetectNonCompliant=No
ContinueOnConfigFailure=No
BeepInDOS=Yes
BeepInWindows=Yes
GrabInitFile=Yes
InitBufferSize=512
FirstLan=1
SecondLan=2
ATATryMemory=No
ATAFirstConf=0
ATASecondConf=1
ATAThirdConf=2
ATAFourthConf=3

[Libraries]

; The Libraries section contains references to any card libraries the user
; wishes to include. Libraries are searched in the specified order. Path
; names are relative to the directory containing CARDID.INI.

;
CardLib=xirdual.clb
CardLib=xircom.clb
CardLib=tdkklan2.clb
CardLib=sundisk5.clb
CardLib=intellan.clb
CardLib=dlink.clb
CardLib=linksys.clb
CardLib=linksys2.clb
CardLib=socketea.clb
CardLib=ibmlan.clb
CardLib=ibmtok.clb
CardLib=ibm3270.clb
CardLib=proxim.clb
CardLib=cbdass.clb
CardLib=genmodem.clb
CardLib=genata.clb
CardLib=wd.clb

Configuration Notes:

In Windows 3.1 and DOS the modem will automatically be configured for Com 2. The drivers for all the above modems are also included in Windows 95, and upon insertion it will be configured for Com 2.

NETWORK CARDS

PLATFORM: *COMPAQ AERO 4/25*

ROM: *07/19/95*

PC CARD: *COMPAQ ETHERNET LAN CARD, PN: 224750-XXX*

OPERATING SYSTEM: *WINDOWS 3.1/DOS 6.2*

NOS: *NOVELL 3.12*

CARD AND SOCKET SERVICES: *1.25*

CONFIG.SYS

REM Compaq LAN Adapter --- Do Not Change Lines Below (MENU)

[menu]

menuitem=CPQ_E_COMPAQ,Load Drivers For Network Access

menuitem=COM_END,Do Not Load Any Compaq Drivers

menucolor=15,0

[CPQ_E_COMPAQ]

[COM_END]

[common]

REM Compaq LAN Adapter --- Do Not Change Lines Above

SHELL=C:\DOS\COMMAND.COM /P /E:1536

STACKS=9,256

DEVICE=C:\DOS\HIMEM.SYS

DEVICE=C:\DOS\EMM386.EXE NOEMS X=D000-DFFF

DOS=UMB

REM *** Begin PCMCIA Drivers

REM Warning: Do not move, reorder, or delete any of these lines.

REM

DEVICE=C:\CPQDOS\PCSMIX.EXE

DEVICEHIGH=C:\CPQDOS\SSVLSI.EXE

DEVICEHIGH=C:\CPQDOS\CS.EXE

DEVICE=C:\CPQDOS\CSALLOC.EXE

DEVICEHIGH=C:\CPQDOS\ATADRV.EXE /D:1

DEVICEHIGH=C:\CPQDOS\CARDID.EXE C:\CPQDOS\CARDID.INI

DEVICEHIGH=C:\CPQDOS\MEMDRV.EXE

;DEVICEHIGH=C:\CPQDOS\DBLFLASH.EXE

;DEVICEHIGH=C:\CPQDOS\MS-FLASH.SYS

REM *** End PCMCIA Drivers

DOS=HIGH

BUFFERS=20

FILES=35

DEVICEHIGH=C:\CPQDOS\POWER.EXE

AUTOEXEC.BAT

@loadhigh C:\DOS\SHARE.EXE /I:500 /F:5100

SET PATH=C:\CPQDOS;C:\;C:\DOS;C:\WINDOWS;C:\MOUSE;C:\WINDOWS\CPQWIN

SET LMOUSE=C:\MOUSE

SET PROMPT=\$PSG

SET TEMP=C:\WINDOWS\TEMP

C:\CPQDOS\HIBRN8.EXE

C:\DOS\SMARTDRV.EXE

LH C:\MOUSE\MOUSE SWAP

C:\CPQDOS\MODE.COM CO80

REM Compaq LAN Adapter --- Do Not Change Lines Below

:COM_MENU

@echo off

cls

goto %config%

:CPQ_E_COMPAQ

C:

cd C:\COMPAQ\CPQ

if not exist CPQODI.COM goto COM_ERROR

CPQCFG.EXE DRIVER=ODI

LSL

CPQODI.COM

IPXODI

AUTOEXEC.BAT-continued

NETX

```
if not exist XCHECK.EXE goto S_CPQ_E_COMPAQ
cls
XCHECK.EXE -e -1 F:
:S_CPQ_E_COMPAQ
F:
login
goto COM_END
:COM_ERROR
echo Error: Unable to locate driver file.
:COM_END
C:
cd \
REM Compaq Ethernet LAN Adapter --- Do Not Change Lines Above
REM Compaq Ethernet LAN Adapter --- Do Not Change Lines Below (PATH)
PATH=%PATH%;C:\COMPAQ\CPQ
REM Compaq Ethernet LAN Adapter --- Do Not Change Lines Above
REM 'win.com' reference moved by Compaq Installation Program
C:\WINDOWS\WIN
```

NETWORK DRIVERS

| | | |
|-------------|--------|----------|
| LSL.COM | 18,285 | 04-17-95 |
| IPXODI.COM | 39,353 | 10-31-94 |
| CPQODI.COM | 53,698 | 11-15-95 |
| CPQTEST.EXE | 68,133 | 11-15-95 |
| CPQCFG.EXE | 29,440 | 11-29-95 |
| NETX.EXE | 78,654 | 11-17-93 |

NET.CFG

```
link driver CPQODI
frame ethernet_802.2
int 5
port 320
mem DE000
```

CARDID.INI

```
[Common]
;
; Common Information section created by Config
;
ComPort1=3F8
ComIRQ1=4
ComPort2=2F8
ComIRQ2=3
ComPort3=3E8
ComIRQ3=4
ComPort4=2E8
ComIRQ4=3
ComBySocket=Yes
ComBDAAbsolute=No
FirstModem=2
SecondModem=2
ThirdModem=3
FourthModem=4
Audio=Yes
RingIndicate=No
Lan1Port=300
Lan1IRQ=5
Lan1MemoryBase1=D8
Lan1MemoryBase2=DC
Lan2Port=310
Lan2IRQ=10
Lan2MemoryBase1=D8
Lan2MemoryBase2=DC
ATATryPrimary=No
ATATrySecondary=Yes
ATATryLinear=Yes
FastTokenRing=Yes
DetectNonCompliant=No
ContinueOnConfigFailure=No
CARDID.INI-continued
```

```
BeepInDOS=Yes
BeepInWindows=Yes
GrabInitFile=Yes
InitBufferSize=512
```

```
[Libraries]
```

```
;  
; The Libraries section contains references to any card libraries the user  
; wishes to include. Libraries are searched in the specified order. Path  
; names are relative to the directory containing CARDID.INI.  
;  
CardLib=cardid.clb
```

Configuration Notes:

The software was installed from Windows 3.1. In order to install the software you must first copy the driver diskettes to the hard drive, and then replace the floppy driver with the ethernet card. The software will correctly install at that point, and with this machine the resource assignments were IRQ 5, I/O 320, and MEM DE000. The drivers for Windows 95 are not built in, so upon insertion it will ask you for a diskette. The Windows 95 drivers are supplied on the diskettes that came with the card.

PLATFORM: *COMPAQ CONCERTO*

ROM: *10/12/93*

PC CARD: *COMPAQ ETHERNET LAN CARD, PN: 224750-XXX*

OPERATING SYSTEM: *WINDOWS 3.1/DOS 6.2*

NOS: *NOVELL 3.12*

CARD AND SOCKET SERVICES: *1.25*

CONFIG.SYS

REM Compaq LAN Adapter --- Do Not Change Lines Below (MENU)

[menu]

menuitem=CPQ_E_COMPAQ,Load Drivers For Network Access

menuitem=COM_END,Do Not Load Any Compaq Drivers

menucolor=15,0

[CPQ_E_COMPAQ]

[COM_END]

[common]

REM Compaq LAN Adapter --- Do Not Change Lines Above

SHELL=C:\DOS\COMMAND.COM /P /E:1536

STACKS=9,256

DEVICE=C:\DOS\HIMEM.SYS

DEVICE=C:\DOS\EMM386.EXE NOEMS X=D000-DFFF

DOS=UMB

REM *** Begin PCMCIA Drivers

REM Warning: Do not move, reorder, or delete any of these lines.

REM

DEVICEHIGH=C:\CPQDOS\SSCIRRUS.EXE

DEVICEHIGH=C:\CPQDOS\CS.EXE

DEVICE=C:\CPQDOS\CSALLOC.EXE

DEVICEHIGH=C:\CPQDOS\ATADRV.EXE

DEVICEHIGH=C:\CPQDOS\CARDID.EXE C:\CPQDOS\CARDID.INI

DEVICEHIGH=C:\CPQDOS\MEMDRV.EXE

;DEVICEHIGH=C:\CPQDOS\DBLFLASH.EXE

;DEVICEHIGH=C:\CPQDOS\MS-FLASH.SYS

REM *** End PCMCIA Drivers

DOS=HIGH

BUFFERS=20

FILES=35

DEVICEHIGH=C:\CPQDOS\POWER.EXE

AUTOEXEC.BAT

SET PATH=C:\CPQDOS;C:\;C:\DOS;C:\WINDOWS;C:\MOUSE;C:\WINDOWS\CPQWIN

SET LMOUSE=C:\MOUSE

SET PROMPT=\$PSG

SET TEMP=C:\WINDOWS\TEMP

C:\CPQDOS\HIBRN8.EXE

C:\DOS\SMARTDRV.EXE

LH C:\MOUSE\MOUSE

C:\CPQDOS\MODE.COM CO80

REM Compaq Ethernet LAN Adapter --- Do Not Change Lines Below

:COM_MENU

@echo off

cls

goto %config%

:CPQ_E_COMPAQ

C:

cd C:\COMPAQ\CPQ

if not exist CPQODI.COM goto COM_ERROR

CPQCFG.EXE DRIVER=ODI

LSL

CPQODI.COM

IPXODI

NETX

if not exist XCHECK.EXE goto S_CPQ_E_COMPAQ

cls

AUTOEXEC.BAT-continued

```

XCHECK.EXE -e -1 H:
:S_CPQ_E_COMPAQ
H:
login
goto COM_END
:COM_ERROR
echo Error: Unable to locate driver file.
:COM_END
C:
cd \
REM Compaq Ethernet LAN Adapter --- Do Not Change Lines Above
REM Compaq Ethernet LAN Adapter --- Do Not Change Lines Below (PATH)
PATH=%PATH%;C:\COMPAQ\CPQ
REM Compaq Ethernet LAN Adapter --- Do Not Change Lines Above
REM 'win.com' reference moved by Compaq Installation Program
C:\WINDOWS\WIN

```

NETWORK DRIVERS

| | | |
|-------------|--------|----------|
| LSL.COM | 18,285 | 04-17-95 |
| IPXODI.COM | 39,353 | 10-31-94 |
| CPQODI.COM | 53,698 | 11-15-95 |
| CPQTEST.EXE | 68,133 | 11-15-95 |
| CPQCFG.EXE | 29,440 | 11-29-95 |
| NETX.EXE | 78,654 | 11-17-93 |

NET.CFG

```

link driver CPQODI
frame ethernet_802.2
int 5
port 320
mem DE000

```

CARDID.INI

```

[Common]
;
; Common Information section created by Config
;
ComPort1=3F8
ComIRQ1=4
ComPort2=2F8
ComIRQ2=3
ComPort3=3E8
ComIRQ3=4
ComPort4=2E8
ComIRQ4=3
ComBySocket=Yes
ComBDAAbsolute=No
FirstModem=2
SecondModem=2
ThirdModem=3
FourthModem=4
Audio=Yes
RingIndicate=No
Lan1Port=300
Lan1IRQ=5
Lan1MemoryBase1=D8
Lan1MemoryBase2=DC
Lan2Port=310
Lan2IRQ=10
Lan2MemoryBase1=D8
Lan2MemoryBase2=DC
ATATryPrimary=No
ATATrySecondary=Yes
ATATryLinear=Yes
FastTokenRing=Yes
DetectNonCompliant=No
ContinueOnConfigFailure=No
BeepInDOS=Yes
BeepInWindows=Yes
GrabInitFile=Yes
CARDID.INI-continued

```

InitBufferSize=512

[Libraries]

;
; The Libraries section contains references to any card libraries the user
; wishes to include. Libraries are searched in the specified order. Path
; names are relative to the directory containing CARDID.INI.
;
CardLib=cardid.clb

Configuration Notes:

The software was installed from Windows 3.1. The software automatically made all the necessary changes, and assigned the resources IRQ 5, I/O 320, and MEM DE000. The drivers for Windows 95 are not built in, so when the card is inserted a window will pop up prompting you for a diskette. The diskette is provided with the card, simply insert diskette and press enter. The card will then be recognized and configured.

PLATFORM: COMPAQ CONTURA 410C

ROM: 04/10/95

PC CARD: COMPAQ ETHERNET LAN CARD, PN: 224750-XXX

OPERATING SYSTEM: WINDOWS 3.1/DOS 6.2

NOS: NOVELL 3.12

CARD AND SOCKET SERVICES: 3.12

CONFIG.SYS

REM Compaq LAN Adapter --- Do Not Change Lines Below (MENU)

[menu]

menuitem=CPQ_E_COMPAQ,Load Drivers For Network Access

menuitem=COM_END,Do Not Load Any Compaq Drivers

menucolor=15,0

[CPQ_E_COMPAQ]

[COM_END]

[common]

REM Compaq LAN Adapter --- Do Not Change Lines Above

switches=/F

SHELL=C:\DOS\COMMAND.COM /P /E:1536

STACKS=9,256

DEVICE=C:\DOS\HIMEM.SYS

DEVICE=C:\DOS\EMM386.EXE NOEMS I=B000-B7FF X=D000-D4FF

DEVICEHIGH=C:\WINDOWS\CPQWIN\CPQCM.SYS

DOS=HIGH,UMB

REM *** Begin PCMCIA Drivers

REM Warning: Do not move, reorder, or delete any of these lines.

REM

;DEVICE=C:\CPQDOS\PCMSMIX.EXE

DEVICEHIGH=C:\CPQDOS\SSVLSI.EXE

DEVICEHIGH=C:\CPQDOS\CS.EXE

DEVICE=C:\CPQDOS\CSALLOC.EXE

;DEVICEHIGH=C:\CPQDOS\ATADRV.EXE

;DEVICEHIGH=C:\CPQDOS\MTAA.EXE

;DEVICEHIGH=C:\CPQDOS\MTAB.EXE

;DEVICEHIGH=C:\CPQDOS\MTI1.EXE

;DEVICEHIGH=C:\CPQDOS\MTI2P.EXE

;DEVICEHIGH=C:\CPQDOS\MTSRAM.EXE

;DEVICEHIGH=C:\CPQDOS\MTDDRV.EXE

;DEVICEHIGH=C:\CPQDOS\DBLFLASH.EXE

;DEVICEHIGH=C:\CPQDOS\MS-FLASH.SYS

DEVICEHIGH=C:\CPQDOS\CARDID.EXE

REM *** End PCMCIA Drivers

BUFFERS=20

FILES=35

DEVICEHIGH=C:\CPQDOS\EPPBIOS.SYS

DEVICEHIGH=C:\CPQDOS\POWER.EXE

AUTOEXEC.BAT

@ECHO OFF

SET PATH=C:\CPQDOS;C:\;C:\DOS;C:\WINDOWS;;C:\WINDOWS\CPQWIN

SET LMOUSE=C:\MOUSE

LH C:\MOUSE\MOUSE

SET PROMPT=\$PSG

SET TEMP=C:\WINDOWS\TEMP

C:\CPQDOS\HIBRN8.EXE

LH C:\DOS\SMARTDRV.EXE

LH SHARE.EXE

REM Compaq Ethernet LAN Adapter --- Do Not Change Lines Below

:COM_MENU

@echo off

cls

goto %config%

:CPQ_E_COMPAQ

AUTOEXEC.BAT-continued

```
C:
cd C:\COMPAQ\CPQ
if not exist CPQODI.COM goto COM_ERROR
CPQCFG.EXE DRIVER=ODI
LSL
CPQODI.COM
IPXODI
NETX
if not exist XCHECK.EXE goto S_CPQ_E_COMPAQ
cls
XCHECK.EXE -e -1 F:
:S_CPQ_E_COMPAQ
F:
login
goto COM_END
:COM_ERROR
echo Error: Unable to locate driver file.
:COM_END
C:
cd \
REM Compaq Ethernet LAN Adapter --- Do Not Change Lines Above
REM Compaq Ethernet LAN Adapter --- Do Not Change Lines Below (PATH)
PATH=%PATH%;C:\COMPAQ\CPQ
REM Compaq Ethernet LAN Adapter --- Do Not Change Lines Above
REM 'win.com' reference moved by Compaq Installation Program
C:\WINDOWS\WIN
```

NETWORK DRIVERS

| | | |
|-------------|--------|----------|
| LSL.COM | 18,285 | 04-17-95 |
| IPXODI.COM | 39,353 | 10-31-94 |
| CPQODI.COM | 53,698 | 11-15-95 |
| CPQTEST.EXE | 68,133 | 11-15-95 |
| CPQCFG.EXE | 29,440 | 11-29-95 |
| NETX.EXE | 78,654 | 11-17-93 |

NET.CFG

```
link driver CPQODI
frame ethernet_802.2
int 5
port 320
mem D3000
```

CARDID.INI

```
[Common]
;
; Common Information section created by Config
;
ComPort1=3F8
ComIRQ1=4
ComPort2=2F8
ComIRQ2=3
ComPort3=3e8
ComIRQ3=4
ComPort4=2E8
ComIRQ4=3
ComBySocket=Yes
ComBDAAbsolute=No
FirstModem=2
SecondModem=2
ThirdModem=3
FourthModem=4
Audio=Yes
RingIndicate=No
Lan1Port=300
Lan1IRQ=5
Lan1MemoryBase1=
Lan1MemoryBase2=
Lan2Port=310
Lan2IRQ=9
Lan2MemoryBase1=
CARDID.INI-continued
```


Lan2MemoryBase2=
ATATryPrimary=No
ATATrySecondary=Yes
ATATryLinear=Yes
FastTokenRing=Yes
DetectNonCompliant=No
ContinueOnConfigFailure=No
BeepInDOS=Yes
BeepInWindows=Yes
GrabInitFile=Yes
InitBufferSize=512
UseEMS=No

[Libraries]

;
; The Libraries section contains references to any card libraries the user
; wishes to include. Libraries are searched in the specified order. Path
; names are relative to the directory containing CARDID.INI.

;
CardLib=canonfd.clb
CardLib=xirdual.clb
CardLib=xircom.clb
CardLib=tdkfan2.clb
CardLib=sundisk5.clb
CardLib=intellan.clb
CardLib=dlink.clb
CardLib=linksys.clb
CardLib=linksys2.clb
CardLib=socketea.clb
CardLib=ibmlan.clb
CardLib=ibmtok.clb
CardLib=ibm3270.clb
CardLib=proxim.clb
CardLib=cbdass.clb
CardLib=genmodem.clb
CardLib=genata.clb
CardLib=wd.clb

Configuration Notes:

The software was installed from Windows 3.1. The software automatically made all the necessary changes, and assigned the resources IRQ 5, I/O 320, and MEM D3000. The drivers for Windows 95 are not built in, so when the card is inserted a window will pop up prompting you for a diskette. The diskette is provided with the card, simply insert diskette and press enter. The card will then be recognized and configured.

PLATFORM: COMPAQ CONTURA 420CX

ROM: 08/20/95

PC CARD: COMPAQ ETHERNET LAN CARD, PN: 224750-XXX

OPERATING SYSTEM: WINDOWS 3.1/DOS 6.2

CARD AND SOCKET SERVICES: 3.12

CONFIG.SYS

REM Compaq LAN Adapter --- Do Not Change Lines Below (MENU)

[menu]

menuitem=CPQ_E_COMPAQ,Load Drivers For Network Access

menuitem=COM_END,Do Not Load Any Compaq Drivers

menucolor=15,0

[CPQ_E_COMPAQ]

[COM_END]

[common]

REM Compaq LAN Adapter --- Do Not Change Lines Above

switches=/F

SHELL=C:\DOS\COMMAND.COM /P /E:1536

STACKS=9,256

DEVICE=C:\DOS\HIMEM.SYS

DEVICE=C:\DOS\EMM386.EXE NOEMS I=B000-B7FF X=D000-D4FF

DEVICEHIGH=C:\WINDOWS\CPQWIN\CPQCM.SYS

DOS=HIGH,UMB

REM *** Begin PCMCIA Drivers

REM Warning: Do not move, reorder, or delete any of these lines.

REM

;DEVICE=C:\CPQDOS\PCMSMIX.EXE

DEVICEHIGH=C:\CPQDOS\SSVLSI.EXE

DEVICEHIGH=C:\CPQDOS\CS.EXE

DEVICE=C:\CPQDOS\CSALLOC.EXE

;DEVICEHIGH=C:\CPQDOS\ATADRV.EXE

;DEVICEHIGH=C:\CPQDOS\MTAA.EXE

;DEVICEHIGH=C:\CPQDOS\MTAB.EXE

;DEVICEHIGH=C:\CPQDOS\MTI1.EXE

;DEVICEHIGH=C:\CPQDOS\MTI2P.EXE

;DEVICEHIGH=C:\CPQDOS\MTSRAM.EXE

;DEVICEHIGH=C:\CPQDOS\MTDDRIV.EXE

;DEVICEHIGH=C:\CPQDOS\DBLFLASH.EXE

;DEVICEHIGH=C:\CPQDOS\MS-FLASH.SYS

DEVICEHIGH=C:\CPQDOS\CARDID.EXE

REM *** End PCMCIA Drivers

BUFFERS=20

FILES=50

DEVICEHIGH=C:\CPQDOS\EPPBIOS.SYS

AUTOEXEC.BAT

@loadhigh C:\DOS\SHARE.EXE /I:500 /f:5100

@ECHO OFF

SET PATH=C:\CPQDOS;C:\;C:\DOS;C:\WINDOWS;;C:\WINDOWS\CPQWIN

SET LMOUSE=C:\MOUSE

LH C:\MOUSE\MOUSE

SET PROMPT=\$P\$G

SET TEMP=C:\WINDOWS\TEMP

C:\CPQDOS\HIBRN8.EXE

C:\DOS\SMARTDRV.EXE 2048 512

REM Compaq Ethernet LAN Adapter --- Do Not Change Lines Below

:COM_MENU

@echo off

cls

goto %config%

:CPQ_E_COMPAQ

C:

cd C:\COMPAQ\CPQ

if not exist CPQODI.COM goto COM_ERROR

CPQCFG.EXE DRIVER=ODI

LSL

AUTOEXEC.BAT-continued

```
CPQODI.COM
IPXODI
NETX
if not exist XCHECK.EXE goto S_CPQ_E_COMPAQ
cls
XCHECK.EXE -e -1 F:
:S_CPQ_E_COMPAQ
F:
login
goto COM_END
:COM_ERROR
echo Error: Unable to locate driver file.
:COM_END
C:
cd \
REM Compaq Ethernet LAN Adapter --- Do Not Change Lines Above
REM Compaq Ethernet LAN Adapter --- Do Not Change Lines Below (PATH)
PATH=%PATH%;C:\COMPAQ\CPQ
REM Compaq Ethernet LAN Adapter --- Do Not Change Lines Above
REM 'win.com' reference moved by Compaq Installation Program
C:\WINDOWS\WIN
```

NETWORK DRIVERS

| | | |
|-------------|--------|----------|
| LSL.COM | 18,285 | 04-17-95 |
| IPXODI.COM | 39,353 | 10-31-94 |
| CPQODI.COM | 53,698 | 11-15-95 |
| CPQTEST.EXE | 68,133 | 11-15-95 |
| CPQCFG.EXE | 29,440 | 11-29-95 |
| NETX.EXE | 78,654 | 11-17-93 |

NET.CFG

```
link driver CPQODI
frame ethernet_802.2
int 5
port 320
mem D3000
```

CARDID.INI

```
[Common]
;
; Common Information section created by Config
;
ComPort1=3F8
ComIRQ1=4
ComPort2=2F8
ComIRQ2=3
ComPort3=3e8
ComIRQ3=4
ComPort4=2E8
ComIRQ4=3
ComBySocket=Yes
ComBDAAbsolute=No
FirstModem=2
SecondModem=2
ThirdModem=3
FourthModem=4
Audio=Yes
RingIndicate=No
Lan1Port=300
Lan1IRQ=5
Lan1MemoryBase1=
Lan1MemoryBase2=
Lan2Port=310
Lan2IRQ=9
Lan2MemoryBase1=
Lan2MemoryBase2=
ATATryPrimary=No
ATATrySecondary=Yes
ATATryLinear=Yes
FastTokenRing=Yes
CARDID.INI-continued
```

DetectNonCompliant=No
ContinueOnConfigFailure=No
BeepInDOS=Yes
BeepInWindows=Yes
GrabInitFile=Yes
InitBufferSize=512
UseEMS=No

[Libraries]

;
; The Libraries section contains references to any card libraries the user
; wishes to include. Libraries are searched in the specified order. Path
; names are relative to the directory containing CARDID.INI.

;
CardLib=canonfd.clb
CardLib=xirdual.clb
CardLib=xircom.clb
CardLib=tdkklan2.clb
CardLib=sundisk5.clb
CardLib=intellan.clb
CardLib=dlink.clb
CardLib=linksys.clb
CardLib=linksys2.clb
CardLib=socketea.clb
CardLib=ibmlan.clb
CardLib=ibmtok.clb
CardLib=ibm3270.clb
CardLib=proxim.clb
CardLib=cbdass.clb
CardLib=genmodem.clb
CardLib=genata.clb
CardLib=wd.clb

Configuration Notes:

The software was installed from Windows 3.1. The software automatically made all the necessary changes, and assigned the resources IRQ 5, I/O 320, and MEM DE000. The drivers for Windows 95 are not built in, so when the card is inserted a window will pop up prompting you for a diskette. The diskette is provided with the card, simply insert diskette and press enter. The card will then be recognized and configured.

PLATFORM: COMPAQ ELITE 4/75CXL

ROM: 07/19/95

PC CARD: COMPAQ ETHERNET LAN CARD, PN: 224750-XXX

OPERATING SYSTEM: WINDOWS 3.1/DOS 6.2

CARD AND SOCKET SERVICES: 3.12

CONFIG.SYS

REM Compaq LAN Adapter --- Do Not Change Lines Below (MENU)

[menu]

menuitem=CPQ_E_COMPAQ,Load Drivers For Network Access

menuitem=COM_END,Do Not Load Any Compaq Drivers

menucolor=15,0

[CPQ_E_COMPAQ]

[COM_END]

[common]

REM Compaq LAN Adapter --- Do Not Change Lines Above

SHELL=C:\DOS\COMMAND.COM /P /E:1536

STACKS=9,256

DEVICE=C:\DOS\HIMEM.SYS

DEVICE=C:\DOS\EMM386.EXE NOEMS I=B000-B7FF X=D000-D4FF

DEVICEHIGH=C:\WINDOWS\CPQWIN\CPQCM.SYS

DOS=HIGH,UMB

REM *** Begin PCMCIA Drivers

REM Warning: Do not move, reorder, or delete any of these lines.

REM

;DEVICE=C:\CPQDOS\PCMSMIX.EXE

DEVICEHIGH=C:\CPQDOS\SSVLSI.EXE

DEVICEHIGH=C:\CPQDOS\CS.EXE

DEVICE=C:\CPQDOS\CSALLOC.EXE

;DEVICEHIGH=C:\CPQDOS\ATADRV.EXE

;DEVICEHIGH=C:\CPQDOS\MTAA.EXE

;DEVICEHIGH=C:\CPQDOS\MTAB.EXE

;DEVICEHIGH=C:\CPQDOS\MTI1.EXE

;DEVICEHIGH=C:\CPQDOS\MTI2P.EXE

;DEVICEHIGH=C:\CPQDOS\MTSRAM.EXE

;DEVICEHIGH=C:\CPQDOS\MTDDRIV.EXE

;DEVICEHIGH=C:\CPQDOS\DBLFLASH.EXE

;DEVICEHIGH=C:\CPQDOS\MS-FLASH.SYS

DEVICEHIGH=C:\CPQDOS\CARDID.EXE

REM *** End PCMCIA Drivers

BUFFERS=20

FILES=35

REM Compaq Ethernet LAN Adapter --- Do Not Change Lines Below (LASTDRIVE)

REM LASTDRIVE = Z

REM Compaq Ethernet LAN Adapter --- Do Not Change Lines Above

DEVICEHIGH=C:\CPQDOS\POWER.EXE

AUTOEXEC.BAT

@ECHO OFF

SET PATH=C:\CPQDOS;C:\;C:\DOS;C:\WINDOWS;;C:\WINDOWS\CPQWIN

SET LMOUSE=C:\MOUSE

LH C:\MOUSE\MOUSE

SET PROMPT=\$PSG

SET TEMP=C:\WINDOWS\TEMP

C:\CPQDOS\HIBRN8.EXE

LH C:\DOS\SMARTDRV.EXE

SET NWLANGUAGE=ENGLISH

REM Compaq Ethernet LAN Adapter --- Do Not Change Lines Below

:COM_MENU

@echo off

cls

goto %config%

:CPQ_E_COMPAQ

AUTOEXEC.BAT-continued

```

C:
cd C:\COMPAQ\CPQ
if not exist CPQODI.COM goto COM_ERROR
CPQCFG.EXE DRIVER=ODI
LSL
CPQODI.COM
IPXODI
NETX
if not exist XCHECK.EXE goto S_CPQ_E_COMPAQ
cls
XCHECK.EXE -e -1 F:
:S_CPQ_E_COMPAQ
F:
login
goto COM_END
:COM_ERROR
echo Error: Unable to locate driver file.
:COM_END
C:
cd \
REM Compaq Ethernet LAN Adapter --- Do Not Change Lines Above
REM Compaq Ethernet LAN Adapter --- Do Not Change Lines Below (PATH)
PATH=%PATH%;C:\COMPAQ\CPQ
REM Compaq Ethernet LAN Adapter --- Do Not Change Lines Above
REM 'win.com' reference moved by Compaq Installation Program
C:\WINDOWS\WIN

```

NETWORK DRIVERS

| | | |
|-------------|--------|----------|
| LSL.COM | 18,285 | 04-17-95 |
| IPXODI.COM | 39,353 | 10-31-94 |
| CPQODI.COM | 53,698 | 11-15-95 |
| CPQTEST.EXE | 68,133 | 11-15-95 |
| CPQCFG.EXE | 29,440 | 11-29-95 |
| NETX.EXE | 78,654 | 11-17-93 |

NET.CFG

```

link driver CPQODI
frame ethernet_802.2
int 5
port 320
mem D3000

```

CARDID.INI

```

[Common]
;
; Common Information section created by Config
;
ComPort1=3F8
ComIRQ1=4
ComPort2=2F8
ComIRQ2=3
ComPort3=3e8
ComIRQ3=4
ComPort4=2E8
ComIRQ4=3
ComBySocket=Yes
ComBDAAbsolute=No
FirstModem=2
SecondModem=2
ThirdModem=3
FourthModem=4
Audio=Yes
RingIndicate=No
Lan1Port=300
Lan1IRQ=5
Lan1MemoryBase1=
Lan1MemoryBase2=
Lan2Port=310
Lan2IRQ=9
Lan2MemoryBase1=
CARDID.INI-continued

```

```
Lan2MemoryBase2=  
ATATryPrimary=No  
ATATrySecondary=Yes  
ATATryLinear=Yes  
FastTokenRing=Yes  
DetectNonCompliant=No  
ContinueOnConfigFailure=No  
BeepInDOS=Yes  
BeepInWindows=Yes  
GrabInitFile=Yes  
InitBufferSize=512  
UseEMS=No
```

[Libraries]

```
;  
; The Libraries section contains references to any card libraries the user  
; wishes to include. Libraries are searched in the specified order. Path  
; names are relative to the directory containing CARDID.INI.  
;
```

```
CardLib=canonfd.clb  
CardLib=xirdual.clb  
CardLib=xircom.clb  
CardLib=tdklan2.clb  
CardLib=sundisk5.clb  
CardLib=intellan.clb  
CardLib=dlink.clb  
CardLib=linksys.clb  
CardLib=linksys2.clb  
CardLib=socketea.clb  
CardLib=ibmlan.clb  
CardLib=ibmtok.clb  
CardLib=ibm3270.clb  
CardLib=proxim.clb  
CardLib=cbdas.clb  
CardLib=genmodem.clb  
CardLib=genata.clb  
CardLib=wd.clb
```

Configuration Notes:

The software was installed from Windows 3.1, it can only be installed while the card is in slot 1. The software automatically made all the necessary changes, and assigned the resources IRQ 5, I/O 320, and MEM D3000. We did change the internal network controller in the base to IRQ 10 I/O 220 so card will function in or out of base without interruption. The drivers for Windows 95 are not built in, so when the card is inserted a window will pop up prompting you for a diskette. The diskette is provided with the card, simply insert diskette and press enter. The card will then be recognized and configured.

PLATFORM: *COMPAQ LTE 5200*

ROM: *09/27/95*

PC CARD: *COMPAQ ETHERNET LAN CARD, PN: 224750-XXX*

OPERATING SYSTEM: *WINDOWS 3.1/DOS 6.2*

CARD AND SOCKET SERVICES: *3.14*

CONFIG.SYS

REM Compaq LAN Adapter --- Do Not Change Lines Below (MENU)

[menu]

menuitem=CPQ_E_COMPAQ,Load Drivers For Network Access

menuitem=COM_END,Do Not Load Any Compaq Drivers

menucolor=15,0

[CPQ_E_COMPAQ]

[COM_END]

[common]

REM Compaq LAN Adapter --- Do Not Change Lines Above

REM MachChk: Verify that this CONFIG.SYS and AUTOEXEC.BAT are for this computer

DEVICE=C:\CPQDOS\MACHCHK.SYS 02A8 02B0 02BA 02CA

DEVICE=C:\DOS\HIMEM.SYS

DEVICEHIGH=C:\DOS\EMM386.EXE NOEMS I=B000-B7FF X=C800-CBFF X=D100-D5FF X=E800-EFFF

X=E800-EFFF

COUNTRY=001,437,C:\DOS\COUNTRY.SYS

REM DEVICE=C:\DOS\DISPLAY.SYS CON=(EGA,,1)

SHELL=C:\DOS\COMMAND.COM /P /E:1536

DOS=HIGH,UMB

FILES=35

BUFFERS=20,0

STACKS=9,256

REM POWER: Remove "REM" to enhance battery life for non-Windows users

REM DEVICEHIGH=C:\DOS\POWER.EXE

REM DEVICEHIGH=C:\DOS\SETVER.EXE

REM CD-ROM: Search for CD-ROM, load driver when found

DEVICEHIGH=C:\AUDIO_CD\TEAC_CDI.SYS /D:TEAC-CDI

LASTDRIVE=M

REM PC Card: Begin PC Card (PCMCIA) Drivers

REM **Warning: Do not move, reorder, or delete any of these lines. **

DEVICEHIGH=C:\CARDWIZ\SSCIRUS2.EXE

DEVICEHIGH=C:\CARDWIZ\CS.EXE /POLL:1

DEVICEHIGH=C:\CARDWIZ\CSALLOC.EXE

DEVICEHIGH=C:\CARDWIZ\CARDID.EXE

REM PC Card: End PC Card(PCMCIA) Drives

AUTOEXEC.BAT

@ECHO OFF

C:\WINDOWS\VGAUTIL\winmode.exe t640=60 t800=60 t1024=87 t1280=87

REM MODE CON CODEPAGE PREPARE=((437) C:\DOS\EGA.CPI)

REM MODE CON CODEPAGE SELECT=437

REM LH KEYB US,,C:\DOS\KEYBOARD.SYS

SET NWLANGUAGE=ENGLISH

PATH C:\WINDOWS;C:\CPQDOS;C:\DOS;C:\AUDIO_CD;C:\CARDWIZ

PROMPT Sp\$g

SET DIRCMD=/ogn

SET TEMP=C:\WINDOWS\TEMP

SET BLASTER=A220 D1 I5

SET LMOUSE=C:\MOUSE

SET MOUSE=C:\MOUSE

C:\MOUSE\MOUSE.EXE MEMU

REM CD-ROM: Search for CD-ROM, load driver when found

C:\DOS\MSCDEX.EXE /D:TEAC-CDI /M:15

IF ERRORLEVEL 1 GOTO NO_CDROM

REM Essvol: Ensure master and Audio CD volume turned up for DOS CDPLAYER.EXE

DOS CDPLAYER.EXE

C:\AUDIO_CD\ESSVOL /V:15 /C:15

:NO_CDROM

IF NOT EXIST C:\CPQDOS\SAVEDONE.CPQ CALL SAVEALL /A

AUTOEXEC.BAT-continued

```

REM SMARTDRV: Load Smart Drive with Read Buffering but not Write Buffering
LH C:\DOS\SMARTDRV.EXE
REM Hibernation: Verify, build new, or rebuild hibernation file.
C:\CPQDOS\0VMAKFIL
REM Compaq Ethernet LAN Adapter --- Do Not Change Lines Below
:COM_MENU
@echo off
cls
goto %config%
:CPQ_E_COMPAQ
C:
cd C:\COMPAQ\CPQ
if not exist CPQODI.COM goto COM_ERROR
CPQCFG.EXE DRIVER=ODI
LSL
CPQODI.COM
IPXODI
NETX
if not exist XCHECK.EXE goto S_CPQ_E_COMPAQ
cls
XCHECK.EXE -e -1 N:
:S_CPQ_E_COMPAQ
N:
login
goto COM_END
:COM_ERROR
echo Error: Unable to locate driver file.
:COM_END
C:
cd \
REM Compaq Ethernet LAN Adapter --- Do Not Change Lines Above
REM Compaq Ethernet LAN Adapter --- Do Not Change Lines Below (PATH)
PATH=%PATH%;C:\COMPAQ\CPQ
REM Compaq Ethernet LAN Adapter --- Do Not Change Lines Above
REM 'win.com' reference moved by Compaq Installation Program
WIN

```

NETWORK DRIVERS

| | | |
|-------------|--------|----------|
| LSL.COM | 18,285 | 04-17-95 |
| IPXODI.COM | 39,353 | 10-31-94 |
| CPQODI.COM | 53,698 | 11-15-95 |
| CPQTEST.EXE | 68,133 | 11-15-95 |
| CPQCFG.EXE | 29,440 | 11-29-95 |
| NETX.EXE | 78,654 | 11-17-93 |

NET.CFG

```

link driver CPQODI
frame ethernet_802.2
int 11
port 320
mem D4000

```

CARDID.INI

```

[Common]
;
; Common Information section created by Config
;
ComPort1=3F8
ComIRQ1=4
ComPort2=2F8
ComIRQ2=3
ComPort3=3E8
ComIRQ3=4
ComPort4=2E8
ComIRQ4=11
ComBySocket=No
ComBDAAbsolute=Yes
ComRollOverOn=No
FirstModem=2
SecondModem=4
CARDID.INI-continued

```

ThirdModem=2
FourthModem=4
Audio=Yes
RingIndicate=No
Suspend_Power=No
Lan1Port=330
Lan1IRQ=11
Lan1MemoryBase1=
Lan1MemoryBase2=
Lan2Port=310
Lan2IRQ=10
Lan2MemoryBase1=
Lan2MemoryBase2=
ATATryPrimary=No
ATATrySecondary=Yes
ATATryLinear=Yes
FastTokenRing=Yes
DetectNonCompliant=No
ContinueOnConfigFailure=No
BeepInDOS=Yes
BeepInWindows=Yes
GrabInitFile=Yes
InitBufferSize=512

[Libraries]

;
; The Libraries section contains references to any card libraries the user
; wishes to include. Libraries are searched in the specified order. Path
; names are relative to the directory containing CARDID.INI.

;
CardLib=xirdual.clb
CardLib=xircom.clb
CardLib=tdkfan2.clb
CardLib=sundisk5.clb
CardLib=intellan.clb
CardLib=dlink.clb
CardLib=linksys.clb
CardLib=linksys2.clb
CardLib=socketea.clb
CardLib=ibmlan.clb
CardLib=ibmtok.clb
CardLib=ibm3270.clb
CardLib=proxim.clb
CardLib=cbdass.clb
CardLib=genmodem.clb
CardLib=genata.clb
CardLib=wd.clb

Configuration Notes:

The software was installed from Windows 3.1. The software automatically made all the necessary changes, and assigned the resources IRQ 11, I/O 320, and MEM D4000. The drivers for Windows 95 are not built in, so when the card is inserted a window will pop up prompting you for a diskette. The diskette is provided with the card, simply insert diskette and press enter. The card will then be recognized and configured.

PLATFORM: COMPAQ AERO 4/33C

ROM: 07/19/95

PC CARD: 3COM ETHERLINK III, PN: 3C589B-COMBO

OPERATING SYSTEM: WINDOWS 3.1/DOS 6.2

NOS: NOVELL 3.12

CARD AND SOCKET SERVICES: 1.25

CONFIG.SYS

```
SHELL=C:\DOS\COMMAND.COM /P /E:1536
STACKS=9,256
DEVICE=C:\DOS\HIMEM.SYS
DEVICE=C:\DOS\EMM386.EXE NOEMS X=D000-DFFF
DOS=UMB
REM *** Begin PCMCIA Drivers
REM Warning: Do not move, reorder, or delete any of these lines.
REM
DEVICE=C:\CPQDOS\PCSMIX.EXE
DEVICEHIGH=C:\CPQDOS\SSVLSI.EXE
DEVICEHIGH=C:\CPQDOS\CS.EXE
DEVICE=C:\CPQDOS\CSALLOC.EXE
DEVICEHIGH=C:\CPQDOS\ATADRV.EXE /D:1
DEVICEHIGH=C:\CPQDOS\CARDID.EXE C:\CPQDOS\CARDID.INI
DEVICEHIGH=C:\CPQDOS\MEMDRV.EXE
;DEVICEHIGH=C:\CPQDOS\DBLFLASH.EXE
;DEVICEHIGH=C:\CPQDOS\MS-FLASH.SYS
REM *** End PCMCIA Drivers
DOS=HIGH
BUFFERS=20
FILES=35
DEVICEHIGH=C:\CPQDOS\POWER.EXE
LASTDRIVE=Z
```

AUTOEXEC.BAT

```
@loadhigh C:\DOS\SHARE.EXE /I:500 /F:5100
SET PATH=C:\CPQDOS;C:\;C:\DOS;C:\WINDOWS; C:\WINDOWS\CPQWIN
SET LMOUSE=C:\MOUSE
SET PROMPT=SPSG
SET TEMP=C:\WINDOWS\TEMP
C:\CPQDOS\HIBRN8.EXE
C:\DOS\SMARTDRV.EXE
LH C:\MOUSE\MOUSE SWAP
C:\CPQDOS\MODE.COM CO80
@echo off
REM Netware startup
if not exist C:\NWCLIENT\isl.com goto noNetware
if not exist C:\NWCLIENT\ipxodi.com goto noNetware
if not exist C:\NWCLIENT\vlm.exe goto noNetware
C:\NWCLIENT\isl.com
C:\NWCLIENT\3C589.com
C:\NWCLIENT\ipxodi.com
C:\NWCLIENT\vlm.exe
f:\login
c:
goto doneNetware
:noNetware
echo Netware client software missing, Netware not started
:doneNetware
```

NETWORK DRIVERS

| | | |
|------------|--------|----------|
| LSL.COM | 18,313 | 10-11-94 |
| IPXODI.COM | 39,353 | 10-31-94 |
| 3C589.COM | 41,520 | 09-08-94 |
| VLM.EXE | 37,611 | 11-08-94 |

NET.CFG

; THIS SECTION IS FOR CONFIGURATION OF LINKWATCH MANAGEABLE END NODES.

```
;
Protocol DME
  BIND #1
; replace with your specific information for LinkWatch
  USER_NAME "Your Name"
  NODE_NAME "Your Node Name"
  NODE_LOCATION "Your Node Location"
; set password according to your network administrator's instructions
; NODE_PASSWORD "ABCDEFGH"
  PHONE_NUMBER "Your Phone Number"
  NOTES "Miscellaneous text"
  NOTES "and more text"
```

LINK DRIVER 3C589

```
; PORT 300
  FRAME ETHERNET_802.2
;
; =====
; | port [index] STARTING_PORT COUNT
; |   This setting is only required when there is two
; |   adapters in the workstation.
; |
; |   All adapter specific parameters are read from the adapter.
; |
; | mem [index] MEMORY_WINDOW (Optional)
; |   If parameter not present in protocol.ini, driver auto selects a
; |   a free 4K memory window. Released after initialization of card.
; |   If specified, forces driver to use this address to map card's
; |   CIS memory during driver initialization. Window is released
; |   after driver finishes initializing card or fails to find card.
; |   Use 0xC000 - 0xEF00 in steps of 0x100
; |
; | NOTE: | frame ethernet_802.3
; | *****| This is a version 4.X DOS ODI driver. The default
; |         | frame type is 802.2, but you may be using 802.3.
; |
; | =====
```

NetWare DOS Requester

FIRST NETWORK DRIVE = F

CARDID.INI

[Common]

```
;
; Common Information section created by Config
;
ComPort1=3F8
ComIRQ1=4
ComPort2=2F8
ComIRQ2=3
ComPort3=3E8
ComIRQ3=4
ComPort4=2E8
ComIRQ4=3
ComBySocket=Yes
ComBDAAbsolute=No
FirstModem=2
SecondModem=2
ThirdModem=3
FourthModem=4
Audio=Yes
RingIndicate=No
Lan1Port=300
Lan1IRQ=5
Lan1MemoryBase1=D8
Lan1MemoryBase2=DC
Lan2Port=310
Lan2IRQ=10
Lan2MemoryBase1=D8
Lan2MemoryBase2=DC
ATATryPrimary=No
CARDID.INI-continued
```

ATATrySecondary=Yes
ATATryLinear=Yes
FastTokenRing=Yes
DetectNonCompliant=No
ContinueOnConfigFailure=No
BeepInDOS=Yes
BeepInWindows=Yes
GrabInitFile=Yes
InitBufferSize=512

[Libraries]

;
; The Libraries section contains references to any card libraries the user
; wishes to include. Libraries are searched in the specified order. Path
; names are relative to the directory containing CARDID.INI.
;
CardLib=cardid.clb

Configuration Notes:

To install in Windows/DOS we used XCOPY and copied the files from the drivers diskette to the hard drive. With the 3Com card inserted we ran the installation program from the hard drive, and it automatically used the resources IRQ 5, and I/O 380. The drivers for Windows 95 are built in, and the card will automatically be recognized and configured upon insertion.

PLATFORM: *COMPAQ CONCERTO*

ROM: *11/17/93*

PC CARD: *3COM ETHERLINK III, PN: 3C589B-COMBO*

OPERATING SYSTEM: *WINDOWS 3.1/DOS 6.2*

NOS: *NOVELL 3.12*

CARD AND SOCKET SERVICES: *1.25*

CONFIG.SYS

```
SHELL=C:\DOS\COMMAND.COM /P /E:1536
STACKS=9,256
DEVICE=C:\DOS\HIMEM.SYS
DEVICE=C:\DOS\EMM386.EXE NOEMS X=D000-DFFF
DOS=UMB
REM *** Begin PCMCIA Drivers
REM Warning: Do not move, reorder, or delete any of these lines.
REM
DEVICEHIGH=C:\CPQDOS\SSCIRRUS.EXE
DEVICEHIGH=C:\CPQDOS\CS.EXE
DEVICE=C:\CPQDOS\CSALLOC.EXE
DEVICEHIGH=C:\CPQDOS\ATADRV.EXE
DEVICEHIGH=C:\CPQDOS\CARDID.EXE C:\CPQDOS\CARDID.INI
DEVICEHIGH=C:\CPQDOS\MEMDRV.EXE
;DEVICEHIGH=C:\CPQDOS\DBLFLASH.EXE
;DEVICEHIGH=C:\CPQDOS\MS-FLASH.SYS
REM *** End PCMCIA Drivers
DOS=HIGH
BUFFERS=20
FILES=35
DEVICEHIGH=C:\CPQDOS\POWER.EXE
lastdrive=z
```

AUTOEXEC.BAT

```
SET PATH=C:\CPQDOS;C:\;C:\DOS;C:\WINDOWS;; C:\WINDOWS\CPQWIN
SET LMOUSE=C:\MOUSE
SET PROMPT=$PSG
SET TEMP=C:\WINDOWS\TEMP
C:\CPQDOS\HIBRN8.EXE
C:\DOS\SMARTDRV.EXE
LH C:\MOUSE\MOUSE
C:\CPQDOS\MODE.COM CO80
@echo off
REM Netware startup
if not exist C:\NWCLIENT\lsl.com goto noNetware
if not exist C:\NWCLIENT\ipxodi.com goto noNetware
if not exist C:\NWCLIENT\vlm.exe goto noNetware
C:\NWCLIENT\lsl.com
C:\NWCLIENT\3C589.com
C:\NWCLIENT\ipxodi.com
C:\NWCLIENT\vlm.exe
f:\login
c:
goto doneNetware
:noNetware
echo Netware client software missing, Netware not started
:doneNetware
```

NETWORK DRIVERS

| | | |
|------------|--------|----------|
| LSL.COM | 18,313 | 10-11-94 |
| IPXODI.COM | 39,353 | 10-31-94 |
| 3C589.COM | 41,520 | 09-08-94 |
| VLM.EXE | 37,611 | 11-08-94 |

NET.CFG

; THIS SECTION IS FOR CONFIGURATION OF LINKWATCH MANAGEABLE END NODES.

```
;
Protocol DME
  BIND #1
; replace with your specific information for LinkWatch
  USER_NAME "Your Name"
  NODE_NAME "Your Node Name"
  NODE_LOCATION "Your Node Location"
; set password according to your network administrator's instructions
; NODE_PASSWORD "ABCDEFGH"
  PHONE_NUMBER "Your Phone Number"
  NOTES "Miscellaneous text"
  NOTES "and more text"
```

LINK DRIVER 3C589

```
; PORT 300
  FRAME ETHERNET_802.2
;
; =====
; | port [index] STARTING_PORT COUNT
; | This setting is only required when there is two
; | adapters in the workstation.
; |
; | All adapter specific parameters are read from the adapter.
; |
; | mem [index] MEMORY_WINDOW (Optional)
; | If parameter not present in protocol.ini, driver auto selects a
; | a free 4K memory window. Released after initialization of card.
; | If specified, forces driver to use this address to map card's
; | CIS memory during driver initialization. Window is released
; | after driver finishes initializing card or fails to find card.
; | Use 0xC000 - 0xEF00 in steps of 0x100
; |
; NOTE: | frame ethernet_802.3
; ***** | This is a version 4.X DOS ODI driver. The default
; | frame type is 802.2, but you may be using 802.3.
; |
; =====
```

NetWare DOS Requester
FIRST NETWORK DRIVE = F

CARDID.INI

```
[Common]
;
; Common Information section created by Config
;
ComPort1=3F8
ComIRQ1=4
ComPort2=2F8
ComIRQ2=3
ComPort3=3E8
ComIRQ3=4
ComPort4=2E8
ComIRQ4=3
ComBySocket=Yes
ComBDAAbsolute=No
FirstModem=2
SecondModem=2
ThirdModem=3
FourthModem=4
Audio=Yes
RingIndicate=No
Lan1Port=300
Lan1IRQ=5
Lan1MemoryBase1=D8
Lan1MemoryBase2=DC
Lan2Port=310
Lan2IRQ=10
Lan2MemoryBase1=D8
Lan2MemoryBase2=DC
ATATryPrimary=No
CARDID.INI-continued
```

ATATrySecondary=Yes
ATATryLinear=Yes
FastTokenRing=Yes
DetectNonCompliant=No
ContinueOnConfigFailure=No
BeepInDOS=Yes
BeepInWindows=Yes
GrabInitFile=Yes
InitBufferSize=512

[Libraries]

;
; The Libraries section contains references to any card libraries the user
; wishes to include. Libraries are searched in the specified order. Path
; names are relative to the directory containing CARDID.INI.
;
CardLib=cardid.clb

Configuration Notes:

Installation for Windows/DOS was accomplished by running installation program from drivers diskette. The install procedure automatically chose the resources IRQ 5 and I/O 380, the install program made all necessary modifications. In Windows 95 the drivers are built in so the card will automatically be recognized and configured upon insertion.

PLATFORM: COMPAQ CONTURA 400CX

ROM: 07/18/95

PC CARD: 3COM ETHERLINK III, PN: 3C589B-COMBO

OPERATING SYSTEM: WINDOWS 3.1/DOS 6.2

NOS: NOVELL 3.12

CARD AND SOCKET SERVICES: 3.12

CONFIG.SYS

```
switches=/F
SHELL=C:\DOS\COMMAND.COM /P /E:1536
STACKS=9,256
DEVICE=C:\DOS\HIMEM.SYS
DEVICE=C:\DOS\EMM386.EXE NOEMS I=B000-B7FF X=D000-D4FF
DEVICEHIGH=C:\WINDOWS\CPQWIN\CPQCM.SYS
DOS=HIGH,UMB
REM *** Begin PCMCIA Drivers
REM Warning: Do not move, reorder, or delete any of these lines.
REM
;DEVICE=C:\CPQDOS\PCSMIX.EXE
DEVICEHIGH=C:\CPQDOS\SSVLSI.EXE
DEVICEHIGH=C:\CPQDOS\CS.EXE
DEVICE=C:\CPQDOS\CSALLOC.EXE
;DEVICEHIGH=C:\CPQDOS\ATADRV.EXE
;DEVICEHIGH=C:\CPQDOS\MTAA.EXE
;DEVICEHIGH=C:\CPQDOS\MTAB.EXE
;DEVICEHIGH=C:\CPQDOS\MTI1.EXE
;DEVICEHIGH=C:\CPQDOS\MTI2P.EXE
;DEVICEHIGH=C:\CPQDOS\MTSRAM.EXE
;DEVICEHIGH=C:\CPQDOS\MTDDRV.EXE
;DEVICEHIGH=C:\CPQDOS\DBLFLASH.EXE
;DEVICEHIGH=C:\CPQDOS\MS-FLASH.SYS
DEVICEHIGH=C:\CPQDOS\CARDID.EXE
REM *** End PCMCIA Drivers
BUFFERS=20
FILES=35
DEVICEHIGH=C:\CPQDOS\EPPBIOS.SYS
DEVICEHIGH=C:\CPQDOS\POWER.EXE
lastdrive=z
```

AUTOEXEC.BAT

```
@ECHO OFF
SET PATH=C:\CPQDOS;C:\;C:\DOS;C:\WINDOWS;;C:\WINDOWS\CPQWIN
SET LMOUSE=C:\MOUSE
LH C:\MOUSE\MOUSE
SET PROMPT=$PSG
SET TEMP=C:\WINDOWS\TEMP
C:\CPQDOS\HIBRN8.EXE
LH C:\DOS\SMARTDRV.EXE
LH SHARE.EXE
@echo off
REM Netware startup
if not exist C:\NWCLIENT\lsl.com goto noNetware
if not exist C:\NWCLIENT\ipxodi.com goto noNetware
if not exist C:\NWCLIENT\vlm.exe goto noNetware
C:\NWCLIENT\lsl.com
C:\NWCLIENT\3C589.com
C:\NWCLIENT\ipxodi.com
C:\NWCLIENT\vlm.exe
f:\login
c:
goto doneNetware
:noNetware
echo Netware client software missing, Netware not started
:doneNetware
```

NETWORK DRIVERS

| | | |
|------------|--------|----------|
| LSL.COM | 18,313 | 10-11-94 |
| IPXODI.COM | 39,353 | 10-31-94 |
| 3C589.COM | 41,520 | 09-08-94 |
| VLM.EXE | 37,611 | 11-08-94 |

NET.CFG

; THIS SECTION IS FOR CONFIGURATION OF LINKWATCH MANAGEABLE END NODES.

```
;
Protocol DME
  BIND #1
; replace with your specific information for LinkWatch
  USER_NAME "Your Name"
  NODE_NAME "Your Node Name"
  NODE_LOCATION "Your Node Location"
; set password according to your network administrator's instructions
; NODE_PASSWORD "ABCDEFGH"
  PHONE_NUMBER "Your Phone Number"
  NOTES "Miscellaneous text"
  NOTES "and more text"
```

LINK DRIVER 3C589

```
; PORT 300
  FRAME ETHERNET_802.2
;
; =====
; | port [index] STARTING_PORT COUNT
; | This setting is only required when there is two
; | adapters in the workstation.
;
; | All adapter specific parameters are read from the adapter.
;
; | mem [index] MEMORY_WINDOW (Optional)
; | If parameter not present in protocol.ini, driver auto selects a
; | a free 4K memory window. Released after initialization of card.
; | If specified, forces driver to use this address to map card's
; | CIS memory during driver initialization. Window is released
; | after driver finishes initializing card or fails to find card.
; | Use 0xC000 - 0xEF00 in steps of 0x100
;
; NOTE: | frame ethernet_802.3
; *****| This is a version 4.X DOS ODI driver. The default
; | frame type is 802.2, but you may be using 802.3.
;
; =====
```

NetWare DOS Requester
FIRST NETWORK DRIVE = F

CARDID.INI

```
[Common]
;
; Common Information section created by Config
;
ComPort1=3F8
ComIRQ1=4
ComPort2=2F8
ComIRQ2=3
ComPort3=3e8
ComIRQ3=4
ComPort4=2E8
ComIRQ4=3
ComBySocket=Yes
ComBDAAbsolute=No
FirstModem=2
SecondModem=2
ThirdModem=3
FourthModem=4
Audio=Yes
RingIndicate=No
```

CARDID.INI-continued

Lan1Port=300
Lan1IRQ=5
Lan1MemoryBase1=
Lan1MemoryBase2=
Lan2Port=310
Lan2IRQ=9
Lan2MemoryBase1=
Lan2MemoryBase2=
ATATryPrimary=No
ATATrySecondary=Yes
ATATryLinear=Yes
FastTokenRing=Yes
DetectNonCompliant=No
ContinueOnConfigFailure=No
BeepInDOS=Yes
BeepInWindows=Yes
GrabInitFile=Yes
InitBufferSize=512
UseEMS=No

[Libraries]

;
; The Libraries section contains references to any card libraries the user
; wishes to include. Libraries are searched in the specified order. Path
; names are relative to the directory containing CARDID.INI.

;
CardLib=canonfd.clb
CardLib=xirdual.clb
CardLib=xircom.clb
CardLib=tdkklan2.clb
CardLib=sundisk5.clb
CardLib=intellan.clb
CardLib=dlink.clb
CardLib=linksys.clb
CardLib=linksys2.clb
CardLib=socketea.clb
CardLib=ibmlan.clb
CardLib=ibmtok.clb
CardLib=ibm3270.clb
CardLib=proxim.clb
CardLib=cbdass.clb
CardLib=genmodem.clb
CardLib=genata.clb
CardLib=wd.clb

Configuration Notes:

Installation for Windows/DOS was accomplished by running installation program from drivers diskette. The install procedure automatically chose the resources IRQ 5 and I/O 380, the install program made all necessary modifications. In Windows 95 the drivers are built in so the card will automatically be recognized and configured upon insertion.

PLATFORM: COMPAQ CONTURA 420CX

ROM: 08/20/95

PC CARD: 3COM ETHERLINK III, PN: 3C589B-COMBO

OPERATING SYSTEM: WINDOWS 3.1/ DOS 6.2

NOS: NOVELL 3.12

CARD AND SOCKET SERVICES: 3.12

CONFIG.SYS

```
SHELL=C:\DOS\COMMAND.COM /P /E:1536
STACKS=9,256
DEVICE=C:\DOS\HIMEM.SYS
DEVICEHIGH=C:\WINDOWS\CPQWIN\CPQCM.SYS
DEVICE=C:\DOS\EMM386.EXE NOEMS I=B000-B7FF X=D000-D4FF
DOS=UMB
REM *** Begin PCMCIA Drivers
REM Warning: Do not move, reorder, or delete any of these lines.
REM
;DEVICE=C:\CPQDOS\PCMSMIX.EXE
DEVICEHIGH=C:\CPQDOS\SSVLSI.EXE
DEVICEHIGH=C:\CPQDOS\CS.EXE
DEVICE=C:\CPQDOS\CSALLOC.EXE
;DEVICEHIGH=C:\CPQDOS\ATADRV.EXE
;DEVICEHIGH=C:\CPQDOS\MTAA.EXE
;DEVICEHIGH=C:\CPQDOS\MTAB.EXE
;DEVICEHIGH=C:\CPQDOS\MTI1.EXE
;DEVICEHIGH=C:\CPQDOS\MTI2P.EXE
;DEVICEHIGH=C:\CPQDOS\MTSRAM.EXE
;DEVICEHIGH=C:\CPQDOS\MTDDRV.EXE
;DEVICEHIGH=C:\CPQDOS\DBLFLASH.EXE
;DEVICEHIGH=C:\CPQDOS\MS-FLASH.SYS
DEVICEHIGH=C:\CPQDOS\CARDID.EXE
REM *** End PCMCIA Drivers
DOS=HIGH
BUFFERS=20
FILES=35
DEVICEHIGH=C:\CPQDOS\EPPBIOS.SYS
LASTDRIVE=Z
```

AUTOEXEC.BAT

```
SET PATH=C:\CPQDOS; C:\; C:\DOS; C:\WINDOWS; C:\WINDOWS\CPQWIN
SET LMOUSE=C:\MOUSE
SET PROMPT=$PSG
SET TEMP=C:\WINDOWS\TEMP
C:\CPQDOS\HIBRN8.EXE
C:\DOS\SMARTDRV.EXE 2048 512
C:\MOUSE\mouse.exe
C:\CPQDOS\MODE.COM CO80
@echo off
REM Network startup
if not exist C:\NWCLIENT\isl.com goto noNetware
if not exist C:\NWCLIENT\ipxodi.com goto noNetware
if not exist C:\NWCLIENT\vlm.exe goto noNetware
C:\NWCLIENT\isl.com
C:\NWCLIENT\3C589.com
C:\NWCLIENT\ipxodi.com
C:\NWCLIENT\vlm.exe
f:\login
c:
goto doneNetware
:noNetware
echo Netware client software missing, Netware not started
:doneNetware
C:\WINDOWS\WIN
```

NETWORK DRIVERS

| | | |
|------------|--------|----------|
| LSL.COM | 18,313 | 10-11-94 |
| IPXODI.COM | 39,353 | 10-31-94 |
| 3C589.COM | 41,520 | 09-08-94 |
| VLM.EXE | 37,611 | 11-08-94 |

NET.CFG

; THIS SECTION IS FOR CONFIGURATION OF LINKWATCH MANAGEABLE END NODES.

```
;
Protocol DME
  BIND #1
; replace with your specific information for LinkWatch
  USER_NAME "Your Name"
  NODE_NAME "Your Node Name"
  NODE_LOCATION "Your Node Location"
; set password according to your network administrator's instructions
; NODE_PASSWORD "ABCDEFGH"
  PHONE_NUMBER "Your Phone Number"
  NOTES "Miscellaneous text"
  NOTES "and more text"
```

LINK DRIVER 3C589

```
; PORT 300
  FRAME ETHERNET_802.2
;
; =====
; | port [index] STARTING_PORT COUNT
; | This setting is only required when there is two
; | adapters in the workstation.
; |
; | All adapter specific parameters are read from the adapter.
; |
; | mem [index] MEMORY_WINDOW (Optional)
; | If parameter not present in protocol.ini, driver auto selects a
; | a free 4K memory window. Released after initialization of card.
; | If specified, forces driver to use this address to map card's
; | CIS memory during driver initialization. Window is released
; | after driver finishes initializing card or fails to find card.
; | Use 0xC000 - 0xEF00 in steps of 0x100
; |
; NOTE: | frame ethernet_802.3
; *****| This is a version 4.X DOS ODI driver. The default
; | frame type is 802.2, but you may be using 802.3.
; |
; =====
```

```
NetWare DOS Requester
  FIRST_NETWORK_DRIVE = F
```

CARDID.INI

```
[Common]
;
; Common Information section created by Config
;
ComPort1=3F8
ComIRQ1=4
ComPort2=2F8
ComIRQ2=3
ComPort3=3e8
ComIRQ3=4
ComPort4=2E8
ComIRQ4=3
ComBySocket=Yes
ComBDAAbsolute=No
FirstModem=2
SecondModem=2
ThirdModem=3
FourthModem=4
Audio=Yes
RingIndicate=No
Lan1Port=300
Lan1IRQ=5
CARDID.INI-continued
```

Lan1MemoryBase1=
Lan1MemoryBase2=
Lan2Port=310
Lan2IRQ=9
Lan2MemoryBase1=
Lan2MemoryBase2=
ATATryPrimary=No
ATATrySecondary=Yes
ATATryLinear=Yes
FastTokenRing=Yes
DetectNonCompliant=No
ContinueOnConfigFailure=No
BeepInDOS=Yes
BeepInWindows=Yes
GrabInitFile=Yes
InitBufferSize=512
UseEMS=No

[Libraries]

;
; The Libraries section contains references to any card libraries the user
; wishes to include. Libraries are searched in the specified order. Path
; names are relative to the directory containing CARDID.INI.

;
CardLib=canonfd.clb
CardLib=xirdual.clb
CardLib=xircom.clb
CardLib=tdkklan2.clb
CardLib=sundisk5.clb
CardLib=intellan.clb
CardLib=dlink.clb
CardLib=linksys.clb
CardLib=linksys2.clb
CardLib=socketea.clb
CardLib=ibmlan.clb
CardLib=ibmtok.clb
CardLib=ibm3270.clb
CardLib=proxim.clb
CardLib=cbdass.clb
CardLib=genmodem.clb
CardLib=genata.clb
CardLib=wd.clb

Configuration Notes:

Installation for Windows/DOS was accomplished by running installation program from drivers diskette. The install procedure automatically chose the resources IRQ 5 and I/O 380, the install program made all necessary modifications. In Windows 95 the drivers are built in so the card will automatically be recognized and configured upon insertion.

PLATFORM: COMPAQ CONTURA 420CX

ROM: 08/20/95

PC CARD: 3COM ETHERLINK III, PN: 3C589B-COMBO

OPERATING SYSTEM: WINDOWS 3.1/DOS 6.2

NOS: NOVELL 3.12

CARD AND SOCKET SERVICES: 3.12

CONFIG.SYS

```
SHELL=C:\DOS\COMMAND.COM /P /E:1536
STACKS=9,256
DEVICE=C:\DOS\HIMEM.SYS
DEVICEHIGH=C:\WINDOWS\CPQWIN\CPQCM.SYS
DEVICE=C:\DOS\EMM386.EXE NOEMS I=B000-B7FF X=D000-D4FF
DOS=UMB
REM *** Begin PCMCIA Drivers
REM Warning: Do not move, reorder, or delete any of these lines.
REM
;DEVICE=C:\CPQDOS\PCMSMIX.EXE
DEVICEHIGH=C:\CPQDOS\SSVLSI.EXE
DEVICEHIGH=C:\CPQDOS\CS.EXE
DEVICE=C:\CPQDOS\CSALLOC.EXE
;DEVICEHIGH=C:\CPQDOS\ATADRV.EXE
;DEVICEHIGH=C:\CPQDOS\MTAA.EXE
;DEVICEHIGH=C:\CPQDOS\MTAB.EXE
;DEVICEHIGH=C:\CPQDOS\MTI1.EXE
;DEVICEHIGH=C:\CPQDOS\MTI2P.EXE
;DEVICEHIGH=C:\CPQDOS\MTSRAM.EXE
;DEVICEHIGH=C:\CPQDOS\MTDDRV.EXE
;DEVICEHIGH=C:\CPQDOS\DBLFLASH.EXE
;DEVICEHIGH=C:\CPQDOS\MS-FLASH.SYS
DEVICEHIGH=C:\CPQDOS\CARDID.EXE
REM *** End PCMCIA Drivers
DOS=HIGH
BUFFERS=20
FILES=35
DEVICEHIGH=C:\CPQDOS\EPPBIOS.SYS
LASTDRIVE=Z
```

AUTOEXEC.BAT

```
SET PATH=C:\CPQDOS; C:\; C:\DOS; C:\WINDOWS; C:\WINDOWS\CPQWIN
SET LMOUSE=C:\MOUSE
SET PROMPT=$PSG
SET TEMP=C:\WINDOWS\TEMP
C:\CPQDOS\HIBRN8.EXE
C:\DOS\SMARTDRV.EXE 2048 512
C:\MOUSE\mouse.exe
C:\CPQDOS\MODE.COM CO80
@echo off
REM Network startup
if not exist C:\NWCLIENT\lsl.com goto noNetware
if not exist C:\NWCLIENT\ipxodi.com goto noNetware
if not exist C:\NWCLIENT\vlm.exe goto noNetware
C:\NWCLIENT\lsl.com
C:\NWCLIENT\3C589.com
C:\NWCLIENT\ipxodi.com
C:\NWCLIENT\vlm.exe
f:\login
c:
goto doneNetware
:noNetware
echo Network client software missing, Netware not started
:doneNetware
C:\WINDOWS\WIN
```

NETWORK DRIVERS

| | | |
|------------|--------|----------|
| LSL.COM | 18,313 | 10-11-94 |
| IPXODI.COM | 39,353 | 10-31-94 |
| 3C589.COM | 41,520 | 09-08-94 |
| VLM.EXE | 37,611 | 11-08-94 |

NET.CFG

; THIS SECTION IS FOR CONFIGURATION OF LINKWATCH MANAGEABLE END NODES.

```
;
Protocol DME
  BIND #1
; replace with your specific information for LinkWatch
  USER_NAME "Your Name"
  NODE_NAME "Your Node Name"
  NODE_LOCATION "Your Node Location"
; set password according to your network administrator's instructions
; NODE_PASSWORD "ABCDEFGH"
  PHONE_NUMBER "Your Phone Number"
  NOTES "Miscellaneous text"
  NOTES "and more text"
```

LINK DRIVER 3C589

```
; PORT 300
  FRAME ETHERNET_802.2
;
; =====
; | port [index] STARTING_PORT COUNT
; | This setting is only required when there is two
; | adapters in the workstation.
; |
; | All adapter specific parameters are read from the adapter.
; |
; | mem [index] MEMORY_WINDOW (Optional)
; | If parameter not present in protocol.ini, driver auto selects a
; | a free 4K memory window. Released after initialization of card.
; | If specified, forces driver to use this address to map card's
; | CIS memory during driver initialization. Window is released
; | after driver finishes initializing card or fails to find card.
; | Use 0xC000 - 0xEF00 in steps of 0x100
; |
; NOTE: | frame ethernet_802.3
; *****| This is a version 4.X DOS ODI driver. The default
; | frame type is 802.2, but you may be using 802.3.
; |
; =====
```

```
NetWare DOS Requester
  FIRST_NETWORK_DRIVE = F
```

CARDID.INI

```
[Common]
;
; Common Information section created by Config
;
ComPort1=3F8
ComIRQ1=4
ComPort2=2F8
ComIRQ2=3
ComPort3=3e8
ComIRQ3=4
ComPort4=2E8
ComIRQ4=3
ComBySocket=Yes
ComBDAAbsolute=No
FirstModem=2
SecondModem=2
ThirdModem=3
FourthModem=4
Audio=Yes
RingIndicate=No
Lan1Port=300
Lan1IRQ=5
CARDID.INI-continued
```


Lan1MemoryBase1=
Lan1MemoryBase2=
Lan2Port=310
Lan2IRQ=9
Lan2MemoryBase1=
Lan2MemoryBase2=
ATATryPrimary=No
ATATrySecondary=Yes
ATATryLinear=Yes
FastTokenRing=Yes
DetectNonCompliant=No
ContinueOnConfigFailure=No
BeepInDOS=Yes
BeepInWindows=Yes
GrabInitFile=Yes
InitBufferSize=512
UseEMS=No

[Libraries]

;
; The Libraries section contains references to any card libraries the user
; wishes to include. Libraries are searched in the specified order. Path
; names are relative to the directory containing CARDID.INI.

;
CardLib=canonfd.clb
CardLib=xirdual.clb
CardLib=xircom.clb
CardLib=tdkklan2.clb
CardLib=sundisk5.clb
CardLib=intellan.clb
CardLib=dlink.clb
CardLib=linksys.clb
CardLib=linksys2.clb
CardLib=socketea.clb
CardLib=ibmlan.clb
CardLib=ibmtok.clb
CardLib=ibm3270.clb
CardLib=proxim.clb
CardLib=cbdass.clb
CardLib=genmodem.clb
CardLib=genata.clb
CardLib=wd.clb

Configuration Notes:

Installation for Windows/DOS was accomplished by running installation program from drivers diskette. The install procedure automatically chose the resources IRQ 5 and I/O 380, the install program made all necessary modifications. In Windows 95 the drivers are built in so the card will automatically be recognized and configured upon insertion.

PLATFORM: COMPAQ ELITE 4/75CXL

ROM: 07/19/95

PC CARD: 3COM ETHERLINK III, PN: 3C589B-COMBO

OPERATING SYSTEM: WINDOWS 3.1/DOS 6.2

NOS: NOVELL 3.12

CARD AND SOCKET SERVICES: 3.12

CONFIG.SYS

```
switches=/F
SHELL=C:\DOS\COMMAND.COM /P /E:1536
STACKS=9,256
DEVICE=C:\DOS\HIMEM.SYS
DEVICE=C:\DOS\EMM386.EXE NOEMS I=B000-B7FF X=D000-D4FF
DEVICEHIGH=C:\WINDOWS\CPQWIN\CPQCM.SYS
DOS=HIGH,UMB
REM *** Begin PCMCIA Drivers
REM Warning: Do not move, reorder, or delete any of these lines.
REM
;DEVICE=C:\CPQDOS\PCSMIX.EXE
DEVICEHIGH=C:\CPQDOS\SSVLSI.EXE
DEVICEHIGH=C:\CPQDOS\CS.EXE
DEVICE=C:\CPQDOS\CSALLOC.EXE
;DEVICEHIGH=C:\CPQDOS\ATADRV.EXE
;DEVICEHIGH=C:\CPQDOS\MTAA.EXE
;DEVICEHIGH=C:\CPQDOS\MTAB.EXE
;DEVICEHIGH=C:\CPQDOS\MTI1.EXE
;DEVICEHIGH=C:\CPQDOS\MTI2P.EXE
;DEVICEHIGH=C:\CPQDOS\MTSRAM.EXE
;DEVICEHIGH=C:\CPQDOS\MTDDRV.EXE
;DEVICEHIGH=C:\CPQDOS\DBLFLASH.EXE
;DEVICEHIGH=C:\CPQDOS\MS-FLASH.SYS
DEVICEHIGH=C:\CPQDOS\CARDID.EXE
REM *** End PCMCIA Drivers
BUFFERS=20
FILES=35
LASTDRIVE = Z
DEVICEHIGH=C:\CPQDOS\POWER.EXE
```

AUTOEXEC.BAT

```
@ECHO OFF
SET PATH=C:\CPQDOS;C:\;C:\DOS;C:\WINDOWS;;C:\WINDOWS\CPQWIN
SET LMOUSE=C:\MOUSE
LH C:\MOUSE\MOUSE
SET PROMPT=$PSG
SET TEMP=C:\WINDOWS\TEMP
C:\CPQDOS\HIBRN8.EXE
LH C:\DOS\SMARTDRV.EXE
SET NWLANGUAGE=ENGLISH
@echo off
REM Netware startup
if not exist C:\NWCLIENT\isl.com goto noNetware
if not exist C:\NWCLIENT\ipxodi.com goto noNetware
if not exist C:\NWCLIENT\vlm.exe goto noNetware
C:\NWCLIENT\isl.com
C:\NWCLIENT\3C589.com
C:\NWCLIENT\ipxodi.com
C:\NWCLIENT\vlm.exe
f:\login
c:
goto doneNetware
:noNetware
echo Netware client software missing, Netware not started
:doneNetware
C:\WINDOWS\WIN
NETWORK DRIVERS
```

```

LSL.COM      17,990  12-02-93
IPXODI.COM   30,126  03-14-94
3C589.COM    41,520  09-08-94
VLM.EXE     36,525  12-09-93

```

NET.CFG

; THIS SECTION IS FOR CONFIGURATION OF LINKWATCH MANAGEABLE END NODES.

; Protocol DME

```

; BIND #1
; replace with your specific information for LinkWatch
; USER_NAME "Your Name"
; NODE_NAME "Your Node Name"
; NODE_LOCATION "Your Node Location"
; set password according to your network administrator's instructions
; NODE_PASSWORD "ABCDEFGH"
; PHONE_NUMBER "Your Phone Number"
; NOTES "Miscellaneous text"
; NOTES "and more text"

```

LINK DRIVER 3C589

```

; PORT 300
; FRAME ETHERNET_802.2
;
; =====
; | port [index] STARTING_PORT COUNT
; | This setting is only required when there is two
; | adapters in the workstation.
; |
; | All adapter specific parameters are read from the adapter.
; |
; | mem [index] MEMORY_WINDOW (Optional)
; | If parameter not present in protocol.ini, driver auto selects a
; | free 4K memory window. Released after initialization of card.
; | If specified, forces driver to use this address to map card's
; | CIS memory during driver initialization. Window is released
; | after driver finishes initializing card or fails to find card.
; | Use 0xC000 - 0xEF00 in steps of 0x100
; |
; NOTE: | frame ethernet_802.3
; ***** | This is a version 4.X DOS ODI driver. The default
; | frame type is 802.2, but you may be using 802.3.
; |
; =====

```

NetWare DOS Requester

FIRST NETWORK DRIVE = F

CARDID.INI

[Common]

```

;
; Common Information section created by Config
;
ComPort1=3F8
ComIRQ1=4
ComPort2=2F8
ComIRQ2=3
ComPort3=3e8
ComIRQ3=4
ComPort4=2E8
ComIRQ4=3
ComBySocket=Yes
ComBDAAbsolute=No
FirstModem=2
SecondModem=2
ThirdModem=3
FourthModem=4
Audio=Yes
RingIndicate=No
Lan1Port=300
Lan1IRQ=5

```

CARDID.INI-continued

Lan1MemoryBase1=
Lan1MemoryBase2=
Lan2Port=310
Lan2IRQ=9
Lan2MemoryBase1=
Lan2MemoryBase2=
ATATryPrimary=No
ATATrySecondary=Yes
ATATryLinear=Yes
FastTokenRing=Yes
DetectNonCompliant=No
ContinueOnConfigFailure=No
BeepInDOS=Yes
BeepInWindows=Yes
GrabInitFile=Yes
InitBufferSize=512
UseEMS=No

[Libraries]

;
; The Libraries section contains references to any card libraries the user
; wishes to include. Libraries are searched in the specified order. Path
; names are relative to the directory containing CARDID.INI.
;

CardLib=canonfd.clb
CardLib=xirdual.clb
CardLib=xircom.clb
CardLib=tdkklan2.clb
CardLib=sundisk5.clb
CardLib=intellan.clb
CardLib=dlink.clb
CardLib=linksys.clb
CardLib=linksys2.clb
CardLib=socketea.clb
CardLib=ibmlan.clb
CardLib=ibmtok.clb
CardLib=ibm3270.clb
CardLib=proxim.clb
CardLib=cbdass.clb
CardLib=genmodem.clb
CardLib=genata.clb
CardLib=wd.clb

Configuration Notes:

Installation for Windows/DOS was accomplished by running installation program from drivers diskette. The install procedure automatically chose the resources IRQ 5 and I/O 380, the install program made all necessary modifications. In Windows 95 the drivers are built in so the card will automatically be recognized and configured upon insertion.

PLATFORM: *COMPAQ LTE 5000*

ROM: *09/19/95*

PC CARD: *3COM ETHERLINK III, PN: 3C589B-COMBO*

OPERATING SYSTEM: *WINDOWS 3.1/DOS 6.2*

NOS: *NOVELL 3.12*

CARD AND SOCKET SERVICES: *3.14*

CONFIG.SYS

```
SHELL=C:\DOS\COMMAND.COM /P /E:1536
DEVICE=C:\CPQDOS\MACHCHK.SYS 02A8 02B0 02BA 02CA
DEVICE=C:\DOS\HIMEM.SYS
DEVICE=C:\DOS\EMM386.exe NOEMS I=B000B 7FF X=C800CBFF X=D100-D5FF X=E800-EFFF
DOS=HIGH, UMB
REM PC Card: Begin PC Card (PCMCIA) Drivers
REM **Warning: Do not move, reorder, or delete any of these lines. **
DEVICEHIGH=C:\CARDWIZ\SSCIRUS2.EXE
DEVICEHIGH=C:\CARDWIZ\CS.EXE /POLL:1
DEVICEHIGH=C:\CARDWIZ\CSALLOC.EXE
DEVICEHIGH=C:\CARDWIZ\CARDID.EXE
REM PC Card: End PC Card(PCMCIA) Drives
FILES=35
BUFFERS=20,0
STACKS=9,256
REM DEVICEHIGH=C:\DOS\POWER.EXE
REM DEVICEHIGH=C:\DOS\SETVER.EXE
DEVICEHIGH=C:\AUDIO_CD\TEAC_CDI.SYS /D:TEAC-CDI
LASTDRIVE=Z
```

AUTOEXEC.BAT

```
@ECHO OFF
PATH C:\WINDOWS;C:\CPQDOS;C:\DOS;C:\AUDIO_CD;C:\CARDWIZ
PROMPT $p$g
SET DIRCMD=/ogn
SET TEMP=C:\WINDOWS\TEMP
SET BLASTER=A220 D1 I5
SET LMOUSE=C:\MOUSE
SET MOUSE=C:\MOUSE
C:\MOUSE\MOUSE.EXE MEMU
C:\DOS\MSCDEX.EXE /D:TEAC-CDI /M:15
IF ERRORLEVEL 1 GOTO NO_CDROM
C:\AUDIO_CD\ESSVOL /V:15 /C:15
:NO_CDROM
IF NOT EXIST C:\CPQDOS\SAVEDONE.CPQ CALL SAVEALL /A
LH C:\DOS\SMARTDRV.EXE
C:\CPQDOS\0VMAKFIL
@echo off
REM Netware startup
if not exist C:\NWCLIENT\lsl.com goto noNetware
if not exist C:\NWCLIENT\ipxodi.com goto noNetware
if not exist C:\NWCLIENT\vlm.exe goto noNetware
C:\NWCLIENT\lsl.com
C:\NWCLIENT\3C589.com
C:\NWCLIENT\ipxodi.com
C:\NWCLIENT\vlm.exe
n:\login
c:
goto doneNetware
:noNetware
echo Netware client software missing, Netware not started
:doneNetware
```

NETWORK DRIVERS

| | | |
|------------|--------|----------|
| LSL.COM | 18,313 | 10-11-94 |
| IPXODI.COM | 39,353 | 10-31-94 |
| 3C589.COM | 41,520 | 09-08-94 |
| VLM.EXE | 37,611 | 11-08-94 |

NET.CFG

; THIS SECTION IS FOR CONFIGURATION OF LINKWATCH MANAGEABLE END NODES.

Protocol DME

```
    BIND #1
; replace with your specific information for LinkWatch
    USER_NAME "Your Name"
    NODE_NAME "Your Node Name"
    NODE_LOCATION "Your Node Location"
; set password according to your network administrator's instructions
; NODE_PASSWORD "ABCDEFGH"
    PHONE_NUMBER "Your Phone Number"
    NOTES "Miscellaneous text"
    NOTES "and more text"
```

LINK DRIVER 3C589

```
;   PORT 300
      FRAME ETHERNET_802.2
      INT 11
;
; =====
;   | port [index] STARTING_PORT COUNT
;   |   This setting is only required when there is two
;   |   adapters in the workstation.
;   |
;   |   All adapter specific parameters are read from the adapter.
;   |
;   | mem [index] MEMORY_WINDOW (Optional)
;   |   If parameter not present in protocol.ini, driver auto selects a
;   |   a free 4K memory window. Released after initialization of card.
;   |   If specified, forces driver to use this address to map card's
;   |   CIS memory during driver initialization. Window is released
;   |   after driver finishes initializing card or fails to find card.
;   |   Use 0xC000 - 0xEF00 in steps of 0x100
;   |
; NOTE: | frame ethernet_802.3
; *****|   This is a version 4.X DOS ODI driver. The default
;   |   frame type is 802.2, but you may be using 802.3.
;   |
;   | =====
```

NetWare DOS Requester

FIRST NETWORK DRIVE = N

CARDID.INI

[Common]

; Common Information section created by Config

```
;
ComPort1=3F8
ComIRQ1=4
ComPort2=2F8
ComIRQ2=3
ComPort3=3E8
ComIRQ3=4
ComPort4=2E8
ComIRQ4=11
ComBySocket=No
ComBDAAbsolute=Yes
ComRollOverOn=No
FirstModem=2
SecondModem=4
ThirdModem=2
FourthModem=4
Audio=Yes
RingIndicate=No
Suspend_Power=No
```

CARDID.INI-continued

Lan1Port=330
Lan1IRQ=11
Lan1MemoryBase1=
Lan1MemoryBase2=
Lan2Port=310
Lan2IRQ=10
Lan2MemoryBase1=
Lan2MemoryBase2=
ATATryPrimary=No
ATATrySecondary=Yes
ATATryLinear=Yes
FastTokenRing=Yes
DetectNonCompliant=No
ContinueOnConfigFailure=No
BeepInDOS=Yes
BeepInWindows=Yes
GrabInitFile=Yes
InitBufferSize=512

[Libraries]

;
; The Libraries section contains references to any card libraries the user
; wishes to include. Libraries are searched in the specified order. Path
; names are relative to the directory containing CARDID.INI.

;
CardLib=xirdual.clb
CardLib=xircom.clb
CardLib=tdkklan2.clb
CardLib=sundisk5.clb
CardLib=intellan.clb
CardLib=dlink.clb
CardLib=linksys.clb
CardLib=linksys2.clb
CardLib=socketea.clb
CardLib=ibmlan.clb
CardLib=ibmtok.clb
CardLib=ibm3270.clb
CardLib=proxim.clb
CardLib=cbdas.clb
CardLib=genmodem.clb
CardLib=genata.clb
CardLib=wd.clb

Configuration Notes:

Installation for Windows/DOS was accomplished by running installation program from drivers diskette. The install procedure automatically chose the resources IRQ 5 and I/O 380, the install program made all necessary modifications. The resources did differ when inserted into the base, we manually changed the integrated network controller to IRQ 10, I/O 220. The card will still work when in the base, it will use the resources IRQ 5 and I/O 360. In Windows 95 the drivers are built in so the card will automatically be recognized and configured upon insertion.

PLATFORM: COMPAQ AERO 4/33C

ROM: 07/19/95

PC CARD: IBM ETHERNET CREDIT CARD ADAPTER II, PN: 0934330

OPERATING SYSTEM: WINDOWS 3.1/DOS 6.2

NOS: NOVELL 3.12

CARD AND SOCKET SERVICES: 1.25

CONFIG.SYS

```
SHELL=C:\DOS\COMMAND.COM /P /E:1536
STACKS=9,256
DEVICE=C:\DOS\HIMEM.SYS
DEVICE=C:\DOS\EMM386.EXE NOEMS X=D000-DFFF
DOS=UMB
REM *** Begin PCMCIA Drivers
REM
DEVICE=C:\CPQDOS\PCSMIX.EXE
DEVICEHIGH=C:\CPQDOS\SSVLSI.EXE
DEVICEHIGH=C:\CPQDOS\CS.EXE
DEVICE=C:\CPQDOS\CSALLOC.EXE
;DEVICEHIGH=C:\CPQDOS\ATADRV.EXE /D:1
DEVICEHIGH=C:\CPQDOS\CARDID.EXE C:\CPQDOS\CARDID.INI
DEVICEHIGH=C:\CPQDOS\MEMDRV.EXE
REM *** End PCMCIA Drivers
DOS=HIGH
BUFFERS=20
FILES=35
DEVICEHIGH=C:\CPQDOS\POWER.EXE
LASTDRIVE=E
```

AUTOEXEC.BAT

```
@loadhigh C:\DOS\SHARE.EXE /I:500 /f:5100
SET PATH=C:\CPQDOS;C:\;C:\DOS;C:\WINDOWS;C:\WINDOWS\CPQWIN
SET LMOUSE=C:\MOUSE
SET PROMPT=$P$G
SET TEMP=C:\WINDOWS\TEMP
C:\CPQDOS\HIBRN8.EXE
C:\DOS\SMARTDRV.EXE
LH C:\MOUSE\MOUSE SWAP
C:\CPQDOS\MODE.COM CO80
C:\WINDOWS\WIN
```

NETWORK DRIVERS

| | | |
|-------------|--------|----------|
| PCMDMCS.COM | 27,532 | 07-15-94 |
| LSL.COM | 17,805 | 09-10-93 |
| IPXODI.COM | 30,247 | 10-07-93 |
| NETX.EXE | 78,654 | 11-17-93 |

NET.CFG

```
Link Driver PCMDMCS
PORT 300
INT 5
MEM D0000
FRAME ETHERNET_802.2
```


CARDID.INI

```
[Common]
;
; Common Information section created by Config
;
ComPort1=3F8
ComIRQ1=4
ComPort2=2F8
ComIRQ2=3
ComPort3=3E8
ComIRQ3=4
ComPort4=2E8
ComIRQ4=3
ComBySocket=Yes
ComBDAAbsolute=No
FirstModem=2
SecondModem=2
ThirdModem=3
FourthModem=4
Audio=Yes
RingIndicate=No
Lan1Port=300
Lan1IRQ=5
Lan1MemoryBase1=D8
Lan1MemoryBase2=DC
Lan2Port=310
Lan2IRQ=10
Lan2MemoryBase1=D8
Lan2MemoryBase2=DC
ATATryPrimary=No
ATATrySecondary=Yes
ATATryLinear=Yes
FastTokenRing=Yes
DetectNonCompliant=No
ContinueOnConfigFailure=No
BeepInDOS=Yes
BeepInWindows=Yes
GrabInitFile=Yes
InitBufferSize=512
```

```
[Libraries]
;
; The Libraries section contains references to any card libraries the user
; wishes to include. Libraries are searched in the specified order. Path
; names are relative to the directory containing CARDID.INI.
;
CardLib=cardid.clb
```

Configuration Notes:

The configuration above used IRQ 5, I/O 300, and the memory range of D000. In order to get the card working in Windows 3.1 or DOS you must remark out the line with ATADRV in the Config.Sys. Must create C:\NETWARE before you start the install program, and it will not copy LSL, IPXODI, or NETX. The drivers for Windows 95 are in place and will be automatically configured upon insertion.

PLATFORM: *COMPAQ CONCERTO*

ROM: *10/12/93*

PC CARD: *IBM ETHERNET CREDIT CARD ADAPTER II, PN: 0934330*

OPERATING SYSTEM: *WINDOWS 3.1/DOS 6.2*

NOS: *NOVELL 3.12*

CARD AND SOCKET SERVICES: *1.25*

CONFIG.SYS

```
SHELL=C:\DOS\COMMAND.COM /P /E:1536
STACKS=9,256
DEVICE=C:\DOS\HIMEM.SYS
DEVICE=C:\DOS\EMM386.EXE NOEMS X=D000-DFFF
DOS=UMB
REM *** Begin PCMCIA Drivers
REM
DEVICEHIGH=C:\CPQDOS\SSCIRRUS.EXE
DEVICEHIGH=C:\CPQDOS\CS.EXE
DEVICE=C:\CPQDOS\CSALLOC.EXE
;DEVICEHIGH=C:\CPQDOS\ATADRV.EXE
DEVICEHIGH=C:\CPQDOS\CARDID.EXE C:\CPQDOS\CARDID.INI
DEVICEHIGH=C:\CPQDOS\MEMDRV.EXE
REM *** End PCMCIA Drivers
DOS=HIGH
BUFFERS=20
FILES=35
DEVICEHIGH=C:\CPQDOS\POWER.EXE
DEVICE=C:\DOS\SETVER.EXE
```

AUTOEXEC.BAT

```
SET PATH=C:\CPQDOS;C:\;C:\DOS;C:\WINDOWS;;C:\WINDOWS\CPQWIN
SET LMOUSE=C:\MOUSE
SET PROMPT=$P$G
SET TEMP=C:\WINDOWS\TEMP
C:\CPQDOS\HIBRN8.EXE
C:\DOS\SMARTDRV.EXE
LH C:\MOUSE\MOUSE
C:\CPQDOS\MODE.COM CO80
C:\WINDOWS\WIN
```

NETWORK DRIVERS

| | | |
|-------------|--------|----------|
| PCMDMCS.COM | 27,532 | 07-15-94 |
| LSL.COM | 8,780 | 11-05-92 |
| IPXODI.COM | 30,051 | 04-23-93 |
| NETX.EXE | 78,654 | 11-17-93 |

NET.CFG

```
Link Driver PCMDMCS
PORT 220
INT 5
MEM D0000
FRAME ETHERNET_802.2
```

CARDID.INI

```
[Common]
;
; Common Information section created by Config
;
ComPort1=3F8
ComIRQ1=4
ComPort2=2F8
ComIRQ2=3
ComPort3=3E8
ComIRQ3=4
ComPort4=2E8
ComIRQ4=3
ComBySocket=Yes
ComBDAAbsolute=No
FirstModem=2
SecondModem=2
ThirdModem=3
FourthModem=4
Audio=Yes
RingIndicate=No
Lan1Port=300
Lan1IRQ=5
Lan1MemoryBase1=D8
Lan1MemoryBase2=DC
Lan2Port=310
Lan2IRQ=10
Lan2MemoryBase1=D8
Lan2MemoryBase2=DC
ATATryPrimary=No
ATATrySecondary=Yes
ATATryLinear=Yes
FastTokenRing=Yes
DetectNonCompliant=No
ContinueOnConfigFailure=No
BeepInDOS=Yes
BeepInWindows=Yes
GrabInitFile=Yes
InitBufferSize=512
```

```
[Libraries]
;
; The Libraries section contains references to any card libraries the user
; wishes to include. Libraries are searched in the specified order. Path
; names are relative to the directory containing CARDID.INI.
;
CardLib=cardid.clb
```

Configuration Notes:

The configuration above used IRQ 5, I/O 220, and the memory range of D000. If you need to use it in a base with an integrated network controller, change the internal controller to IRQ 10, I/O 300. In order to get the card working in Win 3.1 or DOS you must remark out the line with ATADRV in the Config.Sys. Must create C:\NETWARE before you start the install program, and it will not copy LSL, IPXODI, or NETX. The drivers for Windows 95 are in place and the card will be automatically be configured upon insertion.

PLATFORM: COMPAQ CONTURA 400CX

ROM: 07/18/95

PC CARD: IBM ETHERNET CREDIT CARD ADAPTER II, PN: 0934330

OPERATING SYSTEM: WINDOWS 3.1/DOS 6.2

NOS: NOVELL 3.12

CARD AND SOCKET SERVICES: 3.12

CONFIG.SYS

```
SHELL=C:\DOS\COMMAND.COM /P /E:1536
STACKS=9,256
DEVICE=C:\DOS\HIMEM.SYS
DEVICE=C:\DOS\EMM386.EXE NOEMS I=B000-B7FF X=D000-D4FF
DEVICEHIGH=C:\WINDOWS\CPQWIN\CPQCM.SYS
DOS=HIGH,UMB
REM *** Begin PCMCIA Drivers
;DEVICE=C:\CPQDOS\PCSMIX.EXE
DEVICEHIGH=C:\CPQDOS\SSVLSI.EXE
DEVICEHIGH=C:\CPQDOS\CS.EXE
DEVICE=C:\CPQDOS\CSALLOC.EXE
;DEVICEHIGH=C:\CPQDOS\ATADRV.EXE
;DEVICEHIGH=C:\CPQDOS\MTAA.EXE
;DEVICEHIGH=C:\CPQDOS\MTAB.EXE
;DEVICEHIGH=C:\CPQDOS\MTI1.EXE
;DEVICEHIGH=C:\CPQDOS\MTI2P.EXE
;DEVICEHIGH=C:\CPQDOS\MTSRAM.EXE
;DEVICEHIGH=C:\CPQDOS\MTDDRIV.EXE
;DEVICEHIGH=C:\CPQDOS\DBLFLASH.EXE
;DEVICEHIGH=C:\CPQDOS\MS-FLASH.SYS
DEVICEHIGH=C:\CPQDOS\CARDID.EXE
REM *** End PCMCIA Drivers
BUFFERS=20
FILES=35
DEVICEHIGH=C:\CPQDOS\EPPBIOS.SYS
DEVICEHIGH=C:\CPQDOS\POWER.EXE
```

AUTOEXEC.BAT

```
@ECHO OFF
SET PATH=C:\CPQDOS;C:\;C:\DOS;C:\WINDOWS;;C:\WINDOWS\CPQWIN
SET LMOUSE=C:\MOUSE
LH C:\MOUSE\MOUSE
SET PROMPT=$PSG
C:\CPQDOS\HIBRN8.EXE
LH C:\DOS\SMARTDRV.EXE
```

NETWORK DRIVERS

| | | |
|-------------|--------|----------|
| PCMDMCS.COM | 27,532 | 07-15-94 |
| LSL.COM | 17,805 | 09-10-93 |
| IPXODI.COM | 30,247 | 10-07-93 |
| NETX.EXE | 78,654 | 11-17-93 |

NET.CFG

```
Link Driver PCMDMCS
PORT 300
INT 5
MEM D0000
FRAME ETHERNET_802.2
```

CARDID.INI

```

[Common]
;
; Common Information section created by Config
;
ComPort1=3F8
ComIRQ1=4
ComPort2=2F8
ComIRQ2=3
ComPort3=3e8
ComIRQ3=4
ComPort4=2E8
ComIRQ4=3
ComBySocket=Yes
ComBDAAbsolute=No
FirstModem=2
SecondModem=2
ThirdModem=3
FourthModem=4
Audio=Yes
RingIndicate=No
Lan1Port=300
Lan1IRQ=5
Lan1MemoryBase1=
Lan1MemoryBase2=
Lan2Port=310
Lan2IRQ=9
Lan2MemoryBase1=
Lan2MemoryBase2=
ATATryPrimary=No
ATATrySecondary=Yes
ATATryLinear=Yes
FastTokenRing=Yes
DetectNonCompliant=No
ContinueOnConfigFailure=No
BeepInDOS=Yes
BeepInWindows=Yes
GrabInitFile=Yes
InitBufferSize=512
UseEMS=No

```

```

[Libraries]
;
; The Libraries section contains references to any card libraries the user
; wishes to include. Libraries are searched in the specified order. Path
; names are relative to the directory containing CARDID.INI.
;
CardLib=canonfd.clb
CardLib=xirdual.clb
CardLib=xircom.clb
CardLib=tdkklan2.clb
CardLib=sundisk5.clb
CardLib=intellan.clb
CardLib=dlink.clb
CardLib=linksys.clb
CardLib=linksys2.clb
CardLib=socketea.clb
CardLib=ibmlan.clb
CardLib=ibmtok.clb
CardLib=ibm3270.clb
CardLib=proxim.clb
CardLib=cbdass.clb
CardLib=genmodem.clb
CardLib=genata.clb
CardLib=wd.clb

```

Configuration Notes:

The configuration above used IRQ 5, I/O 300, and the memory range of D000. Must create C:\NETWARE before you start the install program, and it will not copy LSL, IPXODI, or NETX. The drivers for Windows 95 are in place and the card will be automatically configured upon insertion.

PLATFORM: COMPAQ CONTURA 420CX

ROM: 08/20/95

PC CARD: IBM ETHERNET CREDIT CARD ADAPTER II, PN: 0934330

OPERATING SYSTEM: WINDOWS 3.1/DOS 6.2

NOS: NOVELL 3.12

CARD AND SOCKET SERVICES: 3.12

CONFIG.SYS

```
SHELL=C:\DOS\COMMAND.COM /P /E:1536
STACKS=9,256
DEVICE=C:\DOS\HIMEM.SYS
DEVICEHIGH=C:\WINDOWS\CPQWIN\CPQCM.SYS
DEVICE=C:\DOS\EMM386.EXE NOEMS I=B000-B7FF X=D000-D4FF
DOS=UMB
REM *** Begin PCMCIA Drivers
;DEVICE=C:\CPQDOS\PCSMIX.EXE
DEVICEHIGH=C:\CPQDOS\SSVLSI.EXE
DEVICEHIGH=C:\CPQDOS\CS.EXE
DEVICE=C:\CPQDOS\CSALLOC.EXE
;DEVICEHIGH=C:\CPQDOS\ATADRV.EXE
;DEVICEHIGH=C:\CPQDOS\MTAA.EXE
;DEVICEHIGH=C:\CPQDOS\MTAB.EXE
;DEVICEHIGH=C:\CPQDOS\MTI1.EXE
;DEVICEHIGH=C:\CPQDOS\MTI2P.EXE
;DEVICEHIGH=C:\CPQDOS\MTSRAM.EXE
;DEVICEHIGH=C:\CPQDOS\MTDDRIV.EXE
;DEVICEHIGH=C:\CPQDOS\DBLFLASH.EXE
;DEVICEHIGH=C:\CPQDOS\MS-FLASH.SYS
DEVICEHIGH=C:\CPQDOS\CARDID.EXE
REM *** End PCMCIA Drivers
DOS=HIGH
BUFFERS=20
FILES=35
DEVICEHIGH=C:\CPQDOS\EPPBIOS.SYS
```

AUTOEXEC.BAT

```
SET PATH=C:\CPQDOS;C:\;C:\DOS;C:\WINDOWS; C:\WINDOWS\CPQWIN
SET LMOUSE=C:\MOUSE
SET PROMPT=$PSG
C:\CPQDOS\HIBRN8.EXE
C:\DOS\SMARTDRV.EXE 2048 512
C:\MOUSE\mouse.exe
C:\CPQDOS\MODE.COM CO80
```

NETWORK DRIVERS

| | | |
|-------------|--------|----------|
| LSL.COM | 8,780 | 04-23-93 |
| IPXODI.COM | 30,051 | 11-05-92 |
| PCMDMCS.COM | 27,532 | 07-15-94 |
| NETX.EXE | 78,654 | 11-17-93 |

NET.CFG

```
Link Driver PCMDMCS
PORT 300
INT 5
MEM D0000
FRAME ETHERNET_802.2
```

CARDID.INI

[Common]

```
;
; Common Information section created by Config
;
ComPort1=3F8
ComIRQ1=4
ComPort2=2F8
ComIRQ2=3
ComPort3=3e8
ComIRQ3=4
ComPort4=2E8
ComIRQ4=3
ComBySocket=Yes
ComBDAAbsolute=No
FirstModem=2
SecondModem=2
ThirdModem=3
FourthModem=4
Audio=Yes
RingIndicate=No
Lan1Port=300
Lan1IRQ=5
Lan1MemoryBase1=
Lan1MemoryBase2=
Lan2Port=310
Lan2IRQ=9
Lan2MemoryBase1=
Lan2MemoryBase2=
ATATryPrimary=No
ATATrySecondary=Yes
ATATryLinear=Yes
FastTokenRing=Yes
DetectNonCompliant=No
ContinueOnConfigFailure=No
BeepInDOS=Yes
BeepInWindows=Yes
GrabInitFile=Yes
InitBufferSize=512
UseEMS=No
```

[Libraries]

```
;
; The Libraries section contains references to any card libraries the user
; wishes to include. Libraries are searched in the specified order. Path
; names are relative to the directory containing CARDID.INI.
;
CardLib=canonfd.clb
CardLib=xirdual.clb
CardLib=xircom.clb
CardLib=tdkklan2.clb
CardLib=sundisk5.clb
CardLib=intellan.clb
CardLib=dlink.clb
CardLib=linksys.clb
CardLib=linksys2.clb
CardLib=socketea.clb
CardLib=ibmlan.clb
CardLib=ibmtok.clb
CardLib=ibm3270.clb
CardLib=proxim.clb
CardLib=cbdass.clb
CardLib=genmodem.clb
CardLib=genata.clb
CardLib=wd.clb
```

Configuration Notes:

The configuration above used IRQ 5, I/O 300, and the memory range of D000. Must create C:\NETWARE before you start the install program, and it will not copy LSL, IPXODI, or NETX. The drivers for Windows 95 are in place and the card will be automatically configured upon insertion.

PLATFORM: COMPAQ ELITE 4/75CXL

ROM: 07/19/95

PC CARD: IBM ETHERNET CREDIT CARD ADAPTER II, PN: 0934330

OPERATING SYSTEM: WINDOWS 3.1/DOS 6.2

NOS: NOVELL 3.12

CARD AND SOCKET SERVICES: 3.12

CONFIG.SYS

```
SHELL=C:\DOS\COMMAND.COM /P /E:1536
STACKS=9,256
DEVICE=C:\DOS\HIMEM.SYS
DEVICE=C:\DOS\EMM386.EXE NOEMS I=B000-B7FF X=D000-D4FF
DEVICEHIGH=C:\WINDOWS\CPQWIN\CPQCM.SYS
DOS=HIGH,UMB
REM *** Begin PCMCIA Drivers
;DEVICE=C:\CPQDOS\PCMSMIX.EXE
DEVICEHIGH=C:\CPQDOS\SSVLSI.EXE
DEVICEHIGH=C:\CPQDOS\CS.EXE
DEVICE=C:\CPQDOS\CSALLOC.EXE
;DEVICEHIGH=C:\CPQDOS\ATADRV.EXE
;DEVICEHIGH=C:\CPQDOS\MTAA.EXE
;DEVICEHIGH=C:\CPQDOS\MTAB.EXE
;DEVICEHIGH=C:\CPQDOS\MTI1.EXE
;DEVICEHIGH=C:\CPQDOS\MTI2P.EXE
;DEVICEHIGH=C:\CPQDOS\MTSRAM.EXE
;DEVICEHIGH=C:\CPQDOS\MTDDRIV.EXE
;DEVICEHIGH=C:\CPQDOS\DBLFLASH.EXE
;DEVICEHIGH=C:\CPQDOS\MS-FLASH.SYS
DEVICEHIGH=C:\CPQDOS\CARDID.EXE
REM *** End PCMCIA Drivers
BUFFERS=20
FILES=35
LASTDRIVE = Z
DEVICEHIGH=C:\CPQDOS\POWER.EXE
```

AUTOEXEC.BAT

```
@ECHO OFF
SET PATH=C:\CPQDOS;C:\;C:\DOS;C:\WINDOWS;;C:\WINDOWS\CPQWIN
SET LMOUSE=C:\MOUSE
LH C:\MOUSE\MOUSE
SET PROMPT=$PSG
C:\CPQDOS\HIBRN8.EXE
LH C:\DOS\SMARTDRV.EXE
```

NETWORK DRIVERS

| | | |
|-------------|--------|----------|
| PCMDMCS.COM | 27,532 | 07-15-94 |
| LSL.COM | 17,805 | 09-10-93 |
| IPXODI.COM | 30,247 | 10-07-93 |
| NETX.EXE | 78,654 | 11-17-93 |

NET.CFG

```
Link Driver PCMDMCS
PORT 300
INT 5
MEM D0000
FRAME ETHERNET_802.2
```


CARDID.INI

```
[Common]
;
; Common Information section created by Config
;
ComPort1=3F8
ComIRQ1=4
ComPort2=2F8
ComIRQ2=3
ComPort3=3e8
ComIRQ3=4
ComPort4=2E8
ComIRQ4=3
ComBySocket=Yes
ComBDAAbsolute=No
FirstModem=2
SecondModem=2
ThirdModem=3
FourthModem=4
Audio=Yes
RingIndicate=No
Lan1Port=300
Lan1IRQ=5
Lan1MemoryBase1=
Lan1MemoryBase2=
Lan2Port=310
Lan2IRQ=9
Lan2MemoryBase1=
Lan2MemoryBase2=
ATATryPrimary=No
ATATrySecondary=Yes
ATATryLinear=Yes
FastTokenRing=Yes
DetectNonCompliant=No
ContinueOnConfigFailure=No
BeepInDOS=Yes
BeepInWindows=Yes
GrabInitFile=Yes
InitBufferSize=512
UseEMS=No
```

```
[Libraries]
;
; The Libraries section contains references to any card libraries the user
; wishes to include. Libraries are searched in the specified order. Path
; names are relative to the directory containing CARDID.INI.
;
CardLib=canonfd.clb
CardLib=xirdual.clb
CardLib=xircom.clb
CardLib=tdkklan2.clb
CardLib=sundisk5.clb
CardLib=intellan.clb
CardLib=dlink.clb
CardLib=linksys.clb
CardLib=linksys2.clb
CardLib=socketea.clb
CardLib=ibmlan.clb
CardLib=ibmtok.clb
CardLib=ibm3270.clb
CardLib=proxim.clb
CardLib=cbdass.clb
CardLib=genmodem.clb
CardLib=genata.clb
CardLib=wd.clb
```

Configuration Notes:

The configuration above used IRQ 5, I/O 300, and the memory range of D000. Must create C:\NETWARE before you start the install program, and it will not copy LSL, IPXODI, or NETX. The drivers for Windows 95 are in place and the card will be automatically configured upon insertion.

PLATFORM: COMPAQ LTE 5000

ROM: 09/19/95

PC CARD: IBM ETHERNET CREDIT CARD ADAPTER II, PN: 0934330

OPERATING SYSTEM: WINDOWS 3.1/DOS 6.2

NOS: NOVELL 3.12

CARD AND SOCKET SERVICES: 3.14

CONFIG.SYS

```
DEVICE=C:\CPQDOS\MACHCHK.SYS 02A8 02B0 02BA 02CA
DEVICE=C:\DOS\HIMEM.SYS
DEVICE=C:\DOS\EMM386.exe NOEMS I=B000-B7FF X=C800-CBFF X=D100-D5FF X=E800-EFFF
COUNTRY=001,437,C:\DOS\COUNTRY.SYS
SHELL=C:\DOS\COMMAND.COM /P /E:1536
DOS=HIGH,UMB
FILES=35
BUFFERS=20,0
STACKS=9,256
DEVICEHIGH=C:\AUDIO_CD\TEAC_CDI.SYS /D:TEAC-CDI
LASTDRIVE=M
REM PC Card: Begin PC Card (PCMCIA) Drivers
DEVICEHIGH=C:\CARDWIZ\SSCIRUS2.EXE
DEVICEHIGH=C:\CARDWIZ\CS.EXE /POLL:1
DEVICEHIGH=C:\CARDWIZ\CSALLOC.EXE
DEVICEHIGH=C:\CARDWIZ\CARDID.EXE
REM PC Card: End PC Card (PCMCIA) Drives
```

AUTOEXEC.BAT

```
@ECHO OFF
C:\WINDOWS\VGAUTIL\winmode.exe t640=60 t800=60 t1024=87 t1280=87
PATH C:\WINDOWS;C:\CPQDOS;C:\DOS;C:\AUDIO_CD;C:\CARDWIZ
PROMPT $p$g
SET DIRCMD=/ogn
SET BLASTER=A220 D1 I5
SET LMOUSE=C:\MOUSE
SET MOUSE=C:\MOUSE
C:\MOUSE\MOUSE.EXE MEMU
C:\DOS\MSCDEX.EXE /D:TEAC-CDI /M:15
C:\AUDIO_CD\ESSVOL /V:15 /C:15
:NO_CDROM
IF NOT EXIST C:\CPQDOS\SAVEDONE.CPQ CALL SAVEALL /A
LH C:\DOS\SMARTDRV.EXE
C:\CPQDOS\0VMAKFIL
```

NETWORK DRIVERS

| | | |
|-------------|--------|----------|
| IPXODI.COM | 30,051 | 04-23-93 |
| LSL.COM | 8,780 | 11-05-92 |
| PCMDMCS.COM | 27,532 | 07-15-94 |
| NETX.EXE | 78,654 | 11-17-93 |

NET.CFG

```
Link Driver PCMDMCS
  port 340
  int 11
  MEM D1000
  FRAME ETHERNET_802.2
  pcmcia
```

CARDID.INI

```
[Common]
;
; Common Information section created by Config
;
ComPort1=3F8
ComIRQ1=4
ComPort2=2F8
ComIRQ2=3
ComPort3=3E8
ComIRQ3=4
ComPort4=2E8
ComIRQ4=11
ComBySocket=No
ComBDAAbsolute=Yes
ComRollOverOn=No
FirstModem=2
SecondModem=4
ThirdModem=2
FourthModem=4
Audio=Yes
RingIndicate=No
Suspend_Power=No
Lan1Port=330
Lan1IRQ=11
Lan1MemoryBase1=0
Lan1MemoryBase2=0
Lan2Port=310
Lan2IRQ=10
Lan2MemoryBase1=0
Lan2MemoryBase2=0
ATATryPrimary=No
ATATrySecondary=Yes
ATATryLinear=Yes
FastTokenRing=Yes
DetectNonCompliant=No
ContinueOnConfigFailure=No
BeepInDOS=Yes
BeepInWindows=Yes
GrabInitFile=Yes
InitBufferSize=512
FirstLan=1
SecondLan=2
```

```
[Libraries]
;
; The Libraries section contains references to any card libraries the user
; wishes to include. Libraries are searched in the specified order. Path
; names are relative to the directory containing CARDID.INI.
;
CardLib=xirdual.clb
CardLib=xircom.clb
CardLib=tdkklan2.clb
CardLib=sundisk5.clb
CardLib=intellan.clb
CardLib=dlink.clb
CardLib=linksys.clb
CardLib=linksys2.clb
CardLib=socketea.clb
;CardLib=ibmlan.clb
CardLib=ibmtok.clb
CardLib=ibm3270.clb
CardLib=proxim.clb
CardLib=cbdass.clb
CardLib=genmodem.clb
CardLib=genata.clb
CardLib=wd.clb
```

Configuration Notes:

The configuration above used IRQ 11, I/O 340, and the memory range of D1000. In order to get the card working in Windows 3.1 or DOS you must remark out the line `CardLib=ibmlan.clb` in the CARDID.INI file located in C:\CARDWIZ directory. The drivers for Windows 95 will automatically configure the card upon insertion.

PLATFORM: *COMPAQ AERO 4/33C*

ROM: 07/19/95

PC CARD: MADGE TOKEN RING SMART 16/4 RINGNODE, PN: 20-00

OPERATING SYSTEM: WINDOWS 3.1/DOS 6.2

NOS: NOVELL 3.12

CARD AND SOCKET SERVICES: 1.25

CONFIG.SYS

```
SHELL=C:\DOS\COMMAND.COM /P /E:1536
STACKS=9,256
DEVICE=C:\DOS\HIMEM.SYS
DEVICE=C:\DOS\EMM386.EXE NOEMS X=D000-DFFF
DOS=UMB
REM *** Begin PCMCIA Drivers
REM Warning: Do not move, reorder, or delete any of these lines.
DEVICE=C:\CPQDOS\PCSMIX.EXE
DEVICEHIGH=C:\CPQDOS\SSVLSI.EXE
DEVICEHIGH=C:\CPQDOS\CS.EXE
DEVICE=C:\CPQDOS\CSALLOC.EXE
;DEVICEHIGH=C:\CPQDOS\ATADRV.EXE /D:1
DEVICEHIGH=C:\CPQDOS\CARDID.EXE C:\CPQDOS\CARDID.INI
DEVICEHIGH=C:\CPQDOS\MEMDRV.EXE
;DEVICEHIGH=C:\CPQDOS\DBLFLASH.EXE
;DEVICEHIGH=C:\CPQDOS\MS-FLASH.SYS
REM *** End PCMCIA Drivers
DOS=HIGH
BUFFERS=20
FILES=35
;DEVICEHIGH=C:\CPQDOS\POWER.EXE
```

AUTOEXEC.BAT

```
@loadhigh C:\DOS\SHARE.EXE /I:500 /F:5100
SET PATH=C:\CPQDOS;C:\;\C:\DOS;C:\WINDOWS; C:\WINDOWS\CPQWIN
SET LMOUSE=C:\MOUSE
SET PROMPT=$PSG
SET TEMP=C:\WINDOWS\TEMP
C:\CPQDOS\HIBRN8.EXE
C:\DOS\SMARTDRV.EXE
LH C:\MOUSE\MOUSE SWAP
C:\CPQDOS\MODE.COM CO80
\madge\smart.exe path=\madge\
\madge\netx
```

NETWORK DRIVERS

| | | |
|-----------|---------|----------|
| IPX.SMT | 36,528 | 03-03-95 |
| SMART.EXE | 148,608 | 03-03-95 |
| SMART.CFG | 58 | 01-08-96 |
| NETX.EXE | 78,654 | 11-17-93 |

CARDID.INI

```
[Common]
;
; Common Information section created by Config
;
ComPort1=3F8
ComIRQ1=4
ComPort2=2F8
ComIRQ2=3
ComPort3=3E8
ComIRQ3=4
ComPort4=2E8
ComIRQ4=3
```

CARDID.INI-continued

ComBySocket=Yes
ComBDAAbsolute=No
FirstModem=2
SecondModem=2
ThirdModem=3
FourthModem=4
Audio=Yes
RingIndicate=No
Lan1Port=300
Lan1IRQ=5
Lan1MemoryBase1=D8
Lan1MemoryBase2=DC
Lan2Port=310
Lan2IRQ=10
Lan2MemoryBase1=D8
Lan2MemoryBase2=DC
ATATryPrimary=No
ATATrySecondary=Yes
ATATryLinear=Yes
FastTokenRing=Yes
DetectNonCompliant=No
ContinueOnConfigFailure=No
BeepInDOS=Yes
BeepInWindows=Yes
GrabInitFile=Yes
InitBufferSize=512

[Libraries]

;
; The Libraries section contains references to any card libraries the user
; wishes to include. Libraries are searched in the specified order. Path
; names are relative to the directory containing CARDID.INI.
;
CardLib=cardid.clb

Configuration Notes:

To install ran setup procedure from drivers diskette. The software chose IRQ 5 and I/O 300 for the resources, and installation procedure made all the required modifications to the Autoexec.Bat file. The program did not supply NETX.EXE , so we had to manually copy that file. Drivers do not use a NET.CFG, uses a file Smart.CFG to hold settings. Windows 95 drivers are built in so card will be automatically recognized and configured upon insertion.

PLATFORM: *COMPAQ CONCERTO*

ROM: *11/17/93*

PC CARD: *MADGE TOKEN RING SMART 16/4 RINGNODE, PN: 20-00*

OPERATING SYSTEM: *WINDOWS 3.1/DOS 6.2*

NOS: *NOVELL 3.12*

CARD AND SOCKET SERVICES: *1.25*

CONFIG.SYS

```
SHELL=C:\DOS\COMMAND.COM /P /E:1536
STACKS=9,256
DEVICE=C:\DOS\HIMEM.SYS
DEVICE=C:\DOS\EMM386.EXE NOEMS X=D000-DFFF
DOS=UMB
REM *** Begin PCMCIA Drivers
REM Warning: Do not move, reorder, or delete any of these lines.
REM
DEVICEHIGH=C:\CPQDOS\SSCIRRUS.EXE
DEVICEHIGH=C:\CPQDOS\CS.EXE
DEVICE=C:\CPQDOS\CSALLOC.EXE
DEVICEHIGH=C:\CPQDOS\ATADRV.EXE
DEVICEHIGH=C:\CPQDOS\CARDID.EXE C:\CPQDOS\CARDID.INI
DEVICEHIGH=C:\CPQDOS\MEMDRV.EXE
;DEVICEHIGH=C:\CPQDOS\DBLFLASH.EXE
;DEVICEHIGH=C:\CPQDOS\MS-FLASH.SYS
REM *** End PCMCIA Drivers
DOS=HIGH
BUFFERS=20
FILES=35
DEVICEHIGH=C:\CPQDOS\POWER.EXE
lastdrive=m
```

AUTOEXEC.BAT

```
SET PATH=C:\CPQDOS;C:\;\C:\DOS;C:\WINDOWS;;C:\WINDOWS\CPQWIN
SET LMOUSE=C:\MOUSE
SET PROMPT=$PSG
SET TEMP=C:\WINDOWS\TEMP
C:\CPQDOS\HIBRN8.EXE
C:\DOS\SMARTDRV.EXE
LH C:\MOUSE\MOUSE
C:\CPQDOS\MODE.COM CO80
\madge\smart.exe path=\madge\
\madge\netx
```

NETWORK DRIVERS

| | | |
|-----------|---------|----------|
| IPX.SMT | 36,528 | 03-03-95 |
| SMART.EXE | 148,608 | 03-03-95 |
| SMART.CFG | 58 | 01-08-96 |
| NETX.EXE | 78,654 | 11-17-93 |

CARDID.INI

```
[Common]
;
; Common Information section created by Config
;
ComPort1=3F8
ComIRQ1=4
ComPort2=2F8
ComIRQ2=3
ComPort3=3E8
ComIRQ3=4
ComPort4=2E8
ComIRQ4=3
```

CARDID.INI-continued

ComBySocket=Yes
ComBDAAbsolute=No
FirstModem=2
SecondModem=2
ThirdModem=3
FourthModem=4
Audio=Yes
RingIndicate=No
Lan1Port=300
Lan1IRQ=5
Lan1MemoryBase1=D8
Lan1MemoryBase2=DC
Lan2Port=310
Lan2IRQ=10
Lan2MemoryBase1=D8
Lan2MemoryBase2=DC
ATATryPrimary=No
ATATrySecondary=Yes
ATATryLinear=Yes
FastTokenRing=Yes
DetectNonCompliant=No
ContinueOnConfigFailure=No
BeepInDOS=Yes
BeepInWindows=Yes
GrabInitFile=Yes
InitBufferSize=512

[Libraries]

;
; The Libraries section contains references to any card libraries the user
; wishes to include. Libraries are searched in the specified order. Path
; names are relative to the directory containing CARDID.INI.
;
CardLib=cardid.clb

Configuration Notes:

To install ran setup procedure from drivers diskette. The software chose IRQ 5 and I/O A20 for the resources , and the installation procedure made all the required modifications to the Autoexec.Bat file. The program did not supply NETX.EXE , so we had to manually copy that file. Drivers do not use a NET.CFG, uses a file Smart.CFG to hold settings. Windows 95 drivers are built in so card will be automatically recognized and configured upon insertion.

PLATFORM: COMPAQ CONTURA 400CX

ROM: 07/18/95

PC CARD: MADGE TOKEN RING SMART 16/4 RINGNODE, PN: 20-00

OPERATING SYSTEM: WINDOWS 3.1/DOS 6.2

NOS: NOVELL 3.12

CARD AND SOCKET SERVICES: 3.12

CONFIG.SYS

```
switches=/F
SHELL=C:\DOS\COMMAND.COM /P /E:1536
STACKS=9,256
DEVICE=C:\DOS\HIMEM.SYS
DEVICE=C:\DOS\EMM386.EXE NOEMS I=B000-B7FF X=D000-D4FF
DEVICEHIGH=C:\WINDOWS\CPQWIN\CPQCM.SYS
DOS=HIGH,UMB
REM *** Begin PCMCIA Drivers
;DEVICE=C:\CPQDOS\PCSMIX.EXE
DEVICEHIGH=C:\CPQDOS\SSVLSI.EXE
DEVICEHIGH=C:\CPQDOS\CS.EXE
DEVICE=C:\CPQDOS\CSALLOC.EXE
;DEVICEHIGH=C:\CPQDOS\ATADRV.EXE
;DEVICEHIGH=C:\CPQDOS\MTAA.EXE
;DEVICEHIGH=C:\CPQDOS\MTAB.EXE
;DEVICEHIGH=C:\CPQDOS\MTI1.EXE
;DEVICEHIGH=C:\CPQDOS\MTI2P.EXE
;DEVICEHIGH=C:\CPQDOS\MTSRAM.EXE
;DEVICEHIGH=C:\CPQDOS\MTDDRV.EXE
;DEVICEHIGH=C:\CPQDOS\DBLFLASH.EXE
;DEVICEHIGH=C:\CPQDOS\MS-FLASH.SYS
DEVICEHIGH=C:\CPQDOS\CARDID.EXE
REM *** End PCMCIA Drivers
BUFFERS=20
FILES=35
DEVICEHIGH=C:\CPQDOS\EPPBIOS.SYS
DEVICEHIGH=C:\CPQDOS\POWER.EXE
```

AUTOEXEC.BAT

```
@ECHO OFF
SET PATH=C:\CPQDOS;C:\;C:\DOS;C:\WINDOWS;;C:\WINDOWS\CPQWIN
SET LMOUSE=C:\MOUSE
LH C:\MOUSE\MOUSE
SET PROMPT=$PSG
SET TEMP=C:\WINDOWS\TEMP
C:\CPQDOS\HIBRN8.EXE
LH C:\DOS\SMARTDRV.EXE
LH SHARE.EXE
\madge\smart.exe path=\madge\
\madge\netx
```

NETWORK DRIVERS

| | | |
|-----------|---------|----------|
| IPX.SMT | 36,528 | 03-03-95 |
| SMART.EXE | 148,608 | 03-03-95 |
| SMART.CFG | 58 | 01-08-96 |
| NETX.EXE | 78,654 | 11-17-93 |

CARDID.INI

```
[Common]
;
; Common Information section created by Config
;
ComPort1=3F8
ComIRQ1=4
ComPort2=2F8
ComIRQ2=3
ComPort3=3e8
ComIRQ3=4
ComPort4=2E8
ComIRQ4=3
ComBySocket=Yes
ComBDAAbsolute=No
FirstModem=2
SecondModem=2
ThirdModem=3
FourthModem=4
Audio=Yes
RingIndicate=No
Lan1Port=300
Lan1IRQ=5
Lan1MemoryBase1=
Lan1MemoryBase2=
Lan2Port=310
Lan2IRQ=9
Lan2MemoryBase1=
Lan2MemoryBase2=
ATATryPrimary=No
ATATrySecondary=Yes
ATATryLinear=Yes
FastTokenRing=Yes
DetectNonCompliant=No
ContinueOnConfigFailure=No
BeepInDOS=Yes
BeepInWindows=Yes
GrabInitFile=Yes
InitBufferSize=512
UseEMS=No
```

```
[Libraries]
;
; The Libraries section contains references to any card libraries the user
; wishes to include. Libraries are searched in the specified order. Path
; names are relative to the directory containing CARDID.INI.
;
CardLib=canonfd.clb
CardLib=xirdual.clb
CardLib=xircom.clb
CardLib=tdkfan2.clb
CardLib=sundisk5.clb
CardLib=intellan.clb
CardLib=dlink.clb
CardLib=linksys.clb
CardLib=linksys2.clb
CardLib=socketea.clb
CardLib=ibmlan.clb
CardLib=ibmtok.clb
CardLib=ibm3270.clb
CardLib=proxim.clb
CardLib=cbdass.clb
CardLib=genmodem.clb
CardLib=genata.clb
CardLib=wd.clb
```

Configuration Notes:

To install ran setup procedure from drivers diskette. The software chose IRQ 5 and I/O A20 for the resources, and the installation procedure made all the required modifications to the Autoexec.Bat file. The program did not supply NETX.EXE, so we had to manually copy that file. Drivers do not use a NET.CFG, uses a file Smart.CFG to hold settings. Windows 95 drivers are built in so card will be automatically recognized and configured upon insertion.

PLATFORM: COMPAQ CONTURA 420CX

ROM: 08/20/95

PC CARD: MADGE TOKEN RING SMART 16/4 RINGNODE, PN: 20-00

OPERATING SYSTEM: WINDOWS 3.1/DOS 6.2

NOS: NOVELL 3.12

CARD AND SOCKET SERVICES: 3.12

CONFIG.SYS

```
SHELL=C:\DOS\COMMAND.COM /P /E:1536
STACKS=9,256
DEVICE=C:\DOS\HIMEM.SYS
DEVICEHIGH=C:\WINDOWS\CPQWIN\CPQCM.SYS
DEVICE=C:\DOS\EMM386.EXE NOEMS I=B000-B7FF X=D000-D4FF
DOS=UMB
REM *** Begin PCMCIA Drivers
REM Warning: Do not move, reorder, or delete any of these lines.
REM
;DEVICE=C:\CPQDOS\PCMSMIX.EXE
DEVICEHIGH=C:\CPQDOS\SSVLSI.EXE
DEVICEHIGH=C:\CPQDOS\CS.EXE
DEVICE=C:\CPQDOS\CSALLOC.EXE
;DEVICEHIGH=C:\CPQDOS\ATADRV.EXE
;DEVICEHIGH=C:\CPQDOS\MTAA.EXE
;DEVICEHIGH=C:\CPQDOS\MTAB.EXE
;DEVICEHIGH=C:\CPQDOS\MTI1.EXE
;DEVICEHIGH=C:\CPQDOS\MTI2P.EXE
;DEVICEHIGH=C:\CPQDOS\MTSRAM.EXE
;DEVICEHIGH=C:\CPQDOS\MTDDRV.EXE
;DEVICEHIGH=C:\CPQDOS\DBLFLASH.EXE
;DEVICEHIGH=C:\CPQDOS\MS-FLASH.SYS
DEVICEHIGH=C:\CPQDOS\CARDID.EXE
REM *** End PCMCIA Drivers
DOS=HIGH
BUFFERS=20
FILES=35
DEVICEHIGH=C:\CPQDOS\EPPBIOS.SYS
```

AUTOEXEC.BAT

```
SET PATH=C:\CPQDOS;C:\;C:\DOS;C:\WINDOWS; C:\WINDOWS\CPQWIN
SET LMOUSE=C:\MOUSE
SET PROMPT=$PSG
SET TEMP=C:\WINDOWS\TEMP
C:\CPQDOS\HIBRN8.EXE
C:\DOS\SMARTDRV.EXE 2048 512
C:\MOUSE\mouse.exe
C:\CPQDOS\MODE.COM CO80
\madge\smart.exe path=\madge\
\madge\netx
```

NETWORK DRIVERS

| | | |
|-----------|---------|----------|
| IPX.SMT | 36,528 | 03-03-95 |
| SMART.EXE | 148,608 | 03-03-95 |
| SMART.CFG | 58 | 01-08-96 |
| NETX.EXE | 78,654 | 11-17-93 |

CARDID.INI

```
[Common]
;
; Common Information section created by Config
;
ComPort1=3F8
ComIRQ1=4
ComPort2=2F8
ComIRQ2=3
ComPort3=3e8
ComIRQ3=4
ComPort4=2E8
ComIRQ4=3
ComBySocket=Yes
ComBDAAbsolute=No
FirstModem=2
SecondModem=2
ThirdModem=3
FourthModem=4
Audio=Yes
RingIndicate=No
Lan1Port=300
Lan1IRQ=5
Lan1MemoryBase1=
Lan1MemoryBase2=
Lan2Port=310
Lan2IRQ=9
Lan2MemoryBase1=
Lan2MemoryBase2=
ATATryPrimary=No
ATATrySecondary=Yes
ATATryLinear=Yes
FastTokenRing=Yes
DetectNonCompliant=No
ContinueOnConfigFailure=No
BeepInDOS=Yes
BeepInWindows=Yes
GrabInitFile=Yes
InitBufferSize=512
UseEMS=No
```

```
[Libraries]
;
; The Libraries section contains references to any card libraries the user
; wishes to include. Libraries are searched in the specified order. Path
; names are relative to the directory containing CARDID.INI.
;
CardLib=canonfd.clb
CardLib=xirdual.clb
CardLib=xircom.clb
CardLib=tdkklan2.clb
CardLib=sundisk5.clb
CardLib=intellan.clb
CardLib=dlink.clb
CardLib=linksys.clb
CardLib=linksys2.clb
CardLib=socketea.clb
CardLib=ibmlan.clb
CardLib=ibmtok.clb
CardLib=ibm3270.clb
CardLib=proxim.clb
CardLib=cbdass.clb
CardLib=genmodem.clb
CardLib=genata.clb
CardLib=wd.clb
```

Configuration Notes:

To install ran setup procedure from drivers diskette. The software chose IRQ 5 and I/O 300 for the resources, and the installation procedure made all the required modifications to the Autoexec.Bat file. The program did not supply NETX.EXE, so we had to manually copy that file. Drivers do not use a NET.CFG, uses a file Smart.CFG to hold settings. Windows 95 drivers are built in so card will be automatically recognized and configured upon insertion.

PLATFORM: COMPAQ ELITE 4/50CX

ROM: 07/19/95

PC CARD: MADGE TOKEN RING SMART 16/4 RINGNODE, PN: 20-00

OPERATING SYSTEM: WINDOWS 3.1/DOS 6.2

NOS: NOVELL 3.12

CARD AND SOCKET SERVICES: 3.12

CONFIG.SYS

```
SHELL=C:\DOS\COMMAND.COM /P /E:1536
STACKS=9,256
DEVICE=C:\DOS\HIMEM.SYS /TESTMEM:OFF
DEVICE=C:\DOS\EMM386.EXE NOEMS I=B000-B7FF X=D000-D4FF
DEVICEHIGH=C:\WINDOWS\CPQWIN\CPQCM.SYS
DOS=HIGH,UMB
REM *** Begin PCMCIA Drivers
;DEVICE=C:\CPQDOS\PCSMIX.EXE
DEVICEHIGH=C:\CPQDOS\SSVLSI.EXE
DEVICEHIGH=C:\CPQDOS\CS.EXE
DEVICE=C:\CPQDOS\CSALLOC.EXE
;DEVICEHIGH=C:\CPQDOS\ATADRV.EXE
;DEVICEHIGH=C:\CPQDOS\MTAA.EXE
;DEVICEHIGH=C:\CPQDOS\MTAB.EXE
;DEVICEHIGH=C:\CPQDOS\MTI1.EXE
;DEVICEHIGH=C:\CPQDOS\MTI2P.EXE
;DEVICEHIGH=C:\CPQDOS\MTSRAM.EXE
;DEVICEHIGH=C:\CPQDOS\MTDDRIV.EXE
;DEVICEHIGH=C:\CPQDOS\DBLFLASH.EXE
;DEVICEHIGH=C:\CPQDOS\MS-FLASH.SYS
DEVICEHIGH=C:\CPQDOS\CARDID.EXE
REM *** End PCMCIA Drivers
BUFFERS=20
FILES=35
LASTDRIVE = M
DEVICEHIGH=C:\CPQDOS\POWER.EXE
```

AUTOEXEC.BAT

```
@ECHO OFF
SET PATH=C:\CPQDOS;C:\;C:\DOS;C:\WINDOWS;;C:\WINDOWS\CPQWIN
SET LMOUSE=C:\MOUSE
LH C:\MOUSE\MOUSE
SET PROMPT=$t $PSG
SET TEMP=C:\WINDOWS\TEMP
C:\CPQDOS\HIBRN8.EXE
LH C:\DOS\SMARTDRV.EXE /f 2048 1024
\madge\smart.exe path=\madge\
\madge\netx
```

NETWORK DRIVERS

| | | |
|-----------|---------|----------|
| IPX.SMT | 36,528 | 03-03-95 |
| SMART.EXE | 148,608 | 03-03-95 |
| SMART.CFG | 58 | 01-08-96 |
| NETX.EXE | 78,654 | 11-17-93 |

CARDID.INI

```
[Common]
;
; Common Information section created by Config
;
ComPort1=3F8
ComIRQ1=4
ComPort2=2F8
ComIRQ2=3
ComPort3=3e8
ComIRQ3=4
ComPort4=2E8
ComIRQ4=3
ComBySocket=Yes
ComBDAAbsolute=No
FirstModem=2
SecondModem=2
ThirdModem=3
FourthModem=4
Audio=Yes
RingIndicate=No
Lan1Port=300
Lan1IRQ=5
Lan1MemoryBase1=
Lan1MemoryBase2=
Lan2Port=310
Lan2IRQ=9
Lan2MemoryBase1=
Lan2MemoryBase2=
ATATryPrimary=No
ATATrySecondary=Yes
ATATryLinear=Yes
FastTokenRing=Yes
DetectNonCompliant=No
ContinueOnConfigFailure=No
BeepInDOS=Yes
BeepInWindows=Yes
GrabInitFile=Yes
InitBufferSize=512
UseEMS=No
```

```
[Libraries]
;
; The Libraries section contains references to any card libraries the user
; wishes to include. Libraries are searched in the specified order. Path
; names are relative to the directory containing CARDID.INI.
;
CardLib=canonfd.clb
CardLib=xirdual.clb
CardLib=xircom.clb
CardLib=tdkklan2.clb
CardLib=sundisk5.clb
CardLib=intellan.clb
CardLib=dlink.clb
CardLib=linksys.clb
CardLib=linksys2.clb
CardLib=socketea.clb
CardLib=ibmlan.clb
CardLib=ibmtok.clb
CardLib=ibm3270.clb
CardLib=proxim.clb
CardLib=cbdass.clb
CardLib=genmodem.clb
CardLib=genata.clb
CardLib=wd.clb
```

Configuration Notes:

To install ran setup procedure from drivers diskette. The software chose IRQ 5 and I/O 300 for the resources, and the installation procedure made all the required modifications to the Autoexec.Bat file. When in the base the software changed the IRQ to 15 automatically while the I/O stayed the same. The program did not supply NETX.EXE, so we had to manually copy that file. Drivers do not use a NET.CFG, uses a file Smart.CFG to hold settings. Windows 95 drivers are built in so card will be automatically recognized and configured upon insertion.

PLATFORM: COMPAQ LTE 5000

ROM: 09/19/95

PC CARD: MADGE TOKEN RING SMART 16/4 RINGNODE, PN: 20-00

OPERATING SYSTEM: WINDOWS 3.1/DOS 6.2

NOS: NOVELL 3.12

CARD AND SOCKET SERVICES: 3.14

CONFIG.SYS

```
DEVICE=C:\CPQDOS\MACHCHK.SYS 02A8 02B0 02BA 02CA
DEVICE=C:\DOS\HIMEM.SYS
DEVICE=C:\DOS\EMM386.exe NOEMS I=B000-B7FF X=C800-CBFF X=D100-D5FF X=E800-EFFF
COUNTRY=001,437,C:\DOS\COUNTRY.SYS
SHELL=C:\DOS\COMMAND.COM /P /E:1536
DOS=HIGH,UMB
FILES=35
BUFFERS=20,0
STACKS=9,256
DEVICEHIGH=C:\AUDIO_CD\TEAC_CDI.SYS /D:TEAC-CDI
LASTDRIVE=M
REM PC Card: Begin PC Card (PCMCIA) Drivers
REM **Warning: Do not move, reorder, or delete any of these lines. **
DEVICEHIGH=C:\CARDWIZ\SSCIRUS2.EXE
DEVICEHIGH=C:\CARDWIZ\CS.EXE /POLL:1
DEVICEHIGH=C:\CARDWIZ\CSALLOC.EXE
DEVICEHIGH=C:\CARDWIZ\CARDID.EXE
REM PC Card: End PC Card(PCMCIA) Drives
```

AUTOEXEC.BAT

```
@ECHO OFF
C:\WINDOWS\VGAUTIL\winmode.exe t640=60 t800=60 t1024=87 t1280=87
SET NWLANGUAGE=ENGLISH
PATH C:\WINDOWS;C:\CPQDOS;C:\DOS;C:\AUDIO_CD;C:\CARDWIZ
PROMPT $p$g
SET DIRCMD=/ogn
SET TEMP=C:\WINDOWS\TEMP
SET BLASTER=A220 D1 I5
SET LMOUSE=C:\MOUSE
SET MOUSE=C:\MOUSE
C:\MOUSE\MOUSE.EXE MEMU
C:\DOS\MSCDEX.EXE /D:TEAC-CDI /M:15
IF ERRORLEVEL 1 GOTO NO_CDROM
C:\AUDIO_CD\ESSVOL /V:15 /C:15
:NO_CDROM
LH C:\DOS\SMARTDRV.EXE
C:\CPQDOS\0VMAKFIL
IF NOT EXIST C:\CPQDOS\SAVEDONE.CPQ CALL SAVEALL /A
\madge\smart.exe path=\madge\
\madge\netx
```

NETWORK DRIVERS

| | | |
|-----------|---------|----------|
| IPX.SMT | 36,528 | 03-03-95 |
| SMART.EXE | 148,608 | 03-03-95 |
| SMART.CFG | 58 | 01-08-96 |
| NETX.EXE | 78,654 | 11-17-93 |

CARDID.INI

```
[Common]
;
; Common Information section created by Config
;
ComPort1=3F8
ComIRQ1=4
ComPort2=2F8
ComIRQ2=3
ComPort3=3E8
ComIRQ3=4
ComPort4=2E8
ComIRQ4=11
ComBySocket=No
ComBDAAbsolute=Yes
ComRollOverOn=No
FirstModem=2
SecondModem=4
ThirdModem=2
FourthModem=4
Audio=Yes
RingIndicate=No
Suspend_Power=No
Lan1Port=330
Lan1IRQ=11
Lan1MemoryBase1=0
Lan1MemoryBase2=D1
Lan2Port=310
Lan2IRQ=10
Lan2MemoryBase1=0
Lan2MemoryBase2=0
ATATryPrimary=No
ATATrySecondary=Yes
ATATryLinear=Yes
FastTokenRing=Yes
DetectNonCompliant=No
ContinueOnConfigFailure=No
BeepInDOS=Yes
BeepInWindows=Yes
GrabInitFile=Yes
InitBufferSize=512
FirstLan=1
SecondLan=2
```

```
[Libraries]
;
; The Libraries section contains references to any card libraries the user
; wishes to include. Libraries are searched in the specified order. Path
; names are relative to the directory containing CARDID.INI.
;
CardLib=xirdual.clb
CardLib=xircom.clb
CardLib=tdkklan2.clb
CardLib=sundisk5.clb
CardLib=intellan.clb
CardLib=dlink.clb
CardLib=linksys.clb
CardLib=linksys2.clb
CardLib=socketea.clb
CardLib=ibmlan.clb
CardLib=ibmtok.clb
CardLib=ibm3270.clb
CardLib=proxim.clb
CardLib=cbdass.clb
CardLib=genmodem.clb
CardLib=genata.clb
CardLib=wd.clb
```

Configuration Notes:

To install ran setup procedure from drivers diskette. The software chose IRQ 10 and I/O A20 for the resources, and the installation procedure made all the required modifications to the Autoexec.Bat file. When in the base the software changed the IRQ to 11 automatically while the I/O stayed the same. The program did not supply NETX.EXE, so we had to manually copy that file. Drivers do not use a NET.CFG, uses a file Smart.CFG to hold settings. Windows 95 drivers are built in so card will be automatically recognized and configured upon insertion.

PLATFORM: *COMPAQ AERO 4/33C*

ROM: 07/19/95

PC CARD: XIRCOM ETHERNET ADAPTER IIPS, PN: PS-CE2-10BC

OPERATING SYSTEM: WINDOWS 3.1/DOS 6.2

NOS: NOVELL 3.12

CARD AND SOCKET SERVICES: 1.25

CONFIG.SYS

REM Xircom CreditCard Adapter --- Do Not Change Lines Below (MENU)

[menu]

menuitem=Xircom_enet, Load Xircom For Network Access

menuitem=Nonet, Do Not Load Any Xircom Drivers

menucolor=15,0

[Xircom_enet]

[Nonet]

[common]

REM Xircom CreditCard Adapter --- Do Not Change Lines Above

SHELL=C:\DOS\COMMAND.COM /P /E:1536

STACKS=9,256

DEVICE=C:\DOS\HIMEM.SYS

DEVICE=C:\DOS\EMM386.EXE NOEMS X=D000-DFFF

DOS=UMB

REM *** Begin PCMCIA Drivers

REM Warning: Do not move, reorder, or delete any of these lines.

REM

DEVICE=C:\CPQDOS\PCSMIX.EXE

DEVICEHIGH=C:\CPQDOS\SSVLSI.EXE

DEVICEHIGH=C:\CPQDOS\CS.EXE

DEVICE=C:\CPQDOS\CSALLOC.EXE

DEVICEHIGH=C:\CPQDOS\ATADRV.EXE /D:1

DEVICEHIGH=C:\CPQDOS\CARDID.EXE C:\CPQDOS\CARDID.INI

DEVICEHIGH=C:\CPQDOS\MEMDRV.EXE

;DEVICEHIGH=C:\CPQDOS\DBLFLASH.EXE

;DEVICEHIGH=C:\CPQDOS\MS-FLASH.SYS

REM *** End PCMCIA Drivers

DOS=HIGH

BUFFERS=20

FILES=35

DEVICEHIGH=C:\CPQDOS\POWER.EXE

AUTOEXEC.BAT

@loadhigh C:\DOS\SHARE.EXE /I:500 /F:5100

SET PATH=C:\CPQDOS;C:\;C:\DOS;C:\WINDOWS; C:\WINDOWS\CPQWIN

SET LMOUSE=C:\MOUSE

SET PROMPT=\$PSG

SET TEMP=C:\WINDOWS\TEMP

C:\CPQDOS\HIBRN8.EXE

C:\DOS\SMARTDRV.EXE

LH C:\MOUSE\MOUSE SWAP

C:\CPQDOS\MODE.COM CO80

C:\WINDOWS\WIN

REM Xircom CreditCard Adapter --- Do Not Change Lines Below

@echo off

cls

goto %config%

:Xircom_enet

C:

cd C:\XIRCOM\PSCE2\ODI

CE2CFG DRIVER=ODI

LSL

CE2ODI

IPXODI

NETX

AUTOEXEC.BAT-continued

```
F:
login
C:
cd \
goto common
:Nonet
:common
REM Xircom CreditCard Adapter --- Do Not Change Lines Above
```

NETWORK DRIVERS

| | | |
|------------|--------|----------|
| LSL.COM | 17,805 | 09-10-93 |
| CE2ODI.COM | 31,716 | 10-05-94 |
| IPXODI.COM | 30,247 | 10-07-93 |
| CE2CFG.EXE | 56,912 | 11-08-94 |
| NETX.EXE | 78,654 | 11-17-93 |

NET.CFG

```
link driver ce2odi
frame ethernet_802.2
int 5
port 300
mem D1000
```

CARDID.INI

```
[Common]
;
; Common Information section created by Config
;
ComPort1=3F8
ComIRQ1=4
ComPort2=2F8
ComIRQ2=3
ComPort3=3E8
ComIRQ3=4
ComPort4=2E8
ComIRQ4=3
ComBySocket=Yes
ComBDAAbsolute=No
FirstModem=2
SecondModem=2
ThirdModem=3
FourthModem=4
Audio=Yes
RingIndicate=No
Lan1Port=300
Lan1IRQ=5
Lan1MemoryBase1=D8
Lan1MemoryBase2=DC
Lan2Port=310
Lan2IRQ=10
Lan2MemoryBase1=D8
Lan2MemoryBase2=DC
ATATryPrimary=No
ATATrySecondary=Yes
ATATryLinear=Yes
FastTokenRing=Yes
DetectNonCompliant=No
ContinueOnConfigFailure=No
BeepInDOS=Yes
BeepInWindows=Yes
GrabInitFile=Yes
InitBufferSize=512
```

CARDID.INI-continued

[Libraries]

;
; The Libraries section contains references to any card libraries the user
; wishes to include. Libraries are searched in the specified order. Path
; names are relative to the directory containing CARDID.INI.
;
CardLib=cardid.clb

Configuration Notes:

The card was configured from Windows using ODI drivers. A custom install was chosen, and defaults were used except the frame type was changed from 802.3 to 802.2. The resources for this card were IRQ 5, I/O 300, and MEM D1000. Windows 95 drivers will automatically configure the card upon insertion.

PLATFORM: *COMPAQ CONCERTO*

ROM: *10/12/93*

PC CARD: *XIRCOM ETHERNET ADAPTER IIPS, PN: PS-CE2-10BC*

OPERATING SYSTEM: *WINDOWS 3.1/DOS 6.2*

NOS: *NOVELL 3.12*

CARD AND SOCKET SERVICES: *1.25*

CONFIG.SYS

REM Xircom CreditCard Adapter --- Do Not Change Lines Below (MENU)

[menu]

menuitem=Xircom_enet, Load Xircom CreditCard For Network Access

menuitem=Nonet, Do Not Load Any Xircom Drivers

menucolor=15,0

[Xircom_enet]

[Nonet]

[common]

REM Xircom CreditCard Adapter --- Do Not Change Lines Above

SHELL=C:\DOS\COMMAND.COM /P /E:1536

STACKS=9,256

DEVICE=C:\DOS\HIMEM.SYS

DEVICE=C:\DOS\EMM386.EXE NOEMS X=D000-DFFF

DOS=UMB

REM * Begin PCMCIA Drivers**

REM Warning: Do not move, reorder, or delete any of these lines.

REM

DEVICEHIGH=C:\CPQDOS\SSCIRRUS.EXE

DEVICEHIGH=C:\CPQDOS\CS.EXE

DEVICE=C:\CPQDOS\CSALLOC.EXE

DEVICEHIGH=C:\CPQDOS\ATADRV.EXE

DEVICEHIGH=C:\CPQDOS\CARDID.EXE C:\CPQDOS\CARDID.INI

DEVICEHIGH=C:\CPQDOS\MEMDRV.EXE

;DEVICEHIGH=C:\CPQDOS\DBLFLASH.EXE

;DEVICEHIGH=C:\CPQDOS\MS-FLASH.SYS

REM * End PCMCIA Drivers**

DOS=HIGH

BUFFERS=20

FILES=35

DEVICEHIGH=C:\CPQDOS\POWER.EXE

LASTDRIVE=Z

AUTOEXEC.BAT

SET PATH=C:\CPQDOS;C:\;C:\DOS;C:\WINDOWS;C:\WINDOWS\CPQWIN

SET LMOUSE=C:\MOUSE

SET PROMPT=\$P\$G

SET TEMP=C:\WINDOWS\TEMP

C:\CPQDOS\HIBRN8.EXE

C:\DOS\SMARTDRV.EXE

LH C:\MOUSE\MOUSE

C:\CPQDOS\MODE.COM CO80

REM Xircom CreditCard Adapter --- Do Not Change Lines Below

@echo off

cls

goto %config%

:Xircom_enet

C:

cd C:\XIRCOM\PSCE2\ODI

CE2CFG DRIVER=ODI

LSL

CE2ODI

IPXODI

NETX

H:

login

AUTOEXEC.BAT-continued

```
C:
cd \
goto common
:Nonet
:common
REM Xircom CreditCard Adapter --- Do Not Change Lines Above
c:\windows\win
```

NETWORK DRIVERS

```
LSL COM 17,805 09-10-93
CE2ODI COM 31,716 10-05-94
IPXODI COM 30,247 10-07-93
CE2CFG EXE 56,912 11-08-94
NETX EXE 78,654 11-17-93
```

NET.CFG

```
link driver ce2odi
frame ethernet_802.2
int 5
port 330
mem D1000
```

CARDID.INI

```
[Common]
:
; Common Information section created by Config
:
ComPort1=3F8
ComIRQ1=4
ComPort2=2F8
ComIRQ2=3
ComPort3=3E8
ComIRQ3=4
ComPort4=2E8
ComIRQ4=3
ComBySocket=Yes
ComBDAAbsolute=No
FirstModem=2
SecondModem=2
ThirdModem=3
FourthModem=4
Audio=Yes
RingIndicate=No
Lan1Port=300
Lan1IRQ=5
Lan1MemoryBase1=D8
Lan1MemoryBase2=DC
Lan2Port=310
Lan2IRQ=10
Lan2MemoryBase1=D8
Lan2MemoryBase2=DC
ATATryPrimary=No
ATATrySecondary=Yes
ATATryLinear=Yes
FastTokenRing=Yes
DetectNonCompliant=No
ContinueOnConfigFailure=No
BeepInDOS=Yes
BeepInWindows=Yes
GrabInitFile=Yes
InitBufferSize=512
```

CARDID.INI-continued

[Libraries]

;
; The Libraries section contains references to any card libraries the user
; wishes to include. Libraries are searched in the specified order. Path
; names are relative to the directory containing CARDID.INI.

;
CardLib=cardid.clb

Configuration Notes:

The card was configured from Windows using ODI drivers. A custom install was chosen, and defaults were used except for I/O and frame type. The resources for this card were IRQ 5, I/O 330, and MEM D1000. Windows 95 drivers will automatically configure the card upon insertion.

PLATFORM: *COMPAQ CONTURA 400CX*

ROM: *07/18/95*

PC CARD: *XIRCOM ETHERNET ADAPTER IIPS, PN: PS-CE2-10BC*

OPERATING SYSTEM: *WINDOWS 3.1/DOS 6.2*

NOS: *NOVELL 3.12*

CARD AND SOCKET SERVICES: *3.12*

CONFIG.SYS

REM Xircom CreditCard Adapter --- Do Not Change Lines Below (MENU)

[menu]

menuitem=Xircom_enet, Load Xircom CreditCard For Network Access

menuitem=Nonet, Do Not Load Any Xircom Drivers

menucolor=15,0

[Xircom_enet]

[Nonet]

[common]

REM Xircom CreditCard Adapter --- Do Not Change Lines Above

switches=/F

SHELL=C:\DOS\COMMAND.COM /P /E:1536

STACKS=9,256

DEVICE=C:\DOS\HIMEM.SYS

DEVICE=C:\DOS\EMM386.EXE NOEMS I=B000-B7FF X=D000-D4FF

DEVICEHIGH=C:\WINDOWS\CPQWIN\CPQCM.SYS

DOS=HIGH,UMB

REM *** Begin PCMCIA Drivers

REM Warning: Do not move, reorder, or delete any of these lines.

REM

;DEVICE=C:\CPQDOS\PCMSMIX.EXE

DEVICEHIGH=C:\CPQDOS\SSVLSI.EXE

DEVICEHIGH=C:\CPQDOS\CS.EXE

DEVICE=C:\CPQDOS\CSALLOC.EXE

;DEVICEHIGH=C:\CPQDOS\ATADRV.EXE

;DEVICEHIGH=C:\CPQDOS\MTAA.EXE

;DEVICEHIGH=C:\CPQDOS\MTAB.EXE

;DEVICEHIGH=C:\CPQDOS\MTI1.EXE

;DEVICEHIGH=C:\CPQDOS\MTI2P.EXE

;DEVICEHIGH=C:\CPQDOS\MTSRAM.EXE

;DEVICEHIGH=C:\CPQDOS\MTDDRV.EXE

;DEVICEHIGH=C:\CPQDOS\DBLFLASH.EXE

;DEVICEHIGH=C:\CPQDOS\MS-FLASH.SYS

DEVICEHIGH=C:\CPQDOS\CARDID.EXE

REM *** End PCMCIA Drivers

BUFFERS=20

FILES=35

DEVICEHIGH=C:\CPQDOS\EPPBIOS.SYS

DEVICEHIGH=C:\CPQDOS\POWER.EXE

AUTOEXEC.BAT

@ECHO OFF

SET PATH=C:\CPQDOS;C:\;C:\DOS;C:\WINDOWS;;C:\WINDOWS\CPQWIN

SET LMOUSE=C:\MOUSE

LH C:\MOUSE\MOUSE

SET PROMPT=\$PSG

SET TEMP=C:\WINDOWS\TEMP

C:\CPQDOS\HIBRN8.EXE

LH C:\DOS\SMARTDRV.EXE

LH SHARE.EXE

rem C:\WINDOWS\WIN

REM Xircom CreditCard Adapter --- Do Not Change Lines Below

@echo off

cls

goto %config%

:Xircom_enet

AUTOEXEC.BAT-continued

```
C:
cd C:\XIRCOM\PSCE2\ODI
CE2CFG DRIVER=ODI
LSL
CE2ODI
IPXODI
NETX
F:
login
C:
cd \
goto common
:Nonet
:common
REM Xircom CreditCard Adapter --- Do Not Change Lines Above
```

NETWORK DRIVERS

| | | |
|------------|--------|----------|
| LSL.COM | 17,805 | 09-10-93 |
| CE2ODI.COM | 31,716 | 10-05-94 |
| IPXODI.COM | 30,247 | 10-07-93 |
| CE2CFG.EXE | 56,912 | 11-08-94 |
| NETX.EXE | 78,654 | 11-17-93 |

NET.CFG

```
link driver ce2odi
mode io
frame ethernet_802.2
int 5
port 300
mem D0000
```

CARDID.INI

```
[Common]
;
; Common Information section created by Config
;
ComPort1=3F8
ComIRQ1=4
ComPort2=2F8
ComIRQ2=3
ComPort3=3e8
ComIRQ3=4
ComPort4=2E8
ComIRQ4=3
ComBySocket=Yes
ComBDAAbsolute=No
FirstModem=2
SecondModem=2
ThirdModem=3
FourthModem=4
Audio=Yes
RingIndicate=No
Lan1Port=300
Lan1IRQ=5
Lan1MemoryBase1=
Lan1MemoryBase2=
Lan2Port=310
Lan2IRQ=9
Lan2MemoryBase1=
Lan2MemoryBase2=
ATATryPrimary=No
ATATrySecondary=Yes
ATATryLinear=Yes
FastTokenRing=Yes
DetectNonCompliant=No
ContinueOnConfigFailure=No
BeepInDOS=Yes
BeepInWindows=Yes
GrabInitFile=Yes
```

CARDID.INI-continued

InitBufferSize=512
UseEMS=No

[Libraries]

;
; The Libraries section contains references to any card libraries the user
; wishes to include. Libraries are searched in the specified order. Path
; names are relative to the directory containing CARDID.INI.

;
CardLib=canonfd.clb
CardLib=xirdual.clb
CardLib=xircom.clb
CardLib=tdkfan2.clb
CardLib=sundisk5.clb
CardLib=intellan.clb
CardLib=dlink.clb
CardLib=linksys.clb
CardLib=linksys2.clb
CardLib=socketea.clb
CardLib=ibmlan.clb
CardLib=ibmtok.clb
CardLib=ibm3270.clb
CardLib=proxim.clb
CardLib=caldas.clb
CardLib=genmodem.clb
CardLib=genata.clb
CardLib=wd.clb

Configuration Notes:

The card was configured from Windows using ODI drivers. A custom install was chosen, and defaults were used except the frame type was changed from 802.3 to 802.2. The resources for this card were IRQ 5, I/O 300, and MEM D0000. Windows 95 drivers will automatically configure the card upon insertion.

PLATFORM: COMPAQ CONTURA 420CX

ROM: 08/20/95

PC CARD: XIRCOM ETHERNET ADAPTER IIPS, PN: PS-CE2-10BC

OPERATING SYSTEM: WINDOWS 3.1/DOS 6.2

NOS: NOVELL 3.12

CARD AND SOCKET SERVICES: 3.12

CONFIG.SYS

REM Xircom CreditCard Adapter --- Do Not Change Lines Below (MENU)

[menu]

menuitem=Xircom_enet, Load Xircom For Network Access

menuitem=Nonet, Do Not Load Any Xircom Drivers

menucolor=15,0

[Xircom_enet]

[Nonet]

[common]

REM Xircom CreditCard Adapter --- Do Not Change Lines Above

SHELL=C:\DOS\COMMAND.COM /P /E:1536

STACKS=9,256

DEVICE=C:\DOS\HIMEM.SYS

DEVICEHIGH=C:\WINDOWS\CPQWIN\CPQCM.SYS

DEVICE=C:\DOS\EMM386.EXE NOEMS I=B000-B7FF X=D000-D4FF

DOS=UMB

REM *** Begin PCMCIA Drivers

REM Warning: Do not move, reorder, or delete any of these lines.

REM

;DEVICE=C:\CPQDOS\PCSMIX.EXE

DEVICEHIGH=C:\CPQDOS\SSVLSI.EXE

DEVICEHIGH=C:\CPQDOS\CS.EXE

DEVICE=C:\CPQDOS\CSALLOC.EXE

;DEVICEHIGH=C:\CPQDOS\ATADRV.EXE

;DEVICEHIGH=C:\CPQDOS\MTAA.EXE

;DEVICEHIGH=C:\CPQDOS\MTAB.EXE

;DEVICEHIGH=C:\CPQDOS\MTI1.EXE

;DEVICEHIGH=C:\CPQDOS\MTI2P.EXE

;DEVICEHIGH=C:\CPQDOS\MTSRAM.EXE

;DEVICEHIGH=C:\CPQDOS\MTDDRV.EXE

;DEVICEHIGH=C:\CPQDOS\DBLFLASH.EXE

;DEVICEHIGH=C:\CPQDOS\MS-FLASH.SYS

DEVICEHIGH=C:\CPQDOS\CARDID.EXE

REM *** End PCMCIA Drivers

DOS=HIGH

BUFFERS=20

FILES=35

DEVICEHIGH=C:\CPQDOS\EPPBIOS.SYS

AUTOEXEC.BAT

SET PATH=C:\CPQDOS;C:\;C:\DOS;C:\WINDOWS; C:\WINDOWS\CPQWIN

SET LMOUSE=C:\MOUSE

SET PROMPT=\$PSG

SET TEMP=C:\WINDOWS\TEMP

C:\CPQDOS\HIBRN8.EXE

C:\DOS\SMARTDRV.EXE 2048 512

C:\MOUSE\mouse.exe

C:\CPQDOS\MODE.COM CO80

REM Xircom CreditCard Adapter --- Do Not Change Lines Below

@echo off

cls

goto %config%

:Xircom_enet

C:

cd C:\XIRCOM\PSCE2\ODI

CE2CFG DRIVER=ODI

AUTOEXEC.BAT-continued

```
LSL
CE2ODI
IPXODI
NETX
F:
login
C:
cd \
goto common
:Nonet
:common
REM Xircom CreditCard Adapter --- Do Not Change Lines Above
```

NETWORK DRIVERS

| | | |
|------------|--------|----------|
| LSL.COM | 17,805 | 09-10-93 |
| CE2ODI.COM | 31,716 | 10-05-94 |
| IPXODI.COM | 30,247 | 10-07-93 |
| CE2CFG.EXE | 56,912 | 11-08-94 |
| NETX.EXE | 78,654 | 11-17-93 |

NET.CFG

```
link driver ce2odi
mode io
frame ethernet_802.2
int 5
port 300
mem D0000
```

CARDID.INI

```
[Common]
;
; Common Information section created by Config
;
ComPort1=3F8
ComIRQ1=4
ComPort2=2F8
ComIRQ2=3
ComPort3=3e8
ComIRQ3=4
ComPort4=2E8
ComIRQ4=3
ComBySocket=Yes
ComBDAAbsolute=No
FirstModem=2
SecondModem=2
ThirdModem=3
FourthModem=4
Audio=Yes
RingIndicate=No
Lan1Port=300
Lan1IRQ=5
Lan1MemoryBase1=
Lan1MemoryBase2=
Lan2Port=310
Lan2IRQ=9
Lan2MemoryBase1=
Lan2MemoryBase2=
ATATryPrimary=No
ATATrySecondary=Yes
ATATryLinear=Yes
FastTokenRing=Yes
DetectNonCompliant=No
ContinueOnConfigFailure=No
BeepInDOS=Yes
BeepInWindows=Yes
GrabInitFile=Yes
InitBufferSize=512
UseEMS=No
```

CARDID.INI-continued

[Libraries]

;
; The Libraries section contains references to any card libraries the user
; wishes to include. Libraries are searched in the specified order. Path
; names are relative to the directory containing CARDID.INI.

;
CardLib=canonfd.clb
CardLib=xirdual.clb
CardLib=xircom.clb
CardLib=tdkklan2.clb
CardLib=sundisk5.clb
CardLib=intellan.clb
CardLib=dlink.clb
CardLib=linksys.clb
CardLib=linksys2.clb
CardLib=socketea.clb
CardLib=ibmlan.clb
CardLib=ibmtok.clb
CardLib=ibm3270.clb
CardLib=proxim.clb
CardLib=cbdass.clb
CardLib=genmodem.clb
CardLib=genata.clb
CardLib=wd.clb

Configuration Notes:

The card was configured from Windows using ODI drivers. A custom install was chosen, and defaults were used except the frame type was changed from 802.3 to 802.2. The resources for this card were IRQ 5, I/O 300, and MEM D0000. Windows 95 drivers will automatically configure the card upon insertion.

PLATFORM: COMPAQ ELITE 4/75CXL

ROM: 07/19/95

PC CARD: XIRCOM ETHERNET ADAPTER IIPS, PN: PS-CE2-10BC

OPERATING SYSTEM: WINDOWS 3.1/DOS 6.2

NOS: NOVELL 3.12

CARD AND SOCKET SERVICES: 3.12

CONFIG.SYS

REM Xircom CreditCard Adapter --- Do Not Change Lines Below (MENU)

[menu]

menuitem=Xircom_enet, Load Xircom CreditCard For Network Access

menuitem=Nonet, Do Not Load Any Xircom Drivers

menucolor=15,0

[Xircom_enet]

[Nonet]

[common]

REM Xircom CreditCard Adapter --- Do Not Change Lines Above

switches=/F

SHELL=C:\DOS\COMMAND.COM /P /E:1536

STACKS=9,256

DEVICE=C:\DOS\HIMEM.SYS

DEVICE=C:\DOS\EMM386.EXE NOEMS I=B000-B7FF X=D000-D4FF

DEVICEHIGH=C:\WINDOWS\CPQWIN\CPQCM.SYS

DOS=HIGH,UMB

REM *** Begin PCMCIA Drivers

REM Warning: Do not move, reorder, or delete any of these lines.

REM

;DEVICE=C:\CPQDOS\PCMSMIX.EXE

DEVICEHIGH=C:\CPQDOS\SSVLSI.EXE

DEVICEHIGH=C:\CPQDOS\CS.EXE

DEVICE=C:\CPQDOS\CSALLOC.EXE

;DEVICEHIGH=C:\CPQDOS\ATADRV.EXE

;DEVICEHIGH=C:\CPQDOS\MTAA.EXE

;DEVICEHIGH=C:\CPQDOS\MTAB.EXE

;DEVICEHIGH=C:\CPQDOS\MTI1.EXE

;DEVICEHIGH=C:\CPQDOS\MTI2P.EXE

;DEVICEHIGH=C:\CPQDOS\MTSRAM.EXE

;DEVICEHIGH=C:\CPQDOS\MTDDRV.EXE

;DEVICEHIGH=C:\CPQDOS\DBLFLASH.EXE

;DEVICEHIGH=C:\CPQDOS\MS-FLASH.SYS

DEVICEHIGH=C:\CPQDOS\CARDID.EXE

REM *** End PCMCIA Drivers

BUFFERS=20

FILES=35

REM Xircom CreditCard --- Do Not Change Lines Below (LASTDRIVE)

REM LASTDRIVE = Z

REM Xircom CreditCard Adapter --- Do Not Change Lines Above

DEVICEHIGH=C:\CPQDOS\POWER.EXE

AUTOEXEC.BAT

@ECHO OFF

SET PATH=C:\CPQDOS;C:\;C:\DOS;C:\WINDOWS;;C:\WINDOWS\CPQWIN

SET LMOUSE=C:\MOUSE

LH C:\MOUSE\MOUSE

SET PROMPT=\$PSG

SET TEMP=C:\WINDOWS\TEMP

C:\CPQDOS\HIBRN8.EXE

LH C:\DOS\SMARTDRV.EXE

SET NWLANGUAGE=ENGLISH

REM Xircom CreditCard Adapter --- Do Not Change Lines Below

@echo off

cls

goto %config%

AUTOEXEC.BAT-continued

```
:Xircom_enet
C:
cd C:\XIRCOM\PSCE2\ODI
CE2CFG DRIVER=ODI
LSL
CE2ODI
IPXODI
NETX
F:
login
C:
cd \
goto common
:Nonet
:common
REM Xircom CreditCard Adapter --- Do Not Change Lines Above
```

NETWORK DRIVERS

| | | |
|------------|--------|----------|
| LSL.COM | 17,805 | 09-10-93 |
| CE2ODI.COM | 31,716 | 10-05-94 |
| IPXODI.COM | 30,247 | 10-07-93 |
| CE2CFG.EXE | 56,912 | 01-08-94 |
| NETX.EXE | 8,654 | 11-17-93 |

NET.CFG

```
link driver ce2odi
mode io
frame ethernet_802.2
int 5
port 300
mem D0000
```

CARDID.INI

```
[Common]
;
; Common Information section created by Config
;
ComPort1=3F8
ComIRQ1=4
ComPort2=2F8
ComIRQ2=3
ComPort3=3e8
ComIRQ3=4
ComPort4=2E8
ComIRQ4=3
ComBySocket=Yes
ComBDAbsolute=No
FirstModem=2
SecondModem=2
ThirdModem=3
FourthModem=4
Audio=Yes
RingIndicate=No
Lan1Port=300
Lan1IRQ=5
Lan1MemoryBase1=
Lan1MemoryBase2=
Lan2Port=310
Lan2IRQ=9
Lan2MemoryBase1=
Lan2MemoryBase2=
ATATryPrimary=No
ATATrySecondary=Yes
ATATryLinear=Yes
FastTokenRing=Yes
DetectNonCompliant=No
ContinueOnConfigFailure=No
BeepInDOS=Yes
BeepInWindows=Yes
```

CARDID.INI-continued

GrabInitFile=Yes
InitBufferSize=512
UseEMS=No

[Libraries]

;
; The Libraries section contains references to any card libraries the user
; wishes to include. Libraries are searched in the specified order. Path
; names are relative to the directory containing CARDID.INI.

;
CardLib=canonfd.clb
CardLib=xirdual.clb
CardLib=xircom.clb
CardLib=tdkklan2.clb
CardLib=sundisk5.clb
CardLib=intellan.clb
CardLib=dlink.clb
CardLib=linksys.clb
CardLib=linksys2.clb
CardLib=socketea.clb
CardLib=ibmlan.clb
CardLib=ibmtok.clb
CardLib=ibm3270.clb
CardLib=proxim.clb
CardLib=cbdass.clb
CardLib=genmodem.clb
CardLib=genata.clb
CardLib=wd.clb

Configuration Notes:

The card was configured from Windows using ODI drivers. A custom install was chosen, and defaults were used except the frame type was changed from 802.3 to 802.2. The resources for this card were IRQ 5, I/O 300, and MEM D0000, and we did change the internal network controller in the base to IRQ 10, I/O 220. This allowed the card to be used inside the base with no resource conflicts. Windows 95 drivers will automatically configure the card upon insertion.

PLATFORM: COMPAQ LTE 5000

ROM: 09/19/95

PC CARD: XIRCOM ETHERNET ADAPTER IIPS, PN: PS-CE2-10BC

OPERATING SYSTEM: WINDOWS 3.1/DOS 6.2

NOS: NOVELL 3.12

CARD AND SOCKET SERVICES: 3.14

CONFIG.SYS

REM Xircom CreditCard Adapter --- Do Not Change Lines Below (MENU)

[menu]

menuitem=Xircom_enet, Load Xircom CreditCard For Network Access

menuitem=Nonet, Do Not Load Any Xircom Drivers

menucolor=15,0

[Xircom_enet]

[Nonet]

[common]

REM Xircom CreditCard Adapter --- Do Not Change Lines Above

DEVICE=C:\CPQDOS\MACHCHK.SYS 02A8 02B0 02BA 02CA

DEVICE=C:\DOS\HIMEM.SYS

DEVICE=C:\DOS\EMM386.exe NOEMS I=B000-B7FF X=C800-CBFF X=D100-D5FF X=E800-EFFF

COUNTRY=001,437,C:\DOS\COUNTRY.SYS

SHELL=C:\DOS\COMMAND.COM /P /E:1536

DOS=HIGH, UMB

FILES=35

BUFFERS=20,0

STACKS=9,256

DEVICEHIGH=C:\AUDIO_CD\TEAC_CDI.SYS /D:TEAC-CDI

LASTDRIVE=M

REM PC Card: Begin PC Card (PCMCIA) Drivers

REM **Warning: Do not move, reorder, or delete any of these lines. **

DEVICEHIGH=C:\CARDWIZ\SSCIRUS2.EXE

DEVICEHIGH=C:\CARDWIZ\CS.EXE /POLL:1

DEVICEHIGH=C:\CARDWIZ\CSALLOC.EXE

DEVICEHIGH=C:\CARDWIZ\CARDID.EXE

REM PC Card: End PC Card(PCMCIA) Drives

AUTOEXEC.BAT

@ECHO OFF

C:\WINDOWS\VGAUTIL\winmode.exe t640=60 t800=60 t1024=87 t1280=87

SET NWLANGUAGE=ENGLISH

PATH C:\WINDOWS;C:\CPQDOS;C:\DOS;C:\AUDIO_CD;C:\CARDWIZ

PROMPT \$p\$g

SET DIRCMD=/ogn

SET TEMP=C:\WINDOWS\TEMP

SET BLASTER=A220 D1 I5

SET LMOUSE=C:\MOUSE

SET MOUSE=C:\MOUSE

C:\MOUSE\MOUSE.EXE MEMU

C:\DOS\MSCDEX.EXE /D:TEAC-CDI /M:15

IF ERRORLEVEL 1 GOTO NO_CDROM

C:\AUDIO_CD\ESSVOL /V:15 /C:15

:NO_CDROM

IF NOT EXIST C:\CPQDOS\SAVEDONE.CPQ CALL SAVEALL /A

LH C:\DOS\SMARTDRV.EXE

REM Xircom CreditCard Adapter --- Do Not Change Lines Below

@echo off

cls

goto %config%

:Xircom_enet

C:

cd C:\XIRCOM\PSCE2\ODI

CE2CFG DRIVER=ODI

LSL

CE2ODI

AUTOEXEC.BAT-continued

IPXODI

NETX

N:

login

C:

**cd **

goto common

:Nonet

:common

REM Xircom CreditCard Adapter --- Do Not Change Lines Above

NETWORK DRIVERS

| | | |
|------------|--------|----------|
| CE2ODI.COM | 31,716 | 10-05-94 |
| IPXODI.COM | 30,247 | 10-07-93 |
| LSL.COM | 17,805 | 09-10-93 |
| CE2CFG.EXE | 56,912 | 11-08-94 |
| NETX.EXE | 78,654 | 11-17-93 |

NET.CFG

link driver ce2odi
mode IO
frame ethernet_802.2
int 11
port 330
mem D1000

CARDID.INI

[Common]
;
; Common Information section created by Config
;
ComPort1=3F8
ComIRQ1=4
ComPort2=2F8
ComIRQ2=3
ComPort3=3E8
ComIRQ3=4
ComPort4=2E8
ComIRQ4=11
ComBySocket=No
ComBDAAbsolute=Yes
ComRollOverOn=No
FirstModem=2
SecondModem=4
ThirdModem=2
FourthModem=4
Audio=Yes
RingIndicate=No
Suspend_Power=No
Lan1Port=330
Lan1IRQ=11
Lan1MemoryBase1=
Lan1MemoryBase2=
Lan2Port=310
Lan2IRQ=10
Lan2MemoryBase1=
Lan2MemoryBase2=
ATATryPrimary=No
ATATrySecondary=Yes
ATATryLinear=Yes
FastTokenRing=Yes
DetectNonCompliant=No
ContinueOnConfigFailure=No
BeepInDOS=Yes
BeepInWindows=Yes
GrabInitFile=Yes
InitBufferSize=512

CARDID.INI-continued

[Libraries]

;
; The Libraries section contains references to any card libraries the user
; wishes to include. Libraries are searched in the specified order. Path
; names are relative to the directory containing CARDID.INI.

;
CardLib=xirdual.clb
CardLib=xircom.clb
CardLib=tdkklan2.clb
CardLib=sundisk5.clb
CardLib=intellan.clb
CardLib=dlink.clb
CardLib=linksys.clb
CardLib=linksys2.clb
CardLib=socketea.clb
CardLib=ibmlan.clb
CardLib=ibmtok.clb
CardLib=ibm3270.clb
CardLib=proxim.clb
CardLib=cbdass.clb
CardLib=genmodem.clb
CardLib=genata.clb
CardLib=wd.clb

Configuration Notes:

The card was configured from Windows using ODI drivers. A custom install was chosen, and resources were chosen to avoid conflicts with internal options. The resources for this card were IRQ 11, I/O 330, and MEM D1000. Windows 95 drivers will automatically configure the card upon insertion.

PLATFORM: COMPAQ AERO 4/33C

ROM: 07/19/95

PC CARD: XIRCOM TOKEN RING ADAPTER IIPS, PN: PS-CT2-16CTP

OPERATING SYSTEM: WINDOWS 3.1/DOS 6.2

NOS: NOVELL 3.12

CARD AND SOCKET SERVICES: 1.25

CONFIG.SYS

```
REM Xircom CreditCard --- Do Not Change Lines Below (CTSETUP)
[Xircom_tok]
DEVICE=c:\xircom\CTSETUP.EXE 16
REM Xircom CreditCard Adapter --- Do Not Change Lines Above
REM Xircom CreditCard Adapter --- Do Not Change Lines Below (MENU)
[menu]
menuitem=Xircom_tok, Load Xircom Drivers for Network Access
menuitem=Nonet, Do Not Load Any Xircom Drivers
menucolor=15,0
[Xircom_tok]
[Nonet]
[common]
REM Xircom CreditCard Adapter --- Do Not Change Lines Above
SHELL=C:\DOS\COMMAND.COM /P /E:1536
STACKS=9,256
DEVICE=C:\DOS\HIMEM.SYS
DEVICE=C:\DOS\EMM386.EXE NOEMS X=D000-DFFF
DOS=UMB
REM *** Begin PCMCIA Drivers
REM Warning: Do not move, reorder, or delete any of these lines.
REM
DEVICE=C:\CPQDOS\PCMSMIX.EXE
DEVICEHIGH=C:\CPQDOS\SSVLSI.EXE
DEVICEHIGH=C:\CPQDOS\CS.EXE
DEVICE=C:\CPQDOS\CSALLOC.EXE
DEVICEHIGH=C:\CPQDOS\ATADRV.EXE
DEVICEHIGH=C:\CPQDOS\CARDID.EXE C:\CPQDOS\CARDID.INI
DEVICEHIGH=C:\CPQDOS\MEMDRV.EXE
;DEVICEHIGH=C:\CPQDOS\DBLFLASH.EXE
;DEVICEHIGH=C:\CPQDOS\MS-FLASH.SYS
REM *** End PCMCIA Drivers
DOS=HIGH
BUFFERS=20
FILES=35
;DEVICEHIGH=C:\CPQDOS\POWER.EXE
```

AUTOEXEC.BAT

```
@loadhigh C:\DOS\SHARE.EXE /l:500 /f:5100
SET PATH=C:\CPQDOS;C:\;C:\DOS;C:\WINDOWS; C:\WINDOWS\CPQWIN
SET LMOUSE=C:\MOUSE
SET PROMPT=$PSG
SET TEMP=C:\WINDOWS\TEMP
C:\CPQDOS\HIBRN8.EXE
C:\DOS\SMARTDRV.EXE
LH C:\MOUSE\MOUSE SWAP
C:\CPQDOS\MODE.COM CO80
REM Xircom CreditCard Adapter --- Do Not Change Lines Below
@echo off
cls
goto %config%
:Xircom_tok
c:
cd c:\xircom\ct\netware
CTCFG DRIVER=IPX
CTIPX
NETX
```

AUTOEXEC.BAT-continued

```
F:
login
c:
cd \
goto common
:Nonet
:common
REM Xircom CreditCard Adapter --- Do Not Change Lines Above
C:\WINDOWS\WIN
```

NETWORK DRIVERS

| | | |
|-----------|---------|----------|
| CTCFG.EXE | 56,656 | 10-28-94 |
| NETX.EXE | 78,654 | 11-17-93 |
| CTIPX.EXE | 237,168 | 10-12-94 |

CARDID.INI

```
[Common]
;
; Common Information section created by Config
;
ComPort1=3F8
ComIRQ1=4
ComPort2=2F8
ComIRQ2=3
ComPort3=3E8
ComIRQ3=4
ComPort4=2E8
ComIRQ4=3
ComBySocket=Yes
ComBDAAbsolute=No
FirstModem=2
SecondModem=2
ThirdModem=3
FourthModem=4
Audio=Yes
RingIndicate=No
Lan1Port=300
Lan1IRQ=5
Lan1MemoryBase1=D8
Lan1MemoryBase2=DC
Lan2Port=310
Lan2IRQ=10
Lan2MemoryBase1=D8
Lan2MemoryBase2=DC
ATATryPrimary=No
ATATrySecondary=Yes
ATATryLinear=Yes
FastTokenRing=Yes
DetectNonCompliant=No
ContinueOnConfigFailure=No
BeepInDOS=Yes
BeepInWindows=Yes
GrabInitFile=Yes
InitBufferSize=512
```

```
[Libraries]
;
; The Libraries section contains references to any card libraries the user
; wishes to include. Libraries are searched in the specified order. Path
; names are relative to the directory containing CARDID.INI.
;
CardLib=cardid.clb
```

Configuration Notes:

Installed the card from Windows . Chose a custom install and used default selections for majority settings, but during installation we did select 16 for ring speed and the frame type was changed to 802.2. The resources assigned to the card were IRQ 5, I/O 300, MEM D000, and if you want to make changes in Windows/DOS it is recommended to rerun the install program instead of trying to do it manually. The Windows 95 drivers are built in and the card will automatically be recognized and configured upon insertion.

PLATFORM: COMPAQ CONCERTO

ROM: 10/12/93

PC CARD: XIRCOM TOKEN RING ADAPTER IIPS, PN: PS-CT2-16CTP

OPERATING SYSTEM: WINDOWS 3.1/DOS 6.2

NOS: NOVELL 3.12

CARD AND SOCKET SERVICES: 1.25

CONFIG.SYS

```
REM Xircom CreditCard --- Do Not Change Lines Below (CTSETUP)
[Xircom_tok]
DEVICE=c:\xircom\CTSETUP.EXE 16
REM Xircom CreditCard Adapter --- Do Not Change Lines Above
REM Xircom CreditCard Adapter --- Do Not Change Lines Below (MENU)
[menu]
menuitem=Xircom_tok, Load Xircom CreditCard For Network Access
menuitem=Nonet, Do Not Load Any Xircom Drivers
menucolor=15,0
[Xircom_tok]
[Nonet]
[common]
REM Xircom CreditCard Adapter --- Do Not Change Lines Above
SHELL=C:\DOS\COMMAND.COM /P /E:1536
STACKS=9,256
DEVICE=C:\DOS\HIMEM.SYS
DEVICE=C:\DOS\EMM386.EXE NOEMS X=D000-DFFF
DOS=UMB
REM *** Begin PCMCIA Drivers
REM Warning: Do not move, reorder, or delete any of these lines.
REM
DEVICEHIGH=C:\CPQDOS\SSCIRRUS.EXE
DEVICEHIGH=C:\CPQDOS\CS.EXE
DEVICE=C:\CPQDOS\CSALLOC.EXE
DEVICEHIGH=C:\CPQDOS\ATADRV.EXE
DEVICEHIGH=C:\CPQDOS\CARDID.EXE C:\CPQDOS\CARDID.INI
DEVICEHIGH=C:\CPQDOS\MEMDRV.EXE
;DEVICEHIGH=C:\CPQDOS\DBLFLASH.EXE
;DEVICEHIGH=C:\CPQDOS\MS-FLASH.SYS
REM *** End PCMCIA Drivers
DOS=HIGH
BUFFERS=20
FILES=35
DEVICEHIGH=C:\CPQDOS\POWER.EXE
```

AUTOEXEC.BAT

```
SET PATH=C:\CPQDOS;C:\;C:\DOS;C:\WINDOWS;C:\WINDOWS\CPQWIN
SET LMOUSE=C:\MOUSE
SET PROMPT=$P$G
SET TEMP=C:\WINDOWS\TEMP
C:\CPQDOS\HIBRN8.EXE
C:\DOS\SMARTDRV.EXE
LH C:\MOUSE\MOUSE
C:\CPQDOS\MODE.COM CO80
REM Xircom CreditCard Adapter --- Do Not Change Lines Below
@echo off
cls
goto %config%
:Xircom_tok
c:
cd c:\xircom\ct\netware
CTCFG DRIVER=IPX io=240
CTIPX io=240
NETX
H:
login
```

AUTOEXEC.BAT-continued

```
c:
cd \
goto common
:Nonet
:common
REM Xircom CreditCard Adapter --- Do Not Change Lines Above
C:\WINDOWS\WIN
```

NETWORK DRIVERS

```
CTCFG.EXE      56,656  10-28-94
NETX.EXE       78,654  11-17-93
CTIPX.EXE     237,168  10-12-94
```

CARDID.INI

```
[Common]
;
; Common Information section created by Config
;
ComPort1=3F8
ComIRQ1=4
ComPort2=2F8
ComIRQ2=3
ComPort3=3E8
ComIRQ3=4
ComPort4=2E8
ComIRQ4=3
ComBySocket=Yes
ComBDAAbsolute=No
FirstModem=2
SecondModem=2
ThirdModem=3
FourthModem=4
Audio=Yes
RingIndicate=No
Lan1Port=300
Lan1IRQ=5
Lan1MemoryBase1=D8
Lan1MemoryBase2=DC
Lan2Port=310
Lan2IRQ=10
Lan2MemoryBase1=D8
Lan2MemoryBase2=DC
ATATryPrimary=No
ATATrySecondary=Yes
ATATryLinear=Yes
FastTokenRing=Yes
DetectNonCompliant=No
ContinueOnConfigFailure=No
BeepInDOS=Yes
BeepInWindows=Yes
GrabInitFile=Yes
InitBufferSize=512

[Libraries]
;
; The Libraries section contains references to any card libraries the user
; wishes to include. Libraries are searched in the specified order. Path
; names are relative to the directory containing CARDID.INI.
;
CardLib=cardid.clb
```

Configuration Notes:

Installed the card from Windows . Chose a custom install and used default selections for majority settings, but the frame type was changed to 802.2. The resources assigned to the card were IRQ 5, I/O 240, MEM D000, and if you want to make changes in Windows/DOS it is recommended to rerun the install program instead of trying to do it manually. The Windows 95 drivers are built in and the card will automatically be recognized and configured upon insertion.

PLATFORM: *COMPAQ CONTURA 400CX*

ROM: 07/18/95

PC CARD: XIRCOM TOKEN RING ADAPTER IIPS, PN: PS-CT2-16CTP

OPERATING SYSTEM: WINDOWS 3.1/DOS 6.2

NOS: NOVELL 3.12

CARD AND SOCKET SERVICES: 3.12

CONFIG.SYS

```
switches=/F
SHELL=C:\DOS\COMMAND.COM /P /E:1536
STACKS=9,256
DEVICE=C:\DOS\HIMEM.SYS
DEVICE=C:\DOS\EMM386.EXE NOEMS I=B000-B7FF X=D000-D4FF
DOS=HIGH,UMB
DEVICEHIGH=C:\WINDOWS\CPQWIN\CPQCM.SYS
REM Xircom CreditCard --- Do Not Change Lines Below (CTSETUP)
[Xircom_tok]
DEVICE=c:\xircom\CTSETUP.EXE 16
REM Xircom CreditCard Adapter --- Do Not Change Lines Above
REM Xircom CreditCard Adapter --- Do Not Change Lines Below (MENU)
[menu]
menuitem=Xircom_tok, Load Xircom CreditCard For Network Access
menuitem=Nonet, Do Not Load Any Xircom Drivers
menucolor=15,0
[Xircom_tok]
[Nonet]
[common]
REM Xircom CreditCard Adapter --- Do Not Change Lines Above
REM *** Begin PCMCIA Drivers
REM Warning: Do not move, reorder, or delete any of these lines.
REM
;DEVICE=C:\CPQDOS\PCSMIX.EXE
DEVICEHIGH=C:\CPQDOS\SSVLSI.EXE
DEVICEHIGH=C:\CPQDOS\CS.EXE
DEVICE=C:\CPQDOS\CSALLOC.EXE
;DEVICEHIGH=C:\CPQDOS\ATADRV.EXE
;DEVICEHIGH=C:\CPQDOS\MTAA.EXE
;DEVICEHIGH=C:\CPQDOS\MTAB.EXE
;DEVICEHIGH=C:\CPQDOS\MTI1.EXE
;DEVICEHIGH=C:\CPQDOS\MTI2P.EXE
;DEVICEHIGH=C:\CPQDOS\MTSRAM.EXE
;DEVICEHIGH=C:\CPQDOS\MTDDRIV.EXE
;DEVICEHIGH=C:\CPQDOS\DBLFLASH.EXE
;DEVICEHIGH=C:\CPQDOS\MS-FLASH.SYS
DEVICEHIGH=C:\CPQDOS\CARDID.EXE
REM *** End PCMCIA Drivers
BUFFERS=20
FILES=35
DEVICEHIGH=C:\CPQDOS\EPPBIOS.SYS
DEVICEHIGH=C:\CPQDOS\POWER.EXE
```

AUTOEXEC.BAT

```
@ECHO OFF
SET PATH=C:\CPQDOS;C:\;C:\DOS;C:\WINDOWS;;C:\WINDOWS\CPQWIN
SET LMOUSE=C:\MOUSE
LH C:\MOUSE\MOUSE
SET PROMPT=$PSG
SET TEMP=C:\WINDOWS\TEMP
C:\CPQDOS\HIBRN8.EXE
LH C:\DOS\SMARTDRV.EXE
LH SHARE.EXE
REM Xircom CreditCard Adapter --- Do Not Change Lines Below
@echo off
```

AUTOEXEC.BAT-continued

```

cls
goto %config%
:Xircom_tok
c:
cd c:\xircom\ct\netware
CTCFG DRIVER=IPX
CTIPX
NETX
F:
login
c:
cd \
goto common
:Nonet
:common
REM Xircom CreditCard Adapter --- Do Not Change Lines Above

```

NETWORK DRIVERS

| | | |
|-----------|---------|----------|
| CTCFG.EXE | 56,656 | 10-28-94 |
| NETX.EXE | 78,654 | 11-17-93 |
| CTIPX.EXE | 237,168 | 10-12-94 |

CARDID.INI

```

[Common]
;
; Common Information section created by Config
;
ComPort1=3F8
ComIRQ1=4
ComPort2=2F8
ComIRQ2=3
ComPort3=3e8
ComIRQ3=4
ComPort4=2E8
ComIRQ4=3
ComBySocket=Yes
ComBDAAbsolute=No
FirstModem=2
SecondModem=2
ThirdModem=3
FourthModem=4
Audio=Yes
RingIndicate=No
Lan1Port=300
Lan1IRQ=5
Lan1MemoryBase1=
Lan1MemoryBase2=
Lan2Port=310
Lan2IRQ=9
Lan2MemoryBase1=
Lan2MemoryBase2=
ATATryPrimary=No
ATATrySecondary=Yes
ATATryLinear=Yes
FastTokenRing=Yes
DetectNonCompliant=No
ContinueOnConfigFailure=No
BeepInDOS=Yes
BeepInWindows=Yes
GrabInitFile=Yes
InitBufferSize=512
UseEMS=No

```

CARDID.INI-continued

[Libraries]

;
; The Libraries section contains references to any card libraries the user
; wishes to include. Libraries are searched in the specified order. Path
; names are relative to the directory containing CARDID.INI.

;
CardLib=canonfd.clb
CardLib=xirdual.clb
CardLib=xircom.clb
CardLib=tdkklan2.clb
CardLib=sundisk5.clb
CardLib=intellan.clb
CardLib=dlink.clb
CardLib=linksys.clb
CardLib=linksys2.clb
CardLib=socketea.clb
CardLib=ibmlan.clb
CardLib=ibmtok.clb
CardLib=ibm3270.clb
CardLib=proxim.clb
CardLib=cbdass.clb
CardLib=genmodem.clb
CardLib=genata.clb
CardLib=wd.clb

Configuration Notes:

Installed the card from Windows . Chose a custom install and used default selections for majority settings, but the frame type was changed to 802.2. The resources assigned to the card were IRQ 5, I/O 300, MEM D000, and if you want to make changes in Windows/DOS it is recommended to rerun the install program instead of trying to do it manually. The Windows 95 drivers are built in and the card will automatically be recognized and configured upon insertion.

PLATFORM: COMPAQ CONTURA 420C

ROM: 08/20/95

PC CARD: XIRCOM TOKEN RING ADAPTER IIPS, PN: PS-CT2-16CTP

OPERATING SYSTEM: WINDOWS 3.1/DOS 6.2

NOS: NOVELL 3.12

CARD AND SOCKET SERVICES: 3.12

CONFIG.SYS

```
REM Xircom CreditCard --- Do Not Change Lines Below (CTSETUP)
[Xircom_tok]
DEVICE=c:\xircom\CTSETUP.EXE 16
REM Xircom CreditCard Adapter --- Do Not Change Lines Above
REM Xircom CreditCard Adapter --- Do Not Change Lines Below (MENU)
[menu]
menuitem=Xircom_tok, Load Xircom CreditCard For Network Access
menuitem=Nonet, Do Not Load Any Xircom Drivers
menucolor=15,0
[Xircom_tok]
[Nonet]
[common]
REM Xircom CreditCard Adapter --- Do Not Change Lines Above
switches=/F
SHELL=C:\DOS\COMMAND.COM /P /E:1536
STACKS=9,256
DEVICE=C:\DOS\HIMEM.SYS
DEVICE=C:\DOS\EMM386.EXE NOEMS I=B000-B7FF X=D000-D4FF
DEVICEHIGH=C:\WINDOWS\CPQWIN\CPQCM.SYS /w
DOS=HIGH,UMB
REM *** Begin PCMCIA Drivers
REM Warning: Do not move, reorder, or delete any of these lines.
REM
;DEVICE=C:\CPQDOS\PCSMIX.EXE
DEVICEHIGH=C:\CPQDOS\SSVLSI.EXE
DEVICEHIGH=C:\CPQDOS\CS.EXE
DEVICE=C:\CPQDOS\CSALLOC.EXE
;DEVICEHIGH=C:\CPQDOS\ATADRV.EXE
;DEVICEHIGH=C:\CPQDOS\MTAA.EXE
;DEVICEHIGH=C:\CPQDOS\MTAB.EXE
;DEVICEHIGH=C:\CPQDOS\MTI1.EXE
;DEVICEHIGH=C:\CPQDOS\MTI2P.EXE
;DEVICEHIGH=C:\CPQDOS\MTSRAM.EXE
;DEVICEHIGH=C:\CPQDOS\MTDDRV.EXE
;DEVICEHIGH=C:\CPQDOS\DBLFLASH.EXE
;DEVICEHIGH=C:\CPQDOS\MS-FLASH.SYS
DEVICEHIGH=C:\CPQDOS\CARDID.EXE
REM *** End PCMCIA Drivers
BUFFERS=20
FILES=35
DEVICEHIGH=C:\CPQDOS\EPPBIOS.SYS
LASTDRIVE=M
```

AUTOEXEC.BAT

```
@ECHO OFF
SET PATH=C:\CPQDOS;C:\;C:\DOS;C:\WINDOWS;
SET LMOUSE=C:\MOUSE
LH C:\MOUSE\MOUSE
SET PROMPT=$PSG
SET TEMP=C:\WINDOWS\TEMP
C:\CPQDOS\HIBRN8.EXE
C:\DOS\SMARTDRV.EXE 2048 512
REM Xircom CreditCard Adapter --- Do Not Change Lines Below
@echo off
cls
```

AUTOEXEC.BAT -continued

```
goto %config%
:Xircom_tok
c:
cd c:\xircom\ct\netware
CTCFG DRIVER=IPX mode=0x01
CTIPX mode=1
NETX
N:
login
c:
cd \
goto common
:Nonet
:common
REM Xircom CreditCard Adapter --- Do Not Change Lines Above
```

NETWORK DRIVERS

| | | |
|-----------|---------|----------|
| CTCFG.EXE | 56,656 | 10-28-94 |
| NETX.EXE | 78,654 | 11-17-93 |
| CTIPX.EXE | 237,168 | 10-12-94 |

CARDID.INI

```
[Common]
;
; Common Information section created by Config
;
ComPort1=3F8
ComIRQ1=4
ComPort2=2F8
ComIRQ2=3
ComPort3=3E8
ComIRQ3=4
ComPort4=2E8
ComIRQ4=3
ComBySocket=Yes
ComBDAAbsolute=No
FirstModem=2
SecondModem=2
ThirdModem=3
FourthModem=4
Audio=Yes
RingIndicate=No
Lan1Port=300
Lan1IRQ=5
Lan1MemoryBase1=D0
Lan1MemoryBase2=0
Lan2Port=310
Lan2IRQ=9
Lan2MemoryBase1=0
Lan2MemoryBase2=0
ATATryPrimary=No
ATATrySecondary=Yes
ATATryLinear=Yes
FastTokenRing=Yes
DetectNonCompliant=No
ContinueOnConfigFailure=No
BeepInDOS=Yes
BeepInWindows=Yes
GrabInitFile=Yes
InitBufferSize=512
UseEMS=No

[Libraries]
;
; The Libraries section contains references to any card libraries the user
; wishes to include. Libraries are searched in the specified order. Path
; names are relative to the directory containing CARDID.INI.
;
CardLib=canonfd.clb
CardLib=xirdual.clb
```

CARDID.INI-continued

CardLib=xircom.clb
CardLib=tdklan2.clb
CardLib=sundisk5.clb
CardLib=intellan.clb
CardLib=dlink.clb
CardLib=linksys.clb
CardLib=linksys2.clb
CardLib=socketea.clb
CardLib=ibmlan.clb
CardLib=ibmtok.clb
CardLib=ibm3270.clb
CardLib=proxim.clb
CardLib=cbdas.clb
CardLib=genmodem.clb
CardLib=genata.clb
CardLib=wd.clb

Configuration Notes:

Installed the card from Windows . Chose a custom install and used default selections for majority settings, but the frame type was changed to 802.2. The resources assigned to the card were IRQ 5, I/O 300, MEM D000, and if you want to make changes in Windows/DOS it is recommended to rerun the install program instead of trying to do it manually. The Windows 95 drivers are built in and the card will automatically be recognized and configured upon insertion.

PLATFORM: COMPAQ ELITE 4/50CX

ROM: 07/19/95

PC CARD: XIRCOM TOKEN RING ADAPTER IIPS, PN: PS-CT2-16CTP

OPERATING SYSTEM: WINDOWS 3.1/DOS 6.2

NOS: NOVELL 3.12

CARD AND SOCKET SERVICES: 3.12

CONFIG.SYS

```
REM Xircom CreditCard --- Do Not Change Lines Below (CTSETUP)
[Xircom_tok]
DEVICE=C:\XIRCOM\CTSETUP.EXE 16
REM Xircom CreditCard Adapter --- Do Not Change Lines Above
REM Xircom CreditCard Adapter --- Do Not Change Lines Below (MENU)
[menu]
menuitem=Xircom_tok, Load Xircom CreditCard Token Ring Drivers
For Network Access
menuitem=Nonet, Do Not Load Any Xircom Drivers
menucolor=15,0
[Xircom_tok]
[Nonet]
[common]
REM Xircom CreditCard Adapter --- Do Not Change Lines Above
switches=/F
SHELL=C:\DOS\COMMAND.COM /P /E:1536
STACKS=9,256
DEVICE=C:\DOS\HIMEM.SYS
DEVICE=C:\DOS\EMM386.EXE NOEMS I=B000-B7FF X=D000-DFFF
DEVICEHIGH=C:\WINDOWS\CPQWIN\CPQCM.SYS
DOS=HIGH,UMB
REM *** Begin PCMCIA Drivers
REM Warning: Do not move, reorder, or delete any of these lines.
REM
;DEVICE=C:\CPQDOS\PCMSMIX.EXE
DEVICEHIGH=C:\CPQDOS\SSVLSI.EXE
DEVICEHIGH=C:\CPQDOS\CS.EXE
DEVICE=C:\CPQDOS\CSALLOC.EXE
;DEVICEHIGH=C:\CPQDOS\ATADRV.EXE
;DEVICEHIGH=C:\CPQDOS\MTAA.EXE
;DEVICEHIGH=C:\CPQDOS\MTAB.EXE
;DEVICEHIGH=C:\CPQDOS\MTI1.EXE
;DEVICEHIGH=C:\CPQDOS\MTI2P.EXE
;DEVICEHIGH=C:\CPQDOS\MTSRAM.EXE
;DEVICEHIGH=C:\CPQDOS\MTDDRV.EXE
;DEVICEHIGH=C:\CPQDOS\DBLFLASH.EXE
;DEVICEHIGH=C:\CPQDOS\MS-FLASH.SYS
DEVICEHIGH=C:\CPQDOS\CARDID.EXE
REM *** End PCMCIA Drivers
BUFFERS=20
FILES=35
LASTDRIVE = e
DEVICEHIGH=C:\CPQDOS\POWER.EXE
```

AUTOEXEC.BAT

```
@ECHO OFF
SET PATH=C:\CPQDOS;C:\;C:\DOS;C:\WINDOWS;;C:\WINDOWS\CPQWIN
SET LMOUSE=C:\MOUSE
LH C:\MOUSE\MOUSE
SET PROMPT=$PSG
SET TEMP=C:\WINDOWS\TEMP
C:\CPQDOS\HIBRN8.EXE
LH C:\DOS\SMARTDRV.EXE
SET NWLANGUAGE=ENGLISH
REM Xircom CreditCard Adapter --- Do Not Change Lines Below
```

AUTOEXEC.BAT-continued

```
@echo off
cls
goto %config%
:Xircom_tok
C:
cd C:\XIRCOM\CT\NETWARE
CTCFG DRIVER=IPX mode=0x01 irq=11
CTIPX mode=1 irq=11
NETX
F:
login
C:
cd \
goto common
:Nonet
:common
REM Xircom CreditCard Adapter --- Do Not Change Lines Above
c:\windows\win
```

NETWORK DRIVERS

| | | |
|-----------|---------|----------|
| CTCFG.EXE | 56,656 | 10-28-94 |
| NETX.EXE | 78,654 | 11-17-93 |
| CTIPX.EXE | 237,168 | 10-12-94 |

CARDID.INI

```
[Common]
;
; Common Information section created by Config
;
ComPort1=3F8
ComIRQ1=4
ComPort2=2F8
ComIRQ2=3
ComPort3=3e8
ComIRQ3=4
ComPort4=2E8
ComIRQ4=3
ComBySocket=Yes
ComBDAAbsolute=No
FirstModem=2
SecondModem=2
ThirdModem=3
FourthModem=4
Audio=Yes
RingIndicate=No
Lan1Port=300
Lan1IRQ=5
Lan1MemoryBase1=
Lan1MemoryBase2=
Lan2Port=310
Lan2IRQ=9
Lan2MemoryBase1=
Lan2MemoryBase2=
ATATryPrimary=No
ATATrySecondary=Yes
ATATryLinear=Yes
FastTokenRing=Yes
DetectNonCompliant=No
ContinueOnConfigFailure=No
BeepInDOS=Yes
BeepInWindows=Yes
GrabInitFile=Yes
InitBufferSize=512
UseEMS=No
```

CARDID.INI-continued

[Libraries]

;
; The Libraries section contains references to any card libraries the user
; wishes to include. Libraries are searched in the specified order. Path
; names are relative to the directory containing CARDID.INI.

;
CardLib=canonfd.clb
CardLib=xirdual.clb
CardLib=xircom.clb
CardLib=tdkfan2.clb
CardLib=sundisk5.clb
CardLib=intellan.clb
CardLib=dlink.clb
CardLib=linksys.clb
CardLib=linksys2.clb
CardLib=socketea.clb
CardLib=ibmlan.clb
CardLib=ibmtok.clb
CardLib=ibm3270.clb
CardLib=proxim.clb
CardLib=cbdas.clb
CardLib=genmodem.clb
CardLib=genata.clb
CardLib=wd.clb

Configuration Notes:

Installed the card from Windows . Chose a custom install and used default selections for majority settings, but the frame type was changed to 802.2. The resources assigned to the card were IRQ 11, I/O 300, MEM D000, and if you want to make changes in Windows/DOS it is recommended to rerun the install program instead of trying to do it manually. While in the base several changes were made so card would function in or out with no problem, the internal SCSI controller was changed to IRQ 10 I/O 140 and the internal network controller I/O was changed to 220. The Windows 95 drivers are built in and the card will automatically be recognized and configured upon insertion.

PLATFORM: COMPAQ LTE 5000

ROM: 09/19/95

PC CARD: XIRCOM TOKEN RING ADAPTER IIPS, PN: PS-CT2-16CTP

OPERATING SYSTEM: WINDOWS 3.1/DOS 6.2

NOS: NOVELL 3.12

CARD AND SOCKET SERVICES: 3.14

CONFIG.SYS

REM Xircom CreditCard Adapter --- Do Not Change Lines Below (CTSETUP)

[Xircom_tok]

DEVICE=c:\xircom\CTSETUP.EXE 16

REM Xircom CreditCard Adapter --- Do Not Change Lines Above

REM Xircom CreditCard Adapter --- Do Not Change Lines Below (MENU)

[menu]

menuitem=Xircom_tok, Load Xircom CreditCard For Network Access

menuitem=Nonet, Do Not Load Any Xircom Drivers

menucolor=15,0

[Xircom_tok]

[Nonet]

[common]

REM Xircom CreditCard Adapter --- Do Not Change Lines Above

DEVICE=C:\CPQDOS\MACHCHK.SYS 02A8 02B0 02BA 02CA

DEVICE=C:\DOS\HIMEM.SYS

DEVICE=C:\DOS\EMM386.exe NOEMS I=B000-B7FF X=C800-CBFF X=D100-D5FF X=E800-EFFF

COUNTRY=001,437,C:\DOS\COUNTRY.SYS

SHELL=C:\DOS\COMMAND.COM /P /E:1536

DOS=HIGH, UMB

FILES=35

BUFFERS=20,0

STACKS=9,256

DEVICEHIGH=C:\AUDIO_CD\TEAC_CDI.SYS /D:TEAC-CDI

LASTDRIVE=M

REM PC Card: Begin PC Card (PCMCIA) Drivers

REM **Warning: Do not move, reorder, or delete any of these lines. **

DEVICEHIGH=C:\CARDWIZ\SSCIRUS2.EXE

DEVICEHIGH=C:\CARDWIZ\CS.EXE /POLL:1

DEVICEHIGH=C:\CARDWIZ\CSALLOC.EXE

DEVICEHIGH=C:\CARDWIZ\CARDID.EXE

REM PC Card: End PC Card(PCMCIA) Drives

AUTOEXEC.BAT

@ECHO OFF

C:\WINDOWS\VGAUTIL\winmode.exe t640=60 t800=60 t1024=87 t1280=87

SET NWLANGUAGE=ENGLISH

PATH C:\WINDOWS;C:\CPQDOS;C:\DOS;C:\AUDIO_CD;C:\CARDWIZ

PROMPT SpSg

SET DIRCMD=/ogn

SET TEMP=C:\WINDOWS\TEMP

SET BLASTER=A220 D1 I5

SET LMOUSE=C:\MOUSE

SET MOUSE=C:\MOUSE

C:\MOUSE\MOUSE.EXE MEMU

C:\DOS\MSCDEX.EXE /D:TEAC-CDI /M:15

IF ERRORLEVEL 1 GOTO NO_CDROM

C:\AUDIO_CD\ESSVOL /V:15 /C:15

:NO_CDROM

LH C:\DOS\SMARTDRV.EXE

C:\CPQDOS\0VMAKFIL

IF NOT EXIST C:\CPQDOS\SAVEDONE.CPQ CALL SAVEALL /A

REM Xircom CreditCard Adapter --- Do Not Change Lines Below

@echo off

cls

goto %config%

:Xircom_tok

AUTOEXEC.BAT-continued

```
c:
cd c:\xircom\ct\netware
CTCFG DRIVER=IPX mem=D100 mode=0x01 irq=11 io=340
CTIPX mem=D1 mode=1 irq=11 io=340
NETX
N:
login
c:
cd \
goto common
:Nonet
:common
REM Xircom CreditCard Adapter --- Do Not Change Lines Above
win
```

NETWORK DRIVERS

| | | |
|-----------|---------|----------|
| CTCFG.EXE | 56,656 | 10-28-94 |
| CTIPX.EXE | 237,168 | 10-12-94 |
| NETX.EXE | 78,654 | 11-17-93 |

CARDID.INI

```
[Common]
;
; Common Information section created by Config
;
ComPort1=3F8
ComIRQ1=4
ComPort2=2F8
ComIRQ2=3
ComPort3=3E8
ComIRQ3=4
ComPort4=2E8
ComIRQ4=11
ComBySocket=No
ComBDAAbsolute=Yes
ComRollOverOn=No
FirstModem=2
SecondModem=4
ThirdModem=2
FourthModem=4
Audio=Yes
RingIndicate=No
Suspend_Power=No
Lan1Port=330
Lan1IRQ=11
Lan1MemoryBase1=0
Lan1MemoryBase2=D1
Lan2Port=310
Lan2IRQ=10
Lan2MemoryBase1=0
Lan2MemoryBase2=0
ATATryPrimary=No
ATATrySecondary=Yes
ATATryLinear=Yes
FastTokenRing=Yes
DetectNonCompliant=No
ContinueOnConfigFailure=No
BeepInDOS=Yes
BeepInWindows=Yes
GrabInitFile=Yes
InitBufferSize=512
FirstLan=1
SecondLan=2
```


CARDID.INI-continued

[Libraries]

;
; The Libraries section contains references to any card libraries the user
; wishes to include. Libraries are searched in the specified order. Path
; names are relative to the directory containing CARDID.INI.

;
CardLib=xirdual.clb
CardLib=xircom.clb
CardLib=tdkklan2.clb
CardLib=sundisk5.clb
CardLib=intellan.clb
CardLib=dlink.clb
CardLib=linksys.clb
CardLib=linksys2.clb
CardLib=socketea.clb
CardLib=ibmlan.clb
CardLib=ibmtok.clb
CardLib=ibm3270.clb
CardLib=proxim.clb
CardLib=cbdass.clb
CardLib=genmodem.clb
CardLib=genata.clb
CardLib=wd.clb

Configuration Notes:

Installed the card from Windows . Chose a custom install and used default selections for majority settings, but the frame type was changed to 802.2. The resources assigned to the card were IRQ 11, I/O 340, MEM D100, and if you want to make changes in Windows/DOS it is recommended to rerun the install program instead of trying to do it manually. The Windows 95 drivers are built in and the card will automatically be recognized and configured upon insertion.

ATA CARDS

PLATFORM: *COMPAQ AERO 4/33C*

ROM: *07/19/95*

PC CARD: *SANDISK 10 MB FLASH ATA, PN: SDP5A-10*

OPERATING SYSTEM: *WINDOWS 3.1/DOS 6.2*

CARD AND SOCKET SERVICES: *1.25*

CONFIG.SYS

```
SHELL=C:\DOS\COMMAND.COM /P /E:1536
STACKS=9,256
DEVICE=C:\DOS\HIMEM.SYS
DEVICE=C:\DOS\EMM386.EXE NOEMS X=D000-DFFF
DOS=UMB
REM *** Begin PCMCIA Drivers
REM Warning: Do not move, reorder, or delete any of these lines.
REM
DEVICE=C:\CPQDOS\PCSMIX.EXE
DEVICEHIGH=C:\CPQDOS\SSVLSI.EXE
DEVICEHIGH=C:\CPQDOS\CS.EXE
DEVICE=C:\CPQDOS\CSALLOC.EXE
DEVICEHIGH=C:\CPQDOS\ATADRV.EXE /D:1
DEVICEHIGH=C:\CPQDOS\CARDID.EXE C:\CPQDOS\CARDID.INI
DEVICEHIGH=C:\CPQDOS\MEMDRV.EXE
DEVICEHIGH=C:\CPQDOS\DBLFLASH.EXE
DEVICEHIGH=C:\CPQDOS\MS-FLASH.SYS
REM *** End PCMCIA Drivers
DOS=HIGH
BUFFERS=20
FILES=35
DEVICEHIGH=C:\CPQDOS\POWER.EXE
```

AUTOEXEC.BAT

```
@loadhigh C:\DOS\SHARE.EXE /I:500 /f:5100
SET PATH=C:\CPQDOS;C:\;C:\DOS;C:\WINDOWS;C:\WINDOWS\CPQWIN
SET LMOUSE=C:\MOUSE
SET PROMPT=SP$G
SET TEMP=C:\WINDOWS\TEMP
C:\CPQDOS\HIBRN8.EXE
C:\DOS\SMARTDRV.EXE
LH C:\MOUSE\MOUSE SWAP
C:\CPQDOS\MODE.COM CO80
C:\WINDOWS\WIN
```

CARDID.INI

```
[Common]
;
; Common Information section created by Config
;
ComPort1=3F8
ComIRQ1=4
ComPort2=2F8
ComIRQ2=3
ComPort3=3E8
ComIRQ3=4
ComPort4=2E8
ComIRQ4=3
ComBySocket=Yes
ComBDAAbsolute=No
FirstModem=2
SecondModem=2
ThirdModem=3
FourthModem=4
Audio=Yes
RingIndicate=No
```

CARDID.INI -continued

Lan1Port=300
Lan1IRQ=5
Lan1MemoryBase1=D8
Lan1MemoryBase2=DC
Lan2Port=310
Lan2IRQ=10
Lan2MemoryBase1=D8
Lan2MemoryBase2=DC
ATATryPrimary=No
ATATrySecondary=Yes
ATATryLinear=Yes
FastTokenRing=Yes
DetectNonCompliant=No
ContinueOnConfigFailure=No
BeepInDOS=Yes
BeepInWindows=Yes
GrabInitFile=Yes
InitBufferSize=512

[Libraries]

;
; The Libraries section contains references to any card libraries the user
; wishes to include. Libraries are searched in the specified order. Path
; names are relative to the directory containing CARDID.INI.
;
CardLib=cardid.clb

Configuration Notes:

Upon insertion the card should automatically be configure in DOS/Windows. The drive letter assigned will normally be D: or E:, but will depend on which slot the card is inserted. To verify what drive letter is assigned type CARDINFO and it will display information about the card including the driver letter assigned. In regards to Windows 95; the drivers for the SanDisk are built in and it will automatically configure.

PLATFORM: *COMPAQ CONCERTO*

ROM: *10/12/93*

PC CARDS: *CALLUNA 170MB HARD DRIVE, PN: CT170MC, SANDISK 10 MB FLASH ATA, PN: SDP5A-10*

OPERATING SYSTEM: *WINDOWS 3.1/DOS 6.2*

CARD AND SOCKET SERVICES: *1.25*

CONFIG.SYS

```
SHELL=C:\DOS\COMMAND.COM /P /E:1536
STACKS=9,256
DEVICE=C:\DOS\HIMEM.SYS
DEVICE=C:\DOS\EMM386.EXE NOEMS X=D000-DFFF
DOS=UMB
REM *** Begin PCMCIA Drivers
REM Warning: Do not move, reorder, or delete any of these lines.
REM
DEVICEHIGH=C:\CPQDOS\SSCIRRUS.EXE
DEVICEHIGH=C:\CPQDOS\CS.EXE
DEVICE=C:\CPQDOS\CSALLOC.EXE
DEVICEHIGH=C:\CPQDOS\ATADRV.EXE
DEVICEHIGH=C:\CPQDOS\CARDID.EXE C:\CPQDOS\CARDID.INI
DEVICEHIGH=C:\CPQDOS\MEMDRV.EXE
;DEVICEHIGH=C:\CPQDOS\DBLFLASH.EXE
;DEVICEHIGH=C:\CPQDOS\MS-FLASH.SYS
REM *** End PCMCIA Drivers
DOS=HIGH
BUFFERS=20
FILES=35
DEVICEHIGH=C:\CPQDOS\POWER.EXE
```

AUTOEXEC.BAT

```
SET PATH=C:\CPQDOS;C:\;C:\DOS;C:\WINDOWS;;C:\WINDOWS\CPQWIN
SET LMOUSE=C:\MOUSE
SET PROMPT=SP$G
SET TEMP=C:\WINDOWS\TEMP
C:\CPQDOS\HIBRN8.EXE
C:\DOS\SMARTDRV.EXE
LH C:\MOUSE\MOUSE
C:\CPQDOS\MODE.COM CO80
C:\WINDOWS\WIN
```

CARDID.INI

```
[Common]
;
; Common Information section created by Config
;
ComPort1=3F8
ComIRQ1=4
ComPort2=2F8
ComIRQ2=3
ComPort3=3E8
ComIRQ3=4
ComPort4=2E8
ComIRQ4=3
ComBySocket=Yes
ComBDAAbsolute=No
FirstModem=2
SecondModem=2
ThirdModem=3
FourthModem=4
Audio=Yes
RingIndicate=No
Lan1Port=300
Lan1IRQ=5
```

CARDID.INI-continued

```
Lan1MemoryBase1=D8
Lan1MemoryBase2=DC
Lan2Port=310
Lan2IRQ=10
Lan2MemoryBase1=D8
Lan2MemoryBase2=DC
ATATryPrimary=No
ATATrySecondary=Yes
ATATryLinear=Yes
FastTokenRing=Yes
DetectNonCompliant=No
ContinueOnConfigFailure=No
BeepInDOS=Yes
BeepInWindows=Yes
GrabInitFile=Yes
InitBufferSize=512
```

```
[Libraries]
```

```
;  
; The Libraries section contains references to any card libraries the user  
; wishes to include. Libraries are searched in the specified order. Path  
; names are relative to the directory containing CARDID.INI.  
;  
CardLib=cardid.clb
```

Configuration Notes:

Upon insertion the card should automatically be configure in DOS/Windows. The drive letter assigned will normally be D: or E:, but will depend on which slot the card is inserted. To verify what drive letter is assigned type CARDINFO and it will display information about the card including the driver letter assigned. In regards to Windows 95; the drivers for the SanDisk are built in and it will automatically configure, but the drivers for the Calluna are not. The solution is to simply choose existing drivers, and select a Maxtor 170MB ATA drive and it should work fine.

PLATFORM: COMPAQ CONTURA 400CX

ROM: 07/18/95

PC CARDS: CALLUNA 170MB HARD DRIVE, PN: CT170MC, SANDISK 10 MB FLASH ATA, PN: SDP5A-10

OPERATING SYSTEM: WINDOWS 3.1/DOS 6.2

CARD AND SOCKET SERVICES: 3.12

CONFIG.SYS

```
switches=/F
SHELL=C:\DOS\COMMAND.COM /P /E:1536
STACKS=9,256
DEVICE=C:\DOS\HIMEM.SYS
DEVICE=C:\DOS\EMM386.EXE NOEMS I=B000-B7FF X=D000-D4FF
DEVICEHIGH=C:\WINDOWS\CPQWIN\CPQCM.SYS
DOS=HIGH,UMB
REM *** Begin PCMCIA Drivers
REM Warning: Do not move, reorder, or delete any of these lines.
REM
;DEVICE=C:\CPQDOS\PCMSMIX.EXE
DEVICEHIGH=C:\CPQDOS\SSVLSI.EXE
DEVICEHIGH=C:\CPQDOS\CS.EXE
DEVICE=C:\CPQDOS\CSALLOC.EXE
DEVICEHIGH=C:\CPQDOS\ATADRV.EXE
;DEVICEHIGH=C:\CPQDOS\MTAA.EXE
;DEVICEHIGH=C:\CPQDOS\MTAB.EXE
;DEVICEHIGH=C:\CPQDOS\MTI1.EXE
;DEVICEHIGH=C:\CPQDOS\MTI2P.EXE
;DEVICEHIGH=C:\CPQDOS\MTSRAM.EXE
;DEVICEHIGH=C:\CPQDOS\MTDDRV.EXE
;DEVICEHIGH=C:\CPQDOS\DBLFLASH.EXE
;DEVICEHIGH=C:\CPQDOS\MS-FLASH.SYS
DEVICEHIGH=C:\CPQDOS\CARDID.EXE
REM *** End PCMCIA Drivers
BUFFERS=20
FILES=35
DEVICEHIGH=C:\CPQDOS\EPPBIOS.SYS
DEVICEHIGH=C:\CPQDOS\POWER.EXE
```

AUTOEXEC.BAT

```
@ECHO OFF
SET PATH=C:\CPQDOS;C:\;C:\DOS;C:\WINDOWS;;C:\WINDOWS\CPQWIN
SET LMOUSE=C:\MOUSE
LH C:\MOUSE\MOUSE
SET PROMPT=$PSG
SET TEMP=C:\WINDOWS\TEMP
C:\CPQDOS\HIBRN8.EXE
LH C:\DOS\SMARTDRV.EXE
LH SHARE.EXE
C:\WINDOWS\WIN
```

CARDID.INI

```
[Common]
;
; Common Information section created by Config
;
ComPort1=3F8
ComIRQ1=4
ComPort2=2F8
ComIRQ2=3
ComPort3=3e8
ComIRQ3=4
ComPort4=2E8
ComIRQ4=3
ComBySocket=Yes
ComBDAAbsolute=No
CARDID.INI-continued
```

FirstModem=2
SecondModem=2
ThirdModem=3
FourthModem=4
Audio=Yes
RingIndicate=No
Lan1Port=300
Lan1IRQ=5
Lan1MemoryBase1=
Lan1MemoryBase2=
Lan2Port=310
Lan2IRQ=9
Lan2MemoryBase1=
Lan2MemoryBase2=
ATATryPrimary=No
ATATrySecondary=Yes
ATATryLinear=Yes
FastTokenRing=Yes
DetectNonCompliant=No
ContinueOnConfigFailure=No
BeepInDOS=Yes
BeepInWindows=Yes
GrabInitFile=Yes
InitBufferSize=512
UseEMS=No

[Libraries]

;
; The Libraries section contains references to any card libraries the user
; wishes to include. Libraries are searched in the specified order. Path
; names are relative to the directory containing CARDID.INI.

;
CardLib=canonfd.clb
CardLib=xirdual.clb
CardLib=xircom.clb
CardLib=tdkfan2.clb
CardLib=sundisk5.clb
CardLib=intellan.clb
CardLib=dlink.clb
CardLib=linksys.clb
CardLib=linksys2.clb
CardLib=socketea.clb
CardLib=ibmlan.clb
CardLib=ibmtok.clb
CardLib=ibm3270.clb
CardLib=proxim.clb
CardLib=cbdass.clb
CardLib=genmodem.clb
CardLib=genata.clb
CardLib=wd.clb

Configuration Notes:

Upon insertion the card should automatically be configured in DOS/Windows. The drive letter assigned will normally be D: or E:, but will depend on which slot the card is inserted. To verify what drive letter is assigned type CARDINFO and it will display information about the card including the driver letter assigned. In regards to Windows 95; the drivers for the SanDisk are built in and it will automatically configure, but the drivers for the Calluna are not. The solution is to simply choose existing drivers, and select a Maxtor 170MB ATA drive and it should work fine.

PLATFORM: COMPAQ CONTURA 420C

ROM: 08/20/95

PC CARDS: CALLUNA 170MB HARD DRIVE, PN: CT170MC, SANDISK 10 MB FLASH ATA, PN: SDP5A-10

OPERATING SYSTEM: WINDOWS 3.1/DOS 6.2

CARD AND SOCKET SERVICES: 3.12

CONFIG.SYS

```
SHELL=C:\DOS\COMMAND.COM /P /E:1536
STACKS=9,256
DEVICE=C:\DOS\HIMEM.SYS
DEVICE=C:\DOS\EMM386.EXE NOEMS I=B000-B7FF X=D000-D4FF
DEVICEHIGH=C:\WINDOWS\CPQWIN\CPQCM.SYS
DOS=HIGH,UMB
REM *** Begin PCMCIA Drivers
REM Warning: Do not move, reorder, or delete any of these lines.
REM
;DEVICE=C:\CPQDOS\PCSMIX.EXE
DEVICEHIGH=C:\CPQDOS\SSVLSI.EXE
DEVICEHIGH=C:\CPQDOS\CS.EXE
DEVICE=C:\CPQDOS\CSALLOC.EXE
DEVICEHIGH=C:\CPQDOS\ATADRV.EXE
;DEVICEHIGH=C:\CPQDOS\MTAA.EXE
;DEVICEHIGH=C:\CPQDOS\MTAB.EXE
;DEVICEHIGH=C:\CPQDOS\MTI1.EXE
;DEVICEHIGH=C:\CPQDOS\MTI2P.EXE
;DEVICEHIGH=C:\CPQDOS\MTSRAM.EXE
;DEVICEHIGH=C:\CPQDOS\MTDDRV.EXE
;DEVICEHIGH=C:\CPQDOS\DBLFLASH.EXE
;DEVICEHIGH=C:\CPQDOS\MS-FLASH.SYS
DEVICEHIGH=C:\CPQDOS\CARDID.EXE
REM *** End PCMCIA Drivers
BUFFERS=20
FILES=35
DEVICEHIGH=C:\CPQDOS\EPPBIOS.SYS
```

AUTOEXEC.BAT

```
@ECHO OFF
SET PATH=C:\CPQDOS;C:\;C:\DOS;C:\WINDOWS;C:\WINDOWS\CPQWIN
SET LMOUSE=C:\MOUSE
LH C:\MOUSE\MOUSE
SET PROMPT=$PSG
SET TEMP=C:\WINDOWS\TEMP
C:\CPQDOS\HIBRN8.EXE
C:\DOS\SMARTDRV.EXE 2048 512
C:\WINDOWS\WIN
```

CARDID.INI

```
[Common]
;
; Common Information section created by Config
;
ComPort1=3F8
ComIRQ1=4
ComPort2=2F8
ComIRQ2=3
ComPort3=3e8
ComIRQ3=4
ComPort4=2E8
ComIRQ4=3
ComBySocket=Yes
ComBDAAbsolute=No
FirstModem=2
SecondModem=2
ThirdModem=3
CARDID.INI-continued
```

FourthModem=4
Audio=Yes
RingIndicate=No
Lan1Port=300
Lan1IRQ=5
Lan1MemoryBase1=
Lan1MemoryBase2=
Lan2Port=310
Lan2IRQ=9
Lan2MemoryBase1=
Lan2MemoryBase2=
ATATryPrimary=No
ATATrySecondary=Yes
ATATryLinear=Yes
FastTokenRing=Yes
DetectNonCompliant=No
ContinueOnConfigFailure=No
BeepInDOS=Yes
BeepInWindows=Yes
GrabInitFile=Yes
InitBufferSize=512
UseEMS=No

[Libraries]

;
; The Libraries section contains references to any card libraries the user
; wishes to include. Libraries are searched in the specified order. Path
; names are relative to the directory containing CARDID.INI.

;
CardLib=canonfd.clb
CardLib=xirdual.clb
CardLib=xircom.clb
CardLib=tdkklan2.clb
CardLib=sundisk5.clb
CardLib=intellan.clb
CardLib=dlink.clb
CardLib=linksys.clb
CardLib=linksys2.clb
CardLib=socketea.clb
CardLib=ibmlan.clb
CardLib=ibmtok.clb
CardLib=ibm3270.clb
CardLib=proxim.clb
CardLib=cbdass.clb
CardLib=genmodem.clb
CardLib=genata.clb
CardLib=wd.clb

Configuration Notes:

Upon insertion the card should automatically be configure in DOS/Windows. The drive letter assigned will normally be D: or E:, but will depend on which slot the card is inserted. To verify what drive letter is assigned type CARDINFO and it will display information about the card including the driver letter assigned. In regards to Windows 95; the drivers for the SanDisk are built in and it will automatically configure, but the drivers for the Calluna are not. The solution is to simply choose existing drivers, and select a Maxtor 170MB ATA drive and it should work fine.

PLATFORM: COMPAQ ELITE 4/50CX

ROM: 07/19/95

PC CARDS: CALLUNA 170MB HARD DRIVE, PN: CT170MC, SANDISK 10 MB FLASH ATA, PN: SDP5A-10

OPERATING SYSTEM: WINDOWS 3.1/DOS 6.2

CARD AND SOCKET SERVICES: 3.12

CONFIG.SYS

```
switches=/F
SHELL=C:\DOS\COMMAND.COM /P /E:1536
STACKS=9,256
DEVICE=C:\DOS\HIMEM.SYS
DEVICE=C:\DOS\EMM386.EXE NOEMS I=B000-B7FF X=D000-D4FF
DEVICEHIGH=C:\WINDOWS\CPQWIN\CPQCM.SYS
DOS=HIGH,UMB
REM *** Begin PCMCIA Drivers
REM Warning: Do not move, reorder, or delete any of these lines.
REM
;DEVICE=C:\CPQDOS\PCMSMIX.EXE
DEVICEHIGH=C:\CPQDOS\SSVLSI.EXE
DEVICEHIGH=C:\CPQDOS\CS.EXE
DEVICE=C:\CPQDOS\CSALLOC.EXE
DEVICEHIGH=C:\CPQDOS\ATADRV.EXE
;DEVICEHIGH=C:\CPQDOS\MTAA.EXE
;DEVICEHIGH=C:\CPQDOS\MTAB.EXE
;DEVICEHIGH=C:\CPQDOS\MTI1.EXE
;DEVICEHIGH=C:\CPQDOS\MTI2P.EXE
;DEVICEHIGH=C:\CPQDOS\MTSRAM.EXE
;DEVICEHIGH=C:\CPQDOS\MTDDRV.EXE
;DEVICEHIGH=C:\CPQDOS\DBLFLASH.EXE
;DEVICEHIGH=C:\CPQDOS\MS-FLASH.SYS
DEVICEHIGH=C:\CPQDOS\CARDID.EXE
REM *** End PCMCIA Drivers
BUFFERS=20
FILES=35
LASTDRIVE = Z
DEVICEHIGH=C:\CPQDOS\POWER.EXE
```

AUTOEXEC.BAT

```
@ECHO OFF
SET PATH=C:\CPQDOS;C:\;C:\DOS;C:\WINDOWS;;C:\WINDOWS\CPQWIN
SET LMOUSE=C:\MOUSE
LH C:\MOUSE\MOUSE
SET PROMPT=$PSG
SET TEMP=C:\WINDOWS\TEMP
C:\CPQDOS\HIBRN8.EXE
LH C:\DOS\SMARTDRV.EXE
SET NWLANGUAGE=ENGLISH
C:\WINDOWS\WIN
```

CARDID.INI

```
[Common]
;
; Common Information section created by Config
;
ComPort1=3F8
ComIRQ1=4
ComPort2=2F8
ComIRQ2=3
ComPort3=3e8
ComIRQ3=4
ComPort4=2E8
ComIRQ4=3
ComBySocket=Yes
ComBDAAbsolute=No
CARDID.INI-continued
```

FirstModem=2
SecondModem=2
ThirdModem=3
FourthModem=4
Audio=Yes
RingIndicate=No
Lan1Port=300
Lan1IRQ=5
Lan1MemoryBase1=c0
Lan1MemoryBase2=0
Lan2Port=310
Lan2IRQ=9
Lan2MemoryBase1=
Lan2MemoryBase2=
ATATryPrimary=No
ATATrySecondary=Yes
ATATryLinear=Yes
FastTokenRing=No
DetectNonCompliant=No
ContinueOnConfigFailure=No
BeepInDOS=Yes
BeepInWindows=Yes
GrabInitFile=Yes
InitBufferSize=512
UseEMS=No

[Libraries]

;
; The Libraries section contains references to any card libraries the user
; wishes to include. Libraries are searched in the specified order. Path
; names are relative to the directory containing CARDID.INI.

;
CardLib=canonfd.clb
CardLib=xirdual.clb
CardLib=xircom.clb
CardLib=tdkfan2.clb
CardLib=sundisk5.clb
CardLib=intellan.clb
CardLib=dlink.clb
CardLib=linksys.clb
CardLib=linksys2.clb
CardLib=socketea.clb
CardLib=ibmlan.clb
CardLib=ibmtok.clb
CardLib=ibm3270.clb
CardLib=proxim.clb
CardLib=cbdass.clb
CardLib=genmodem.clb
CardLib=genata.clb
CardLib=wd.clb

Configuration Notes:

Upon insertion the card should automatically be configured in DOS/Windows. The drive letter assigned will normally be D: or E:, but will depend on which slot the card is inserted. To verify what drive letter is assigned type CARDINFO and it will display information about the card including the driver letter assigned. In regards to Windows 95; the drivers for the SanDisk are built in and it will automatically configure, but the drivers for the Calluna are not. The solution is to simply choose existing drivers, and select a Maxtor 170MB ATA drive and it should work fine.

PLATFORM: COMPAQ LTE 5000

ROM: 09/19/95

PC CARDS: CALLUNA 170MB HARD DRIVE, PN: CT170MC, SANDISK 10 MB FLASH ATA, PN: SDP5A-10

OPERATING SYSTEM: WINDOWS 3.1/DOS 6.2

CARD AND SOCKET SERVICES: 3.14

CONFIG.SYS

```
DEVICE=C:\CPQDOS\MACHCHK.SYS 02A8 02B0 02BA 02CA
DEVICE=C:\DOS\HIMEM.SYS
DEVICE=C:\DOS\EMM386.exe NOEMS I=B000-B7FF X=C800-CBFF X=D100-D5FF X=E800-EFFF
COUNTRY=001,437,C:\DOS\COUNTRY.SYS
SHELL=C:\DOS\COMMAND.COM /P /E:1536
DOS=HIGH, UMB
FILES=35
BUFFERS=20,0
STACKS=9,256
DEVICEHIGH=C:\AUDIO_CD\TEAC_CDI.SYS /D:TEAC-CDI
LASTDRIVE=M
REM PC Card: Begin PC Card (PCMCIA) Drivers
REM **Warning: Do not move, reorder, or delete any of these lines. **
DEVICEHIGH=C:\CARDWIZ\SSCIRUS2.EXE
DEVICEHIGH=C:\CARDWIZ\CS.EXE /POLL:1
DEVICEHIGH=C:\CARDWIZ\CSALLOC.EXE
DEVICEHIGH=C:\CARDWIZ\ATADRV.EXE
DEVICEHIGH=C:\CARDWIZ\CARDID.EXE
REM PC Card: End PC Card(PCMCIA) Drives
```

AUTOEXEC.BAT

```
@ECHO OFF
C:\WINDOWS\VGAUTIL\winmode.exe t640=60 t800=60 t1024=87 t1280=87
SET NWLANGUAGE=ENGLISH
PATH C:\WINDOWS;C:\CPQDOS;C:\DOS;C:\AUDIO_CD;C:\CARDWIZ
PROMPT Sp$g
SET DIRCMD=/ogn
SET TEMP=C:\WINDOWS\TEMP
SET BLASTER=A220 D1 I5
SET LMOUSE=C:\MOUSE
SET MOUSE=C:\MOUSE
C:\MOUSE\MOUSE.EXE MEMU
C:\DOS\MSCDEX.EXE /D:TEAC-CDI /M:15
IF ERRORLEVEL 1 GOTO NO_CDROM
C:\AUDIO_CD\ESSVOL /V:15 /C:15
:NO_CDROM
IF NOT EXIST C:\CPQDOS\SAVEDONE.CPQ CALL SAVEALL /A
LH C:\DOS\SMARTDRV.EXE
C:\CPQDOS\0VMAKFIL
WIN
```

CARDID.INI

```
[Common]
;
; Common Information section created by Config
;
ComPort1=3F8
ComIRQ1=4
ComPort2=2F8
ComIRQ2=3
ComPort3=3E8
ComIRQ3=4
ComPort4=2E8
ComIRQ4=11
ComBySocket=No
ComBDAAbsolute=Yes
ComRollOverOn=No
CARDID.INI-continued
```

FirstModem=2
SecondModem=4
ThirdModem=2
FourthModem=4
Audio=Yes
RingIndicate=No
Suspend_Power=No
Lan1Port=330
Lan1IRQ=11
Lan1MemoryBase1=
Lan1MemoryBase2=
Lan2Port=310
Lan2IRQ=10
Lan2MemoryBase1=
Lan2MemoryBase2=
ATATryPrimary=No
ATATrySecondary=Yes
ATATryLinear=Yes
FastTokenRing=Yes
DetectNonCompliant=No
ContinueOnConfigFailure=No
BeepInDOS=Yes
BeepInWindows=Yes
GrabInitFile=Yes
InitBufferSize=512

[Libraries]

;
; The Libraries section contains references to any card libraries the user
; wishes to include. Libraries are searched in the specified order. Path
; names are relative to the directory containing CARDID.INI.
;

CardLib=xirdual.clb
CardLib=xircom.clb
CardLib=tdkklan2.clb
CardLib=sundisk5.clb
CardLib=intellan.clb
CardLib=dlink.clb
CardLib=linksys.clb
CardLib=linksys2.clb
CardLib=socketea.clb
CardLib=ibmlan.clb
CardLib=ibmtok.clb
CardLib=ibm3270.clb
CardLib=proxim.clb
CardLib=cbdass.clb
CardLib=genmodem.clb
CardLib=genata.clb
CardLib=wd.clb

Configuration Notes:

Upon insertion the card should automatically be configured in DOS/Windows. The drive letter assigned will normally be D: or E:, but will depend on which slot the card is inserted. To verify what drive letter is assigned type CARDINFO and it will display information about the card including the driver letter assigned. In regards to Windows 95; the drivers for the SanDisk are built in and it will automatically configure, but the drivers for the Calluna are not. The solution is to simply choose existing drivers, and select a Maxtor 170MB ATA drive and it should work fine.

AUDIO CARDS

PLATFORM: COMPAQ AERO 4/25

ROM: 07/19/95

PC CARD: NEW MEDIA WAVJAMMER, PN: NMC00166

OPERATING SYSTEM: WINDOWS 3.1/DOS 6.2

CARD AND SOCKET SERVICES: 1.25

CONFIG.SYS

```
SHELL=C:\DOS\COMMAND.COM /P /E:1536
STACKS=9,256
DEVICE=C:\DOS\HIMEM.SYS
DEVICE=C:\DOS\EMM386.EXE NOEMS X=D000-DFFF
DOS=UMB
REM *** Begin PCMCIA Drivers
REM Warning: Do not move, reorder, or delete any of these lines.
REM
DEVICE=C:\CPQDOS\PCMSMIX.EXE
DEVICEHIGH=C:\CPQDOS\SSVLSI.EXE
DEVICEHIGH=C:\CPQDOS\CS.EXE
DEVICE=C:\CPQDOS\CSALLOC.EXE
DEVICEHIGH=C:\CPQDOS\ATADRV.EXE /D:1
DEVICEHIGH=C:\CPQDOS\CARDID.EXE C:\CPQDOS\CARDID.INI
DEVICEHIGH=C:\CPQDOS\MEMDRV.EXE
;DEVICEHIGH=C:\CPQDOS\DBLFLASH.EXE
;DEVICEHIGH=C:\CPQDOS\MS-FLASH.SYS
REM *** End PCMCIA Drivers
DOS=HIGH
BUFFERS=20
FILES=35
DEVICEHIGH=C:\CPQDOS\POWER.EXE
REM *** Start of .WAVjammer Install ***
REM ** DEVICEHIGH=C:\NEWMEDIA\WAVJAMMR\WAVJAMMR.SYS
REM *** End of .WAVjammer Install ***
```

AUTOEXEC.BAT

```
@loadhigh C:\DOS\SHARE.EXE /I:500 /f:5100
SET PATH=C:\CPQDOS;C:\;C:\DOS;C:\WINDOWS;;C:\WINDOWS\CPQWIN
SET LMOUSE=C:\MOUSE
SET PROMPT=SP$G
SET TEMP=C:\WINDOWS\TEMP
C:\CPQDOS\HIBRN8.EXE
C:\DOS\SMARTDRV.EXE
LH C:\MOUSE\MOUSE SWAP
C:\CPQDOS\MODE.COM CO80
C:\WINDOWS\WIN
```

CARDID.INI

```
[Common]
;
; Common Information section created by Config
;
ComPort1=3F8
ComIRQ1=4
ComPort2=2F8
ComIRQ2=3
ComPort3=3E8
ComIRQ3=4
ComPort4=2E8
ComIRQ4=3
ComBySocket=Yes
ComBDAAbsolute=No
FirstModem=2
SecondModem=2
ThirdModem=3
```


CARDID.INI-continued

```
FourthModem=4
Audio=Yes
RingIndicate=No
Lan1Port=300
Lan1IRQ=5
Lan1MemoryBase1=D8
Lan1MemoryBase2=DC
Lan2Port=310
Lan2IRQ=10
Lan2MemoryBase1=D8
Lan2MemoryBase2=DC
ATATryPrimary=No
ATATrySecondary=Yes
ATATryLinear=Yes
FastTokenRing=Yes
DetectNonCompliant=No
ContinueOnConfigFailure=No
BeepInDOS=Yes
BeepInWindows=Yes
GrabInitFile=Yes
InitBufferSize=512
```

[Libraries]

```
;
; The Libraries section contains references to any card libraries the user
; wishes to include. Libraries are searched in the specified order. Path
; names are relative to the directory containing CARDID.INI.
;
CardLib=cardid.clb
```

Configuration Notes:

In DOS/Windows 3.1 you must install the drivers from DOS. It will not run the program from Windows, and on this platform the Express Setup was chosen. The software automatically assigned the resources WAV I/O 390, MIDI I/O 388, and IRQ 6. The software was installed first, removed floppy and inserted WavJammer and rebooted. The card configured and worked properly. The drivers for Win 95 are built in so the card should configure upon insertion.

PLATFORM: *COMPAQ CONCERTO*

ROM: *10/12/93*

PC CARD: *NEW MEDIA WAVJAMMER, PN: NMC00166*

OPERATING SYSTEM: *WINDOWS 3.1/DOS 6.2*

CARD AND SOCKET SERVICES: *1.25*

CONFIG.SYS

```
SHELL=C:\DOS\COMMAND.COM /P /E:1536
STACKS=9,256
DEVICE=C:\DOS\HIMEM.SYS
DEVICE=C:\DOS\EMM386.EXE NOEMS X=D000-DFFF
DOS=UMB
REM *** Begin PCMCIA Drivers
REM Warning: Do not move, reorder, or delete any of these lines.
REM
DEVICEHIGH=C:\CPQDOS\SSCIRRUS.EXE
DEVICEHIGH=C:\CPQDOS\CS.EXE
DEVICE=C:\CPQDOS\CSALLOC.EXE
DEVICEHIGH=C:\CPQDOS\ATADRV.EXE
DEVICEHIGH=C:\CPQDOS\CARDID.EXE C:\CPQDOS\CARDID.INI
DEVICEHIGH=C:\CPQDOS\MEMDRV.EXE
;DEVICEHIGH=C:\CPQDOS\DBLFLASH.EXE
;DEVICEHIGH=C:\CPQDOS\MS-FLASH.SYS
REM *** End PCMCIA Drivers
DOS=HIGH
BUFFERS=20
FILES=35
DEVICEHIGH=C:\CPQDOS\POWER.EXE
REM *** Start of .WAVjammer Install ***
DEVICEHIGH=C:\NEWMEDIA\WAVJAMMR\WAVJAMMR.SYS
REM *** End of .WAVjammer Install ***
```

AUTOEXEC.BAT

```
SET PATH=C:\CPQDOS;C:\;C:\DOS;C:\WINDOWS;;C:\WINDOWS\CPQWIN
SET LMOUSE=C:\MOUSE
SET PROMPT=$PSG
SET TEMP=C:\WINDOWS\TEMP
C:\CPQDOS\HIBRN8.EXE
C:\DOS\SMARTDRV.EXE
LH C:\MOUSE\MOUSE
C:\CPQDOS\MODE.COM CO80
C:\WINDOWS\WIN
```

CARDID.INI

```
[Common]
;
; Common Information section created by Config
;
ComPort1=3F8
ComIRQ1=4
ComPort2=2F8
ComIRQ2=3
ComPort3=3E8
ComIRQ3=4
ComPort4=2E8
ComIRQ4=3
ComBySocket=Yes
ComBDAAbsolute=No
FirstModem=2
SecondModem=2
ThirdModem=3
FourthModem=4
Audio=Yes
RingIndicate=No
CARDID.INI-continued
```

Lan1Port=300
Lan1IRQ=5
Lan1MemoryBase1=D8
Lan1MemoryBase2=DC
Lan2Port=310
Lan2IRQ=10
Lan2MemoryBase1=D8
Lan2MemoryBase2=DC
ATATryPrimary=No
ATATrySecondary=Yes
ATATryLinear=Yes
FastTokenRing=Yes
DetectNonCompliant=No
ContinueOnConfigFailure=No
BeepInDOS=Yes
BeepInWindows=Yes
GrabInitFile=Yes
InitBufferSize=512

[Libraries]

;
; The Libraries section contains references to any card libraries the user
; wishes to include. Libraries are searched in the specified order. Path
; names are relative to the directory containing CARDID.INI.
;
CardLib=cardid.clb

Configuration Notes:

In DOS/Windows 3.1 you must install the drivers from DOS. It will not run the program from Windows, and on this platform the Express Setup was chosen. The software automatically assigned the resources WAV I/O 390, MIDI I/O 388, and IRQ 6. The software was installed first, removed floppy and inserted WavJammer and rebooted. The card configured and worked properly. The drivers for Win 95 are built in so the card should configure upon insertion.

PLATFORM: COMPAQ CONTURA 400CX

ROM: 04/10/95

PC CARD: NEW MEDIA WAVJAMMER, PN: NMC00166

OPERATING SYSTEM: WINDOWS 3.1/DOS 6.2

CARD AND SOCKET SERVICES: 3.12

CONFIG.SYS

```
switches=/F
SHELL=C:\DOS\COMMAND.COM /P /E:1536
STACKS=9,256
DEVICE=C:\DOS\HIMEM.SYS
DEVICEHIGH=C:\WINDOWS\CPQWIN\CPQCM.SYS
DEVICE=C:\DOS\EMM386.EXE NOEMS I=B000-B7FF X=D000-D4FF
DOS=HIGH,UMB
REM *** Begin PCMCIA Drivers
REM Warning: Do not move, reorder, or delete any of these lines.
REM
;DEVICE=C:\CPQDOS\PCMSMIX.EXE
DEVICEHIGH=C:\CPQDOS\SSVLSI.EXE
DEVICEHIGH=C:\CPQDOS\CS.EXE
DEVICE=C:\CPQDOS\CSALLOC.EXE
;DEVICEHIGH=C:\CPQDOS\ATADRV.EXE
;DEVICEHIGH=C:\CPQDOS\MTAA.EXE
;DEVICEHIGH=C:\CPQDOS\MTAB.EXE
;DEVICEHIGH=C:\CPQDOS\MTI1.EXE
;DEVICEHIGH=C:\CPQDOS\MTI2P.EXE
;DEVICEHIGH=C:\CPQDOS\MTSRAM.EXE
;DEVICEHIGH=C:\CPQDOS\MTDDRV.EXE
;DEVICEHIGH=C:\CPQDOS\DBLFLASH.EXE
;DEVICEHIGH=C:\CPQDOS\MS-FLASH.SYS
DEVICEHIGH=C:\CPQDOS\CARDID.EXE
REM *** End PCMCIA Drivers
BUFFERS=20
FILES=35
DEVICEHIGH=C:\CPQDOS\EPPBIOS.SYS
;DEVICEHIGH=C:\CPQDOS\POWER.EXE
DEVICEHIGH=C:\CPQDOS\POWER.EXE
REM *** Start of .WAVjammer Install ***
DEVICEHIGH=C:\NEWMEDIA\WAVJAMMR\WAVJAMMR.SYS
REM *** End of .WAVjammer Install ***
```

AUTOEXEC.BAT

```
@loadhigh C:\DOS\SHARE.EXE /I:500 /f:5100
@ECHO OFF
SET PATH=C:\CPQDOS;C:\;C:\DOS;C:\WINDOWS;;C:\WINDOWS\CPQWIN
SET LMOUSE=C:\MOUSE
LH C:\MOUSE\MOUSE
SET PROMPT=$PSG
SET TEMP=C:\WINDOWS\TEMP
C:\CPQDOS\HIBRN8.EXE
LH C:\DOS\SMARTDRV.EXE
C:\WINDOWS\WIN
```

CARDID.INI

```
[Common]
;
; Common Information section created by Config
;
ComPort1=3F8
ComIRQ1=4
ComPort2=2F8
ComIRQ2=3
ComPort3=3e8
ComIRQ3=4
CARDID.INI-continued
```

ComPort4=2E8
ComIRQ4=3
ComBySocket=Yes
ComBDAAbsolute=No
FirstModem=2
SecondModem=2
ThirdModem=3
FourthModem=4
Audio=Yes
RingIndicate=No
Lan1Port=300
Lan1IRQ=5
Lan1MemoryBase1=
Lan1MemoryBase2=
Lan2Port=310
Lan2IRQ=9
Lan2MemoryBase1=
Lan2MemoryBase2=
ATATryPrimary=No
ATATrySecondary=Yes
ATATryLinear=Yes
FastTokenRing=Yes
DetectNonCompliant=No
ContinueOnConfigFailure=No
BeepInDOS=Yes
BeepInWindows=Yes
GrabInitFile=Yes
InitBufferSize=512
UseEMS=No

[Libraries]

;
; The Libraries section contains references to any card libraries the user
; wishes to include. Libraries are searched in the specified order. Path
; names are relative to the directory containing CARDID.INI.

;
CardLib=canonfd.clb
CardLib=xirdual.clb
CardLib=xircom.clb
CardLib=tdkklan2.clb
CardLib=sundisk5.clb
CardLib=intellan.clb
CardLib=dlink.clb
CardLib=linksys.clb
CardLib=linksys2.clb
CardLib=socketea.clb
CardLib=ibmlan.clb
CardLib=ibmtok.clb
CardLib=ibm3270.clb
CardLib=proxim.clb
CardLib=cbdas.clb
CardLib=genmodem.clb
CardLib=genata.clb
CardLib=wd.clb

Configuration Notes:

In DOS/Windows 3.1 you must install the drivers from DOS. It will not run the program from Windows, and on this platform the Express Setup was chosen. The software automatically assigned the resources WAV I/O 390, MIDI I/O 388, and IRQ 6. The software was installed first, removed floppy and inserted WavJammer and rebooted. The card configured and worked properly. The drivers for Win 95 are built in so the card should configure upon insertion.

PLATFORM: COMPAQ CONTURA 420C

ROM: 06/16/95

PC CARD: NEW MEDIA WAVJAMMER, PN: NMC00166

OPERATING SYSTEM: WINDOWS 3.1/DOS 6.2

CARD AND SOCKET SERVICES: 3.12

CONFIG.SYS

```
switches=/F
SHELL=C:\DOS\COMMAND.COM /P /E:1536
STACKS=9,256
DEVICE=C:\DOS\HIMEM.SYS
DEVICE=C:\DOS\EMM386.EXE NOEMS I=B000-B7FF X=D000-D4FF
DEVICEHIGH=C:\WINDOWS\CPQWIN\CPQCM.SYS
DOS=HIGH,UMB
REM *** Begin PCMCIA Drivers
REM Warning: Do not move, reorder, or delete any of these lines.
REM
;DEVICE=C:\CPQDOS\PCSMIX.EXE
DEVICEHIGH=C:\CPQDOS\SSVLSI.EXE
DEVICEHIGH=C:\CPQDOS\CS.EXE
DEVICE=C:\CPQDOS\CSALLOC.EXE
;DEVICEHIGH=C:\CPQDOS\ATADRV.EXE
;DEVICEHIGH=C:\CPQDOS\MTAA.EXE
;DEVICEHIGH=C:\CPQDOS\MTAB.EXE
;DEVICEHIGH=C:\CPQDOS\MTI1.EXE
;DEVICEHIGH=C:\CPQDOS\MTI2P.EXE
;DEVICEHIGH=C:\CPQDOS\MTSRAM.EXE
;DEVICEHIGH=C:\CPQDOS\MTDDRV.EXE
;DEVICEHIGH=C:\CPQDOS\DBLFLASH.EXE
;DEVICEHIGH=C:\CPQDOS\MS-FLASH.SYS
DEVICEHIGH=C:\CPQDOS\CARDID.EXE
REM *** End PCMCIA Drivers
BUFFERS=20
FILES=35
DEVICEHIGH=C:\CPQDOS\EPPBIOS.SYS
REM *** Start of .WAVjammer Install ***
DEVICEHIGH=C:\NEWMEDIA\WAVJAMMR\WAVJAMMR.SYS
REM *** End of .WAVjammer Install ***
```

AUTOEXEC.BAT

```
@ECHO OFF
SET PATH=C:\CPQDOS;C:\;C:\DOS;C:\WINDOWS;;C:\WINDOWS\CPQWIN
SET LMOUSE=C:\MOUSE
LH C:\MOUSE\MOUSE
SET PROMPT=$PSG
SET TEMP=C:\WINDOWS\TEMP
C:\CPQDOS\HIBRN8.EXE
C:\DOS\SMARTDRV.EXE 2048 512
C:\WINDOWS\WIN
```

CARDID.INI

```
[Common]
:
; Common Information section created by Config
:
ComPort1=3F8
ComIRQ1=4
ComPort2=2F8
ComIRQ2=3
ComPort3=3e8
ComIRQ3=4
ComPort4=2E8
ComIRQ4=3
ComBySocket=Yes
CARDID.INI-continued
```

ComBDAAbsolute=No
FirstModem=2
SecondModem=2
ThirdModem=3
FourthModem=4
Audio=Yes
RingIndicate=No
Lan1Port=300
Lan1IRQ=5
Lan1MemoryBase1=
Lan1MemoryBase2=
Lan2Port=310
Lan2IRQ=9
Lan2MemoryBase1=
Lan2MemoryBase2=
ATATryPrimary=No
ATATrySecondary=Yes
ATATryLinear=Yes
FastTokenRing=Yes
DetectNonCompliant=No
ContinueOnConfigFailure=No
BeepInDOS=Yes
BeepInWindows=Yes
GrabInitFile=Yes
InitBufferSize=512
UseEMS=No

[Libraries]

;
; The Libraries section contains references to any card libraries the user
; wishes to include. Libraries are searched in the specified order. Path
; names are relative to the directory containing CARDID.INI.

;
CardLib=canonfd.clb
CardLib=xirdual.clb
CardLib=xircom.clb
CardLib=tdkklan2.clb
CardLib=sundisk5.clb
CardLib=intellan.clb
CardLib=dlink.clb
CardLib=linksys.clb
CardLib=linksys2.clb
CardLib=socketea.clb
CardLib=ibmlan.clb
CardLib=ibmtok.clb
CardLib=ibm3270.clb
CardLib=proxim.clb
CardLib=cbdass.clb
CardLib=genmodem.clb
CardLib=genata.clb
CardLib=wd.clb

Configuration Notes:

In DOS/Windows 3.1 you must install the drivers from DOS. It will not run the program from Windows, and on this platform the Express Setup was chosen. The software automatically assigned the resources WAV I/O 390, MIDI I/O 388, and IRQ 6. The software was installed first, removed floppy and inserted WavJammer and rebooted. The card configured and worked properly. The drivers for Win 95 are built in so the card should configure upon insertion.

PLATFORM: COMPAQ ELITE 4/75CXL

ROM: 07/19/95

PC CARD: NEW MEDIA WAVJAMMER, PN: NMC00166

OPERATING SYSTEM: WINDOWS 3.1/DOS 6.2

CARD AND SOCKET SERVICES: 3.12

CONFIG.SYS

```
switches=/F
SHELL=C:\DOS\COMMAND.COM /P /E:1536
STACKS=9,256
DEVICE=C:\DOS\HIMEM.SYS
DEVICE=C:\DOS\EMM386.EXE NOEMS I=B000-B7FF X=D000-D4FF
DEVICEHIGH=C:\WINDOWS\CPQWIN\CPQCM.SYS
DOS=HIGH,UMB
REM *** Begin PCMCIA Drivers
REM Warning: Do not move, reorder, or delete any of these lines.
REM
;DEVICE=C:\CPQDOS\PCMSMIX.EXE
DEVICEHIGH=C:\CPQDOS\SSVLSI.EXE
DEVICEHIGH=C:\CPQDOS\CS.EXE
DEVICE=C:\CPQDOS\CSALLOC.EXE
;DEVICEHIGH=C:\CPQDOS\ATADRV.EXE
;DEVICEHIGH=C:\CPQDOS\MTAA.EXE
;DEVICEHIGH=C:\CPQDOS\MTAB.EXE
;DEVICEHIGH=C:\CPQDOS\MTI1.EXE
;DEVICEHIGH=C:\CPQDOS\MTI2P.EXE
;DEVICEHIGH=C:\CPQDOS\MTSRAM.EXE
;DEVICEHIGH=C:\CPQDOS\MTDDRV.EXE
;DEVICEHIGH=C:\CPQDOS\DBLFLASH.EXE
;DEVICEHIGH=C:\CPQDOS\MS-FLASH.SYS
DEVICEHIGH=C:\CPQDOS\CARDID.EXE
REM *** End PCMCIA Drivers
BUFFERS=20
FILES=35
LASTDRIVE = Z
DEVICEHIGH=C:\CPQDOS\POWER.EXE
REM *** Start of .WAVjammer Install ***
DEVICEHIGH=C:\NEWMEDIA\WAVJAMMR\WAVJAMMR.SYS
REM *** End of .WAVjammer Install ***
```

AUTOEXEC.BAT

```
@ECHO OFF
SET PATH=C:\CPQDOS;C:\;C:\DOS;C:\WINDOWS;;C:\WINDOWS\CPQWIN
SET LMOUSE=C:\MOUSE
LH C:\MOUSE\MOUSE
SET PROMPT=$PSG
SET TEMP=C:\WINDOWS\TEMP
C:\CPQDOS\HIBRN8.EXE
LH C:\DOS\SMARTDRV.EXE
SET NWLANGUAGE=ENGLISH
C:\WINDOWS\WIN
```

CARDID.INI

```
[Common]
;
; Common Information section created by Config
;
ComPort1=3F8
ComIRQ1=4
ComPort2=2F8
ComIRQ2=3
ComPort3=3e8
ComIRQ3=4
ComPort4=2E8
CARDID.INI-continued
```

ComIRQ4=3
ComBySocket=Yes
ComBDAAbsolute=No
FirstModem=2
SecondModem=2
ThirdModem=3
FourthModem=4
Audio=Yes
RingIndicate=No
Lan1Port=300
Lan1IRQ=5
Lan1MemoryBase1=
Lan1MemoryBase2=
Lan2Port=310
Lan2IRQ=9
Lan2MemoryBase1=
Lan2MemoryBase2=
ATATryPrimary=No
ATATrySecondary=Yes
ATATryLinear=Yes
FastTokenRing=Yes
DetectNonCompliant=No
ContinueOnConfigFailure=No
BeepInDOS=Yes
BeepInWindows=Yes
GrabInitFile=Yes
InitBufferSize=512
UseEMS=No

[Libraries]

;
; The Libraries section contains references to any card libraries the user
; wishes to include. Libraries are searched in the specified order. Path
; names are relative to the directory containing CARDID.INI.

;
CardLib=canonfd.clb
CardLib=xirdual.clb
CardLib=xircom.clb
CardLib=tdkklan2.clb
CardLib=sundisk5.clb
CardLib=intellan.clb
CardLib=dlink.clb
CardLib=linksys.clb
CardLib=linksys2.clb
CardLib=socketea.clb
CardLib=ibmlan.clb
CardLib=ibmtok.clb
CardLib=ibm3270.clb
CardLib=proxim.clb
CardLib=cbdass.clb
CardLib=genmodem.clb
CardLib=genata.clb
CardLib=wd.clb

Configuration Notes:

In DOS/Windows 3.1 you must install the drivers from DOS. It will not run the program from Windows, and on this platform the Express Setup was chosen. The software automatically assigned the resources WAV I/O 390, MIDI I/O 388, and IRQ 6. The software was installed first, removed floppy and inserted WavJammer and rebooted. The card configured and worked properly. The drivers for Win 95 are built in so the card should configure upon insertion.

PLATFORM: *COMPAQ LTE 5100*

ROM: *07/29/95*

PC CARD: *NEW MEDIA WAVJAMMER, PN: NMC00166*

OPERATING SYSTEM: *WINDOWS 3.1/DOS 6.2*

CARD AND SOCKET SERVICES: *3.14*

CONFIG.SYS

```
DEVICE=C:\CPQDOS\MACHCHK.SYS 02A8 02B0 02BA 02CA
DEVICE=C:\DOS\HIMEM.SYS
DEVICEHIGH=C:\DOS\EMM386.EXE NOEMS I=B000-B7FF X=C800-CBFF X=D100-D5FF X=E800-EFFF
COUNTRY=001,437,C:\DOS\COUNTRY.SYS
SHELL=C:\DOS\COMMAND.COM /P /E:1536
DOS=HIGH, UMB
FILES=35
BUFFERS=20,0
STACKS=9,256
DEVICEHIGH=C:\AUDIO_CD\TEAC_CDI.SYS /D:TEAC-CDI
LASTDRIVE=M
REM PC Card: Begin PC Card (PCMCIA) Drivers
REM **Warning: Do not move, reorder, or delete any of these lines. **
DEVICEHIGH=C:\CARDWIZ\SSCIRUS2.EXE
DEVICEHIGH=C:\CARDWIZ\CS.EXE /POLL:1
DEVICEHIGH=C:\CARDWIZ\CSALLOC.EXE
DEVICEHIGH=C:\CARDWIZ\CARDID.EXE
REM PC Card: End PC Card (PCMCIA) Drives
REM *** Start of .WAVjammer Install ***
DEVICEHIGH=C:\NEWMEDIA\WAVJAMMR\WAVJAMMR.SYS
REM *** End of .WAVjammer Install ***
```

AUTOEXEC.BAT

```
@ECHO OFF
C:\WINDOWS\VGAUTIL\winmode.exe t640=60 t800=60 t1024=87 t1280=87
SET NWLANGUAGE=ENGLISH
PATH C:\WINDOWS;C:\CPQDOS;C:\DOS;C:\AUDIO_CD;C:\CARDWIZ
PROMPT $p$g
SET DIRCMD=/ogn
SET TEMP=C:\WINDOWS\TEMP
SET BLASTER=A220 D1 I5
SET LMOUSE=C:\MOUSE
SET MOUSE=C:\MOUSE
C:\MOUSE\MOUSE.EXE MEMU
C:\DOS\MSCDEX.EXE /D:TEAC-CDI /M:15
IF ERRORLEVEL 1 GOTO NO_CDROM
C:\AUDIO_CD\ESSVOL /V:15 /C:15
:NO_CDROM
LH C:\DOS\SMARTDRV.EXE
C:\CPQDOS\0VMAKFIL
IF NOT EXIST C:\CPQDOS\SAVEDONE.CPQ CALL SAVEALL /A
WIN
```

CARDID.INI

```
[Common]
;
; Common Information section created by Config
;
ComPort1=3F8
ComIRQ1=4
ComPort2=2F8
ComIRQ2=3
ComPort3=3E8
ComIRQ3=4
ComPort4=2E8
ComIRQ4=11
ComBySocket=No
ComBDAAbsolute=Yes
CARDID.INI-continued
```

```
ComRollOverOn=No
FirstModem=2
SecondModem=4
ThirdModem=2
FourthModem=4
Audio=Yes
RingIndicate=No
Suspend_Power=No
Lan1Port=330
Lan1IRQ=11
Lan1MemoryBase1=
Lan1MemoryBase2=
Lan2Port=310
Lan2IRQ=10
Lan2MemoryBase1=
Lan2MemoryBase2=
ATATryPrimary=No
ATATrySecondary=Yes
ATATryLinear=Yes
FastTokenRing=Yes
DetectNonCompliant=No
ContinueOnConfigFailure=No
BeepInDOS=Yes
BeepInWindows=Yes
GrabInitFile=Yes
InitBufferSize=512
```

[Libraries]

```
;  
; The Libraries section contains references to any card libraries the user  
; wishes to include. Libraries are searched in the specified order. Path  
; names are relative to the directory containing CARDID.INI.
```

```
;  
CardLib=xirdual.clb  
CardLib=xircom.clb  
CardLib=tdkklan2.clb  
CardLib=sundisk5.clb  
CardLib=intellan.clb  
CardLib=dlink.clb  
CardLib=linksys.clb  
CardLib=linksys2.clb  
CardLib=socketea.clb  
CardLib=ibmlan.clb  
CardLib=ibmtok.clb  
CardLib=ibm3270.clb  
CardLib=proxim.clb  
CardLib=cbdas.clb  
CardLib=genmodem.clb  
CardLib=genata.clb  
CardLib=wd.clb
```

Configuration Notes:

In DOS/Windows 3.1 you must install the drivers from DOS. It will not run the program from Windows, and on this platform the Express Setup was chosen. The software automatically assigned the resources WAV I/O 390, MIDI I/O 388, and IRQ 6. The software was installed first, removed floppy and inserted WavJammer and rebooted. The card configured and worked properly. The drivers for Win 95 are built in so the card should configure upon insertion.

COMBINATION CARDS

PLATFORM: COMPAQ AERO 4/33C

ROM: 07/19/95

PC CARD: NEW MEDIA TOAST 'N JAM (SCSI & AUDIO), PN: NMC00436

OPERATING SYSTEM: WINDOWS 3.1/DOS 6.2

CARD AND SOCKET SERVICES: 1.25

CONFIG.SYS

```
SHELL=C:\DOS\COMMAND.COM /P /E:1536
STACKS=9,256
DEVICE=C:\DOS\HIMEM.SYS
DEVICE=C:\DOS\EMM386.EXE NOEMS X=D000-DFFF
DOS=UMB
REM *** Begin PCMCIA Drivers
REM Warning: Do not move, reorder, or delete any of these lines.
REM
DEVICE=C:\CPQDOS\PCSMIX.EXE
DEVICEHIGH=C:\CPQDOS\SSVLSI.EXE
DEVICEHIGH=C:\CPQDOS\CS.EXE
DEVICE=C:\CPQDOS\CSALLOC.EXE
DEVICEHIGH=C:\CPQDOS\ATADRV.EXE /D:1
DEVICEHIGH=C:\CPQDOS\CARDID.EXE C:\CPQDOS\CARDID.INI
DEVICEHIGH=C:\CPQDOS\MEMDRV.EXE
;DEVICEHIGH=C:\CPQDOS\DBLFLASH.EXE
;DEVICEHIGH=C:\CPQDOS\MS-FLASH.SYS
REM *** End PCMCIA Drivers
DOS=HIGH
BUFFERS=20
FILES=35
DEVICEHIGH=C:\CPQDOS\POWER.EXE
REM *** Start of Multimedia Sound/SCSI Combo Install ***
DEVICEHIGH=C:\NEWMEDIA\NMCUTIL\NMCUTIL.SYS
DEVICEHIGH=C:\NEWMEDIA\NMCMMMS\MMSCLNT.EXE /irq=5
DEVICEHIGH=C:\NEWMEDIA\NMCMMMS\MMSASPL.SYS /E /V
REM *** End of Multimedia Sound/SCSI Combo Install ***
DEVICE=C:\CORELDRV\CUNI_ASP.SYS
DEVICE=C:\CORELDRV\UNI_ASP.SYS
LASTDRIVE=J
```

AUTOEXEC.BAT

```
@loadhigh C:\DOS\SHARE.EXE /I:500 /f:5100
SET PATH=C:\CPQDOS;C:\;C:\DOS;C:\WINDOWS;C:\WINDOWS\CPQWIN
SET LMOUSE=C:\MOUSE
SET PROMPT=$PSG
SET TEMP=C:\WINDOWS\TEMP
C:\CPQDOS\HIBRN8.EXE
C:\DOS\SMARTDRV.EXE
LH C:\MOUSE\MOUSE SWAP
C:\CPQDOS\MODE.COM C080
SET PATH=%PATH%;C:\CORELDRV
C:\CORELDRV\CORELCDX
C:\WINDOWS\WIN
```

CARDID.INI

```
[Common]
;
; Common Information section created by Config
;
ComPort1=3F8
ComIRQ1=4
ComPort2=2F8
ComIRQ2=3
ComPort3=3E8
ComIRQ3=4
CARDID.INI-continued
```

ComPort4=2E8
ComIRQ4=3
ComBySocket=Yes
ComBDAAbsolute=No
FirstModem=2
SecondModem=2
ThirdModem=3
FourthModem=4
Audio=Yes
RingIndicate=No
Lan1Port=300
Lan1IRQ=5
Lan1MemoryBase1=D8
Lan1MemoryBase2=DC
Lan2Port=310
Lan2IRQ=10
Lan2MemoryBase1=D8
Lan2MemoryBase2=DC
ATATryPrimary=No
ATATrySecondary=Yes
ATATryLinear=Yes
FastTokenRing=Yes
DetectNonCompliant=No
ContinueOnConfigFailure=No
BeepInDOS=Yes
BeepInWindows=Yes
GrabInitFile=Yes
InitBufferSize=512

[Libraries]

;
; The Libraries section contains references to any card libraries the user
; wishes to include. Libraries are searched in the specified order. Path
; names are relative to the directory containing CARDID.INI.
;
CardLib=cardid.clb

Configuration Notes:

In DOS/Windows ran installation program. Resources used were IRQ 5 and I/O 340, and the software made all necessary changes to files. The drivers for Windows 95 are built in so the card should be recognized and configured when inserted.

PLATFORM: *COMPAQ CONCERTO*

ROM: *10/12/93*

PC CARD: *NEW MEDIA TOAST 'N JAM (SCSI & AUDIO), PN: NMC00436*

OPERATING SYSTEM: *WINDOWS 3.1/DOS 6.2*

CARD AND SOCKET SERVICES: *1.25*

CONFIG.SYS

```
SHELL=C:\DOS\COMMAND.COM /P /E:1536
STACKS=9,256
DEVICE=C:\DOS\HIMEM.SYS
DEVICE=C:\DOS\EMM386.EXE NOEMS X=D000-DFFF
DOS=UMB
REM *** Begin PCMCIA Drivers
REM Warning: Do not move, reorder, or delete any of these lines.
REM
DEVICEHIGH=C:\CPQDOS\SSCIRRUS.EXE
DEVICEHIGH=C:\CPQDOS\CS.EXE
DEVICE=C:\CPQDOS\CSALLOC.EXE
DEVICEHIGH=C:\CPQDOS\ATADRV.EXE
DEVICEHIGH=C:\CPQDOS\CARDID.EXE C:\CPQDOS\CARDID.INI
;DEVICEHIGH=C:\CPQDOS\MEMDRV.EXE
;DEVICEHIGH=C:\CPQDOS\DBLFLASH.EXE
;DEVICEHIGH=C:\CPQDOS\MS-FLASH.SYS
REM *** End PCMCIA Drivers
DOS=HIGH
BUFFERS=20
FILES=35
;DEVICEHIGH=C:\CPQDOS\POWER.EXE
LASTDRIVE=Z
REM *** Start of Multimedia Sound/SCSI Combo Install ***
DEVICEHIGH=C:\NEWMEDIA\NMCUTIL\NMCUTIL.SYS
DEVICEHIGH=C:\NEWMEDIA\NMCMMMS\MMSCLNT.EXE
DEVICEHIGH=C:\NEWMEDIA\NMCMMMS\MMSASPL.SYS /E /V
REM *** End of Multimedia Sound/SCSI Combo Install ***
REM *** Start of Multimedia Sound/SCSI Combo Install ***
DEVICEHIGH=C:\NEWMEDIA\COREL2\UNI_ASP.SYS
DEVICEHIGH=C:\NEWMEDIA\COREL2\CUNI_ASP.SYS
REM *** End of Multimedia Sound/SCSI Combo Install ***
```

AUTOEXEC.BAT

```
REM *** Start of Multimedia Sound/SCSI Combo Install ***
C:\NEWMEDIA\COREL2\CORELCDX.COM
REM *** End of Multimedia Sound/SCSI Combo Install ***
SET PATH=C:\CPQDOS;C:\;C:\DOS;C:\WINDOWS;;C:\WINDOWS\CPQWIN
SET LMOUSE=C:\MOUSE
SET PROMPT=$PSG
SET TEMP=C:\WINDOWS\TEMP
C:\CPQDOS\HIBRN8.EXE
C:\DOS\SMARTDRV.EXE
LH C:\MOUSE\MOUSE
C:\CPQDOS\MODE.COM CO80
C:\WINDOWS\WIN
```

CARDID.INI

```
[Common]
;
; Common Information section created by Config
;
ComPort1=3F8
ComIRQ1=4
ComPort2=2F8
ComIRQ2=3
ComPort3=3E8
ComIRQ3=4
CARDID.INI-continued
```

ComPort4=2E8
ComIRQ4=3
ComBySocket=Yes
ComBDAAbsolute=No
FirstModem=2
SecondModem=2
ThirdModem=3
FourthModem=4
Audio=Yes
RingIndicate=No
Lan1Port=300
Lan1IRQ=5
Lan1MemoryBase1=D8
Lan1MemoryBase2=DC
Lan2Port=310
Lan2IRQ=10
Lan2MemoryBase1=D8
Lan2MemoryBase2=DC
ATATryPrimary=No
ATATrySecondary=Yes
ATATryLinear=Yes
FastTokenRing=Yes
DetectNonCompliant=No
ContinueOnConfigFailure=No
BeepInDOS=Yes
BeepInWindows=Yes
GrabInitFile=Yes
InitBufferSize=512

[Libraries]

;
; The Libraries section contains references to any card libraries the user
; wishes to include. Libraries are searched in the specified order. Path
; names are relative to the directory containing CARDID.INI.
;
CardLib=cardid.clb

Configuration Notes:

In DOS/Windows ran installation program. Resources used were IRQ 10 and I/O 340, and the software made all necessary changes to files. While in the base the resources used were IRQ 10 I/O 140. The drivers for Windows 95 are built in so the card should be recognized and configured when inserted.

PLATFORM: COMPAQ CONTURA 400CX

ROM: 04/10/95

PC CARD: NEW MEDIA TOAST 'N JAM (SCSI & AUDIO), PN: NMC00436

OPERATING SYSTEM: WINDOWS 3.1/DOS 6.2

CARD AND SOCKET SERVICES: 3.12

CONFIG.SYS

```
SHELL=C:\DOS\COMMAND.COM /P /E:1536
STACKS=9,256
DEVICE=C:\DOS\HIMEM.SYS
DEVICE=C:\DOS\EMM386.EXE NOEMS I=B000-B7FF X=D000-D4FF
DEVICEHIGH=C:\WINDOWS\CPQWIN\CPQCM.SYS
DOS=HIGH,UMB
REM *** Begin PCMCIA Drivers
REM Warning: Do not move, reorder, or delete any of these lines.
REM
;DEVICE=C:\CPQDOS\PCMSMIX.EXE
;DEVICEHIGH=C:\CPQDOS\SSVLSI.EXE
;DEVICEHIGH=C:\CPQDOS\CS.EXE
;DEVICE=C:\CPQDOS\CSALLOC.EXE
;DEVICEHIGH=C:\CPQDOS\ATADRV.EXE
;DEVICEHIGH=C:\CPQDOS\MTAA.EXE
;DEVICEHIGH=C:\CPQDOS\MTAB.EXE
;DEVICEHIGH=C:\CPQDOS\MTI1.EXE
;DEVICEHIGH=C:\CPQDOS\MTI2P.EXE
;DEVICEHIGH=C:\CPQDOS\MTSRAM.EXE
;DEVICEHIGH=C:\CPQDOS\MTDDRV.EXE
;DEVICEHIGH=C:\CPQDOS\DBLFLASH.EXE
;DEVICEHIGH=C:\CPQDOS\MS-FLASH.SYS
;DEVICEHIGH=C:\CPQDOS\CARDID.EXE
REM *** End PCMCIA Drivers
BUFFERS=20
FILES=35
;DEVICEHIGH=C:\CPQDOS\EPPBIOS.SYS
;DEVICEHIGH=C:\CPQDOS\POWER.EXE
REM *** Start of Multimedia Sound/SCSI Combo Install ***
;DEVICEHIGH=C:\NEWMEDIA\NMCUTIL\NMCUTIL.SYS
;DEVICEHIGH=C:\NEWMEDIA\NMCMMMS\MMSCLNT.EXE
;DEVICEHIGH=C:\NEWMEDIA\NMCMMMS\MMSASPL.SYS /E /V
REM *** End of Multimedia Sound/SCSI Combo Install ***
REM *** Start of Multimedia Sound/SCSI Combo Install ***
;DEVICEHIGH=C:\NEWMEDIA\COREL2\UNI_ASP.SYS
;DEVICEHIGH=C:\NEWMEDIA\COREL2\CUNI_ASP.SYS
REM *** End of Multimedia Sound/SCSI Combo Install ***
```

AUTOEXEC.BAT

```
@loadhigh C:\DOS\SHARE.EXE /l:500 /f:5100
REM *** Start of Multimedia Sound/SCSI Combo Install ***
C:\NEWMEDIA\COREL2\CORELCDX.COM
REM *** End of Multimedia Sound/SCSI Combo Install ***
@ECHO OFF
SET PATH=C:\CPQDOS;C:\;C:\DOS;C:\WINDOWS;;C:\WINDOWS\CPQWIN
SET LMOUSE=C:\MOUSE
LH C:\MOUSE\MOUSE
SET PROMPT=$PSG
SET TEMP=C:\WINDOWS\TEMP
C:\CPQDOS\HIBRN8.EXE
LH C:\DOS\SMARTDRV.EXE
C:\WINDOWS\WIN
```

CARDID.INI

```
[Common]
;
; Common Information section created by Config
;
ComPort1=3F8
ComIRQ1=4
ComPort2=2F8
ComIRQ2=3
ComPort3=3e8
ComIRQ3=4
ComPort4=2E8
ComIRQ4=3
ComBySocket=Yes
ComBDAAbsolute=No
FirstModem=2
SecondModem=2
ThirdModem=3
FourthModem=4
Audio=Yes
RingIndicate=No
Lan1Port=300
Lan1IRQ=5
Lan1MemoryBase1=
Lan1MemoryBase2=
Lan2Port=310
Lan2IRQ=9
Lan2MemoryBase1=
Lan2MemoryBase2=
ATATryPrimary=No
ATATrySecondary=Yes
ATATryLinear=Yes
FastTokenRing=Yes
DetectNonCompliant=No
ContinueOnConfigFailure=No
BeepInDOS=Yes
BeepInWindows=Yes
GrabInitFile=Yes
InitBufferSize=512
UseEMS=No
```

```
[Libraries]
;
; The Libraries section contains references to any card libraries the user
; wishes to include. Libraries are searched in the specified order. Path
; names are relative to the directory containing CARDID.INI.
;
CardLib=canonfd.clb
CardLib=xirdual.clb
CardLib=xircom.clb
CardLib=tdkklan2.clb
CardLib=sundisk5.clb
CardLib=intellan.clb
CardLib=dlink.clb
CardLib=linksys.clb
CardLib=linksys2.clb
CardLib=socketea.clb
CardLib=ibmlan.clb
CardLib=ibmtok.clb
CardLib=ibm3270.clb
CardLib=proxim.clb
CardLib=cbdass.clb
CardLib=genmodem.clb
CardLib=genata.clb
CardLib=wd.clb
```

Configuration Notes:

In DOS/Windows ran installation program. Resources used were IRQ 9 and I/O 340, and the software made all necessary changes to files. The drivers for Windows 95 are built in so the card should be recognized and configured when inserted.

PLATFORM: COMPAQ CONTURA 420C

ROM: 08/20/95

PC CARD: NEW MEDIA TOAST 'N JAM (SCSI & AUDIO), PN: NMC00436

OPERATING SYSTEM: WINDOWS 3.1/DOS 6.2

CARD AND SOCKET SERVICES: 3.12

CONFIG.SYS

```
switches=/F
SHELL=C:\DOS\COMMAND.COM /P /E:1536
STACKS=9,256
DEVICE=C:\DOS\HIMEM.SYS
DEVICE=C:\DOS\EMM386.EXE NOEMS I=B000-B7FF X=D000-D4FF
DEVICEHIGH=C:\WINDOWS\CPQWIN\CPQCM.SYS
DOS=HIGH,UMB
REM *** Begin PCMCIA Drivers
REM Warning: Do not move, reorder, or delete any of these lines.
REM
;DEVICE=C:\CPQDOS\PCMSMIX.EXE
DEVICEHIGH=C:\CPQDOS\SSVLSI.EXE
DEVICEHIGH=C:\CPQDOS\CS.EXE
DEVICE=C:\CPQDOS\CSALLOC.EXE
;DEVICEHIGH=C:\CPQDOS\ATADRV.EXE
;DEVICEHIGH=C:\CPQDOS\MTAA.EXE
;DEVICEHIGH=C:\CPQDOS\MTAB.EXE
;DEVICEHIGH=C:\CPQDOS\MTI1.EXE
;DEVICEHIGH=C:\CPQDOS\MTI2P.EXE
;DEVICEHIGH=C:\CPQDOS\MTSRAM.EXE
;DEVICEHIGH=C:\CPQDOS\MTDDRV.EXE
;DEVICEHIGH=C:\CPQDOS\DBLFLASH.EXE
;DEVICEHIGH=C:\CPQDOS\MS-FLASH.SYS
DEVICEHIGH=C:\CPQDOS\CARDID.EXE
REM *** End PCMCIA Drivers
BUFFERS=20
FILES=35
DEVICEHIGH=C:\CPQDOS\EPPBIOS.SYS
REM *** Start of Multimedia Sound/SCSI Combo Install ***
DEVICEHIGH=C:\NEWMEDIA\NMCUTIL\NMCUTIL.SYS
DEVICEHIGH=C:\NEWMEDIA\NMCMMMS\MMSCLNT.EXE
DEVICEHIGH=C:\NEWMEDIA\NMCMMMS\MMSASPL.SYS /V /Y
REM *** End of Multimedia Sound/SCSI Combo Install ***
REM *** Start of Multimedia Sound/SCSI Combo Install ***
DEVICEHIGH=C:\NEWMEDIA\COREL2\UNI_ASP.SYS
DEVICEHIGH=C:\NEWMEDIA\COREL2\CUNI_ASP.SYS
REM *** End of Multimedia Sound/SCSI Combo Install ***
```

AUTOEXEC.BAT

```
@ECHO OFF
SET PATH=C:\CPQDOS;C:\;C:\DOS;C:\WINDOWS;;C:\WINDOWS\CPQWIN
SET LMOUSE=C:\MOUSE
LH C:\MOUSE\MOUSE
SET PROMPT=$PSG
SET TEMP=C:\WINDOWS\TEMP
C:\CPQDOS\HIBRN8.EXE
C:\DOS\SMARTDRV.EXE 2048 512
C:\NEWMEDIA\COREL2\CORELCDX.COM
WIN
```

CARDID.INI

```
[Common]
;
; Common Information section created by Config
;
ComPort1=3F8
ComIRQ1=4
ComPort2=2F8
ComIRQ2=3
ComPort3=3e8
ComIRQ3=4
ComPort4=2E8
ComIRQ4=3
ComBySocket=Yes
ComBDAAbsolute=No
FirstModem=2
SecondModem=2
ThirdModem=3
FourthModem=4
Audio=Yes
RingIndicate=No
Lan1Port=300
Lan1IRQ=5
Lan1MemoryBase1=
Lan1MemoryBase2=
Lan2Port=310
Lan2IRQ=9
Lan2MemoryBase1=
Lan2MemoryBase2=
ATATryPrimary=No
ATATrySecondary=Yes
ATATryLinear=Yes
FastTokenRing=Yes
DetectNonCompliant=No
ContinueOnConfigFailure=No
BeepInDOS=Yes
BeepInWindows=Yes
GrabInitFile=Yes
InitBufferSize=512
UseEMS=No
```

```
[Libraries]
;
; The Libraries section contains references to any card libraries the user
; wishes to include. Libraries are searched in the specified order. Path
; names are relative to the directory containing CARDID.INI.
;
CardLib=canonfd.clb
CardLib=xirdual.clb
CardLib=xircom.clb
CardLib=tdkklan2.clb
CardLib=sundisk5.clb
CardLib=intellan.clb
CardLib=dlink.clb
CardLib=linksys.clb
CardLib=linksys2.clb
CardLib=socketea.clb
CardLib=ibmlan.clb
CardLib=ibmtok.clb
CardLib=ibm3270.clb
CardLib=proxim.clb
CardLib=cbdas.clb
CardLib=genmodem.clb
CardLib=genata.clb
CardLib=wd.clb
```

Configuration Notes:

In DOS/Windows ran installation program. Resources used were IRQ 9 and I/O 340, and the software made all necessary changes to files. The drivers for Windows 95 are built in so the card should be recognized and configured when inserted.

PLATFORM: *COMPAQ ELITE 4/50CX*

ROM: *07/19/95*

PC CARD: *NEW MEDIA TOAST 'N JAM (SCSI & AUDIO), PN: NMC00436*

OPERATING SYSTEM: *WINDOWS 3.1/DOS 6.2*

CARD AND SOCKET SERVICES: *3.12*

CONFIG.SYS

```
switches=/F
SHELL=C:\DOS\COMMAND.COM /P /E:1536
STACKS=9,256
DEVICE=C:\DOS\HIMEM.SYS /testmem:off
DEVICE=C:\DOS\EMM386.EXE NOEMS I=B000-B7FF X=D000-D4FF
DEVICEHIGH=C:\WINDOWS\CPQWIN\CPQCM.SYS
DOS=HIGH,UMB
REM *** Begin PCMCIA Drivers
REM Warning: Do not move, reorder, or delete any of these lines.
REM
;DEVICE=C:\CPQDOS\PCMSMIX.EXE
DEVICEHIGH=C:\CPQDOS\SSVLSI.EXE
DEVICEHIGH=C:\CPQDOS\CS.EXE
DEVICE=C:\CPQDOS\CSALLOC.EXE
;DEVICEHIGH=C:\CPQDOS\ATADRV.EXE
;DEVICEHIGH=C:\CPQDOS\MTAA.EXE
;DEVICEHIGH=C:\CPQDOS\MTAB.EXE
;DEVICEHIGH=C:\CPQDOS\MTI1.EXE
;DEVICEHIGH=C:\CPQDOS\MTI2P.EXE
;DEVICEHIGH=C:\CPQDOS\MTSRAM.EXE
;DEVICEHIGH=C:\CPQDOS\MTDDRV.EXE
;DEVICEHIGH=C:\CPQDOS\DBLFLASH.EXE
;DEVICEHIGH=C:\CPQDOS\MS-FLASH.SYS
DEVICEHIGH=C:\CPQDOS\CARDID.EXE
REM *** End PCMCIA Drivers
BUFFERS=20
FILES=35
LASTDRIVE = Z
REM *** Start of Multimedia Sound/SCSI Combo Install ***
DEVICEHIGH=C:\NEWMEDIA\NMCUTIL\NMCUTIL.SYS
DEVICEHIGH=C:\NEWMEDIA\NMCMMMS\MMSCLNT.EXE
DEVICEHIGH=C:\NEWMEDIA\NMCMMMS\MMSASPL.SYS /V /Y
REM *** End of Multimedia Sound/SCSI Combo Install ***
REM *** Start of Multimedia Sound/SCSI Combo Install ***
DEVICEHIGH=C:\NEWMEDIA\COREL2\UNI_ASP.SYS
DEVICEHIGH=C:\NEWMEDIA\COREL2\CUNI_ASP.SYS
REM *** End of Multimedia Sound/SCSI Combo Install ***
DEVICEHIGH=C:\CPQDOS\POWER.EXE
```

AUTOEXEC.BAT

```
@ECHO OFF
SET PATH=C:\CPQDOS;C:\;C:\DOS;C:\WINDOWS;;C:\WINDOWS\CPQWIN
SET LMOUSE=C:\MOUSE
LH C:\MOUSE\MOUSE
SET PROMPT=St SP&G
SET TEMP=C:\WINDOWS\TEMP
C:\CPQDOS\HIBRN8.EXE
LH C:\DOS\SMARTDRV.EXE /f 2048 1024
SET NWLANGUAGE=ENGLISH
REM *** Start of Multimedia Sound/SCSI Combo Install ***
C:\NEWMEDIA\COREL2\CORELCDX.COM
REM *** End of Multimedia Sound/SCSI Combo Install ***
```

CARDID.INI

```
[Common]
;
; Common Information section created by Config
;
ComPort1=3F8
ComIRQ1=4
ComPort2=2F8
ComIRQ2=3
ComPort3=3e8
ComIRQ3=4
ComPort4=2E8
ComIRQ4=3
ComBySocket=Yes
ComBDAAbsolute=No
FirstModem=2
SecondModem=2
ThirdModem=3
FourthModem=4
Audio=Yes
RingIndicate=No
Lan1Port=300
Lan1IRQ=5
Lan1MemoryBase1=
Lan1MemoryBase2=
Lan2Port=310
Lan2IRQ=9
Lan2MemoryBase1=
Lan2MemoryBase2=
ATATryPrimary=No
ATATrySecondary=Yes
ATATryLinear=Yes
FastTokenRing=Yes
DetectNonCompliant=No
ContinueOnConfigFailure=No
BeepInDOS=Yes
BeepInWindows=Yes
GrabInitFile=Yes
InitBufferSize=512
UseEMS=No
```

```
[Libraries]
;
; The Libraries section contains references to any card libraries the user
; wishes to include. Libraries are searched in the specified order. Path
; names are relative to the directory containing CARDID.INI.
;
CardLib=canonfd.clb
CardLib=xirdual.clb
CardLib=xircom.clb
CardLib=tdkklan2.clb
CardLib=sundisk5.clb
CardLib=intellan.clb
CardLib=dlink.clb
CardLib=linksys.clb
CardLib=linksys2.clb
CardLib=socketea.clb
CardLib=ibmlan.clb
CardLib=ibmtok.clb
CardLib=ibm3270.clb
CardLib=proxim.clb
CardLib=cbdas.clb
CardLib=genmodem.clb
CardLib=genata.clb
CardLib=wd.clb
```

Configuration Notes:

In DOS/Windows ran installation program. Resources used were IRQ 9 and I/O 340, and the software made all necessary changes to files. The drivers for Windows 95 are built in so the card should be recognized and configured when inserted.

PLATFORM: *COMPAQ LTE 5000*

ROM: *09/19/95*

PC CARD: *NEW MEDIA TOAST 'N JAM (SCSI & AUDIO), PN: NMC00436*

OPERATING SYSTEM: *WINDOWS 3.1/DOS 6.2*

CARD AND SOCKET SERVICES: *3.14*

CONFIG.SYS

```
DEVICE=C:\CPQDOS\MACHCHK.SYS 02A8 02B0 02BA 02CA
DEVICE=C:\DOS\HIMEM.SYS
DEVICE=C:\DOS\EMM386.exe NOEMS I=B000-B7FF X=C800-CBFF X=D100-D5FF X=E800-EFFF
COUNTRY=001,437,C:\DOS\COUNTRY.SYS
SHELL=C:\DOS\COMMAND.COM /P /E:1536
DOS=HIGH,UMB
FILES=35
BUFFERS=20,0
STACKS=9,256
DEVICEHIGH=C:\AUDIO_CD\TEAC_CDI.SYS /D:TEAC-CDI
LASTDRIVE=M
REM PC Card: Begin PC Card (PCMCIA) Drivers
REM **Warning: Do not move, reorder, or delete any of these lines. **
DEVICEHIGH=C:\CARDWIZ\SSCIRUS2.EXE
DEVICEHIGH=C:\CARDWIZ\CS.EXE /POLL:1
DEVICEHIGH=C:\CARDWIZ\CSALLOC.EXE
DEVICEHIGH=C:\CARDWIZ\CARDID.EXE
REM PC Card: End PC Card(PCMCIA) Drives
REM *** Start of Multimedia Sound/SCSI Combo Install ***
DEVICEHIGH=C:\NEWMEDIA\NMCUTIL\NMCUTIL.SYS
DEVICEHIGH=C:\NEWMEDIA\NMCMMMS\MMSCLNT.EXE /NOMIDI
DEVICEHIGH=C:\NEWMEDIA\NMCMMMS\MMSASPL.SYS /E /V
REM *** End of Multimedia Sound/SCSI Combo Install ***
REM *** Start of Multimedia Sound/SCSI Combo Install ***
DEVICEHIGH=C:\NEWMEDIA\COREL2\UNI_ASP.SYS
DEVICEHIGH=C:\NEWMEDIA\COREL2\CUNI_ASP.SYS
REM *** End of Multimedia Sound/SCSI Combo Install ***
```

AUTOEXEC.BAT

```
@ECHO OFF
C:\WINDOWS\VGAUTIL\winmode.exe t640=60 t800=60 t1024=87 t1280=87
SET NWLANGUAGE=ENGLISH
PATH C:\WINDOWS;C:\CPQDOS;C:\DOS;C:\AUDIO_CD;C:\CARDWIZ
PROMPT $p$g
SET DIRCMD=/ogn
SET TEMP=C:\WINDOWS\TEMP
SET BLASTER=A220 D1 15
SET LMOUSE=C:\MOUSE
SET MOUSE=C:\MOUSE
C:\MOUSE\MOUSE.EXE MEMU
IF ERRORLEVEL 1 GOTO NO_CDROM
C:\AUDIO_CD\ESSVOL /V:15 /C:15
:NO_CDROM
REM *** Start of Multimedia Sound/SCSI Combo Install ***
C:\NEWMEDIA\COREL2\CORELCDX.COM
REM *** End of Multimedia Sound/SCSI Combo Install ***
LH C:\DOS\SMARTDRV.EXE
C:\CPQDOS\0VMAKFIL
IF NOT EXIST C:\CPQDOS\SAVEDONE.CPQ CALL SAVEALL /A
WIN
```

CARDID.INI

```
[Common]
;
; Common Information section created by Config
;
ComPort1=3F8
ComIRQ1=4
ComPort2=2F8
ComIRQ2=3
ComPort3=3E8
ComIRQ3=4
ComPort4=2E8
ComIRQ4=11
ComBySocket=No
ComBDAAbsolute=Yes
ComRollOverOn=No
FirstModem=2
SecondModem=4
ThirdModem=2
FourthModem=4
Audio=Yes
RingIndicate=No
Suspend_Power=No
Lan1Port=330
Lan1IRQ=11
Lan1MemoryBase1=
Lan1MemoryBase2=
Lan2Port=310
Lan2IRQ=10
Lan2MemoryBase1=
Lan2MemoryBase2=
ATATryPrimary=No
ATATrySecondary=Yes
ATATryLinear=Yes
FastTokenRing=Yes
DetectNonCompliant=No
ContinueOnConfigFailure=No
BeepInDOS=Yes
BeepInWindows=Yes
GrabInitFile=Yes
InitBufferSize=512
```

```
[Libraries]
;
; The Libraries section contains references to any card libraries the user
; wishes to include. Libraries are searched in the specified order. Path
; names are relative to the directory containing CARDID.INI.
;
CardLib=xirdual.clb
CardLib=xircom.clb
CardLib=tdkklan2.clb
CardLib=sundisk5.clb
CardLib=intellan.clb
CardLib=dlink.clb
CardLib=linksys.clb
CardLib=linksys2.clb
CardLib=socketea.clb
CardLib=ibmlan.clb
CardLib=ibmtok.clb
CardLib=ibm3270.clb
CardLib=proxim.clb
CardLib=cbdas.clb
CardLib=genmodem.clb
CardLib=genata.clb
CardLib=wd.clb
```

Configuration Notes:

In DOS/Windows ran installation program. Resources used were IRQ 9 and I/O 340, and the software made all necessary changes to files. The drivers for Windows 95 are built in so the card should be recognized and configured when inserted.

PLATFORM: COMPAQ AERO 4/33C

ROM: 07/19/95

PC CARD: XIRCOM CREDITCARD ETHERNET + 19.2 MODEM II, PN: CEM2-10BC

OPERATING SYSTEM: WINDOWS 3.1/DOS 6.2

NOS: NOVELL 3.12

CARD AND SOCKET SERVICES: 1.25

CONFIG.SYS

REM Xircom CreditCard Adapter --- Do Not Change Lines Below (MENU)

[menu]

menuitem=Xir_enet+modem, Load Xircom Drivers For Network Access

menuitem=Xircom_modem, Load Xircom Modem Drivers Only

menuitem=Nonet, Do Not Load Any Xircom Drivers

menucolor=15,0

[Xir_enet+modem]

[Xircom_modem]

[Nonet]

[common]

REM Xircom CreditCard Adapter --- Do Not Change Lines Above

SHELL=C:\DOS\COMMAND.COM /P /E:1536

STACKS=9,256

DEVICE=C:\DOS\HIMEM.SYS

DEVICE=C:\DOS\EMM386.EXE NOEMS X=D000-DFFF

DOS=UMB

REM *** Begin PCMCIA Drivers

REM Warning: Do not move, reorder, or delete any of these lines.

REM

DEVICE=C:\CPQDOS\PCSMIX.EXE

DEVICEHIGH=C:\CPQDOS\SSVLSI.EXE

DEVICEHIGH=C:\CPQDOS\CS.EXE

DEVICE=C:\CPQDOS\CSALLOC.EXE

DEVICEHIGH=C:\CPQDOS\ATADRV.EXE /D:1

DEVICEHIGH=C:\CPQDOS\CARDID.EXE C:\CPQDOS\CARDID.INI

DEVICEHIGH=C:\CPQDOS\MEMDRV.EXE

;DEVICEHIGH=C:\CPQDOS\DBLFLASH.EXE

;DEVICEHIGH=C:\CPQDOS\MS-FLASH.SYS

REM *** End PCMCIA Drivers

DOS=HIGH

BUFFERS=20

FILES=35

DEVICEHIGH=C:\CPQDOS\POWER.EXE

AUTOEXEC.BAT

@loadhigh C:\DOS\SHARE.EXE /I:500 /F:5100

SET PATH=C:\CPQDOS;C:\;C:\DOS;C:\WINDOWS; C:\WINDOWS\CPQWIN

SET LMOUSE=C:\MOUSE

SET PROMPT=\$PSG

SET TEMP=C:\WINDOWS\TEMP

C:\CPQDOS\HIBRN8.EXE

C:\DOS\SMARTDRV.EXE

LH C:\MOUSE\MOUSE SWAP

C:\CPQDOS\MODE.COM CO80

REM Xircom CreditCard Adapter --- Do Not Change Lines Below

@echo off

cls

goto %config%

:Xir_enet+modem

C:

cd C:\XIRCOM\CEM2\ODI

CXCFG DRIVER=ODI

LSL

CEM2ODI

IPXODI

AUTOEXEC.BAT-continued

```
NETX
F:
login
C:
cd \
goto common
:Xircom_modem
C:
cd C:\XIRCOM\CEM2\ODI
CXCFG
CM2DRIVE COM3 INTERRUPT=5 IOADDRESS=300 MEM=D2000
C:
cd \
goto common
:Nonet
:common
REM Xircom CreditCard Adapter --- Do Not Change Lines Above
REM Xircom CreditCard Adapter --- Do Not Change Lines Below (PATH)
PATH=%PATH%;C:\XIRCOM\CEM2\ODI
REM Xircom CreditCard Adapter --- Do Not Change Lines Above
c:\windows\win
```

NETWORK DRIVERS

| | | |
|--------------|--------|----------|
| LSL.COM | 18,315 | 08-17-94 |
| CEM2ODI.COM | 53,856 | 09-11-95 |
| IPXODI.COM | 30,247 | 10-07-93 |
| CM2DRIVE.COM | 24,084 | 04-13-95 |
| CXCFG.EXE | 29,632 | 09-06-95 |
| NETX.EXE | 78,654 | 11-17-93 |

NET.CFG

```
link driver cem2odi
frame ethernet_802.2
int 5
port 300
mem D2000
COM3
```

CARDID.INI

```
[Common]
;
; Common Information section created by Config
;
ComPort1=3F8
ComIRQ1=4
ComPort2=2F8
ComIRQ2=11
ComPort3=3E8
ComIRQ3=4
ComPort4=2E8
ComIRQ4=3
ComBySocket=Yes
ComBDAAbsolute=No
FirstModem=2
SecondModem=2
ThirdModem=3
FourthModem=4
Audio=Yes
RingIndicate=No
Lan1Port=300
Lan1IRQ=5
Lan1MemoryBase1=D8
Lan1MemoryBase2=DC
Lan2Port=310
Lan2IRQ=10
Lan2MemoryBase1=D8
Lan2MemoryBase2=DC
ATATryPrimary=No
ATATrySecondary=Yes
```

CARDID.INI-continued

```
ATATryLinear=Yes
FastTokenRing=Yes
DetectNonCompliant=No
ContinueOnConfigFailure=No
BeepInDOS=Yes
BeepInWindows=Yes
GrabInitFile=Yes
InitBufferSize=512
```

[Libraries]

```

;
; The Libraries section contains references to any card libraries the user
; wishes to include. Libraries are searched in the specified order. Path
; names are relative to the directory containing CARDID.INI.
;
CardLib=cardid.clb
```

Configuration Notes:

To install this card you must copy the installation and network driver diskette to your root directory. Insert card and run installation from Windows. During installation choose the default values, except change the frame type to 802.2 for Novell 3.12. The Windows 95 drivers are built in so the card should be recognized and configure upon insertion.

PLATFORM: *COMPAQ CONCERTO*

ROM: *10/12/93*

PC CARD: *XIRCOM CREDITCARD ETHERNET + 19.2 MODEM II, PN: CEM2-10BC*

OPERATING SYSTEM: *WINDOWS 3.1/DOS 6.2*

NOS: *NOVELL 3.12*

CARD AND SOCKET SERVICES: *1.25*

CONFIG.SYS

REM Xircom CreditCard Adapter --- Do Not Change Lines Below (MENU)

[menu]

menuitem=Xir_enet+modem, Load Xircom Drivers For Network Access

menuitem=Xircom_modem, Load Xircom Modem Drivers Only

menuitem=Nonet, Do Not Load Any Xircom Drivers

menucolor=15,0

[Xir_enet+modem]

[Xircom_modem]

[Nonet]

[common]

REM Xircom CreditCard Adapter --- Do Not Change Lines Above

SHELL=C:\DOS\COMMAND.COM /P /E:1536

STACKS=9,256

DEVICE=C:\DOS\HIMEM.SYS

DEVICE=C:\DOS\EMM386.EXE NOEMS X=D000-DFFF

DOS=UMB

REM *** Begin PCMCIA Drivers

REM Warning: Do not move, reorder, or delete any of these lines.

REM

DEVICEHIGH=C:\CPQDOS\SSCIRRUS.EXE

DEVICEHIGH=C:\CPQDOS\CS.EXE

DEVICE=C:\CPQDOS\CSALLOC.EXE

DEVICEHIGH=C:\CPQDOS\ATADRV.EXE

DEVICEHIGH=C:\CPQDOS\CARDID.EXE C:\CPQDOS\CARDID.INI

DEVICEHIGH=C:\CPQDOS\MEMDRV.EXE

;DEVICEHIGH=C:\CPQDOS\DBLFLASH.EXE

;DEVICEHIGH=C:\CPQDOS\MS-FLASH.SYS

REM *** End PCMCIA Drivers

DOS=HIGH

BUFFERS=20

FILES=35

DEVICEHIGH=C:\CPQDOS\POWER.EXE

AUTOEXEC.BAT

SET PATH=C:\CPQDOS;C:\;C:\DOS;C:\WINDOWS;;C:\WINDOWS\CPQWIN

SET LMOUSE=C:\MOUSE

SET PROMPT=\$P\$G

SET TEMP=C:\WINDOWS\TEMP

C:\CPQDOS\HIBRN8.EXE

C:\DOS\SMARTDRV.EXE

LH C:\MOUSE\MOUSE

C:\CPQDOS\MODE.COM CO80

REM Xircom CreditCard Adapter --- Do Not Change Lines Below

@echo off

cls

goto %config%

:Xir_enet+modem

c:

cd c:\xircom\cem2\odi

CXCFG DRIVER=ODI

LSL

CEM2ODI

IPXODI

NETX

AUTOEXEC.BAT-continued

```
H:
login
c:
cd \
goto common
:Xircom_modem
c:
cd c:\xircom\cem2\odi
CXCFG
CM2DRIVE COM3 INTERRUPT=5 IOADDRESS=300 MEM=D2000
c:
cd \
goto common
:Nonet
:common
REM Xircom CreditCard Adapter --- Do Not Change Lines Above
REM Xircom CreditCard Adapter --- Do Not Change Lines Below (PATH)
PATH=%PATH%;c:\xircom\cem2\odi
REM Xircom CreditCard Adapter --- Do Not Change Lines Above
```

NETWORK DRIVERS

| | | |
|--------------|--------|----------|
| LSL.COM | 18,315 | 08-17-94 |
| CEM2ODI.COM | 53,856 | 09-11-95 |
| IPXODI.COM | 30,247 | 10-07-93 |
| CM2DRIVE.COM | 24,084 | 04-13-95 |
| CXCFG.EXE | 29,632 | 09-06-95 |
| NETX.EXE | 78,654 | 11-17-93 |

NET.CFG

```
link driver cem2odi
frame ethernet_802.2
int 5
port 300
mem D2000
COM3
```

CARDID.INI

```
[Common]
;
; Common Information section created by Config
;
ComPort1=3F8
ComIRQ1=4
ComPort2=2F8
ComIRQ2=3
ComPort3=3E8
ComIRQ3=4
ComPort4=2E8
ComIRQ4=3
ComBySocket=Yes
ComBDAAbsolute=No
FirstModem=2
SecondModem=2
ThirdModem=3
FourthModem=4
Audio=Yes
RingIndicate=No
Lan1Port=300
Lan1IRQ=5
Lan1MemoryBase1=D8
Lan1MemoryBase2=DC
Lan2Port=310
Lan2IRQ=10
Lan2MemoryBase1=D8
Lan2MemoryBase2=DC
ATATryPrimary=No
ATATrySecondary=Yes
ATATryLinear=Yes
FastTokenRing=Yes
```

CARDID.INI-continued

DetectNonCompliant=No
ContinueOnConfigFailure=No
BeepInDOS=Yes
BeepInWindows=Yes
GrabInitFile=Yes
InitBufferSize=512

[Libraries]

;
; The Libraries section contains references to any card libraries the user
; wishes to include. Libraries are searched in the specified order. Path
; names are relative to the directory containing CARDID.INI.
;
CardLib=cardid.clb

Configuration Notes:

Insert card and run installation from Windows. During installation choose the default values, except change the frame type to 802.2 for Novell 3.12. The Windows 95 drivers are built in so the card should be recognized and configure upon insertion.

PLATFORM: COMPAQ CONTURA 400CX

ROM: 07/18/95

PC CARD: XIRCOM CREDITCARD ETHERNET + 19.2 MODEM II, PN: CEM2-10BC

OPERATING SYSTEM: WINDOWS 3.1/DOS 6.2

NOS: NOVELL 3.12

CARD AND SOCKET SERVICES: 3.12

CONFIG.SYS

REM Xircrom CreditCard Adapter --- Do Not Change Lines Below (MENU)

[menu]

menuitem=Xir_enet+modem, Load Xircrom CreditCard Ethernet+Modem Drivers
For Network Access

menuitem=Xircrom_modem, Load Xircrom Modem Drivers Only

menuitem=Nonet, Do Not Load Any Xircrom Drivers

menucolor=15,0

[Xir_enet+modem]

[Xircrom_modem]

[Nonet]

[common]

REM Xircrom CreditCard Adapter --- Do Not Change Lines Above

switches=/F

SHELL=C:\DOS\COMMAND.COM /P /E:1536

STACKS=9,256

DEVICE=C:\DOS\HIMEM.SYS

DEVICE=C:\DOS\EMM386.EXE NOEMS I=B000-B7FF X=D000-D4FF

DEVICEHIGH=C:\WINDOWS\CPQWIN\CPQCM.SYS

DOS=HIGH,UMB

REM *** Begin PCMCIA Drivers

REM Warning: Do not move, reorder, or delete any of these lines.

REM

;DEVICE=C:\CPQDOS\PCSMIX.EXE

DEVICEHIGH=C:\CPQDOS\SSVLSI.EXE

DEVICEHIGH=C:\CPQDOS\CS.EXE

DEVICE=C:\CPQDOS\CSALLOC.EXE

;DEVICEHIGH=C:\CPQDOS\ATADRV.EXE

;DEVICEHIGH=C:\CPQDOS\MTAA.EXE

;DEVICEHIGH=C:\CPQDOS\MTAB.EXE

;DEVICEHIGH=C:\CPQDOS\MTI1.EXE

;DEVICEHIGH=C:\CPQDOS\MTI2P.EXE

;DEVICEHIGH=C:\CPQDOS\MTSRAM.EXE

;DEVICEHIGH=C:\CPQDOS\MTDDRIV.EXE

;DEVICEHIGH=C:\CPQDOS\DBLFLASH.EXE

;DEVICEHIGH=C:\CPQDOS\MS-FLASH.SYS

DEVICEHIGH=C:\CPQDOS\CARDID.EXE

REM *** End PCMCIA Drivers

BUFFERS=20

FILES=35

DEVICEHIGH=C:\CPQDOS\EPPBIOS.SYS

DEVICEHIGH=C:\CPQDOS\POWER.EXE

AUTOEXEC.BAT

@ECHO OFF

SET PATH=C:\CPQDOS;C:\;C:\DOS;C:\WINDOWS;C:\WINDOWS\CPQWIN

SET LMOUSE=C:\MOUSE

LH C:\MOUSE\MOUSE

SET PROMPT=\$PSG

SET TEMP=C:\WINDOWS\TEMP

C:\CPQDOS\HIBRN8.EXE

LH C:\DOS\SMARTDRV.EXE

LH SHARE.EXE

REM Xircrom CreditCard Adapter --- Do Not Change Lines Below

@echo off

AUTOEXEC.BAT-continued

```
cls
goto %config%
:Xir_enet+modem
c:
cd c:\xircom\cem2\odi
CXCFG DRIVER=ODI
LSL
CEM2ODI
IPXODI
NETX
F:
login
c:
cd \
goto common
:Xircom_modem
c:
cd c:\xircom\cem2\odi
CXCFG
CM2DRIVE COM3 INTERRUPT=11 IOADDRESS=300 MEM=D2000
c:
cd \
goto common
:Nonet
:common
REM Xircom CreditCard Adapter --- Do Not Change Lines Above
REM Xircom CreditCard Adapter --- Do Not Change Lines Below (PATH)
PATH=%PATH%;c:\xircom\cem2\odi
REM Xircom CreditCard Adapter --- Do Not Change Lines Above
```

NETWORK DRIVERS

| | | |
|--------------|--------|----------|
| LSL.COM | 18,315 | 08-17-94 |
| CEM2ODI.COM | 53,856 | 09-11-95 |
| IPXODI.COM | 30,247 | 10-07-93 |
| CM2DRIVE.COM | 24,084 | 04-13-95 |
| CXCFG.EXE | 29,632 | 09-06-95 |
| NETX.EXE | 78,654 | 11-17-93 |

NET.CFG

```
link driver cem2odi
frame ethernet_802.2
int 5
port 300
mem D2000
COM2
```

CARDID.INI

```
[Common]
;
; Common Information section created by Config
;
ComPort1=3F8
ComIRQ1=4
ComPort2=2f8
ComIRQ2=11
ComPort3=3e8
ComIRQ3=4
ComPort4=2E8
ComIRQ4=3
ComBySocket=Yes
ComBDAAbsolute=No
FirstModem=2
SecondModem=2
ThirdModem=3
FourthModem=4
Audio=Yes
RingIndicate=No
Lan1Port=300
Lan1IRQ=5
```


CARDID.INI-continued

Lan1MemoryBase1=
Lan1MemoryBase2=
Lan2Port=310
Lan2IRQ=9
Lan2MemoryBase1=
Lan2MemoryBase2=
ATATryPrimary=No
ATATrySecondary=Yes
ATATryLinear=Yes
FastTokenRing=Yes
DetectNonCompliant=No
ContinueOnConfigFailure=No
BeepInDOS=Yes
BeepInWindows=Yes
GrabInitFile=Yes
InitBufferSize=512
UseEMS=No

[Libraries]

;
; The Libraries section contains references to any card libraries the user
; wishes to include. Libraries are searched in the specified order. Path
; names are relative to the directory containing CARDID.INI.

;
CardLib=canonfd.clb
CardLib=xirdual.clb
CardLib=xircom.clb
CardLib=tdkklan2.clb
CardLib=sundisk5.clb
CardLib=intellan.clb
CardLib=dlink.clb
CardLib=linksys.clb
CardLib=linksys2.clb
CardLib=socketea.clb
CardLib=ibmlan.clb
CardLib=ibmtok.clb
CardLib=ibm3270.clb
CardLib=proxim.clb
CardLib=caldas.clb
CardLib=genmodem.clb
CardLib=genata.clb
CardLib=wd.clb

Configuration Notes:

Insert card and run installation from Windows. During installation choose the default values, except change the frame type to 802.2 for Novell 3.12. The Windows 95 drivers are built in so the card should be recognized and configure upon insertion.

PLATFORM: COMPAQ CONTURA 420C

ROM: 08/20/95

PC CARD: XIRCOM CREDITCARD ETHERNET + 19.2 MODEM II, PN: CEM2-10BC

OPERATING SYSTEM: WINDOWS 3.1/DOS 6.2

NOS: NOVELL 3.12

CARD AND SOCKET SERVICES: 3.12

CONFIG.SYS

REM Xircom CreditCard Adapter --- Do Not Change Lines Below (MENU)

[menu]

menuitem=Xir_enet+modem, Load Xircom Drivers For Network Access

menuitem=Xircom_modem, Load Xircom Modem Drivers Only

menuitem=Nonet, Do Not Load Any Xircom Drivers

menucolor=15,0

[Xir_enet+modem]

[Xircom_modem]

[Nonet]

[common]

REM Xircom CreditCard Adapter --- Do Not Change Lines Above

switches=/F

SHELL=C:\DOS\COMMAND.COM /P /E:1536

STACKS=9,256

DEVICE=C:\DOS\HIMEM.SYS

DEVICE=C:\DOS\EMM386.EXE NOEMS I=B000-B7FF X=D000-D4FF

DEVICEHIGH=C:\WINDOWS\CPQWIN\CPQCM.SYS

DOS=HIGH,UMB

REM *** Begin PCMCIA Drivers

REM Warning: Do not move, reorder, or delete any of these lines.

REM

;DEVICE=C:\CPQDOS\PCMSMIX.EXE

DEVICEHIGH=C:\CPQDOS\SSVLSI.EXE

DEVICEHIGH=C:\CPQDOS\CS.EXE

DEVICE=C:\CPQDOS\CSALLOC.EXE

;DEVICEHIGH=C:\CPQDOS\ATADRV.EXE

;DEVICEHIGH=C:\CPQDOS\MTAA.EXE

;DEVICEHIGH=C:\CPQDOS\MTAB.EXE

;DEVICEHIGH=C:\CPQDOS\MTI1.EXE

;DEVICEHIGH=C:\CPQDOS\MTI2P.EXE

;DEVICEHIGH=C:\CPQDOS\MTSRAM.EXE

;DEVICEHIGH=C:\CPQDOS\MTDDRIV.EXE

;DEVICEHIGH=C:\CPQDOS\DBLFLASH.EXE

;DEVICEHIGH=C:\CPQDOS\MS-FLASH.SYS

DEVICEHIGH=C:\CPQDOS\CARDID.EXE

REM *** End PCMCIA Drivers

BUFFERS=20

FILES=35

DEVICEHIGH=C:\CPQDOS\EPPBIOS.SYS

AUTOEXEC.BAT

@ECHO OFF

SET PATH=C:\CPQDOS;C:\;C:\DOS;C:\WINDOWS;

SET LMOUSE=C:\MOUSE

LH C:\MOUSE\MOUSE

SET PROMPT=\$PSG

SET TEMP=C:\WINDOWS\TEMP

C:\CPQDOS\HIBRN8.EXE

C:\DOS\SMARTDRV.EXE 2048 512

REM Xircom CreditCard Adapter --- Do Not Change Lines Below

@echo off

cls

goto %config%

:Xir_enet+modem

C:

AUTOEXEC.BAT-continued

```
cd C:\XIRCOM\CEM2\ODI
CXCFG DRIVER=ODI
LSL
CEM2ODI
IPXODI
NETX
F:
login
C:
cd \
goto common
:Xircom_modem
C:
cd C:\XIRCOM\CEM2\ODI
CXCFG
CM2DRIVE COM3 INTERRUPT=5 IOADDRESS=300 MEM=D2000
C:
cd \
goto common
:Nonet
:common
REM Xircom CreditCard Adapter --- Do Not Change Lines Above
REM Xircom CreditCard Adapter --- Do Not Change Lines Below (PATH)
PATH=%PATH%;C:\XIRCOM\CEM2\ODI
REM Xircom CreditCard Adapter --- Do Not Change Lines Above
C:\WINDOWS\WIN
```

NETWORK DRIVERS

| | | |
|--------------|--------|----------|
| LSL.COM | 18,315 | 08-17-94 |
| CEM2ODI.COM | 53,856 | 09-11-95 |
| IPXODI.COM | 30,247 | 10-07-93 |
| CM2DRIVE.COM | 24,084 | 04-13-95 |
| CXCFG.EXE | 29,632 | 09-06-95 |
| NETX.EXE | 78,654 | 11-17-93 |

NET.CFG

```
link driver cem2odi
frame ethernet_802.2
mode io
int 5
port 300
mem D2000
COM3
```

CARDID.INI

```
[Common]
;
; Common Information section created by Config
;
ComPort1=3F8
ComIRQ1=4
ComPort2=2F8
ComIRQ2=3
ComPort3=3e8
ComIRQ3=5
ComPort4=2E8
ComIRQ4=3
ComBySocket=Yes
ComBDAAbsolute=No
FirstModem=2
SecondModem=2
ThirdModem=3
FourthModem=4
Audio=Yes
RingIndicate=No
Lan1Port=300
Lan1IRQ=5
Lan1MemoryBase1=
Lan1MemoryBase2=
```

CARDID.INI-continued

Lan2IRQ=9
Lan2MemoryBase1=
Lan2MemoryBase2=
ATATryPrimary=No
ATATrySecondary=Yes
ATATryLinear=Yes
FastTokenRing=Yes
DetectNonCompliant=No
ContinueOnConfigFailure=No
BeepInDOS=Yes
BeepInWindows=Yes
GrabInitFile=Yes
InitBufferSize=512
UseEMS=No

[Libraries]

;
; The Libraries section contains references to any card libraries the user
; wishes to include. Libraries are searched in the specified order. Path
; names are relative to the directory containing CARDID.INI.

;
CardLib=canonfd.clb
CardLib=xirdual.clb
CardLib=xircom.clb
CardLib=tdkklan2.clb
CardLib=sundisk5.clb
CardLib=intellan.clb
CardLib=dlink.clb
CardLib=linksys.clb
CardLib=linksys2.clb
CardLib=socketea.clb
CardLib=ibmlan.clb
CardLib=ibmtok.clb
CardLib=ibm3270.clb
CardLib=proxim.clb
CardLib=cbdass.clb
CardLib=genmodem.clb
CardLib=genata.clb
CardLib=wd.clb

Configuration Notes:

Insert card and run installation from Windows. During installation choose the default values, except change the frame type to 802.2 for Novell 3.12. The Windows 95 drivers are built in so the card should be recognized and configure upon insertion.

PLATFORM: COMPAQ ELITE 4/75CXL

ROM: 07/19/95

PC CARD: XIRCOM CREDITCARD ETHERNET + 19.2 MODEM II, PN: CEM2-10BC

OPERATING SYSTEM: WINDOWS 3.1/DOS 6.2

NOS: NOVELL 3.12

CARD AND SOCKET SERVICES: 3.12

CONFIG.SYS

REM Xircom CreditCard Adapter --- Do Not Change Lines Below (MENU)

[menu]

menuitem=Xir_enet+modem, Load Xircom CreditCard For Network Access

menuitem=Xircom_modem, Load Xircom Modem Drivers Only

menuitem=Nonet, Do Not Load Any Xircom Drivers

menucolor=15,0

[Xir_enet+modem]

[Xircom_modem]

[Nonet]

[common]

REM Xircom CreditCard Adapter --- Do Not Change Lines Above

switches=/F

SHELL=C:\DOS\COMMAND.COM /P /E:1536

STACKS=9,256

DEVICE=C:\DOS\HIMEM.SYS

DEVICE=C:\DOS\EMM386.EXE NOEMS I=B000-B7FF X=D000-D4FF

DEVICEHIGH=C:\WINDOWS\CPQWIN\CPQCM.SYS

DOS=HIGH,UMB

REM *** Begin PCMCIA Drivers

REM Warning: Do not move, reorder, or delete any of these lines.

REM

;DEVICE=C:\CPQDOS\PCSMIX.EXE

DEVICEHIGH=C:\CPQDOS\SSVLSI.EXE

DEVICEHIGH=C:\CPQDOS\CS.EXE

DEVICE=C:\CPQDOS\CSALLOC.EXE

;DEVICEHIGH=C:\CPQDOS\ATADRV.EXE

;DEVICEHIGH=C:\CPQDOS\MTAA.EXE

;DEVICEHIGH=C:\CPQDOS\MTAB.EXE

;DEVICEHIGH=C:\CPQDOS\MTI1.EXE

;DEVICEHIGH=C:\CPQDOS\MTI2P.EXE

;DEVICEHIGH=C:\CPQDOS\MTSRAM.EXE

;DEVICEHIGH=C:\CPQDOS\MTDDRIV.EXE

;DEVICEHIGH=C:\CPQDOS\DBLFLASH.EXE

;DEVICEHIGH=C:\CPQDOS\MS-FLASH.SYS

DEVICEHIGH=C:\CPQDOS\CARDID.EXE

REM *** End PCMCIA Drivers

BUFFERS=20

FILES=35

REM Xircom CreditCard Adapter --- Do Not Change Lines Below (LASTDRIVE)

REM LASTDRIVE = Z

REM Xircom CreditCard Adapter --- Do Not Change Lines Above

DEVICEHIGH=C:\CPQDOS\POWER.EXE

AUTOEXEC.BAT

@ECHO OFF

SET PATH=C:\CPQDOS;C:\;C:\DOS;C:\WINDOWS;;C:\WINDOWS\CPQWIN

SET LMOUSE=C:\MOUSE

LH C:\MOUSE\MOUSE

SET PROMPT=\$PSG

SET TEMP=C:\WINDOWS\TEMP

C:\CPQDOS\HIBRN8.EXE

LH C:\DOS\SMARTDRV.EXE

SET NWLANGUAGE=ENGLISH

REM Xircom CreditCard Adapter --- Do Not Change Lines Below

@echo off

AUTOEXEC.BAT-continued

```
cls
goto %config%
:Xir_enet+modem
C:
cd C:\XIRCOM\CEM2\ODI
CXCFG DRIVER=ODI
LSL
CEM2ODI
IPXODI
NETX
F:
login
C:
cd \
goto common
:Xircom_modem
C:
cd C:\XIRCOM\CEM2\ODI
CXCFG
CM2DRIVE COM3 INTERRUPT=5 IOADDRESS=300 MEM=D200
C:
cd \
goto common
:Nonet
:common
REM Xircom CreditCard Adapter --- Do Not Change Lines Above
REM Xircom CreditCard Adapter --- Do Not Change Lines Below (PATH)
PATH=%PATH%;C:\XIRCOM\CEM2\ODI
REM Xircom CreditCard Adapter --- Do Not Change Lines Above
C:\WINDOWS\WIN
```

NETWORK DRIVERS

| | | |
|--------------|--------|----------|
| LSL.COM | 18,315 | 08-17-94 |
| CEM2ODI.COM | 53,140 | 04-13-95 |
| IPXODI.COM | 30,247 | 10-07-93 |
| CM2DRIVE.COM | 24,084 | 04-13-95 |
| CXCFG.EXE | 26,480 | 04-11-95 |
| NETX.EXE | 78,654 | 11-17-93 |

NET.CFG

```
link driver cem2odi
frame ethernet_802.2
int 5
port 300
mem D200
COM3
```

CARDID.INI

```
[Common]
;
; Common Information section created by Config
;
ComPort1=3F8
ComIRQ1=4
ComPort2=2f8
ComIRQ2=5
ComPort3=3e8
ComIRQ3=4
ComPort4=2E8
ComIRQ4=3
ComBySocket=Yes
ComBDAAbsolute=No
FirstModem=2
SecondModem=2
ThirdModem=3
FourthModem=4
Audio=Yes
RingIndicate=No
Lan1Port=300
```

CARDID.INI-continued

```
Lan1IRQ=5
Lan1MemoryBase1=
Lan1MemoryBase2=
Lan2Port=310
Lan2IRQ=9
Lan2MemoryBase1=
Lan2MemoryBase2=
ATATryPrimary=No
ATATrySecondary=Yes
ATATryLinear=Yes
FastTokenRing=Yes
DetectNonCompliant=No
ContinueOnConfigFailure=No
BeepInDOS=Yes
BeepInWindows=Yes
GrabInitFile=Yes
InitBufferSize=512
UseEMS=No
```

[Libraries]

```
;
; The Libraries section contains references to any card libraries the user
; wishes to include. Libraries are searched in the specified order. Path
; names are relative to the directory containing CARDID.INI.
```

```
;
CardLib=canonfd.clb
CardLib=xirdual.clb
CardLib=xircom.clb
CardLib=tdkklan2.clb
CardLib=sundisk5.clb
CardLib=intellan.clb
CardLib=dlink.clb
CardLib=linksys.clb
CardLib=linksys2.clb
CardLib=socketea.clb
CardLib=ibmlan.clb
CardLib=ibmtok.clb
CardLib=ibm3270.clb
CardLib=proxim.clb
CardLib=cbdass.clb
CardLib=genmodem.clb
CardLib=genata.clb
CardLib=wd.clb
```

Configuration Notes:

Insert card and run installation from Windows. During installation choose the default values, except change the frame type to 802.2 for Novell 3.12. The internal network controller in the base was changed to IRQ 10 I/O 220 to avoid interruption of card in or out of the base. The drivers for Windows 95 are built in so the card should be recognized and configure upon insertion.

PLATFORM: *COMPAQ LTE 5000*

ROM: *09/19/95*

PC CARD: *XIRCOM CREDITCARD ETHERNET + 19.2 MODEM II, PN: CEM2-10BC*

OPERATING SYSTEM: *WINDOWS 3.1/DOS 6.2*

NOS: *NOVELL 3.12*

CARD AND SOCKET SERVICES: *3.14*

CONFIG.SYS

REM Xircom CreditCard Adapter --- Do Not Change Lines Below (MENU)

[menu]

menuitem=Xir_enet+modem, Load Xircom CreditCard Ethernet+Modem Drivers For Network Access

menuitem=Xircom_modem, Load Xircom Modem Drivers Only

menuitem=Nonet, Do Not Load Any Xircom Drivers

menucolor=15,0

[Xir_enet+modem]

[Xircom_modem]

[Nonet]

[common]

REM Xircom CreditCard Adapter --- Do Not Change Lines Above

DEVICE=C:\CPQDOS\MACHCHK.SYS 02A8 02B0 02BA 02CA

DEVICE=C:\DOS\HIMEM.SYS

DEVICE=C:\DOS\EMM386.exe NOEMS I=B000-B7FF X=C800-CBFF X=D100-D5FF X=E800-EFFF

COUNTRY=001,437,C:\DOS\COUNTRY.SYS

SHELL=C:\DOS\COMMAND.COM /P /E:1536

DOS=HIGH,UMB

FILES=35

BUFFERS=20,0

STACKS=9,256

DEVICEHIGH=C:\AUDIO_CD\TEAC_CDI.SYS /D:TEAC-CDI

LASTDRIVE=M

REM PC Card: Begin PC Card (PCMCIA) Drivers

REM **Warning: Do not move, reorder, or delete any of these lines. **

DEVICEHIGH=C:\CARDWIZ\SSCIRUS2.EXE

DEVICEHIGH=C:\CARDWIZ\CS.EXE /POLL:1

DEVICEHIGH=C:\CARDWIZ\CSALLOC.EXE

DEVICEHIGH=C:\CARDWIZ\CARDID.EXE

REM PC Card: End PC Card(PCMCIA) Drives

AUTOEXEC.BAT

@ECHO OFF

C:\WINDOWS\VGAUTIL\winmode.exe t640=60 t800=60 t1024=87 t1280=87

SET NWLANGUAGE=ENGLISH

PATH C:\WINDOWS;C:\CPQDOS;C:\DOS;C:\AUDIO_CD;C:\CARDWIZ

PROMPT Sp\$g

SET DIRCMD=/ogn

SET TEMP=C:\WINDOWS\TEMP

SET BLASTER=A220 D1 I5

SET LMOUSE=C:\MOUSE

SET MOUSE=C:\MOUSE

C:\MOUSE\MOUSE.EXE MEMU

C:\DOS\MSCDEX.EXE /D:TEAC-CDI /M:15

IF ERRORLEVEL 1 GOTO NO_CDROM

C:\AUDIO_CD\ESSVOL /V:15 /C:15

:NO_CDROM

LH C:\DOS\SMARTDRV.EXE

C:\CPQDOS\0VMAKFIL

IF NOT EXIST C:\CPQDOS\SAVEDONE.CPQ CALL SAVEALL /A

REM Xircom CreditCard Adapter --- Do Not Change Lines Below

@echo off

cls

goto %config%

:Xir_enet+modem

c:

AUTOEXEC.BAT-continued

```
cd c:\xircom\cem2\odi
CXCFG DRIVER=ODI
LSL
CEM2ODI
IPXODI
NETX
N:
login
c:
cd \
goto common
:Xircom_modem
c:
cd c:\xircom\cem2\odi
CXCFG
CM2DRIVE COM2 INTERRUPT=11 IOADDRESS=300 MEM=D2000
c:
cd \
goto common
:Nonet
:common
REM Xircom CreditCard Adapter --- Do Not Change Lines Above
REM Xircom CreditCard Adapter --- Do Not Change Lines Below (PATH)
PATH=%PATH%;c:\xircom\cem2\odi
REM Xircom CreditCard Adapter --- Do Not Change Lines Above
win
```

NETWORK DRIVERS

| | | |
|--------------|--------|----------|
| CEM2ODI.COM | 53,856 | 09-11-95 |
| CM2DRIVE.COM | 24,084 | 04-13-95 |
| IPXODI.COM | 30,247 | 10-07-93 |
| LSL.COM | 18,315 | 08-17-94 |
| CXCFG.EXE | 29,632 | 09-06-95 |
| NETX.EXE | 78,654 | 11-17-93 |

NET.CFG

```
link driver cem2odi
frame ethernet_802.2
int 11
port 300
mem D2000
COM2
```

CARDID.INI

```
[Common]
;
; Common Information section created by Config
;
ComPort1=3F8
ComIRQ1=4
ComPort2=2F8
ComIRQ2=3
ComPort3=3E8
ComIRQ3=4
ComPort4=2E8
ComIRQ4=11
ComBySocket=No
ComBDAAbsolute=Yes
ComRollOverOn=No
FirstModem=2
SecondModem=4
ThirdModem=2
FourthModem=4
Audio=Yes
RingIndicate=No
Suspend_Power=No
Lan1Port=330
Lan1IRQ=11
Lan1MemoryBase1=0
```

CARDID.INI-continued

```
Lan1MemoryBase2=D1
Lan2Port=310
Lan2IRQ=10
Lan2MemoryBase1=0
Lan2MemoryBase2=0
ATATryPrimary=No
ATATrySecondary=Yes
ATATryLinear=Yes
FastTokenRing=Yes
DetectNonCompliant=No
ContinueOnConfigFailure=No
BeepInDOS=Yes
BeepInWindows=Yes
GrabInitFile=Yes
InitBufferSize=512
FirstLan=1
SecondLan=2
```

[Libraries]

```

;
; The Libraries section contains references to any card libraries the user
; wishes to include. Libraries are searched in the specified order. Path
; names are relative to the directory containing CARDID.INI.
```

```

;
CardLib=xirdual.clb
CardLib=xircom.clb
CardLib=tdkklan2.clb
CardLib=sundisk5.clb
CardLib=intellan.clb
CardLib=dlink.clb
CardLib=linksys.clb
CardLib=linksys2.clb
CardLib=socketea.clb
CardLib=ibmlan.clb
CardLib=ibmtok.clb
CardLib=ibm3270.clb
CardLib=proxim.clb
CardLib=cbdass.clb
CardLib=genmodem.clb
CardLib=genata.clb
CardLib=wd.clb
```

Configuration Notes:

Insert card and run installation from Windows. During installation choose the IRQ 11 or the interrupt, COM2 for the modem, and change the frame type to 802.2 for Novell 3.12. The com port settings in Windows must also be changed to show the port association of COM2. In the Control Panel select ports, then select com 2, click Settings and then click Advanced. Change the IRQ to 11 and click OK, the system will now require you to restart Windows. When the system restarts Windows the modem should be functional. The Windows 95 drivers are built in so the card should be recognized and configure upon insertion.

EMULATION CARDS

PLATFORM: *COMPAQ AERO 4/33C*

ROM: *07/19/95*

PC CARD: *DCI 5250 PC CARD, PN: 4050*

OPERATING SYSTEM: *WINDOWS 3.1/DOS 6.2*

CARD AND SOCKET SERVICES: *1.25*

CONFIG.SYS

```
SHELL=C:\DOS\COMMAND.COM /P /E:1536
STACKS=9,256
DEVICE=C:\DOS\HIMEM.SYS
DEVICE=C:\DOS\EMM386.EXE NOEMS X=D000-DFFF
DOS=UMB
REM *** Begin PCMCIA Drivers
REM Warning: Do not move, reorder, or delete any of these lines.
REM
DEVICE=C:\CPQDOS\PCSMIX.EXE
DEVICEHIGH=C:\CPQDOS\SSVLSI.EXE
DEVICEHIGH=C:\CPQDOS\CS.EXE
DEVICE=C:\CPQDOS\CSALLOC.EXE
DEVICEHIGH=C:\CPQDOS\ATADRV.EXE /D:1
DEVICEHIGH=C:\CPQDOS\CARDID.EXE C:\CPQDOS\CARDID.INI
DEVICEHIGH=C:\CPQDOS\MEMDRV.EXE
;DEVICEHIGH=C:\CPQDOS\DBLFLASH.EXE
;DEVICEHIGH=C:\CPQDOS\MS-FLASH.SYS
REM *** End PCMCIA Drivers
DOS=HIGH
BUFFERS=20
FILES=35
DEVICEHIGH=C:\CPQDOS\POWER.EXE
REM *****
REM ** DCI 5250-PC CARD **
REM *****
DEVICE=C:\DCI_PC\PCDD5250.SYS
```

AUTOEXEC.BAT

```
@loadhigh C:\DOS\SHARE.EXE /I:500 /f:5100
SET PATH=C:\CPQDOS;C:\;C:\DOS;C:\WINDOWS; C:\WINDOWS\CPQWIN
SET LMOUSE=C:\MOUSE
SET PROMPT=$P$G
SET TEMP=C:\WINDOWS\TEMP
C:\CPQDOS\HIBRN8.EXE
C:\DOS\SMARTDRV.EXE
LH C:\MOUSE\MOUSE SWAP
C:\CPQDOS\MODE.COM CO80
REM *****
REM ** DCI 5250-PC CARD **
REM *****
SET ENB5250=C:\DCI_PC
```

CARDID.INI

```
[Common]
;
; Common Information section created by Config
;
ComPort1=3F8
ComIRQ1=4
ComPort2=2F8
ComIRQ2=3
ComPort3=3E8
ComIRQ3=4
ComPort4=2E8
ComIRQ4=3
ComBySocket=Yes
CARDID.INI-continued
```

ComBDAAbsolute=No
FirstModem=2
SecondModem=2
ThirdModem=3
FourthModem=4
Audio=Yes
RingIndicate=No
Lan1Port=300
Lan1IRQ=5
Lan1MemoryBase1=D8
Lan1MemoryBase2=DC
Lan2Port=310
Lan2IRQ=10
Lan2MemoryBase1=D8
Lan2MemoryBase2=DC
ATATryPrimary=No
ATATrySecondary=Yes
ATATryLinear=Yes
FastTokenRing=Yes
DetectNonCompliant=No
ContinueOnConfigFailure=No
BeepInDOS=Yes
BeepInWindows=Yes
GrabInitFile=Yes
InitBufferSize=512

[Libraries]

;
; The Libraries section contains references to any card libraries the user
; wishes to include. Libraries are searched in the specified order. Path
; names are relative to the directory containing CARDID.INI.
;
CardLib=cardid.clb

Configuration Notes:

PLATFORM: *COMPAQ CONCERTO*

ROM: *10/12/93*

PC CARD: *DCI 5250 PC CARD, PN: 4050*

OPERATING SYSTEM: *WINDOWS 3.1/DOS 6.2*

CARD AND SOCKET SERVICES: *1.25*

CONFIG.SYS

```
SHELL=C:\DOS\COMMAND.COM /P /E:1536
STACKS=9,256
DEVICE=C:\DOS\HIMEM.SYS
DEVICE=C:\DOS\EMM386.EXE NOEMS X=D000-DFFF
DOS=UMB
REM *** Begin PCMCIA Drivers
REM Warning: Do not move, reorder, or delete any of these lines.
REM
DEVICEHIGH=C:\CPQDOS\SSCIRRUS.EXE
DEVICEHIGH=C:\CPQDOS\CS.EXE
DEVICE=C:\CPQDOS\CSALLOC.EXE
;DEVICEHIGH=C:\CPQDOS\ATADRV.EXE
DEVICEHIGH=C:\CPQDOS\CARDID.EXE C:\CPQDOS\CARDID.INI
;DEVICEHIGH=C:\CPQDOS\MEMDRV.EXE
;DEVICEHIGH=C:\CPQDOS\DBLFLASH.EXE
;DEVICEHIGH=C:\CPQDOS\MS-FLASH.SYS
REM *** End PCMCIA Drivers
DOS=HIGH
BUFFERS=20
FILES=35
DEVICEHIGH=C:\CPQDOS\POWER.EXE
REM *****
REM ** DCI 5250-PC CARD **
REM *****
DEVICE=C:\DCI_PC\PCDD5250.SYS
```

AUTOEXEC.BAT

```
SET PATH=C:\CPQDOS;C:\;\;C:\DOS;C:\WINDOWS;;C:\WINDOWS\CPQWIN
SET LMOUSE=C:\MOUSE
SET PROMPT=$PSG
SET TEMP=C:\WINDOWS\TEMP
C:\CPQDOS\HIBRN8.EXE
C:\DOS\SMARTDRV.EXE
LH C:\MOUSE\MOUSE
C:\CPQDOS\MODE.COM CO80
REM *****
REM ** DCI 5250-PC CARD **
REM *****
SET ENB5250=C:\DCI_PC
```

CARDID.INI

```
[Common]
;
; Common Information section created by Config
;
ComPort1=3F8
ComIRQ1=4
ComPort2=2F8
ComIRQ2=3
ComPort3=3E8
ComIRQ3=4
ComPort4=2E8
ComIRQ4=3
ComBySocket=Yes
ComBDAAbsolute=No
FirstModem=2
SecondModem=2
CARDID.INI-continued
```

ThirdModem=3
FourthModem=4
Audio=Yes
RingIndicate=No
Lan1Port=300
Lan1IRQ=5
Lan1MemoryBase1=D8
Lan1MemoryBase2=DC
Lan2Port=310
Lan2IRQ=10
Lan2MemoryBase1=D8
Lan2MemoryBase2=DC
ATATryPrimary=No
ATATrySecondary=Yes
ATATryLinear=Yes
FastTokenRing=Yes
DetectNonCompliant=No
ContinueOnConfigFailure=No
BeepInDOS=Yes
BeepInWindows=Yes
GrabInitFile=Yes
InitBufferSize=512

[Libraries]

;
; The Libraries section contains references to any card libraries the user
; wishes to include. Libraries are searched in the specified order. Path
; names are relative to the directory containing CARDID.INI.
;
CardLib=cardid.clb

Configuration Notes:

PLATFORM: COMPAQ CONTURA 400CX

ROM: 07/18/95

PC CARD: DCI 5250 PC CARD, PN: 4050

OPERATING SYSTEM: WINDOWS 3.1/DOS 6.2

CARD AND SOCKET SERVICES: 3.12

CONFIG.SYS

```
switches=/F
SHELL=C:\DOS\COMMAND.COM /P /E:1536
STACKS=9,256
DEVICE=C:\DOS\HIMEM.SYS
DEVICE=C:\DOS\EMM386.EXE NOEMS I=B000-B7FF X=D000-D4FF
DEVICEHIGH=C:\WINDOWS\CPQWIN\CPQCM.SYS
DOS=HIGH,UMB
REM *** Begin PCMCIA Drivers
REM Warning: Do not move, reorder, or delete any of these lines.
REM
;DEVICE=C:\CPQDOS\PCSMIX.EXE
DEVICEHIGH=C:\CPQDOS\SSVLSI.EXE
DEVICEHIGH=C:\CPQDOS\CS.EXE
DEVICE=C:\CPQDOS\CSALLOC.EXE
;DEVICEHIGH=C:\CPQDOS\ATADRV.EXE
;DEVICEHIGH=C:\CPQDOS\MTAA.EXE
;DEVICEHIGH=C:\CPQDOS\MTAB.EXE
;DEVICEHIGH=C:\CPQDOS\MTI1.EXE
;DEVICEHIGH=C:\CPQDOS\MTI2P.EXE
;DEVICEHIGH=C:\CPQDOS\MTSRAM.EXE
;DEVICEHIGH=C:\CPQDOS\MTDDRV.EXE
;DEVICEHIGH=C:\CPQDOS\DBLFLASH.EXE
;DEVICEHIGH=C:\CPQDOS\MS-FLASH.SYS
DEVICEHIGH=C:\CPQDOS\CARDID.EXE
REM *** End PCMCIA Drivers
BUFFERS=20
FILES=35
DEVICEHIGH=C:\CPQDOS\EPPBIOS.SYS
DEVICEHIGH=C:\CPQDOS\POWER.EXE
REM *****
REM ** DCI 5250-PC CARD **
REM *****
DEVICE=C:\DCI_PC\PCDD5250.SYS
```

AUTOEXEC.BAT

```
@ECHO OFF
SET PATH=C:\CPQDOS;C:\;C:\DOS;C:\WINDOWS;;C:\WINDOWS\CPQWIN
SET LMOUSE=C:\MOUSE
LH C:\MOUSE\MOUSE
SET PROMPT=SPSG
SET TEMP=C:\WINDOWS\TEMP
C:\CPQDOS\HIBRN8.EXE
LH C:\DOS\SMARTDRV.EXE
LH SHARE.EXE
REM *****
REM ** DCI 5250-PC CARD **
REM *****
SET ENB5250=C:\DCI_PC
```

CARDID.INI

```
[Common]
;
; Common Information section created by Config
;
ComPort1=3F8
ComIRQ1=4
ComPort2=2F8
CARDID.INI-continued
```

ComIRQ2=3
ComPort3=3e8
ComIRQ3=4
ComPort4=2E8
ComIRQ4=3
ComBySocket=Yes
ComBDAAbsolute=No
FirstModem=2
SecondModem=2
ThirdModem=3
FourthModem=4
Audio=Yes
RingIndicate=No
Lan1Port=300
Lan1IRQ=5
Lan1MemoryBase1=
Lan1MemoryBase2=
Lan2Port=310
Lan2IRQ=9
Lan2MemoryBase1=
Lan2MemoryBase2=
ATATryPrimary=No
ATATrySecondary=Yes
ATATryLinear=Yes
FastTokenRing=Yes
DetectNonCompliant=No
ContinueOnConfigFailure=No
BeepInDOS=Yes
BeepInWindows=Yes
GrabInitFile=Yes
InitBufferSize=512
UseEMS=No

[Libraries]

;
; The Libraries section contains references to any card libraries the user
; wishes to include. Libraries are searched in the specified order. Path
; names are relative to the directory containing CARDID.INI.

;
CardLib=canonfd.clb
CardLib=xirdual.clb
CardLib=xircom.clb
CardLib=tdkfan2.clb
CardLib=sundisk5.clb
CardLib=intellan.clb
CardLib=dlink.clb
CardLib=linksys.clb
CardLib=linksys2.clb
CardLib=socketea.clb
CardLib=ibmlan.clb
CardLib=ibmtok.clb
CardLib=ibm3270.clb
CardLib=proxim.clb
CardLib=cbdass.clb
CardLib=genmodem.clb
CardLib=genata.clb
CardLib=wd.clb

Configuration Notes:

PLATFORM: COMPAQ CONTURA 420C

ROM: 08/20/95

PC CARD: DCI 5250 PC CARD, PN: 4050

OPERATING SYSTEM: WINDOWS 3.1/DOS 6.2

CARD AND SOCKET SERVICES: 3.12

CONFIG.SYS

```
SHELL=C:\DOS\COMMAND.COM /P /E:1536
STACKS=9,256
DEVICE=C:\DOS\HIMEM.SYS
DEVICE=C:\DOS\EMM386.EXE NOEMS I=B000-B7FF X=D000-D4FF
DEVICEHIGH=C:\WINDOWS\CPQWIN\CPQCM.SYS
DOS=HIGH,UMB
REM *** Begin PCMCIA Drivers
REM Warning: Do not move, reorder, or delete any of these lines.
REM
;DEVICE=C:\CPQDOS\PCMSMIX.EXE
DEVICEHIGH=C:\CPQDOS\SSVLSI.EXE
DEVICEHIGH=C:\CPQDOS\CS.EXE
DEVICE=C:\CPQDOS\CSALLOC.EXE
;DEVICEHIGH=C:\CPQDOS\ATADRV.EXE
;DEVICEHIGH=C:\CPQDOS\MTAA.EXE
;DEVICEHIGH=C:\CPQDOS\MTAB.EXE
;DEVICEHIGH=C:\CPQDOS\MTI1.EXE
;DEVICEHIGH=C:\CPQDOS\MTI2P.EXE
;DEVICEHIGH=C:\CPQDOS\MTSRAM.EXE
;DEVICEHIGH=C:\CPQDOS\MTDDRV.EXE
;DEVICEHIGH=C:\CPQDOS\DBLFLASH.EXE
;DEVICEHIGH=C:\CPQDOS\MS-FLASH.SYS
DEVICEHIGH=C:\CPQDOS\CARDID.EXE
REM *** End PCMCIA Drivers
BUFFERS=20
FILES=35
DEVICEHIGH=C:\CPQDOS\EPPBIOS.SYS
REM *****
REM ** DCI 5250-PC CARD **
REM *****
DEVICE=C:\DCI_PC\PCDD5250.SYS
```

AUTOEXEC.BAT

```
@ECHO OFF
SET PATH=C:\CPQDOS;C:\;C:\DOS;C:\WINDOWS;
SET LMOUSE=C:\MOUSE
LH C:\MOUSE\MOUSE
SET PROMPT=$PSG
SET TEMP=C:\WINDOWS\TEMP
C:\CPQDOS\HIBRN8.EXE
C:\DOS\SMARTDRV.EXE 2048 512
REM *****
REM ** DCI 5250-PC CARD **
REM *****
SET ENB5250=C:\DCI_PC
```

CARDID.INI

```
[Common]
;
; Common Information section created by Config
;
ComPort1=3F8
ComIRQ1=4
ComPort2=2F8
ComIRQ2=3
ComPort3=3e8
ComIRQ3=4
CARDID.INI-continued
```

ComPort4=2E8
ComIRQ4=3
ComBySocket=Yes
ComBDAAbsolute=No
FirstModem=2
SecondModem=2
ThirdModem=3
FourthModem=4
Audio=Yes
RingIndicate=No
Lan1Port=300
Lan1IRQ=5
Lan1MemoryBase1=
Lan1MemoryBase2=
Lan2Port=310
Lan2IRQ=9
Lan2MemoryBase1=
Lan2MemoryBase2=
ATATryPrimary=No
ATATrySecondary=Yes
ATATryLinear=Yes
FastTokenRing=Yes
DetectNonCompliant=No
ContinueOnConfigFailure=No
BeepInDOS=Yes
BeepInWindows=Yes
GrabInitFile=Yes
InitBufferSize=512
UseEMS=No

[Libraries]

;
; The Libraries section contains references to any card libraries the user
; wishes to include. Libraries are searched in the specified order. Path
; names are relative to the directory containing CARDID.INI.

;
CardLib=canonfd.clb
CardLib=xirdual.clb
CardLib=xircom.clb
CardLib=tdkklan2.clb
CardLib=sundisk5.clb
CardLib=intellan.clb
CardLib=dlink.clb
CardLib=linksys.clb
CardLib=linksys2.clb
CardLib=socketea.clb
CardLib=ibmlan.clb
CardLib=ibmtok.clb
CardLib=ibm3270.clb
CardLib=proxim.clb
CardLib=cbdass.clb
CardLib=genmodem.clb
CardLib=genata.clb
CardLib=wd.clb

Configuration Notes:

PLATFORM: COMPAQ ELITE 450CX

ROM: 07/19/95

PC CARD: DCI 5250 PC CARD, PN: 4050

OPERATING SYSTEM: WINDOWS 3.1/DOS 6.2

CARD AND SOCKET SERVICES: 3.12

CONFIG.SYS

```
switches=/F
SHELL=C:\DOS\COMMAND.COM /P /E:1536
STACKS=9,256
DEVICE=C:\DOS\HIMEM.SYS /TESTMEM:OFF
DEVICE=C:\DOS\EMM386.EXE NOEMS I=B000-B7FF X=D000-D4FF
DEVICEHIGH=C:\WINDOWS\CPQWIN\CPQCM.SYS
DOS=HIGH,UMB
REM *** Begin PCMCIA Drivers
REM Warning: Do not move, reorder, or delete any of these lines.
REM
;DEVICE=C:\CPQDOS\PCSMIX.EXE
DEVICEHIGH=C:\CPQDOS\SSVLSI.EXE
DEVICEHIGH=C:\CPQDOS\CS.EXE
DEVICE=C:\CPQDOS\CSALLOC.EXE
;DEVICEHIGH=C:\CPQDOS\ATADRV.EXE
;DEVICEHIGH=C:\CPQDOS\MTAA.EXE
;DEVICEHIGH=C:\CPQDOS\MTAB.EXE
;DEVICEHIGH=C:\CPQDOS\MTI1.EXE
;DEVICEHIGH=C:\CPQDOS\MTI2P.EXE
;DEVICEHIGH=C:\CPQDOS\MTSRAM.EXE
;DEVICEHIGH=C:\CPQDOS\MTDDRV.EXE
;DEVICEHIGH=C:\CPQDOS\DBLFLASH.EXE
;DEVICEHIGH=C:\CPQDOS\MS-FLASH.SYS
DEVICEHIGH=C:\CPQDOS\CARDID.EXE
REM *** End PCMCIA Drivers
BUFFERS=20
FILES=35
LASTDRIVE = Z
DEVICEHIGH=C:\CPQDOS\POWER.EXE
REM *****
REM ** DCI 5250-PC CARD **
REM *****
DEVICE=C:\DCI_PC\PCDD5250.SYS
```

AUTOEXEC.BAT

```
@ECHO OFF
SET PATH=C:\CPQDOS;C:\;C:\DOS;C:\WINDOWS;;C:\WINDOWS\CPQWIN
SET LMOUSE=C:\MOUSE
LH C:\MOUSE\MOUSE
SET PROMPT=St SP$G
SET TEMP=C:\WINDOWS\TEMP
C:\CPQDOS\HIBRN8.EXE
LH C:\DOS\SMARTDRV.EXE /f 2048 1024
SET NWLANGUAGE=ENGLISH
rem C:\WINDOWS\WIN
REM *****
REM ** DCI 5250-PC CARD **
REM *****
SET ENB5250=C:\DCI_PC
```

CARDID.INI

```
[Common]
;
; Common Information section created by Config
;
ComPort1=3F8
ComIRQ1=4
CARDID.INI-continued
```

ComPort2=2F8
ComIRQ2=3
ComPort3=3e8
ComIRQ3=4
ComPort4=2E8
ComIRQ4=3
ComBySocket=Yes
ComBDAAbsolute=No
FirstModem=2
SecondModem=2
ThirdModem=3
FourthModem=4
Audio=Yes
RingIndicate=No
Lan1Port=300
Lan1IRQ=5
Lan1MemoryBase1=c0
Lan1MemoryBase2=0
Lan2Port=310
Lan2IRQ=9
Lan2MemoryBase1=
Lan2MemoryBase2=
ATATryPrimary=No
ATATrySecondary=Yes
ATATryLinear=Yes
FastTokenRing=No
DetectNonCompliant=No
ContinueOnConfigFailure=No
BeepInDOS=Yes
BeepInWindows=Yes
GrabInitFile=Yes
InitBufferSize=512
UseEMS=No

[Libraries]

;
; The Libraries section contains references to any card libraries the user
; wishes to include. Libraries are searched in the specified order. Path
; names are relative to the directory containing CARDID.INI.
;

CardLib=canonfd.clb
CardLib=xirdual.clb
CardLib=xircom.clb
CardLib=tdkklan2.clb
CardLib=sundisk5.clb
CardLib=intellan.clb
CardLib=dlink.clb
CardLib=linksys.clb
CardLib=linksys2.clb
CardLib=socketea.clb
CardLib=ibmlan.clb
CardLib=ibmtok.clb
CardLib=ibm3270.clb
CardLib=proxim.clb
CardLib=cbdass.clb
CardLib=genmodem.clb
CardLib=genata.clb
CardLib=wd.clb

Configuration Notes:

PLATFORM: *COMPAQ LTE 5000*

ROM: *09/19/95*

PC CARD: *DCI 5250 PC CARD, PN: 4050*

OPERATING SYSTEM: *WINDOWS 3.1/DOS 6.2*

CARD AND SOCKET SERVICES: *3.14*

CONFIG.SYS

```
DEVICE=C:\CPQDOS\MACHCHK.SYS 02A8 02B0 02BA 02CA
DEVICE=C:\DOS\HIMEM.SYS
DEVICE=C:\DOS\EMM386.exe NOEMS I=B000-B7FF X=C800-CBFF X=D100-D5FF X=E800-EFFF
COUNTRY=001,437,C:\DOS\COUNTRY.SYS
SHELL=C:\DOS\COMMAND.COM /P /E:1536
DOS=HIGH,UMB
FILES=35
BUFFERS=20,0
STACKS=9,256
DEVICEHIGH=C:\AUDIO_CD\TEAC_CDI.SYS /D:TEAC-CDI
LASTDRIVE=M
REM PC Card: Begin PC Card (PCMCIA) Drivers
REM **Warning: Do not move, reorder, or delete any of these lines. **
DEVICEHIGH=C:\CARDWIZ\SSCIRUS2.EXE
DEVICEHIGH=C:\CARDWIZ\CS.EXE /POLL:1
DEVICEHIGH=C:\CARDWIZ\CSALLOC.EXE
DEVICEHIGH=C:\CARDWIZ\CARDID.EXE
REM PC Card: End PC Card(PCMCIA) Drives
REM *****
REM ** DCI 5250-PC CARD **
REM *****
DEVICE=C:\DCI_PC\PCDD5250.SYS
```

AUTOEXEC.BAT

```
@ECHO OFF
C:\WINDOWS\VGAUTIL\winmode.exe t640=60 t800=60 t1024=87 t1280=87
SET NWLANGUAGE=ENGLISH
PATH C:\WINDOWS;C:\CPQDOS;C:\DOS;C:\AUDIO_CD;C:\CARDWIZ
PROMPT $p$g
SET DIRCMD=/ogn
SET TEMP=C:\WINDOWS\TEMP
SET BLASTER=A220 D1 15
SET LMOUSE=C:\MOUSE
SET MOUSE=C:\MOUSE
C:\MOUSE\MOUSE.EXE MEMU
C:\DOS\MSCDEX.EXE /D:TEAC-CDI /M:15
IF ERRORLEVEL 1 GOTO NO_CDROM
C:\AUDIO_CD\ESSVOL /V:15 /C:15
:NO_CDROM
LH C:\DOS\SMARTDRV.EXE
C:\CPQDOS\0VMAKFIL
IF NOT EXIST C:\CPQDOS\SAVEDONE.CPQ CALL SAVEALL /A
REM *****
REM ** DCI 5250-PC CARD **
REM *****
SET ENB5250=C:\DCI_PC
```

CARDID.INI

```
[Common]
;
; Common Information section created by Config
;
ComPort1=3F8
ComIRQ1=4
ComPort2=2F8
ComIRQ2=3
ComPort3=3E8
CARDID.INI-continued
```

ComIRQ3=4
ComPort4=2E8
ComIRQ4=11
ComBySocket=No
ComBDAAbsolute=Yes
ComRollOverOn=No
FirstModem=2
SecondModem=4
ThirdModem=2
FourthModem=4
Audio=Yes
RingIndicate=No
Suspend_Power=No
Lan1Port=330
Lan1IRQ=11
Lan1MemoryBase1=
Lan1MemoryBase2=
Lan2Port=310
Lan2IRQ=10
Lan2MemoryBase1=
Lan2MemoryBase2=
ATATryPrimary=No
ATATrySecondary=Yes
ATATryLinear=Yes
FastTokenRing=Yes
DetectNonCompliant=No
ContinueOnConfigFailure=No
BeepInDOS=Yes
BeepInWindows=Yes
GrabInitFile=Yes
InitBufferSize=512

[Libraries]

;
; The Libraries section contains references to any card libraries the user
; wishes to include. Libraries are searched in the specified order. Path
; names are relative to the directory containing CARDID.INI.

;
CardLib=xirdual.clb
CardLib=xircom.clb
CardLib=tdkklan2.clb
CardLib=sundisk5.clb
CardLib=intellan.clb
CardLib=dlink.clb
CardLib=linksys.clb
CardLib=linksys2.clb
CardLib=socketea.clb
CardLib=ibmlan.clb
CardLib=ibmtok.clb
CardLib=ibm3270.clb
CardLib=proxim.clb
CardLib=cbdass.clb
CardLib=genmodem.clb
CardLib=genata.clb
CardLib=wd.clb

Configuration Notes:

MEMORY CARDS

PLATFORM: *COMPAQ AERO 4/33C*

ROM: *07/19/95*

PC CARD: *INTEL SERIES 2 20MB FLASH MEMORY CARD, PN: IMC020FLSA*

OPERATING SYSTEM: *WINDOWS 3.1/DOS 6.2*

CARD AND SOCKET SERVICES: *1.25*

CONFIG.SYS

```
SHELL=C:\DOS\COMMAND.COM /P /E:1536
STACKS=9,256
DEVICE=C:\DOS\HIMEM.SYS
DEVICE=C:\DOS\EMM386.EXE NOEMS X=D000-DFFF
DOS=UMB
REM *** Begin PCMCIA Drivers
REM Warning: Do not move, reorder, or delete any of these lines.
REM
DEVICE=C:\CPQDOS\PCSMIX.EXE
DEVICEHIGH=C:\CPQDOS\SSVLSI.EXE
DEVICEHIGH=C:\CPQDOS\CS.EXE
DEVICE=C:\CPQDOS\CSALLOC.EXE
DEVICEHIGH=C:\CPQDOS\ATADRV.EXE /D:1
DEVICEHIGH=C:\CPQDOS\CARDID.EXE C:\CPQDOS\CARDID.INI
DEVICEHIGH=C:\CPQDOS\MEMDRV.EXE
;DEVICEHIGH=C:\CPQDOS\DBLFLASH.EXE
DEVICEHIGH=C:\CPQDOS\MS-FLASH.SYS
REM *** End PCMCIA Drivers
DOS=HIGH
BUFFERS=20
FILES=35
DEVICEHIGH=C:\CPQDOS\POWER.EXE
```

AUTOEXEC.BAT

```
@loadhigh C:\DOS\SHARE.EXE /I:500 /F:5100
SET PATH=C:\CPQDOS;C:\;C:\DOS;C:\WINDOWS; C:\WINDOWS\CPQWIN
SET LMOUSE=C:\MOUSE
SET PROMPT=$PSG
SET TEMP=C:\WINDOWS\TEMP
C:\CPQDOS\HIBRN8.EXE
C:\DOS\SMARTDRV.EXE
LH C:\MOUSE\MOUSE SWAP
C:\CPQDOS\MODE.COM CO80
C:\WINDOWS\WIN
```

CARDID.INI

```
[Common]
;
; Common Information section created by Config
;
ComPort1=3F8
ComIRQ1=4
ComPort2=2F8
ComIRQ2=3
ComPort3=3E8
ComIRQ3=4
ComPort4=2E8
ComIRQ4=3
ComBySocket=Yes
ComBDAAbsolute=No
FirstModem=2
SecondModem=2
ThirdModem=3
FourthModem=4
Audio=Yes
RingIndicate=No
CARDID.INI-continued
```

Lan1Port=300
Lan1IRQ=5
Lan1MemoryBase1=D8
Lan1MemoryBase2=DC
Lan2Port=310
Lan2IRQ=10
Lan2MemoryBase1=D8
Lan2MemoryBase2=DC
ATATryPrimary=No
ATATrySecondary=Yes
ATATryLinear=Yes
FastTokenRing=Yes
DetectNonCompliant=No
ContinueOnConfigFailure=No
BeepInDOS=Yes
BeepInWindows=Yes
GrabInitFile=Yes
InitBufferSize=512

[Libraries]

;
; The Libraries section contains references to any card libraries the user
; wishes to include. Libraries are searched in the specified order. Path
; names are relative to the directory containing CARDID.INI.
;
CardLib=cardid.clb

Configuration Notes:

In Windows 3.1/DOS you must unremark the highlighted line in the Config.Sys. The Compaq Aero only supports MS-Flash, and does not support FTL with the supplied card and socket services. Windows 95 drivers do not correctly work, and you must load the real mode drivers in order for the card to function in Windows 95. You will use **MEMCARD** to partition and format the card.

PLATFORM: *COMPAQ CONCERTO*

ROM: *10/12/93*

PC CARD: *INTEL SERIES 2 20MB FLASH MEMORY CARD, PN: IMC020FLSA*

OPERATING SYSTEM: *WINDOWS 3.1/DOS 6.2*

CARD AND SOCKET SERVICES: *1.25*

CONFIG.SYS

```
SHELL=C:\DOS\COMMAND.COM /P /E:1536
STACKS=9,256
DEVICE=C:\DOS\HIMEM.SYS
DEVICE=C:\DOS\EMM386.EXE NOEMS X=D000-DFFF
DOS=UMB
REM *** Begin PCMCIA Drivers
REM Warning: Do not move, reorder, or delete any of these lines.
REM
DEVICEHIGH=C:\CPQDOS\SSCIRRUS.EXE
DEVICEHIGH=C:\CPQDOS\CS.EXE
DEVICE=C:\CPQDOS\CSALLOC.EXE
DEVICEHIGH=C:\CPQDOS\ATADRV.EXE
DEVICEHIGH=C:\CPQDOS\CARDID.EXE C:\CPQDOS\CARDID.INI
DEVICEHIGH=C:\CPQDOS\MEMDRV.EXE
;DEVICEHIGH=C:\CPQDOS\DBLFLASH.EXE
DEVICEHIGH=C:\CPQDOS\MS-FLASH.SYS
REM *** End PCMCIA Drivers
DOS=HIGH
BUFFERS=20
FILES=35
DEVICEHIGH=C:\CPQDOS\POWER.EXE
```

AUTOEXEC.BAT

```
SET PATH=C:\CPQDOS;C:\;C:\DOS;C:\WINDOWS;;C:\WINDOWS\CPQWIN
SET LMOUSE=C:\MOUSE
SET PROMPT=$P$G
SET TEMP=C:\WINDOWS\TEMP
C:\CPQDOS\HIBRN8.EXE
C:\DOS\SMARTDRV.EXE
LH C:\MOUSE\MOUSE
C:\CPQDOS\MODE.COM CO80
C:\WINDOWS\WIN
```

CARDID.INI

```
[Common]
;
; Common Information section created by Config
;
ComPort1=3F8
ComIRQ1=4
ComPort2=2F8
ComIRQ2=3
ComPort3=3E8
ComIRQ3=4
ComPort4=2E8
ComIRQ4=3
ComBySocket=Yes
ComBDAAbsolute=No
FirstModem=2
SecondModem=2
ThirdModem=3
FourthModem=4
Audio=Yes
RingIndicate=No
Lan1Port=300
Lan1IRQ=5
Lan1MemoryBase1=D8
CARDID.INI-continued
```

Lan1MemoryBase2=DC
Lan2Port=310
Lan2IRQ=10
Lan2MemoryBase1=D8
Lan2MemoryBase2=DC
ATATryPrimary=No
ATATrySecondary=Yes
ATATryLinear=Yes
FastTokenRing=Yes
DetectNonCompliant=No
ContinueOnConfigFailure=No
BeepInDOS=Yes
BeepInWindows=Yes
GrabInitFile=Yes
InitBufferSize=512

[Libraries]

;
; The Libraries section contains references to any card libraries the user
; wishes to include. Libraries are searched in the specified order. Path
; names are relative to the directory containing CARDID.INI.
;
CardLib=cardid.clb

Configuration Notes:

In Windows 3.1/DOS you must unremark the highlighted line in the Config.Sys. The Compaq Concerto only supports MS-Flash, and does not support FTL with the supplied card and socket services. Windows 95 drivers do not correctly work, and you must load the real mode drivers in order for the card to function in Windows 95. You will use **MEMCARD** to partition and format the card.

PLATFORM: COMPAQ CONTURA 400CX

ROM: 04/10/95

PC CARD: INTEL SERIES 2 20MB FLASH MEMORY CARD, PN: IMC020FLSA

OPERATING SYSTEM: WINDOWS 3.1/DOS 6.2

CARD AND SOCKET SERVICES: 3.12

CONFIG.SYS

```
SHELL=C:\DOS\COMMAND.COM /P /E:1536
STACKS=9,256
DEVICE=C:\DOS\HIMEM.SYS
DEVICE=C:\DOS\EMM386.EXE NOEMS I=B000-B7FF X=D000-D4FF
DEVICEHIGH=C:\WINDOWS\CPQWIN\CPQCM.SYS
DOS=HIGH,UMB
REM *** Begin PCMCIA Drivers
REM Warning: Do not move, reorder, or delete any of these lines.
REM
;DEVICE=C:\CPQDOS\PCMSMIX.EXE
DEVICEHIGH=C:\CPQDOS\SSVLSI.EXE
DEVICEHIGH=C:\CPQDOS\CS.EXE
DEVICE=C:\CPQDOS\CSALLOC.EXE
;DEVICEHIGH=C:\CPQDOS\ATADRV.EXE
;DEVICEHIGH=C:\CPQDOS\MTAA.EXE
;DEVICEHIGH=C:\CPQDOS\MTAB.EXE
;DEVICEHIGH=C:\CPQDOS\MTI1.EXE
DEVICEHIGH=C:\CPQDOS\MTI2P.EXE
;DEVICEHIGH=C:\CPQDOS\MTSRAM.EXE
DEVICEHIGH=C:\CPQDOS\MTDDRV.EXE
;DEVICEHIGH=C:\CPQDOS\DBLFLASH.EXE
DEVICEHIGH=C:\CPQDOS\MS-FLASH.SYS
DEVICEHIGH=C:\CPQDOS\CARDID.EXE
REM *** End PCMCIA Drivers
BUFFERS=20
FILES=35
DEVICEHIGH=C:\CPQDOS\EPPBIOS.SYS
DEVICEHIGH=C:\CPQDOS\POWER.EXE
```

AUTOEXEC.BAT

```
@loadhigh C:\DOS\SHARE.EXE /I:500 /f:5100
@ECHO OFF
SET PATH=C:\CPQDOS;C:\;C:\DOS;C:\WINDOWS;;C:\WINDOWS\CPQWIN
SET LMOUSE=C:\MOUSE
LH C:\MOUSE\MOUSE
SET PROMPT=$PSG
SET TEMP=C:\WINDOWS\TEMP
C:\CPQDOS\HIBRN8.EXE
LH C:\DOS\SMARTDRV.EXE
C:\WINDOWS\WIN
```

CARDID.INI

```
[Common]
;
; Common Information section created by Config
;
ComPort1=3F8
ComIRQ1=4
ComPort2=2F8
ComIRQ2=3
ComPort3=3e8
ComIRQ3=4
ComPort4=2E8
ComIRQ4=3
ComBySocket=Yes
ComBDAAbsolute=No
FirstModem=2
CARDID.INI-continued
```

SecondModem=2
ThirdModem=3
FourthModem=4
Audio=Yes
RingIndicate=No
Lan1Port=300
Lan1IRQ=5
Lan1MemoryBase1=
Lan1MemoryBase2=
Lan2Port=310
Lan2IRQ=9
Lan2MemoryBase1=
Lan2MemoryBase2=
ATATryPrimary=No
ATATrySecondary=Yes
ATATryLinear=Yes
FastTokenRing=Yes
DetectNonCompliant=No
ContinueOnConfigFailure=No
BeepInDOS=Yes
BeepInWindows=Yes
GrabInitFile=Yes
InitBufferSize=512
UseEMS=No

[Libraries]

;
; The Libraries section contains references to any card libraries the user
; wishes to include. Libraries are searched in the specified order. Path
; names are relative to the directory containing CARDID.INI.

;
CardLib=canonfd.clb
CardLib=xirdual.clb
CardLib=xircom.clb
CardLib=tdkklan2.clb
CardLib=sundisk5.clb
CardLib=intellan.clb
CardLib=dlink.clb
CardLib=linksys.clb
CardLib=linksys2.clb
CardLib=socketea.clb
CardLib=ibmlan.clb
CardLib=ibmtok.clb
CardLib=ibm3270.clb
CardLib=proxim.clb
CardLib=cbdass.clb
CardLib=genmodem.clb
CardLib=genata.clb
CardLib=wd.clb

Configuration Notes:

In Windows 3.1/DOS you must unremark the highlighted lines in the Config.Sys. The Compaq Contura 400 only supports MS-Flash, and does not support FTL with the supplied card and socket services. Windows 95 drivers do not correctly work, and you must load the real mode drivers in order for the card to function in Windows 95. You will use **MEMCARD** to partition and format the card.

PLATFORM: COMPAQ CONTURA 420C

ROM: 08/20/95

PC CARD: INTEL SERIES 2 20MB FLASH MEMORY CARD, PN: IMC020FLSA

OPERATING SYSTEM: WINDOWS 3.1/DOS 6.2

CARD AND SOCKET SERVICES: 3.12

CONFIG.SYS

```
switches=/F
SHELL=C:\DOS\COMMAND.COM /P /E:1536
STACKS=9,256
DEVICE=C:\DOS\HIMEM.SYS
DEVICE=C:\DOS\EMM386.EXE NOEMS I=B000-B7FF X=D000-D4FF
DEVICEHIGH=C:\WINDOWS\CPQWIN\CPQCM.SYS
DOS=HIGH,UMB
REM *** Begin PCMCIA Drivers
REM Warning: Do not move, reorder, or delete any of these lines.
REM
;DEVICE=C:\CPQDOS\PCMSMIX.EXE
DEVICEHIGH=C:\CPQDOS\SSVLSI.EXE
DEVICEHIGH=C:\CPQDOS\CS.EXE
DEVICE=C:\CPQDOS\CSALLOC.EXE
;DEVICEHIGH=C:\CPQDOS\ATADRV.EXE
;DEVICEHIGH=C:\CPQDOS\MTAA.EXE
;DEVICEHIGH=C:\CPQDOS\MTAB.EXE
;DEVICEHIGH=C:\CPQDOS\MTI1.EXE
DEVICEHIGH=C:\CPQDOS\MTI2P.EXE
;DEVICEHIGH=C:\CPQDOS\MTSRAM.EXE
DEVICEHIGH=C:\CPQDOS\MTDDRV.EXE
;DEVICEHIGH=C:\CPQDOS\DBLFLASH.EXE
DEVICEHIGH=C:\CPQDOS\MS-FLASH.SYS
DEVICEHIGH=C:\CPQDOS\CARDID.EXE
REM *** End PCMCIA Drivers
BUFFERS=20
FILES=35
DEVICEHIGH=C:\CPQDOS\EPPBIOS.SYS
```

AUTOEXEC.BAT

```
@ECHO OFF
SET PATH=C:\CPQDOS;C:\;C:\DOS;C:\WINDOWS;;C:\WINDOWS\CPQWIN
SET LMOUSE=C:\MOUSE
LH C:\MOUSE\MOUSE
SET PROMPT=$P$G
SET TEMP=C:\WINDOWS\TEMP
C:\CPQDOS\HIBRN8.EXE
C:\DOS\SMARTDRV.EXE 2048 512
C:\WINDOWS\WIN
```

CARDID.INI

```
[Common]
;
; Common Information section created by Config
;
ComPort1=3F8
ComIRQ1=4
ComPort2=2F8
ComIRQ2=3
ComPort3=3e8
ComIRQ3=4
ComPort4=2E8
ComIRQ4=3
ComBySocket=Yes
ComBDAAbsolute=No
FirstModem=2
SecondModem=2
CARDID.INI-continued
```

ThirdModem=3
FourthModem=4
Audio=Yes
RingIndicate=No
Lan1Port=300
Lan1IRQ=5
Lan1MemoryBase1=
Lan1MemoryBase2=
Lan2Port=310
Lan2IRQ=9
Lan2MemoryBase1=
Lan2MemoryBase2=
ATATryPrimary=No
ATATrySecondary=Yes
ATATryLinear=Yes
FastTokenRing=Yes
DetectNonCompliant=No
ContinueOnConfigFailure=No
BeepInDOS=Yes
BeepInWindows=Yes
GrabInitFile=Yes
InitBufferSize=512
UseEMS=No

[Libraries]

;
; The Libraries section contains references to any card libraries the user
; wishes to include. Libraries are searched in the specified order. Path
; names are relative to the directory containing CARDID.INI.

;
CardLib=canonfd.clb
CardLib=xirdual.clb
CardLib=xircom.clb
CardLib=tdkklan2.clb
CardLib=sundisk5.clb
CardLib=intellan.clb
CardLib=dlink.clb
CardLib=linksys.clb
CardLib=linksys2.clb
CardLib=socketea.clb
CardLib=ibmlan.clb
CardLib=ibmtok.clb
CardLib=ibm3270.clb
CardLib=proxim.clb
CardLib=cbdass.clb
CardLib=genmodem.clb
CardLib=genata.clb
CardLib=wd.clb

Configuration Notes:

In Windows 3.1/DOS you must unremark the highlighted lines in the Config.Sys. The Compaq Contura 420 only supports MS-Flash, and does not support FTL with the supplied card and socket services. Windows 95 drivers do not correctly work, and you must load the real mode drivers in order for the card to function in Windows 95. You will use **MEMCARD** to partition and format the card.

PLATFORM: COMPAQ ELITE 4/50CX

ROM: 07/19/95

PC CARD: INTEL SERIES 2 20MB FLASH MEMORY CARD, PN: IMC020FLSA

OPERATING SYSTEM: WINDOWS 3.1/DOS 6.2

CARD AND SOCKET SERVICES: 3.12

CONFIG.SYS

```
switches=/F
SHELL=C:\DOS\COMMAND.COM /P /E:1536
STACKS=9,256
DEVICE=C:\DOS\HIMEM.SYS
DEVICE=C:\DOS\EMM386.EXE NOEMS I=B000-B7FF X=D000-D4FF
DEVICEHIGH=C:\WINDOWS\CPQWIN\CPQCM.SYS
DOS=HIGH,UMB
REM *** Begin PCMCIA Drivers
REM Warning: Do not move, reorder, or delete any of these lines.
REM
;DEVICE=C:\CPQDOS\PCMSMIX.EXE
DEVICEHIGH=C:\CPQDOS\SSVLSI.EXE
DEVICEHIGH=C:\CPQDOS\CS.EXE
DEVICE=C:\CPQDOS\CSALLOC.EXE
;DEVICEHIGH=C:\CPQDOS\ATADRV.EXE
;DEVICEHIGH=C:\CPQDOS\MTAA.EXE
;DEVICEHIGH=C:\CPQDOS\MTAB.EXE
;DEVICEHIGH=C:\CPQDOS\MTI1.EXE
DEVICEHIGH=C:\CPQDOS\MTI2P.EXE
;DEVICEHIGH=C:\CPQDOS\MTSRAM.EXE
DEVICEHIGH=C:\CPQDOS\MTDDRV.EXE
;DEVICEHIGH=C:\CPQDOS\DBLFLASH.EXE
DEVICEHIGH=C:\CPQDOS\MS-FLASH.SYS
DEVICEHIGH=C:\CPQDOS\CARDID.EXE
REM *** End PCMCIA Drivers
BUFFERS=20
FILES=35
DEVICEHIGH=C:\CPQDOS\POWER.EXE
```

AUTOEXEC.BAT

```
@ECHO OFF
SET PATH=C:\CPQDOS;C:\;C:\DOS;C:\WINDOWS;;C:\WINDOWS\CPQWIN
SET LMOUSE=C:\MOUSE
LH C:\MOUSE\MOUSE
SET PROMPT=$P$G
SET TEMP=C:\WINDOWS\TEMP
C:\CPQDOS\HIBRN8.EXE
LH C:\DOS\SMARTDRV.EXE
SET NWLANGUAGE=ENGLISH
C:\WINDOWS\WIN
```

CARDID.INI

```
[Common]
;
; Common Information section created by Config
;
ComPort1=3F8
ComIRQ1=4
ComPort2=2F8
ComIRQ2=3
ComPort3=3e8
ComIRQ3=4
ComPort4=2E8
ComIRQ4=3
ComBySocket=Yes
ComBDAAbsolute=No
```

CARDID.INI-continued

```
FirstModem=2
SecondModem=2
ThirdModem=3
FourthModem=4
Audio=Yes
RingIndicate=No
Lan1Port=300
Lan1IRQ=5
Lan1MemoryBase1=c0
Lan1MemoryBase2=c0
Lan2Port=310
Lan2IRQ=9
Lan2MemoryBase1=
Lan2MemoryBase2=
ATATryPrimary=No
ATATrySecondary=Yes
ATATryLinear=Yes
FastTokenRing=No
DetectNonCompliant=No
ContinueOnConfigFailure=No
BeepInDOS=Yes
BeepInWindows=Yes
GrabInitFile=Yes
InitBufferSize=512
UseEMS=No
```

[Libraries]

```
;  
; The Libraries section contains references to any card libraries the user  
; wishes to include. Libraries are searched in the specified order. Path  
; names are relative to the directory containing CARDID.INI.
```

```
;  
CardLib=canonfd.clb  
CardLib=xirdual.clb  
CardLib=xircom.clb  
CardLib=tdkklan2.clb  
CardLib=sundisk5.clb  
CardLib=intellan.clb  
CardLib=dlink.clb  
CardLib=linksys.clb  
CardLib=linksys2.clb  
CardLib=socketea.clb  
CardLib=ibmlan.clb  
CardLib=ibmtok.clb  
CardLib=ibm3270.clb  
CardLib=proxim.clb  
CardLib=cbdass.clb  
CardLib=genmodem.clb  
CardLib=genata.clb  
CardLib=wd.clb
```

Configuration Notes:

In Windows 3.1/DOS you must unremark the highlighted line in the Config.Sys. The Compaq Elite only supports MS-Flash, and does not support FTL with the supplied card and socket services. Windows 95 drivers do not correctly work, and you must load the real mode drivers in order for the card to function in Windows 95. You will use **MEMCARD** to partition and format the card.

PLATFORM: COMPAQ LTE 5000

ROM: 09/19/95

PC CARD: INTEL SERIES 2 20MB FLASH MEMORY CARD, PN: IMC020FLSA

OPERATING SYSTEM: WINDOWS 3.1/DOS 6.2

CARD AND SOCKET SERVICES: 3.14

CONFIG.SYS

```
DEVICE=C:\CPQDOS\MACHCHK.SYS 02A8 02B0 02BA 02CA
DEVICE=C:\DOS\HIMEM.SYS
DEVICE=C:\DOS\EMM386.exe NOEMS I=B000-B7FF X=C800-CBFF X=D100-D5FF X=E800-EFFF
COUNTRY=001,437,C:\DOS\COUNTRY.SYS
SHELL=C:\DOS\COMMAND.COM /P /E:1536
DOS=HIGH,UMB
FILES=35
BUFFERS=20,0
STACKS=9,256
DEVICEHIGH=C:\AUDIO_CD\TEAC_CDI.SYS /D:TEAC-CDI
LASTDRIVE=M
REM PC Card: Begin PC Card (PCMCIA) Drivers
REM **Warning: Do not move, reorder, or delete any of these lines. **
DEVICEHIGH=C:\CARDWIZ\SSCIRUS2.EXE
DEVICEHIGH=C:\CARDWIZ\CS.EXE /POLL:1
DEVICEHIGH=C:\CARDWIZ\CSALLOC.EXE
;DEVICEHIGH=C:\CARDWIZ\ATADRV.EXE
;DEVICEHIGH=C:\CARDWIZ\MTAA.EXE
;DEVICEHIGH=C:\CARDWIZ\MTAB.EXE
;DEVICEHIGH=C:\CARDWIZ\MTI1.EXE
DEVICEHIGH=C:\CARDWIZ\MTI2P.EXE
DEVICEHIGH=C:\CARDWIZ\MTATM.EXE
DEVICEHIGH=C:\CARDWIZ\MTDDR.V.EXE
DEVICEHIGH=C:\CARDWIZ\FTL.EXE
DEVICEHIGH=C:\CARDWIZ\CARDID.EXE
REM PC Card: End PC Card(PCMCIA) Drives
```

AUTOEXEC.BAT

```
@ECHO OFF
C:\WINDOWS\VGAUTIL\winmode.exe t640=60 t800=60 t1024=87 t1280=87
SET NWLANGUAGE=ENGLISH
PATH C:\WINDOWS;C:\CPQDOS;C:\DOS;C:\AUDIO_CD;C:\CARDWIZ
PROMPT $p$g
SET DIRCMD=/ogn
SET TEMP=C:\WINDOWS\TEMP
SET BLASTER=A220 D1 I5
SET LMOUSE=C:\MOUSE
SET MOUSE=C:\MOUSE
C:\MOUSE\MOUSE.EXE MEMU
C:\DOS\MSCDEX.EXE /D:TEAC-CDI /M:15
IF ERRORLEVEL 1 GOTO NO_CDROM
C:\AUDIO_CD\ESSVOL /V:15 /C:15
:NO_CDROM
LH C:\DOS\SMARTDRV.EXE
C:\CPQDOS\0VMAKFIL
IF NOT EXIST C:\CPQDOS\SAVEDONE.CPQ CALL SAVEALL /A
WIN
```

CARDID.INI

```
[Common]
; Common Information section created by Config
ComPort1=3F8
ComIRQ1=4
ComPort2=2F8
ComIRQ2=9
ComPort3=3E8
ComIRQ3=4
CARDID.INI-continued
```

ComPort4=2E8
ComIRQ4=3
ComBySocket=No
ComBDAAbsolute=Yes
ComRollOverOn=No
FirstModem=4
SecondModem=2
ThirdModem=2
FourthModem=1
Audio=Yes
RingIndicate=No
Suspend_Power=No
Lan1Port=300
Lan1IRQ=5
Lan1MemoryBase1=D4
Lan1MemoryBase2=D6
Lan2Port=310
Lan2IRQ=10
Lan2MemoryBase1=D8
Lan2MemoryBase2=DC
ATATryPrimary=Yes
ATATrySecondary=Yes
ATATryLinear=Yes
FastTokenRing=No
DetectNonCompliant=No
ContinueOnConfigFailure=No
BeepInDOS=Yes
BeepInWindows=Yes
GrabInitFile=Yes
InitBufferSize=512
FirstLan=1
SecondLan=2
ATATryMemory=No
ATAFirstConf=0
ATASecondConf=1
ATAThirdConf=2
ATAFourthConf=3

[Libraries]

; The Libraries section contains references to any card libraries the user
; wishes to include. Libraries are searched in the specified order. Path
; names are relative to the directory containing CARDID.INI.

;
CardLib=xirdual.clb
CardLib=xircom.clb
CardLib=tdkklan2.clb
CardLib=sundisk5.clb
CardLib=intellan.clb
CardLib=dlink.clb
CardLib=linksys.clb
CardLib=linksys2.clb
CardLib=socketea.clb
CardLib=ibmlan.clb
CardLib=ibmtok.clb
CardLib=ibm3270.clb
CardLib=proxim.clb
CardLib=cbdass.clb
CardLib=genmodem.clb
CardLib=genata.clb
CardLib=wd.clb

Configuration Notes:

In Windows 3.1/DOS you must unremark the highlighted lines in the Config.Sys. The COMPAQ LTE 5000 supports both FTL and MS-Flash, and you can choose your preference when partitioning and formatting the card. Windows 95 drivers do not correctly work with FTL either, so you must load the real mode drivers in order for the card to function in Windows 95. You will use **MCFORMAT** to partition and format the card with either MS-FLASH or FTL.

SCSI

PLATFORM: *COMPAQ AERO 4/33C*

ROM: *07/19/95*

PC CARD: *ADAPTEC SLIM SCSI, PN: APA-1460*

OPERATING SYSTEM: *WINDOWS 3.1/DOS 6.2*

CARD AND SOCKET SERVICES: *1.25*

CONFIG.SYS

```
SHELL=C:\DOS\COMMAND.COM /P /E:1536
STACKS=9,256
DEVICE=C:\DOS\HIMEM.SYS
DEVICE=C:\DOS\EMM386.EXE NOEMS X=D000-DFFF
DOS=UMB
REM *** Begin PCMCIA Drivers
REM Warning: Do not move, reorder, or delete any of these lines.
REM
DEVICE=C:\CPQDOS\PCSMIX.EXE
DEVICEHIGH=C:\CPQDOS\SSVLSI.EXE
DEVICEHIGH=C:\CPQDOS\CS.EXE
DEVICE=C:\CPQDOS\CSALLOC.EXE
DEVICEHIGH=C:\CPQDOS\ATADRV.EXE
DEVICEHIGH=C:\CPQDOS\CARDID.EXE C:\CPQDOS\CARDID.INI
DEVICEHIGH=C:\CPQDOS\MEMDRV.EXE
;DEVICEHIGH=C:\CPQDOS\DBLFLASH.EXE
;DEVICEHIGH=C:\CPQDOS\MS-FLASH.SYS
REM *** End PCMCIA Drivers
DOS=HIGH
BUFFERS=20
FILES=35
;DEVICEHIGH=C:\CPQDOS\POWER.EXE
DEVICE=C:\SCSI\ASPI2DOS.SYS /D /PCMCIA /Z /Q10
DEVICE=C:\SCSI\ASPICD.SYS /D:ASPICD0
```

AUTOEXEC.BAT

```
C:\SCSI\MSCDEX.EXE /D:ASPICD0 /M:12 /L:F
@loadhigh C:\DOS\SHARE.EXE /l:500 /f:5100
SET PATH=C:\CPQDOS;C:\;C:\DOS;C:\WINDOWS; C:\WINDOWS\CPQWIN
SET LMOUSE=C:\MOUSE
SET PROMPT=$PSG
SET TEMP=C:\WINDOWS\TEMP
C:\CPQDOS\HIBRN8.EXE
C:\DOS\SMARTDRV.EXE
LH C:\MOUSE\MOUSE SWAP
C:\CPQDOS\MODE.COM CO80
C:\WINDOWS\WIN
```

CARDID.INI

```
[Common]
;
; Common Information section created by Config
;
ComPort1=3F8
ComIRQ1=4
ComPort2=2F8
ComIRQ2=3
ComPort3=3E8
ComIRQ3=4
ComPort4=2E8
ComIRQ4=3
ComBySocket=Yes
ComBDAAbsolute=No
FirstModem=2
SecondModem=2
```

CARDID.INI-continued

ThirdModem=3
FourthModem=4
Audio=Yes
RingIndicate=No
Lan1Port=300
Lan1IRQ=5
Lan1MemoryBase1=D8
Lan1MemoryBase2=DC
Lan2Port=310
Lan2IRQ=10
Lan2MemoryBase1=D8
Lan2MemoryBase2=DC
ATATryPrimary=No
ATATrySecondary=Yes
ATATryLinear=Yes
FastTokenRing=Yes
DetectNonCompliant=No
ContinueOnConfigFailure=No
BeepInDOS=Yes
BeepInWindows=Yes
GrabInitFile=Yes
InitBufferSize=512

[Libraries]

;
; The Libraries section contains references to any card libraries the user
; wishes to include. Libraries are searched in the specified order. Path
; names are relative to the directory containing CARDID.INI.
;
CardLib=cardid.clb

Configuration Notes:

In DOS/Windows ran installation program. Resources used were IRQ 5 and I/O 380, and the software made all necessary changes to files. The drivers for Windows 95 are built in so the card should be recognized and configured when inserted.

PLATFORM: *COMPAQ CONCERTO*

ROM: *10/12/93*

PC CARD: *ADAPTEC SLIM SCSI, PN: APA-1460*

OPERATING SYSTEM: *WINDOWS 3.1/DOS 6.2*

CARD AND SOCKET SERVICES: *1.25*

CONFIG.SYS

```
SHELL=C:\DOS\COMMAND.COM /P /E:1536
STACKS=9,256
DEVICE=C:\DOS\HIMEM.SYS
DEVICE=C:\DOS\EMM386.EXE NOEMS X=D000-DFFF
DOS=UMB
REM *** Begin PCMCIA Drivers
REM Warning: Do not move, reorder, or delete any of these lines.
REM
DEVICEHIGH=C:\CPQDOS\SSCIRRUS.EXE
DEVICEHIGH=C:\CPQDOS\CS.EXE
DEVICE=C:\CPQDOS\CSALLOC.EXE
DEVICEHIGH=C:\CPQDOS\ATADRV.EXE
DEVICEHIGH=C:\CPQDOS\CARDID.EXE C:\CPQDOS\CARDID.INI
DEVICEHIGH=C:\CPQDOS\MEMDRV.EXE
;DEVICEHIGH=C:\CPQDOS\DBLFLASH.EXE
;DEVICEHIGH=C:\CPQDOS\MS-FLASH.SYS
REM *** End PCMCIA Drivers
DOS=HIGH
BUFFERS=20
FILES=35
DEVICEHIGH=C:\CPQDOS\POWER.EXE
LASTDRIVE = J
DEVICE=C:\SCSI\ASPI2DOS.SYS /D /PCMCIA /Z /Q10
DEVICE=C:\SCSI\ASPICD.SYS /D:ASPICD0
```

AUTOEXEC.BAT

```
C:\SCSI\MSCDEX.EXE /D:ASPICD0 /M:12 /L:J
SET PATH=C:\CPQDOS;C:\;\C:\DOS;C:\WINDOWS;;C:\WINDOWS\CPQWIN
SET LMOUSE=C:\MOUSE
SET PROMPT=$PSG
SET TEMP=C:\WINDOWS\TEMP
C:\CPQDOS\HIBRN8.EXE
C:\DOS\SMARTDRV.EXE
LH C:\MOUSE\MOUSE
C:\CPQDOS\MODE.COM CO80
C:\WINDOWS\WIN
```

CARDID.INI

```
[Common]
;
; Common Information section created by Config
;
ComPort1=3F8
ComIRQ1=4
ComPort2=2F8
ComIRQ2=3
ComPort3=3E8
ComIRQ3=4
ComPort4=2E8
ComIRQ4=3
ComBySocket=Yes
ComBDAAbsolute=No
FirstModem=2
SecondModem=2
ThirdModem=3
FourthModem=4
```


CARDID.INI-continued

Audio=Yes
RingIndicate=No
Lan1Port=300
Lan1IRQ=5
Lan1MemoryBase1=D8
Lan1MemoryBase2=DC
Lan2Port=310
Lan2IRQ=10
Lan2MemoryBase1=D8
Lan2MemoryBase2=DC
ATATryPrimary=No
ATATrySecondary=Yes
ATATryLinear=Yes
FastTokenRing=Yes
DetectNonCompliant=No
ContinueOnConfigFailure=No
BeepInDOS=Yes
BeepInWindows=Yes
GrabInitFile=Yes
InitBufferSize=512

[Libraries]

;
; The Libraries section contains references to any card libraries the user
; wishes to include. Libraries are searched in the specified order. Path
; names are relative to the directory containing CARDID.INI.
;
CardLib=cardid.clb

Configuration Notes:

In DOS/Windows ran installation program. Resources used were IRQ 10 and I/O 340, and the software made all necessary changes to files. While in the base the software will use I/O 140 while the interrupt stays the same, and this is done automatically so there is no need for modification. The drivers for Windows 95 are built in so the card should be recognized and configured when inserted.

PLATFORM: *COMPAQ CONTURA 400CX*

ROM: *04/10/95*

PC CARD: *ADAPTEC SLIM SCSI, PN: APA-1460*

OPERATING SYSTEM: *WINDOWS 3.1/DOS 6.2*

CARD AND SOCKET SERVICES: *3.12*

CONFIG.SYS

```
SHELL=C:\DOS\COMMAND.COM /P /E:1536
STACKS=9,256
DEVICE=C:\DOS\HIMEM.SYS
DEVICE=C:\DOS\EMM386.EXE NOEMS I=B000-B7FF X=D000-D4FF
DEVICEHIGH=C:\WINDOWS\CPQWIN\CPQCM.SYS
DOS=HIGH,UMB
REM *** Begin PCMCIA Drivers
REM Warning: Do not move, reorder, or delete any of these lines.
REM
;DEVICE=C:\CPQDOS\PCMSMIX.EXE
DEVICEHIGH=C:\CPQDOS\SSVLSI.EXE
DEVICEHIGH=C:\CPQDOS\CS.EXE
DEVICE=C:\CPQDOS\CSALLOC.EXE
;DEVICEHIGH=C:\CPQDOS\ATADRV.EXE
;DEVICEHIGH=C:\CPQDOS\MTAA.EXE
;DEVICEHIGH=C:\CPQDOS\MTAB.EXE
;DEVICEHIGH=C:\CPQDOS\MTI1.EXE
;DEVICEHIGH=C:\CPQDOS\MTI2P.EXE
;DEVICEHIGH=C:\CPQDOS\MTSRAM.EXE
;DEVICEHIGH=C:\CPQDOS\MTDDRV.EXE
;DEVICEHIGH=C:\CPQDOS\DBLFLASH.EXE
;DEVICEHIGH=C:\CPQDOS\MS-FLASH.SYS
DEVICEHIGH=C:\CPQDOS\CARDID.EXE
REM *** End PCMCIA Drivers
BUFFERS=20
FILES=35
DEVICEHIGH=C:\CPQDOS\EPPBIOS.SYS
DEVICEHIGH=C:\CPQDOS\POWER.EXE
DEVICE=C:\SCSI\ASPI2DOS.SYS /D /PCMCIA /Z /Q9
DEVICE=C:\SCSI\ASPICD.SYS /D:ASPICD0
```

AUTOEXEC.BAT

```
C:\SCSI\MSCDEX.EXE /D:ASPICD0 /M:12
@loadhigh C:\DOS\SHARE.EXE /I:500 /f:5100
@ECHO OFF
SET PATH=C:\CPQDOS;C:\;C:\DOS;C:\WINDOWS;;C:\WINDOWS\CPQWIN
SET LMOUSE=C:\MOUSE
LH C:\MOUSE\MOUSE
SET PROMPT=$PSG
SET TEMP=C:\WINDOWS\TEMP
C:\CPQDOS\HIBRN8.EXE
LH C:\DOS\SMARTDRV.EXE
C:\WINDOWS\WIN
```

CARDID.INI

```
[Common]
;
; Common Information section created by Config
;
ComPort1=3F8
ComIRQ1=4
ComPort2=2F8
ComIRQ2=3
ComPort3=3e8
ComIRQ3=4
ComPort4=2E8
ComIRQ4=3
CARDID.INI-continued
```

ComBySocket=Yes
ComBDAAbsolute=No
FirstModem=2
SecondModem=2
ThirdModem=3
FourthModem=4
Audio=Yes
RingIndicate=No
Lan1Port=300
Lan1IRQ=5
Lan1MemoryBase1=
Lan1MemoryBase2=
Lan2Port=310
Lan2IRQ=9
Lan2MemoryBase1=
Lan2MemoryBase2=
ATATryPrimary=No
ATATrySecondary=Yes
ATATryLinear=Yes
FastTokenRing=Yes
DetectNonCompliant=No
ContinueOnConfigFailure=No
BeepInDOS=Yes
BeepInWindows=Yes
GrabInitFile=Yes
InitBufferSize=512
UseEMS=No

[Libraries]

;
; The Libraries section contains references to any card libraries the user
; wishes to include. Libraries are searched in the specified order. Path
; names are relative to the directory containing CARDID.INI.

;
CardLib=canonfd.clb
CardLib=xirdual.clb
CardLib=xircom.clb
CardLib=tdkklan2.clb
CardLib=sundisk5.clb
CardLib=intellan.clb
CardLib=dlink.clb
CardLib=linksys.clb
CardLib=linksys2.clb
CardLib=socketea.clb
CardLib=ibmlan.clb
CardLib=ibmtok.clb
CardLib=ibm3270.clb
CardLib=proxim.clb
CardLib=cbdas.clb
CardLib=genmodem.clb
CardLib=genata.clb
CardLib=wd.clb

Configuration Notes:

In DOS/Windows ran installation program. Resources used were IRQ 11 and I/O 340, and the software made all necessary changes to files. The drivers for Windows 95 are built in so the card should be recognized and configured when inserted.

PLATFORM: COMPAQ CONTURA 420C

ROM: 08/20/95

PC CARD: ADAPTEC SLIM SCSI, PN: APA-1460

OPERATING SYSTEM: WINDOWS 3.1/DOS 6.2

CARD AND SOCKET SERVICES: 3.12

CONFIG.SYS

```
SHELL=C:\DOS\COMMAND.COM /P /E:1536
STACKS=9,256
DEVICE=C:\DOS\HIMEM.SYS
DEVICE=C:\DOS\EMM386.EXE NOEMS I=B000-B7FF X=D000-D4FF
DEVICEHIGH=C:\WINDOWS\CPQWIN\CPQCM.SYS
DOS=HIGH,UMB
REM *** Begin PCMCIA Drivers
REM Warning: Do not move, reorder, or delete any of these lines.
REM
;DEVICE=C:\CPQDOS\PCMSMIX.EXE
DEVICEHIGH=C:\CPQDOS\SSVLSI.EXE
DEVICEHIGH=C:\CPQDOS\CS.EXE
DEVICE=C:\CPQDOS\CSALLOC.EXE
;DEVICEHIGH=C:\CPQDOS\ATADRV.EXE
;DEVICEHIGH=C:\CPQDOS\MTAA.EXE
;DEVICEHIGH=C:\CPQDOS\MTAB.EXE
;DEVICEHIGH=C:\CPQDOS\MTI1.EXE
;DEVICEHIGH=C:\CPQDOS\MTI2P.EXE
;DEVICEHIGH=C:\CPQDOS\MTSRAM.EXE
;DEVICEHIGH=C:\CPQDOS\MTDDRV.EXE
;DEVICEHIGH=C:\CPQDOS\DBLFLASH.EXE
;DEVICEHIGH=C:\CPQDOS\MS-FLASH.SYS
DEVICEHIGH=C:\CPQDOS\CARDID.EXE
REM *** End PCMCIA Drivers
BUFFERS=20
FILES=35
DEVICEHIGH=C:\CPQDOS\EPPBIOS.SYS
DEVICE=C:\SCSI\ASPI2DOS.SYS /D /PCMCIA /Z /Q9
DEVICE=C:\SCSI\ASPICD.SYS /D:ASPICD0
```

AUTOEXEC.BAT

```
C:\SCSI\MSCDEX.EXE /D:ASPICD0 /M:12
@ECHO OFF
SET PATH=C:\CPQDOS;C:\;C:\DOS;C:\WINDOWS;
SET LMOUSE=C:\MOUSE
LH C:\MOUSE\MOUSE
SET PROMPT=$PSG
SET TEMP=C:\WINDOWS\TEMP
C:\CPQDOS\HIBRN8.EXE
C:\DOS\SMARTDRV.EXE 2048 512
C:\WINDOWS\WIN
```

CARDID.INI

```
[Common]
;
; Common Information section created by Config
;
ComPort1=3F8
ComIRQ1=4
ComPort2=2F8
ComIRQ2=3
ComPort3=3e8
ComIRQ3=4
ComPort4=2E8
ComIRQ4=3
ComBySocket=Yes
```

CARDID.INI-continued

ComBDAAbsolute=No
FirstModem=2
SecondModem=2
ThirdModem=3
FourthModem=4
Audio=Yes
RingIndicate=No
Lan1Port=300
Lan1IRQ=5
Lan1MemoryBase1=
Lan1MemoryBase2=
Lan2Port=310
Lan2IRQ=9
Lan2MemoryBase1=
Lan2MemoryBase2=
ATATryPrimary=No
ATATrySecondary=Yes
ATATryLinear=Yes
FastTokenRing=Yes
DetectNonCompliant=No
ContinueOnConfigFailure=No
BeepInDOS=Yes
BeepInWindows=Yes
GrabInitFile=Yes
InitBufferSize=512
UseEMS=No

[Libraries]

;
; The Libraries section contains references to any card libraries the user
; wishes to include. Libraries are searched in the specified order. Path
; names are relative to the directory containing CARDID.INI.

;
CardLib=canonfd.clb
CardLib=xirdual.clb
CardLib=xircom.clb
CardLib=tdkklan2.clb
CardLib=sundisk5.clb
CardLib=intellan.clb
CardLib=dlink.clb
CardLib=linksys.clb
CardLib=linksys2.clb
CardLib=socketea.clb
CardLib=ibmlan.clb
CardLib=ibmtok.clb
CardLib=ibm3270.clb
CardLib=proxim.clb
CardLib=cbdass.clb
CardLib=genmodem.clb
CardLib=genata.clb
CardLib=wd.clb

Configuration Notes:

In DOS/Windows ran installation program. Resources used were IRQ 11 and I/O 340, and the software made all necessary changes to files. The drivers for Windows 95 are built in so the card should be recognized and configured when inserted.

PLATFORM: *COMPAQ ELITE 4/50CX*

ROM: *07/19/95*

PC CARD: *ADAPTEC SLIM SCSI, PN: APA-1460*

OPERATING SYSTEM: *WINDOWS 3.1/DOS 6.2*

CARD AND SOCKET SERVICES: *3.12*

CONFIG.SYS

```
switches=/F
SHELL=C:\DOS\COMMAND.COM /P /E:1536
STACKS=9,256
DEVICE=C:\DOS\HIMEM.SYS /TESTMEM:OFF
DEVICE=C:\DOS\EMM386.EXE NOEMS I=B000-B7FF X=D000-D4FF
DEVICEHIGH=C:\WINDOWS\CPQWIN\CPQCM.SYS
DOS=HIGH,UMB
REM *** Begin PCMCIA Drivers
REM Warning: Do not move, reorder, or delete any of these lines.
REM
;DEVICE=C:\CPQDOS\PCMSMIX.EXE
DEVICEHIGH=C:\CPQDOS\SSVLSI.EXE
DEVICEHIGH=C:\CPQDOS\CS.EXE
DEVICE=C:\CPQDOS\CSALLOC.EXE
;DEVICEHIGH=C:\CPQDOS\ATADRV.EXE
;DEVICEHIGH=C:\CPQDOS\MTAA.EXE
;DEVICEHIGH=C:\CPQDOS\MTAB.EXE
;DEVICEHIGH=C:\CPQDOS\MTI1.EXE
;DEVICEHIGH=C:\CPQDOS\MTI2P.EXE
;DEVICEHIGH=C:\CPQDOS\MTSRAM.EXE
;DEVICEHIGH=C:\CPQDOS\MTDDRV.EXE
;DEVICEHIGH=C:\CPQDOS\DBLFLASH.EXE
;DEVICEHIGH=C:\CPQDOS\MS-FLASH.SYS
DEVICEHIGH=C:\CPQDOS\CARDID.EXE
REM *** End PCMCIA Drivers
BUFFERS=20
FILES=35
LASTDRIVE = Z
DEVICEHIGH=C:\CPQDOS\POWER.EXE
DEVICE=C:\SCSI\ASPI2DOS.SYS /D /PCMCIA /Z /Q9
DEVICE=C:\SCSI\ASPICD.SYS /D:ASPICD0
```

AUTOEXEC.BAT

```
C:\SCSI\MSCDEX.EXE /D:ASPICD0 /M:12
@ECHO OFF
SET PATH=C:\CPQDOS;C:\;C:\DOS;C:\WINDOWS;;C:\WINDOWS\CPQWIN
SET LMOUSE=C:\MOUSE
LH C:\MOUSE\MOUSE
SET PROMPT=$t $PSG
SET TEMP=C:\WINDOWS\TEMP
C:\CPQDOS\HIBRN8.EXE
LH C:\DOS\SMARTDRV.EXE /f 2048 1024
SET NWLANGUAGE=ENGLISH
C:\WINDOWS\WIN
```

CARDID.INI

```
[Common]
;
; Common Information section created by Config
;
ComPort1=3F8
ComIRQ1=4
ComPort2=2F8
ComIRQ2=3
ComPort3=3e8
ComIRQ3=4
```

CARDID.INI-continued

```
ComPort4=2E8
ComIRQ4=3
ComBySocket=Yes
ComBDAAbsolute=No
FirstModem=2
SecondModem=2
ThirdModem=3
FourthModem=4
Audio=Yes
RingIndicate=No
Lan1Port=300
Lan1IRQ=5
Lan1MemoryBase1=
Lan1MemoryBase2=
Lan2Port=310
Lan2IRQ=9
Lan2MemoryBase1=
Lan2MemoryBase2=
ATATryPrimary=No
ATATrySecondary=Yes
ATATryLinear=Yes
FastTokenRing=Yes
DetectNonCompliant=No
ContinueOnConfigFailure=No
BeepInDOS=Yes
BeepInWindows=Yes
GrabInitFile=Yes
InitBufferSize=512
UseEMS=No
```

[Libraries]

```
;  
; The Libraries section contains references to any card libraries the user  
; wishes to include. Libraries are searched in the specified order. Path  
; names are relative to the directory containing CARDID.INI.
```

```
;  
CardLib=canonfd.clb  
CardLib=xirdual.clb  
CardLib=xircom.clb  
CardLib=tdkklan2.clb  
CardLib=sundisk5.clb  
CardLib=intellan.clb  
CardLib=dlink.clb  
CardLib=linksys.clb  
CardLib=linksys2.clb  
CardLib=socketea.clb  
CardLib=ibmlan.clb  
CardLib=ibmtok.clb  
CardLib=ibm3270.clb  
CardLib=proxim.clb  
CardLib=cbdass.clb  
CardLib=genmodem.clb  
CardLib=genata.clb  
CardLib=wd.clb
```

Configuration Notes:

In DOS/Windows ran installation program. Resources used were IRQ 11 and I/O 340, and the software made all necessary changes to files. When system in base you must use IRQ 9 and I/O 140, but this can be changed if the internal options are changed in computer setup. The drivers for Windows 95 are built in so the card should be recognized and configured when inserted.

PLATFORM: *COMPAQ LTE 5000*

ROM: *09/19/95*

PC CARD: *ADAPTEC SLIM SCSI, PN: APA-1460*

OPERATING SYSTEM: *WINDOWS 3.1/DOS 6.2*

CARD AND SOCKET SERVICES: *3.14*

CONFIG.SYS

```
DEVICE=C:\CPQDOS\MACHCHK.SYS 02A8 02B0 02BA 02CA
DEVICE=C:\DOS\HIMEM.SYS
DEVICE=C:\DOS\EMM386.exe NOEMS I=B000-B7FF X=C800-CBFF X=D100-D5FF X=E800-EFFF
COUNTRY=001,437,C:\DOS\COUNTRY.SYS
SHELL=C:\DOS\COMMAND.COM /P /E:1536
DOS=HIGH,UMB
FILES=35
BUFFERS=20,0
STACKS=9,256
DEVICEHIGH=C:\AUDIO_CD\TEAC_CDI.SYS /D:TEAC-CDI
LASTDRIVE=M
REM PC Card: Begin PC Card (PCMCIA) Drivers
REM **Warning: Do not move, reorder, or delete any of these lines. **
DEVICEHIGH=C:\CARDWIZ\SSCIRUS2.EXE
DEVICEHIGH=C:\CARDWIZ\CS.EXE /POLL:1
DEVICEHIGH=C:\CARDWIZ\CSALLOC.EXE
DEVICEHIGH=C:\CARDWIZ\CARDID.EXE
REM PC Card: End PC Card(PCMCIA) Drives
DEVICE=C:\SCSI\ASPI2DOS.SYS /D /PCMCIA /Z /Q9
DEVICE=C:\SCSI\ASPICD.SYS /D:ASPICD0
```

AUTOEXEC.BAT

```
@ECHO OFF
C:\WINDOWS\VGAUTIL\winmode.exe t640=60 t800=60 t1024=87 t1280=87
SET NWLANGUAGE=ENGLISH
PATH C:\WINDOWS;C:\CPQDOS;C:\DOS;C:\AUDIO_CD;C:\CARDWIZ
PROMPT $p$g
SET DIRCMD=/ogn
SET TEMP=C:\WINDOWS\TEMP
SET BLASTER=A220 D1 I5
SET LMOUSE=C:\MOUSE
SET MOUSE=C:\MOUSE
C:\MOUSE\MOUSE.EXE MEMU
C:\SCSI\MSCDEX.EXE /D:ASPICD0 /M:12
IF ERRORLEVEL 1 GOTO NO_CDROM
C:\AUDIO_CD\ESSVOL /V:15 /C:15
:NO_CDROM
IF NOT EXIST C:\CPQDOS\SAVEDONE.CPQ CALL SAVEALL /A
LH C:\DOS\SMARTDRV.EXE
C:\CPQDOS\0VMAKFIL
WIN
```

CARDID.INI

```
[Common]
; Common Information section created by Config
;
ComPort1=3F8
ComIRQ1=4
ComPort2=2F8
ComIRQ2=3
ComPort3=3E8
ComIRQ3=4
ComPort4=2E8
ComIRQ4=11
ComBySocket=No
ComBDAAbsolute=Yes
ComRollOverOn=No
CARDID.INI-continued
```

FirstModem=2
SecondModem=4
ThirdModem=2
FourthModem=4
Audio=Yes
RingIndicate=No
Suspend_Power=No
Lan1Port=300
Lan1IRQ=11
Lan1MemoryBase1=
Lan1MemoryBase2=
Lan2Port=310
Lan2IRQ=10
Lan2MemoryBase1=
Lan2MemoryBase2=
ATATryPrimary=No
ATATrySecondary=Yes
ATATryLinear=Yes
FastTokenRing=Yes
DetectNonCompliant=No
ContinueOnConfigFailure=No
BeepInDOS=Yes
BeepInWindows=Yes
GrabInitFile=Yes
InitBufferSize=512

[Libraries]

;
; The Libraries section contains references to any card libraries the user
; wishes to include. Libraries are searched in the specified order. Path
; names are relative to the directory containing CARDID.INI.

;
CardLib=xirdual.clb
CardLib=xircom.clb
CardLib=tdkklan2.clb
CardLib=sundisk5.clb
CardLib=intellan.clb
CardLib=dlink.clb
CardLib=linksys.clb
CardLib=linksys2.clb
CardLib=socketea.clb
CardLib=ibmlan.clb
CardLib=ibmtok.clb
CardLib=ibm3270.clb
CardLib=proxim.clb
CardLib=cbdas.clb
CardLib=genmodem.clb
CardLib=genata.clb
CardLib=wd.clb

Configuration Notes:

In DOS/Windows ran installation program. Resources used were IRQ 11 and I/O 340, and the software made all necessary changes to files. The drivers for Windows 95 are built in so the card should be recognized and configured when inserted.

PLATFORM: *COMPAQ AERO 4/33C*

ROM: *07/19/95*

PC CARD: *NEW MEDIA BUS TOASTER, PN: NMC00505*

OPERATING SYSTEM: *WINDOWS 3.1/DOS 6.2*

CARD AND SOCKET SERVICES: *1.25*

CONFIG.SYS

```
SHELL=C:\DOS\COMMAND.COM /P /E:1536
STACKS=9,256
DEVICE=C:\DOS\HIMEM.SYS
DEVICE=C:\DOS\EMM386.EXE NOEMS X=D000-DFFF
DOS=UMB
REM *** Begin PCMCIA Drivers
REM Warning: Do not move, reorder, or delete any of these lines.
REM
DEVICE=C:\CPQDOS\PCMSMIX.EXE
DEVICEHIGH=C:\CPQDOS\SSVLSI.EXE
DEVICEHIGH=C:\CPQDOS\CS.EXE
DEVICE=C:\CPQDOS\CSALLOC.EXE
DEVICEHIGH=C:\CPQDOS\ATADRV.EXE /D:1
DEVICEHIGH=C:\CPQDOS\CARDID.EXE C:\CPQDOS\CARDID.INI
DEVICEHIGH=C:\CPQDOS\MEMDRV.EXE
;DEVICEHIGH=C:\CPQDOS\DBLFLASH.EXE
;DEVICEHIGH=C:\CPQDOS\MS-FLASH.SYS
REM *** End PCMCIA Drivers
DOS=HIGH
BUFFERS=20
FILES=35
DEVICEHIGH=C:\CPQDOS\POWER.EXE
DEVICE=C:\BT\BTASPI.SYS /D
DEVICE=C:\CORELDRV\CUNI_ASP.SYS
DEVICE=C:\CORELDRV\UNI_ASP.SYS
```

AUTOEXEC.BAT

```
@loadhigh C:\DOS\SHARE.EXE /I:500 /f:5100
SET PATH=C:\CPQDOS;C:\;C:\DOS;C:\WINDOWS; C:\WINDOWS\CPQWIN
SET LMOUSE=C:\MOUSE
SET PROMPT=$P$G
SET TEMP=C:\WINDOWS\TEMP
C:\CPQDOS\HIBRN8.EXE
C:\DOS\SMARTDRV.EXE
LH C:\MOUSE\MOUSE SWAP
C:\CPQDOS\MODE.COM CO80
SET PATH=%PATH%;C:\CORELDRV
C:\CORELDRV\CORELCDX
C:\WINDOWS\WIN
```

CARDID.INI

```
[Common]
;
; Common Information section created by Config
;
ComPort1=3F8
ComIRQ1=4
ComPort2=2F8
ComIRQ2=3
ComPort3=3E8
ComIRQ3=4
ComPort4=2E8
ComIRQ4=3
ComBySocket=Yes
ComBDAAbsolute=No
FirstModem=2
SecondModem=2
CARDID.INI-continued
```

ThirdModem=3
FourthModem=4
Audio=Yes
RingIndicate=No
Lan1Port=300
Lan1IRQ=5
Lan1MemoryBase1=D8
Lan1MemoryBase2=DC
Lan2Port=310
Lan2IRQ=10
Lan2MemoryBase1=D8
Lan2MemoryBase2=DC
ATATryPrimary=No
ATATrySecondary=Yes
ATATryLinear=Yes
FastTokenRing=Yes
DetectNonCompliant=No
ContinueOnConfigFailure=No
BeepInDOS=Yes
BeepInWindows=Yes
GrabInitFile=Yes
InitBufferSize=512

[Libraries]

;
; The Libraries section contains references to any card libraries the user
; wishes to include. Libraries are searched in the specified order. Path
; names are relative to the directory containing CARDID.INI.
;
CardLib=cardid.clb

Configuration Notes:

In DOS/Windows ran installation program. Resources used were IRQ 10 and I/O 340, and the software made all necessary changes to files. The drivers for Windows 95 are built in so the card should be recognized and configured when inserted.

PLATFORM: *COMPAQ CONCERTO*

ROM: *10/12/93*

PC CARD: *NEW MEDIA BUS TOASTER, PN: NMC00505*

OPERATING SYSTEM: *WINDOWS 3.1/DOS 6.2*

CARD AND SOCKET SERVICES: *1.25*

CONFIG.SYS

```
SHELL=C:\DOS\COMMAND.COM /P /E:1536
STACKS=9,256
DEVICE=C:\DOS\HIMEM.SYS
DEVICE=C:\DOS\EMM386.EXE NOEMS X=D000-DFFF
DOS=UMB
REM *** Begin PCMCIA Drivers
REM Warning: Do not move, reorder, or delete any of these lines.
REM
DEVICEHIGH=C:\CPQDOS\SSCIRRUS.EXE
DEVICEHIGH=C:\CPQDOS\CS.EXE
DEVICE=C:\CPQDOS\CSALLOC.EXE
DEVICEHIGH=C:\CPQDOS\ATADRV.EXE
DEVICEHIGH=C:\CPQDOS\CARDID.EXE C:\CPQDOS\CARDID.INI
;DEVICEHIGH=C:\CPQDOS\MEMDRV.EXE
;DEVICEHIGH=C:\CPQDOS\DBLFLASH.EXE
;DEVICEHIGH=C:\CPQDOS\MS-FLASH.SYS
REM *** End PCMCIA Drivers
DOS=HIGH
BUFFERS=20
FILES=35
DEVICEHIGH=C:\CPQDOS\POWER.EXE
DEVICE=C:\BT\BTASPL.SYS /D
DEVICE=C:\CORELDRV\CUNI_ASP.SYS
DEVICE=C:\CORELDRV\UNI_ASP.SYS
LASTDRIVE=Z
```

AUTOEXEC.BAT

```
SET PATH=C:\CPQDOS;C:\;\;C:\DOS;C:\WINDOWS;;C:\WINDOWS\CPQWIN
SET LMOUSE=C:\MOUSE
SET PROMPT=$PSG
SET TEMP=C:\WINDOWS\TEMP
C:\CPQDOS\HIBRN8.EXE
C:\DOS\SMARTDRV.EXE
LH C:\MOUSE\MOUSE
C:\CPQDOS\MODE.COM CO80
SET PATH=%PATH%;C:\CORELDRV
C:\CORELDRV\CORELCDX
C:\WINDOWS\WIN
```

CARDID.INI

```
[Common]
;
; Common Information section created by Config
;
ComPort1=3F8
ComIRQ1=4
ComPort2=2F8
ComIRQ2=3
ComPort3=3E8
ComIRQ3=4
ComPort4=2E8
ComIRQ4=3
ComBySocket=Yes
ComBDAAbsolute=No
FirstModem=2
SecondModem=2
```

CARDID.INI-continued

ThirdModem=3
FourthModem=4
Audio=Yes
RingIndicate=No
Lan1Port=300
Lan1IRQ=5
Lan1MemoryBase1=D8
Lan1MemoryBase2=DC
Lan2Port=310
Lan2IRQ=10
Lan2MemoryBase1=D8
Lan2MemoryBase2=DC
ATATryPrimary=No
ATATrySecondary=Yes
ATATryLinear=Yes
FastTokenRing=Yes
DetectNonCompliant=No
ContinueOnConfigFailure=No
BeepInDOS=Yes
BeepInWindows=Yes
GrabInitFile=Yes
InitBufferSize=512

[Libraries]

;
; The Libraries section contains references to any card libraries the user
; wishes to include. Libraries are searched in the specified order. Path
; names are relative to the directory containing CARDID.INI.
;
CardLib=cardid.clb

Configuration Notes:

In DOS/Windows ran installation program. Resources used were IRQ 5 and I/O 380, and the software made all necessary changes to files. The drivers for Windows 95 are built in so the card should be recognized and configured when inserted.

PLATFORM: COMPAQ CONTURA 400CX

ROM: 04/10/95

PC CARD: NEW MEDIA BUS TOASTER, PN: NMC00505

OPERATING SYSTEM: WINDOWS 3.1/DOS 6.2

CARD AND SOCKET SERVICES: 3.12

CONFIG.SYS

```
SHELL=C:\DOS\COMMAND.COM /P /E:1536
STACKS=9,256
DEVICE=C:\DOS\HIMEM.SYS
DEVICE=C:\DOS\EMM386.EXE NOEMS I=B000-B7FF X=D000-D4FF
DEVICEHIGH=C:\WINDOWS\CPQWIN\CPQCM.SYS
DOS=HIGH,UMB
REM *** Begin PCMCIA Drivers
REM Warning: Do not move, reorder, or delete any of these lines.
REM
;DEVICE=C:\CPQDOS\PCMSMIX.EXE
DEVICEHIGH=C:\CPQDOS\SSVLSI.EXE
DEVICEHIGH=C:\CPQDOS\CS.EXE
DEVICE=C:\CPQDOS\CSALLOC.EXE
;DEVICEHIGH=C:\CPQDOS\ATADRV.EXE
;DEVICEHIGH=C:\CPQDOS\MTAA.EXE
;DEVICEHIGH=C:\CPQDOS\MTAB.EXE
;DEVICEHIGH=C:\CPQDOS\MTI1.EXE
;DEVICEHIGH=C:\CPQDOS\MTI2P.EXE
;DEVICEHIGH=C:\CPQDOS\MTSRAM.EXE
;DEVICEHIGH=C:\CPQDOS\MTDDR.V.EXE
;DEVICEHIGH=C:\CPQDOS\DBLFLASH.EXE
;DEVICEHIGH=C:\CPQDOS\MS-FLASH.SYS
DEVICEHIGH=C:\CPQDOS\CARDID.EXE
REM *** End PCMCIA Drivers
BUFFERS=20
FILES=35
DEVICEHIGH=C:\CPQDOS\EPPBIOS.SYS
DEVICEHIGH=C:\CPQDOS\POWER.EXE
DEVICE=C:\BT\BTASPI.SYS /D
DEVICE=C:\CORELDRV\CUNI_ASP.SYS
DEVICE=C:\CORELDRV\UNI_ASP.SYS
LASTDRIVE=F
```

AUTOEXEC.BAT

```
@loadhigh C:\DOS\SHARE.EXE /l:500 /f:5100
@ECHO OFF
SET PATH=C:\CPQDOS;C:\;C:\DOS;C:\WINDOWS;;C:\WINDOWS\CPQWIN
SET LMOUSE=C:\MOUSE
LH C:\MOUSE\MOUSE
SET PROMPT=SPSG
SET TEMP=C:\WINDOWS\TEMP
C:\CPQDOS\HIBRN8.EXE
LH C:\DOS\SMARTDRV.EXE
SET PATH=%PATH%;C:\CORELDRV
C:\CORELDRV\CORELCDX
win
```

CARDID.INI

```
[Common]
;
; Common Information section created by Config
;
ComPort1=3F8
ComIRQ1=4
ComPort2=2F8
ComIRQ2=3
ComPort3=3e8
CARDID.INI-continued
```

ComIRQ3=4
ComPort4=2E8
ComIRQ4=3
ComBySocket=Yes
ComBDAAbsolute=No
FirstModem=2
SecondModem=2
ThirdModem=3
FourthModem=4
Audio=Yes
RingIndicate=No
Lan1Port=300
Lan1IRQ=5
Lan1MemoryBase1=
Lan1MemoryBase2=
Lan2Port=310
Lan2IRQ=9
Lan2MemoryBase1=
Lan2MemoryBase2=
ATATryPrimary=No
ATATrySecondary=Yes
ATATryLinear=Yes
FastTokenRing=Yes
DetectNonCompliant=No
ContinueOnConfigFailure=No
BeepInDOS=Yes
BeepInWindows=Yes
GrabInitFile=Yes
InitBufferSize=512
UseEMS=No

[Libraries]

;
; The Libraries section contains references to any card libraries the user
; wishes to include. Libraries are searched in the specified order. Path
; names are relative to the directory containing CARDID.INI.

;
CardLib=canonfd.clb
CardLib=xirdual.clb
CardLib=xircom.clb
CardLib=tdkklan2.clb
CardLib=sundisk5.clb
CardLib=intellan.clb
CardLib=dlink.clb
CardLib=linksys.clb
CardLib=linksys2.clb
CardLib=socketea.clb
CardLib=ibmlan.clb
CardLib=ibmtok.clb
CardLib=ibm3270.clb
CardLib=proxim.clb
CardLib=cbdass.clb
CardLib=genmodem.clb
CardLib=genata.clb
CardLib=wd.clb

Configuration Notes:

In DOS/Windows ran installation program. Resources used were IRQ 5 and I/O 380, and the software made all necessary changes to files. The drivers for Windows 95 are built in so the card should be recognized and configured when inserted.

PLATFORM: COMPAQ CONTURA 420C

ROM: 08/20/95

PC CARD: NEW MEDIA BUS TOASTER, PN: NMC00505

OPERATING SYSTEM: WINDOWS 3.1/DOS 6.2

CARD AND SOCKET SERVICES: 3.12

CONFIG.SYS

```
switches=/F
SHELL=C:\DOS\COMMAND.COM /P /E:1536
STACKS=9,256
DEVICE=C:\DOS\HIMEM.SYS
DEVICE=C:\DOS\EMM386.EXE NOEMS I=B000-B7FF X=D000-D4FF
DEVICEHIGH=C:\WINDOWS\CPQWIN\CPQCM.SYS
DOS=HIGH,UMB
REM *** Begin PCMCIA Drivers
REM Warning: Do not move, reorder, or delete any of these lines.
REM
;DEVICE=C:\CPQDOS\PCMSMIX.EXE
DEVICEHIGH=C:\CPQDOS\SSVLSI.EXE
DEVICEHIGH=C:\CPQDOS\CS.EXE
DEVICE=C:\CPQDOS\CSALLOC.EXE
;DEVICEHIGH=C:\CPQDOS\ATADRV.EXE
;DEVICEHIGH=C:\CPQDOS\MTAA.EXE
;DEVICEHIGH=C:\CPQDOS\MTAB.EXE
;DEVICEHIGH=C:\CPQDOS\MTI1.EXE
;DEVICEHIGH=C:\CPQDOS\MTI2P.EXE
;DEVICEHIGH=C:\CPQDOS\MTSRAM.EXE
;DEVICEHIGH=C:\CPQDOS\MTDDRV.EXE
;DEVICEHIGH=C:\CPQDOS\DBLFLASH.EXE
;DEVICEHIGH=C:\CPQDOS\MS-FLASH.SYS
DEVICEHIGH=C:\CPQDOS\CARDID.EXE
REM *** End PCMCIA Drivers
BUFFERS=20
FILES=35
DEVICEHIGH=C:\CPQDOS\EPPBIOS.SYS
DEVICE=C:\BT\BTASPI.SYS /D
DEVICE=C:\CORELDRV\CUNI_ASP.SYS
DEVICE=C:\CORELDRV\UNI_ASP.SYS
LASTDRIVE=F
```

AUTOEXEC.BAT

```
@ECHO OFF
SET PATH=C:\CPQDOS;C:\;C:\DOS;C:\WINDOWS;
SET LMOUSE=C:\MOUSE
LH C:\MOUSE\MOUSE
SET PROMPT=$PSG
SET TEMP=C:\WINDOWS\TEMP
C:\CPQDOS\HIBRN8.EXE
C:\DOS\SMARTDRV.EXE 2048 512
SET PATH=%PATH%;C:\CORELDRV
C:\CORELDRV\CORELCDX
C:\WINDOWS\WIN
```

CARDID.INI

```
[Common]
;
; Common Information section created by Config
;
ComPort1=3F8
ComIRQ1=4
ComPort2=2F8
ComIRQ2=3
ComPort3=3e8
ComIRQ3=4
CARDID.INI-continued
```

ComPort4=2E8
ComIRQ4=3
ComBySocket=Yes
ComBDAAbsolute=No
FirstModem=2
SecondModem=2
ThirdModem=3
FourthModem=4
Audio=Yes
RingIndicate=No
Lan1Port=300
Lan1IRQ=5
Lan1MemoryBase1=
Lan1MemoryBase2=
Lan2Port=310
Lan2IRQ=9
Lan2MemoryBase1=
Lan2MemoryBase2=
ATATryPrimary=No
ATATrySecondary=Yes
ATATryLinear=Yes
FastTokenRing=Yes
DetectNonCompliant=No
ContinueOnConfigFailure=No
BeepInDOS=Yes
BeepInWindows=Yes
GrabInitFile=Yes
InitBufferSize=512
UseEMS=No

[Libraries]

;
; The Libraries section contains references to any card libraries the user
; wishes to include. Libraries are searched in the specified order. Path
; names are relative to the directory containing CARDID.INI.

;
CardLib=canonfd.clb
CardLib=xirdual.clb
CardLib=xircom.clb
CardLib=tdkfan2.clb
CardLib=sundisk5.clb
CardLib=intellan.clb
CardLib=dlink.clb
CardLib=linksys.clb
CardLib=linksys2.clb
CardLib=socketea.clb
CardLib=ibmlan.clb
CardLib=ibmtok.clb
CardLib=ibm3270.clb
CardLib=proxim.clb
CardLib=cbdass.clb
CardLib=genmodem.clb
CardLib=genata.clb
CardLib=wd.clb

Configuration Notes:

In DOS/Windows ran installation program. Resources used were IRQ 5 and I/O 380, and the software made all necessary changes to files. The drivers for Windows 95 are built in so the card should be recognized and configured when inserted.

PLATFORM: COMPAQ ELITE 4/50CX

ROM: 07/19/95

PC CARD: NEW MEDIA BUS TOASTER, PN: NMC00505

OPERATING SYSTEM: WINDOWS 3.1 / DOS 6.2

CARD AND SOCKET SERVICES: 3.12

CONFIG.SYS

```
switches=/F
SHELL=C:\DOS\COMMAND.COM /P /E:1536
STACKS=9,256
DEVICE=C:\DOS\HIMEM.SYS /TESTMEM:OFF
DEVICE=C:\DOS\EMM386.EXE NOEMS I=B000-B7FF X=D000-D4FF
DEVICEHIGH=C:\WINDOWS\CPQWIN\CPQCM.SYS
DOS=HIGH,UMB
REM *** Begin PCMCIA Drivers
REM Warning: Do not move, reorder, or delete any of these lines.
REM
;DEVICE=C:\CPQDOS\PCSMIX.EXE
DEVICEHIGH=C:\CPQDOS\SSVLSI.EXE
DEVICEHIGH=C:\CPQDOS\CS.EXE
DEVICE=C:\CPQDOS\CSALLOC.EXE
;DEVICEHIGH=C:\CPQDOS\ATADRV.EXE
;DEVICEHIGH=C:\CPQDOS\MTAA.EXE
;DEVICEHIGH=C:\CPQDOS\MTAB.EXE
;DEVICEHIGH=C:\CPQDOS\MTI1.EXE
;DEVICEHIGH=C:\CPQDOS\MTI2P.EXE
;DEVICEHIGH=C:\CPQDOS\MTSRAM.EXE
;DEVICEHIGH=C:\CPQDOS\MTDDRV.EXE
;DEVICEHIGH=C:\CPQDOS\DBLFLASH.EXE
;DEVICEHIGH=C:\CPQDOS\MS-FLASH.SYS
DEVICEHIGH=C:\CPQDOS\CARDID.EXE
REM *** End PCMCIA Drivers
BUFFERS=20
FILES=35
LASTDRIVE=P
DEVICEHIGH=C:\CPQDOS\POWER.EXE
DEVICE=C:\BT\BTASPL.SYS /D
DEVICEHIGH=C:\CORELDRV\CUNI_ASP.SYS
DEVICEHIGH=C:\CORELDRV\UNI_ASP.SYS
```

AUTOEXEC.BAT

```
@ECHO OFF
SET PATH=C:\CPQDOS;C:\;C:\DOS;C:\WINDOWS;;C:\WINDOWS\CPQWIN
SET LMOUSE=C:\MOUSE
LH C:\MOUSE\MOUSE
SET PROMPT=$t $PSG
SET TEMP=C:\WINDOWS\TEMP
C:\CPQDOS\HIBRN8.EXE
LH C:\DOS\SMARTDRV.EXE /f 2048 1024
SET NWLANGUAGE=ENGLISH
SET PATH=%PATH%;C:\CORELDRV
C:\CORELDRV\CORELCDX
win
```

CARDID.INI

```
[Common]
;
; Common Information section created by Config
;
ComPort1=3F8
ComIRQ1=4
ComPort2=2F8
ComIRQ2=3
ComPort3=3e8
CARDID.INI-continued
```

ComIRQ3=4
ComPort4=2E8
ComIRQ4=3
ComBySocket=Yes
ComBDAAbsolute=No
FirstModem=2
SecondModem=2
ThirdModem=3
FourthModem=4
Audio=Yes
RingIndicate=No
Lan1Port=300
Lan1IRQ=5
Lan1MemoryBase1=
Lan1MemoryBase2=
Lan2Port=310
Lan2IRQ=9
Lan2MemoryBase1=
Lan2MemoryBase2=
ATATryPrimary=No
ATATrySecondary=Yes
ATATryLinear=Yes
FastTokenRing=Yes
DetectNonCompliant=No
ContinueOnConfigFailure=No
BeepInDOS=Yes
BeepInWindows=Yes
GrabInitFile=Yes
InitBufferSize=512
UseEMS=No

[Libraries]

;
; The Libraries section contains references to any card libraries the user
; wishes to include. Libraries are searched in the specified order. Path
; names are relative to the directory containing CARDID.INI.

;
CardLib=canonfd.clb
CardLib=xirdual.clb
CardLib=xircom.clb
CardLib=tdkfan2.clb
CardLib=sundisk5.clb
CardLib=intellan.clb
CardLib=dlink.clb
CardLib=linksys.clb
CardLib=linksys2.clb
CardLib=socketea.clb
CardLib=ibmlan.clb
CardLib=ibmtok.clb
CardLib=ibm3270.clb
CardLib=proxim.clb
CardLib=cbdass.clb
CardLib=genmodem.clb
CardLib=genata.clb
CardLib=wd.clb

Configuration Notes:

In DOS/Windows ran installation program. Resources used were IRQ 5 and I/O 380, and the software made all necessary changes to files. The drivers for Windows 95 are built in so the card should be recognized and configured when inserted.

PLATFORM: *COMPAQ LTE 5000*

ROM: *09/19/95*

PC CARD: *NEW MEDIA BUS TOASTER, PN: NMC00505*

OPERATING SYSTEM: *WINDOWS 3.1/DOS 6.2*

CARD AND SOCKET SERVICES: *3.14*

CONFIG.SYS

```
DEVICE=C:\CPQDOS\MACHCHK.SYS 02A8 02B0 02BA 02CA
DEVICE=C:\DOS\HIMEM.SYS
DEVICE=C:\DOS\EMM386.exe NOEMS I=B000-B7FF X=C800-CBFF X=D100-D5FF X=E800-EFFF
COUNTRY=001,437,C:\DOS\COUNTRY.SYS
SHELL=C:\DOS\COMMAND.COM /P /E:1536
DOS=HIGH,UMB
FILES=35
BUFFERS=20,0
STACKS=9,256
DEVICEHIGH=C:\AUDIO_CD\TEAC_CDI.SYS /D:TEAC-CDI
LASTDRIVE=Z
REM PC Card: Begin PC Card (PCMCIA) Drivers
REM **Warning: Do not move, reorder, or delete any of these lines. **
DEVICEHIGH=C:\CARDWIZ\SSCIRUS2.EXE
DEVICEHIGH=C:\CARDWIZ\CS.EXE /POLL:1
DEVICEHIGH=C:\CARDWIZ\CSALLOC.EXE
DEVICEHIGH=C:\CARDWIZ\CARDID.EXE
REM PC Card: End PC Card(PCMCIA) Drives
DEVICE=C:\BT\BTASPL.SYS /D
DEVICE=C:\CORELDRV\CUNI_ASP.SYS
DEVICE=C:\CORELDRV\UNI_ASP.SYS
```

AUTOEXEC.BAT

```
@ECHO OFF
C:\WINDOWS\VGUTIL\winmode.exe t640=60 t800=60 t1024=87 t1280=87
SET NWLANGUAGE=ENGLISH
PATH C:\WINDOWS;C:\CPQDOS;C:\DOS;C:\AUDIO_CD;C:\CARDWIZ
PROMPT Sp$g
SET DIRCMD=/ogn
SET TEMP=C:\WINDOWS\TEMP
SET BLASTER=A220 D1 I5
SET LMOUSE=C:\MOUSE
SET MOUSE=C:\MOUSE
C:\MOUSE\MOUSE.EXE MEMU
C:\CORELDRV\CORELCDX
IF ERRORLEVEL 1 GOTO NO_CDROM
C:\AUDIO_CD\ESSVOL /V:15 /C:15
:NO_CDROM
LH C:\DOS\SMARTDRV.EXE
C:\CPQDOS\0VMAKFIL
IF NOT EXIST C:\CPQDOS\SAVEDONE.CPQ CALL SAVEALL /A
SET PATH=%PATH%;C:\CORELDRV
WIN
```

CARDID.INI

```
[Common]
;
; Common Information section created by Config
;
ComPort1=3F8
ComIRQ1=4
ComPort2=2F8
ComIRQ2=3
ComPort3=3E8
ComIRQ3=4
ComPort4=2E8
ComIRQ4=11
CARDID.INI-continued
```

ComBySocket=No
ComBDAAbsolute=Yes
ComRollOverOn=No
FirstModem=2
SecondModem=4
ThirdModem=2
FourthModem=4
Audio=Yes
RingIndicate=No
Suspend_Power=No
Lan1Port=330
Lan1IRQ=11
Lan1MemoryBase1=0
Lan1MemoryBase2=D1
Lan2Port=310
Lan2IRQ=10
Lan2MemoryBase1=0
Lan2MemoryBase2=0
ATATryPrimary=No
ATATrySecondary=Yes
ATATryLinear=Yes
FastTokenRing=Yes
DetectNonCompliant=No
ContinueOnConfigFailure=No
BeepInDOS=Yes
BeepInWindows=Yes
GrabInitFile=Yes
InitBufferSize=512
FirstLan=1
SecondLan=2

[Libraries]

;
; The Libraries section contains references to any card libraries the user
; wishes to include. Libraries are searched in the specified order. Path
; names are relative to the directory containing CARDID.INI.

;
CardLib=xirdual.clb
CardLib=xircom.clb
CardLib=tdkklan2.clb
CardLib=sundisk5.clb
CardLib=intellan.clb
CardLib=dlink.clb
CardLib=linksys.clb
CardLib=linksys2.clb
CardLib=socketea.clb
CardLib=ibmlan.clb
CardLib=ibmtok.clb
CardLib=ibm3270.clb
CardLib=proxim.clb
CardLib=caldas.clb
CardLib=genmodem.clb
CardLib=genata.clb
CardLib=wd.clb

Configuration Notes:

In DOS/Windows ran installation program. Resources used were IRQ 5 and I/O 380, and the software made all necessary changes to files. The drivers for Windows 95 are built in so the card should be recognized and configured when inserted.