HP Cluster Configuration Support Matrix
For Microsoft Windows 2000 Advanced Server & HP StorageWorks MSA500

Config	Supported Servers	Server Software	Host Bus Adapters (HBAs)	Multipath Software	Storage Information	Other
#1 Windows 2000 Advanced Server Service Pack 4	Max supported nodes = 2 ProLiant: • DL360 G3, DL360 G4 • DL380 G3, DL380 G4 • DL560 • DL580 G2 • DL585 • DL740 • DL760 G2 • ML350 G3, ML350 G4 • ML370 G3, ML370 G4 • ML530 G2 • ML570 G2	SmartStart **Ver:** 7.1 utilized with PSP 7.10A	Smart Array 642 **Driver:** 5.62.0.32 **FW:** 2.26 Smart Array 6i * **Driver:** 5.62.0.32 **FW:** 2.26 ***Note:** only used with the DL360 G4 and DL380 G4 servers.	Smart Array Multipath Software **Ver:** 2.0b	StorageWorks MSA500 G2 **Storage Controller FW:** 1.40 **Storage EMU FW:** 2.28 on 2-port 2.30 on 4-port **Array Configuration Utility** **Ver:** 7.15.19.0	Product Page Supporting Documentation MSCS Support Matrix - Archive **September 2004**
#2 Windows 2000 Advanced Server Service Pack 4	Max supported nodes = 2 ProLiant: • DL360 G3 • DL380 G3 • DL560 • DL580 G2 • DL740 • DL760 G2 • ML350 G3 • ML370 G3 • ML530 G2 • ML570 G2	SmartStart **Ver:** 7.0 utilized with PSP 7.00A	Smart Array 642 **Driver:** 5.50.0.32 **FW:** 1.92	Smart Array Multipath Software **Ver:** 2.0a	StorageWorks MSA500 G2 **Storage Controller FW:** 1.14 **Storage EMU FW:** 1.92 on 2-port and 4-port modules **Array Configuration Utility** **Ver:** 7.10.5.0	Product Page Supporting Documentation MSCS Support Matrix - Archive **May 2004**
#3 Windows 2000 Advanced Server Service Pack 4	Max supported nodes = 2 ProLiant: • DL360 G2, DL360 G3 • DL380 G2, DL380 G3 • DL560 • DL580, DL580 G2 • DL740 • DL760, DL760 G2 • ML350 G2, ML350 G3 • ML370 G2, ML370 G3	SmartStart **Ver:** 6.40 utilized with PSP 6.40a	Smart Array 5i **Driver:** 5.46.2.32 **FW:** 2.56 Smart Array 5i Plus **Driver:** 5.46.2.32 **FW:** 2.56 Smart Array 532 **Driver:** 5.46.2.32 **FW:** 2.56	Smart Array Multipath Software **Ver:** 2.0	StorageWorks MSA500 **Storage Controller FW:** 1.80 **Storage EMU FW:** 1.86 on 2-port module 1.88 on 4-port module **Array Configuration Utility** **Ver:** 6.40.11.0	Product Page **December 2003**
#4 Windows 2000 Advanced Server Service Pack 4	Max supported nodes = 2 ProLiant: • DL360 G2, DL360 G3 • DL380 G2, DL380 G3 • DL560 • DL580, DL580 G2 • DL740 • DL760, DL760 G2 • ML350 G2, ML350 G3 • ML370 G2, ML370 G3	SmartStart **Ver:** 6.40 utilized with PSP 6.40a	Smart Array 5i **Driver:** 5.46.2.32 **FW:** 2.38 Smart Array 5i Plus **Driver:** 5.46.2.32 **FW:** 2.38 Smart Array 532 **Driver:** 5.46.2.32 **FW:** 2.38	**N/A**	Smart Array Cluster Storage **Storage Controller FW:** 1.70 **Storage EMU FW:** 1.86 on 2-port module 1.88 on 4-port module **Array Configuration Utility** **Ver:** 6.40.11.0	Product Page **June 2003**