



HP Cluster Configuration Support Matrix For Microsoft Windows Server 2003, EE x86/32-bit & HP ProLiant DL380 Packaged Cluster with MSA500 G2

Config	Supported Servers	Server Software	Host Bus Adapters (HBAs)	Multipath Software	Storage Information	Other
#1 Windows Server 2003, EE R2, x86/32-bit	Max supported nodes = 2 ProLiant: <ul style="list-style-type: none"> DL380 G4 or DL380 G3* *Note: must use the Smart Array 642 controller.	SmartStart Ver: 7.70	Smart Array 642 Driver: 5.74.0.32 FW: 2.68 Smart Array 6i * Driver: 5.74.0.32 FW: 2.68 *Note: only used with the DL380 G4 servers.	Smart Array Multipath Software Ver: 2.0d	StorageWorks MSA500 G2 Storage Controller FW: 1.56 Storage EMU FW: 2.28 on 2-port 2.30 on 4-port Array Configuration Utility Ver: 7.60.18.0 or later	Product Page Supporting Documentation January 2007
#2 Windows Server 2003, EE R2	Max supported nodes = 2 ProLiant: <ul style="list-style-type: none"> DL380 G4 or DL380 G3* *Note: must use the Smart Array 642 controller.	SmartStart Ver: 7.60	Smart Array 642 Driver: 5.74.0.32 FW: 2.68 Smart Array 6i * Driver: 5.74.0.32 FW: 2.68 *Note: only used with the DL380 G4 servers.	Smart Array Multipath Software Ver: 2.0c	StorageWorks MSA500 G2 Storage Controller FW: 1.56 Storage EMU FW: 2.28 on 2-port 2.30 on 4-port Array Configuration Utility Ver: 7.60.18.0 or later	Product Page Supporting Documentation November 2006
#3 Windows Server 2003, EE	Max supported nodes = 2 ProLiant: <ul style="list-style-type: none"> DL380 G4 or DL380 G3* *Note: must use the Smart Array 642 controller.	SmartStart Ver: 7.1 utilized with PSP 7.01A	Smart Array 642 Driver: 5.62.0.32 FW: 2.26 Smart Array 6i Driver: 5.62.0.32 FW: 2.26	Smart Array Multipath Software Ver: 2.0b	StorageWorks MSA500 G2 Storage Controller FW: 1.40 Storage EMU FW: 2.28 on 2-port 2.30 on 4-port Array Configuration Utility Ver: 7.15.19.0	Product Page Supporting Documentation MSCS Support Matrix - Archive September 2004
#4 Windows Server 2003, EE	Max supported nodes = 2 ProLiant: <ul style="list-style-type: none"> DL380 G3 	SmartStart Ver: 7.0 utilized with PSP 7.00A	Smart Array 642 Driver: 5.50.0.32 FW: 1.92	Smart Array Multipath Software Ver: 2.0a	StorageWorks MSA500 G2 Storage Controller FW: 1.14 Storage EMU FW: 1.92 on 2-port and 4-port modules Array Configuration Utility Ver: 7.10.5.0	Product Page Supporting Documentation MSCS Support Matrix - Archive May 2004